

July, 1952

40 Cents

45c in Canada

QST

devoted entirely to

amateur radio



PUBLISHED BY THE AMERICAN RADIO RELAY LEAGUE




FILTER SPECIALISTS


PRODUCERS OF PERMALLOY DUST TOROID COILS AND FILTERS FOR OVER A DECADE




FOR FILTERS




**BROAD BAND
SHARP CUTOFF
FILTER**



**NARROW BAND
SHARP CUTOFF
FILTER**



**ATTENUATOR
10K TO 30
MEGACYCLES**



**LOW FREQUENCY
— LOW PASS
FILTER**

SUB-OUNCER TOROID FILTERS

Filters employing SUB-OUNCER toroids and special condensers represent the optimum in miniaturized filter performance. The band pass filter shown weighs 6 ounces.


HQA, C, D TOROID COILS
1 1/2" Dia. x 1 1/2" High.



HQB TOROID COIL
2 1/8" L. x 1 1/2" W. x 2 1/2" H.



UNCASED TOROIDS








**VIC
VARIABLE
INDUCTOR**

1 1/2" L. x 1 1/4" W. x 1 1/2" H.




FOR HIGH Q COILS



Write for our latest catalog.

United Transformer Co.
150 VARICK STREET NEW YORK 13, N. Y.
EXPORT DIVISION, 13 EAST 40TH STREET, NEW YORK 16, N. Y. CABLES: "ARLAB"

Hear ALL that your antenna pulls in,
with G. E.'s brand-new



Heater voltage, a-c or d-c	6.3 v
Heater current	0.225 amp
Amplification factor	42
Transconductance	10,000 micromhos
Plate current	16 ma
Power gain at 900 mc, for 10-mc band width	7 db
Noise figure at 900 mc	15 db

YOU don't have to push G. E.'s 6AJ4 to get the ultra-high frequencies that will make your receiver all-band. This new triode was *designed* for u-h-f.

● So . . . tube noise level is low at all times! And the 6AJ4 has a high power gain. You hear clearly on every channel.

● Price? A real bargain. The 6AJ4 costs you less than the average panel meter! For the first time, you can enjoy fine u-h-f reception without strain on your pocketbook . . . and with the same tube that serves you well on 6 and 2 meters.

● Check 6AJ4 ratings at right, then see your G-E tube distributor for price and further facts. Bear in mind that this tube—now in quantity production for TV—is a *proved* performer in every respect! Tube Department, General Electric Company, Schenectady 5, New York.

KEY TO U-H-F!

● Here is a part chronology of G. E.'s pioneering work in the ultra-highs, much of it tube design that was basic:

- 1928 — Split-anode magnetron built and tested at 1,000 mc.
- 1930 — Magnetron made commercially available.
- 1935 — Centimeter waves used to measure speed and direction of aircraft.
- 1936 — Velocity-modulation tube developed.
- 1940 — Disk triode developed.
- 1942 — Lighthouse tubes introduced for radar.

This 24-year background contributes to the efficiency of new G-E u-h-f types like the 6AJ4. Knowing how first, has created greater G-E design know-how . . . from which you benefit in the superior performance of G-E tubes you buy!

ELECTRONIC TUBES OF ALL TYPES FOR THE RADIO AMATEUR

GENERAL  ELECTRIC

146-187

AUTHORIZED COLLINS DISTRIBUTORS

- Aberdeen, South Dakota**
● Burghardt Radio Supply
P.O. Box 342
- Albany, New York**
● Ft. Orange Radio Distributing Co., Inc., 642-644 Broadway
- Albuquerque, New Mexico**
● Radio Equipment Co.
523 E. Central Ave.
- Allentown, Pennsylvania**
● Radio Electric Service Co. of Pa., Inc., 1042 Hamilton St.
- Amsterdam, New York**
● Adirondack Radio Supply
P.O. Box 88, 32 Guy Park Ave.
- Atlanta, Georgia**
● Specialty Distributing Co.
425 Peachtree St., N.E.
- Atlantic, New Jersey**
● Radio Electric Service Co. of Pa., Inc., 452 N. Albany Ave.
- Augusta, Georgia**
● Specialty Distributing Co.
644 Reynolds St.
- Baltimore, Maryland**
● Kann-Ellert Electronics, Inc., 9 South Howard St.
- Birmingham, Alabama**
● Ack Radio Supply Co.
2205 Third Ave., N.
- Boston, Massachusetts**
● DeMambro Radio Supply, Inc., 1111 Commonwealth Ave.
● Radio Shack Corp.
167 Washington St.
- Butler, Missouri**
● Henry Radio Co.
211 North Main
- Camden, New Jersey**
● Radio Electric Service Co. of Pa., Inc., 513-15 Cooper St.
- Chattanooga, Tennessee**
● Specialty Distributing Co.
709 Chestnut St.
- Chicago, Illinois**
● Allied Radio Corp.
833 W. Jackson Blvd.
● Newark Electric Co.
323 W. Madison St.
- Cincinnati, Ohio**
● Steinberg's Inc.
633 Walnut St.
- Cleveland, Ohio**
● The Progress Radio Supply Co., 413-15 Huron Road
● Radio & Electronic Parts Co.
3235 Prospect Ave.
- Columbus, Ohio**
● Thompson Radio Supplies
182 E. Long St.
- Concord, New Hampshire**
● Evans Radio
10 Hills Ave.
- Corpus Christi, Texas**
● Electronic Equipment & Engineering Co.
805 S. Staples St.
- Council Bluffs, Iowa**
● World Radio Laboratories, Inc., 744 West Broadway
- Dallas, Texas**
● Crabtree's Wholesale Radio
2608 Ross Ave.
- Dayton, Ohio**
● SREPCO, Inc.
135 E. Second St.
- Denver, Colorado**
● Radio Products Sales Co.
1237 Sixteenth St.
- Des Moines, Iowa**
● Radio Trade Supply Co.
1224 Grand Ave.
- Detroit, Michigan**
● M. N. Dully & Co.
2040 Grand River Ave., W.
- Duluth, Minnesota**
● Lew Bonn Co.
228 E. Superior St.
- Easton, Pennsylvania**
● Radio Electric Service Co. of Pa., Inc.
916 Northampton St.
- El Paso, Texas**
● C. C. McNicols
811 Estrella
- Eugene, Oregon**
● United Radio Supply Co.
179 W. Eighth St.
- Everett, Washington**
● Pringle Radio Wholesale Co.
2514 Colby Ave.
- Ft. Wayne, Indiana**
● Ft. Wayne Electronics Supply, Inc.
223 E. Main St.
- Greensboro, North Carolina**
● Johannessen Electric Co., Inc., 312-14 N. Eugene St.
- Hollywood, Florida**
● Carl's Radio Shop
2323 Hollywood Blvd.
- Indianapolis, Indiana**
● Graham Electronic Supply, Inc., 102 S. Pennsylvania St.
- Jackson, Tennessee**
● L. K. Rush Co.
P.O. Box 1418
- Jacksonville, Florida**
● Kinkade Radio Supply
1402 Laura St.
- Jamaica, New York**
● Harrison Radio Corp.
172-31 Hillside Ave.
- Johnstown, Pennsylvania**
● Cambria Equipment Co.
17 Johns St.
- Kansas City, Missouri**
● Radiolab
1612 Grand Ave.
- Lafayette, Indiana**
● Lafayette Radio Supply, Inc., 627 Main St.
- Lexington, Kentucky**
● Radio Equipment Co.
480 Skain Ave.
- Little Rock, Arkansas**
● Carlton Wholesale Radio
- Long Beach, California**
● Scott Radio Supply
266 Alamitos Ave.
- Los Angeles, California**
● Henry Radio
11240 W. Olympic Blvd.
● Kierulff & Co.
820-830 W. Olympic Blvd.
● Radio Products Sales, Inc.
1501 S. Hill St.
- Louisville, Kentucky**
● Universal Radio Supply Co., Inc., 333 S. Seventh St.
- Madison, Wisconsin**
● Satterfield Radio Supply, Inc., 326 W. Gorham St.
- Memphis, Tennessee**
● Lavender Radio Supply Co., Inc., 1014-16 Union Ave.
● W & W Distributing Co.
639 Madison Ave.
- Milwaukee, Wisconsin**
● Central Radio Parts Co.
1723 W. Fond du Lac Ave.
- Minneapolis, Minnesota**
● Lew Bonn Co.
1211 La Salle Ave.
- Muncie, Indiana**
● Radio Supply of Muncie, Inc., 305 N. Madison
- New Haven, Connecticut**
● Dale-Connecticut, Inc.
140 Ferry St.
- New Orleans, Louisiana**
● Radio Parts, Inc.
807 Howard Ave.
- New York, New York**
● Harrison Radio Corp.
10 West Broadway
● Harvey Radio Co., Inc.
103 W. 43rd St.
- Norfolk, Virginia**
● Radio Equipment Co.
821 W. 21st St.
- Oakland, California**
● W. D. Brill Co.
10th & Jackson Sts.
● Electric Supply Co.
140 - 11th St. at Madison
- Peoria, Illinois**
● Klaus Radio & Electric Co.
707 Main St.
- Philadelphia, Pennsylvania**
● Radio Electric Service Co. of Pa., Inc.
3412 Germantown Ave.
● Radio Electric Service Co. of Pa., Inc., 5930 Market St.
● Radio Electric Service Co. of Pa., Inc., N.W. Corner 7th & Arch Sts.
- Phoenix, Arizona**
● Radio Parts of Arizona
214 S. 11th St.
- Pittsburgh, Pennsylvania**
● Cameradio Co.
963 Liberty Ave.
● The Tydings Co.
5800 Baum Blvd.
- Portland, Oregon**
● Pacific Stationery Wholesale Radio Dept.
414 S.W. Second Ave.
● United Radio Supply Co.
22 N.W. Ninth Ave.
- Providence, Rhode Island**
● W. H. Edwards Co.
94 Broadway
- Rock Island, Illinois**
● Tri-City Radio Supply Co.
1919 Fourth Ave.
- St. Louis, Missouri**
● Walter Ashe Radio Co.
1125 Pine St.
- St. Paul, Minnesota**
● Lew Bonn Co.
141-147 W. Seventh St.
● Hall Electric Co.
386 Minnesota St.
- San Antonio, Texas**
● Amateur Headquarters & Supply, P.O. Box 5086,
Beacon Hill Station
- San Diego, California**
● Western Radio & TV Supply Co., 1415 India St.
- San Francisco, California**
● San Francisco Radio & Supply Co.
1282-1284 Market St.
- Seattle, Washington**
● Western Electronic Supply Co., 717 Dexter
- South Bend, Indiana**
● Radio Distributing Co.
432 Carroll St.
- Spokane, Washington**
● Northwest Electronic Co.
N. 102 Monroe St.
- Springfield, Ohio**
● SREPCO, Inc.
119 W. Main St.
- Tacoma, Washington**
● C & G Radio Supply Co.
2502-6 Jefferson Ave.
- Tampa, Florida**
● Kinkade Radio Supply
402-04 W. Fortune St.
- Texarkana, Arkansas-Texas**
● Lavender Radio Supply Co., Inc., 520 E. Fourth St.,
P.O. Box 596
- Toledo, Ohio**
● Selectronic Supplies, Inc.
1013 Jefferson Ave.
- Topeka, Kansas**
● The Overton Electric Co., Inc., 522 Jackson St.
- Tucson, Arizona**
● Elliott Electronics, Inc.
Box 5081
418 N. Fourth Ave.
- Tulsa, Oklahoma**
● Radio, Inc.
1000 S. Main St.
- Tyler, Texas**
● Lavender Radio Supply Co., Inc., 503 E. Oakwood
- Washington, D. C.**
● Electronic Wholesalers, Inc.
2345 Sherman Ave., N.W.
- Watertown, South Dakota**
● Burghardt Radio Supply
P.O. Box 41
- Wilmington, Delaware**
● Radio Electric Service Co. of Pa., Inc., S.E. Corner Third & Tatnall Sts.

FOR THE BEST IN AMATEUR RADIO, IT'S . . .



COLLINS RADIO COMPANY, Cedar Rapids, Iowa

11 W. 42nd St., NEW YORK 18

1930 Carpenter Blvd., DALLAS 2

2700 W. Olive Ave., BURBANK

PUBLISHED, MONTHLY, AS ITS OFFICIAL ORGAN, BY THE AMERICAN RADIO RELAY LEAGUE, INC., AT WEST HARTFORD, CONN., U. S. A.; OFFICIAL ORGAN OF THE INTERNATIONAL AMATEUR RADIO UNION

STAFF

Editorial

A. L. BUDLONG, WIBUD
Editor

HAROLD M. McKEAN, WICEG
Managing Editor

GEORGE GRAMMER, WIDF
Technical Editor

DONALD H. MIX, WITS
BYRON GOODMAN, WIDX
Assistant Technical Editors

EDWARD P. TILTON, WIHDQ
V.H.F. Editor

RICHARD M. SMITH, WIFTX
C. VERNON CHAMBERS, WJJEQ
Technical Assistants

ROD NEWKIRK, WIVMW
DX Editor

ELEANOR WILSON, WIQON
YL Editor

DOROTHY C. ARCHER
Production Assistant

WALTER E. BRADLEY, WIFWH
Technical Information Service

Advertising

LORENTZ A. MORROW, WIVG
Advertising Manager

EDGAR D. COLLINS
Advertising Assistant

Circulation

DAVID H. HOUGHTON
Circulation Manager

HARRY PASTON, WIDJV

HAROLD K. ISHAM, WIMFA
Assistant Circulation Managers

OFFICES

38 La Salle Road

West Hartford 7, Connecticut

TEL.: 3-6268 TWX: HF 88
Subscription rate in United States and Possessions, \$4.00 per year, postpaid; \$4.25 in the Dominion of Canada, \$5.00 in all other countries. Single copies, 40 cents. Foreign remittances should be by international postal or express money order or bank draft negotiable in the U. S. and for an equivalent amount in U. S. funds.

Entered as second-class matter May 29, 1919, at the post office at Hartford, Connecticut, under the Act of March 3, 1879. Acceptance for mailing at special rate of postage provided for in section 1102, Act of October 3, 1917, authorized September 9, 1922. Additional entry at Concord, N. H., authorized February 21, 1929, under the Act of February 28, 1925.

Copyright 1952 by the American Radio Relay League, Inc. Title registered at U. S. Patent Office. International copyright secured. All rights reserved. Quedan reservados todos los derechos. Printed in U. S. A.

INDEXED BY
INDUSTRIAL ARTS INDEX

—CONTENTS—

TECHNICAL—

- A High-Powered Driver-Amplifier for 144 Mc.
E. P. Tilton, WIHDQ 11
- The Siamese Paddle.....*Myron Hexter, W9FKC* 16
- A Phase-Angle Detector for R.F. Transmission Lines
G. Robert Mezger, W2BLL 17
- Two-Element Driven Arrays.....*L. A. Moxon, G6XN* 28
- Antenna-Mast Loading and Guying
Charles Kandel, W2VOU 42
- Constructing Safety Interlocks from Standard Parts
Ronald L. Ives 45
- Simple VFO Construction for the 75-Meter 'Phone Band
Charles McDowell, W4JJX 46
- A 200-Watt for 160..*Robert M. Resconsin, W1TRF* 48
- Technical Topics — "How Come No 160?"..... 60

MOBILE—

- A Quadriband Mobile Transmitter
Charles J. Schauers, W6QLV 24

NOVICE—

- Getting the Most Into Your Antenna
Richard M. Smith, W1FTX 21

OPERATING—

- Recap — DX Contest High Claimed C.W. Scores..... 64

GENERAL—

- Arkansas-Tennessee Tornadoes..*George Hart, W1NJM* 51
- ARRL Articles of Association and By-Laws..... 54

- "It Seems to Us . . ."..... 9
- Quist Quiz..... 10
- Hamfest Calendar..... 10
- Feed-back..... 10
- Silent Keys..... 20
- Happenings of the Month..... 32
- YL News and Views..... 39
- On the Air with Single Sideband 40
- In QST 25 Years Ago..... 60
- The World Above 50 Mc..... 61
- United States Naval Reserve... 64
- How's DX?..... 65
- Hints & Kinks..... 68
- Correspondence from Members. 69
- Operating News..... 70
- With the AREC..... 72
- Station Activities..... 76

hallicrafters

Announces


THE WINNERS!

Here are the "FIRST TEN" Novices who have qualified under Hallicrafters 1951-52 Awards . . . and the winners of the famous Hallicrafters S-76 Receivers!



Here they are . . .

W5TPR	Chuck F. Riker Box 1546, Levelland, Texas	W4TFX	Philip E. Battey 2008 N. Cleveland, Arlington, Va.
W1UBM	Miss Norma Jean Guile 188 Boswell Ave., Norwich, Conn.	W6NGZ	Jack D. Reeder, 1712 Camino Primevera, Bakersfield, Calif.
W6NDP	Ken Lamkin 4717 Huntington St., Fresno, Calif.	W5TFP	Ray Thacker, 725 Cherry Ave., N.W., Ardmore, Okla.
W5TFD	James R. Cromwell R.F.D. 63 N, Lacombe, La.	W8HEV	Thomas J. Woodward, 3792 Montgomery, Detroit 6, Mich.
W4TED	William A. Brown, Apt. C-14, Felton Homes, Macon, Ga.	W5TIQ	Fred G. Apple, Jr. 1615 Gum St., N. Little Rock, Ark.



S-76

You Can Still WIN \$25.00

Remember, every novice who works all states and obtains his General or Conditional Class Amateur License between Sept. 7, 1951, and Sept. 7, 1952, will win \$25.00. For rules governing contacts and verifications, see page 6, "Operating an Amateur Station." Verifications must be postmarked no later than October 7, 1952.

So keep trying . . . and the best of luck!

WORLD'S LEADING MANUFACTURERS OF PRECISION
RADIO & TELEVISION • CHICAGO 24, ILLINOIS

hallicrafters
"The Radio Man's Radio"

Military Performance and Dependability

THE SX-73 COMMUNICATIONS RECEIVER

"A Gibraltar of Stability"

It is the ultimate in all-wave receivers . . . this jewel of precision craftsmanship! Refined in even the smallest detail, the SX-73 meets the tough military communications specifications.

Hallicrafters is proud to place its name on the SX-73.

PRECISION

hallicrafters

SX-73

Frequency Range:

540 kc to 54 Mc in six turret-selected bands.

20 tubes, including rectifier, voltage regulation and ballast tubes.

Dual conversion, 455 kc and 6 Mc crystal controlled.

Receiver type: Single superheterodyne in tuning ranges of 540 kc to 7.0 Mc and dual conversion on tuning ranges from 7.0 to 54.0 Mc.

Types of signals: AM, CW, MCW, ICW, and Carrier Shift Tele-typewriter.

Frequency calibration: 2 tenths of one per cent or less at all frequencies.

Image rejection: Not less than 80 db at any frequency.

Front panel controls: R.F. gain, AC on/off; b.f.o. pitch; audio gain; crystal phasing; selectivity; V.F.O./Crystal; crystal vernier; band selector; frequency; receiver send; CW/modulation; A.G.C./manual; A.N.L./off; antenna adjust.



FRONT VIEW,
SX-73

HALLICRAFTERS • WORLD'S LEADING MANUFACTURER OF PRECISION RADIO & TELEVISION
CHICAGO 24, ILL.

Section Communications Managers of the ARRL Communications Department

Reports Invited. All amateurs, especially League members, are invited to report station activities on the first of each month (or preceding month) direct to the SCM, the administrative ARRL official elected by members in each Section. Radio Club reports are also desired by SCMs for inclusion in *OST*. **All ARRL Field Organization appointments** are now available to League members. These include DKS, OES, OPS, OO and OBS. Also, where vacancies exist SCMs desire applications for SEC, EC, RM, and PAM. In addition to station and leadership appointments for Members, *all amateurs* in the United States and Canada are invited to join the Amateur Radio Emergency Corps (ask for Form 7).

ATLANTIC DIVISION			
Eastern Pennsylvania	W1BVE	John H. DuBois	4105 E. Elbridge St.
Maryland-Delaware-D.C.	W1OMN	James W. Join	79 Fawcett St.
Southern New Jersey	W2UCV	Lloyd L. Gainey	Hoffman Ave. & Marlton Pike
Western New York	W2JIV	Edward Graf	81 King St.
Western Pennsylvania	W3KWL	Ernest J. Hineky	309 Beechwood Ave.
CENTRAL DIVISION			
Illinois	W9KQL	H. F. Lund	3135 S. 5th St.
Indiana	W9DGA	Clifford C. McGuyer	1321 South Governor St.
Wisconsin	W9RQM	Reno W. Goetsch	929 S. 7th Ave.
DAKOTA DIVISION			
North Dakota	W0VKP	Everett E. Hill	1527 Fifth Ave., So.
South Dakota	W0RRN	J. W. Sikorski	1900 South Menlo Ave.
Minnesota	W0MNC	Charles M. Bove	1611 1/2 E. Lake St.
DELTA DIVISION			
Arkansas	W5DRW	Dr. John L. Stockton	P. O. Box 302
Louisiana	W5GHF	Robert E. Barr	Box 440
Mississippi	W5JHS	Norman B. Feehan	P. O. Box 491
Tennessee	W4CXY	Mark M. Howelle	109 Dixie Lane
GREAT LAKES DIVISION			
Kentucky	W4KKG	I. W. Lyle, Jr.	R. R. 3
Michigan	W8DLZ	Norman C. MacPhail	1340 Giddings, S.E.
Ohio	W8AJW	John E. Stringer	2972 Clague Rd.
HUDSON DIVISION			
Eastern New York	W2ILI	Stephen J. Neason	794 River St.
N. Y. C. & Long Island	W20BU	George V. Cooke	88-31 29th St.
Northern New Jersey	W2NKT	Thomas J. Ryan, Jr.	1082 Anna St.
MIDWEST DIVISION			
Iowa	W0PPP	William C. Davis	3rd St.
Kansas	W0ICV	Earl N. Johnston	624 Roosevelt
Missouri	W0GBI	Clarence L. Arundale	1048 South Jefferson Ave.
Nebraska	W0KJP	Guy R. Bailey	111 North 38 St.
NEW ENGLAND DIVISION			
Connecticut	W1HYF	Roger C. Amundsen	RFD 4
Maine	W1PTL	Orestes R. Brackett	Goodrich St.
Eastern Massachusetts	W1ALP	Frank L. Baker, Jr.	91 Atlantic St.
Western Massachusetts	W1EOB	Viktor W. Pasznoff	702 Rogers Ave.
New Hampshire	W1INC	Norman A. Chapman	98 South St.
Rhode Island	W1CIH	Roy B. Fuller	17 Lodge Road
Vermont	W1EFS	Raymond N. Flood	2 Marlboro Ave.
NORTHWESTERN DIVISION			
Alaska	KL2NT	Glen Jefferson	918-3rd Ave.
Idaho	W7WU	Alan K. Ross	2105 Irene St.
Montana	W7KJG	Edward G. Brown	421 Yellowstone Ave.
Oregon	W7MQ	J. E. Roden	519 N. W. Ninth
Washington	W7CZY	Laurence Schring	Route 2, Box 384
PACIFIC DIVISION			
Hawaii	KH6RU	John R. Sanders	c/o Mackay Radio & Tele- graph Co. Inc., Box 2993
Nevada	W7JU	Ray T. Warner	539 Birch St.
Santa Clara Valley	W6JZL	Roy J. Cousin	16615 Englewood Ave.
East Bay	W6JZ	Ray H. Cornell	909 Curtis St.
San Francisco	W6ATO	R. F. Czekowicz	241 Colon Ave.
Sacramento Valley*	W6KCV	Willie van de Kamp	RFD 1, Box 492A
San Joaquin Valley	W6FYM	E. Howard Hale	741 E. Main St.
ROANOKE DIVISION			
North Carolina	W4DLN	J. C. Gosslen	1832 Lodge Ave.
South Carolina	W4ANK	T. Hunter Wood	1702 North Rhett Ave.
Virginia	W4FF	H. Edgar Lindauer	Route 1, Box 431
West Virginia	W8MCR	John T. Steele	
ROCKY MOUNTAIN DIVISION			
Colorado	W0IOZ	Dr. Arthur W. Woods	1939 Uinta St.
Utah	W7UTM	Floyd L. Hinchaw	165 East 4th, North
Wyoming	W7HNI	A. D. Gaddis	P. O. Box 786
SOUTHEASTERN DIVISION			
Alabama	W4GIW	Dr. Arthur W. Woods	411 Woodward Bldg
Eastern Florida	W4FWZ	John W. Hollister	3809 Springfield Blvd.
Western Florida	W4MS	Edward J. Collins	1005 E. Blount St.
Georgia	W4ZD	James P. Born, Jr.	25 First Ave., N.E.
West Indies (Cuba-P.R.-V.I.)	KP4DJ	William Werner	563 Ramon Llovet
Canal Zone	KZ5AW	Everett R. Kimmel	Box 264
SOUTHWESTERN DIVISION			
Los Angeles	W6ESR	Samuel A. Greenlee	1701 Sepulveda Blvd.
Arizona	W7LVR	Albert Steinbrecher	Maple Road, RFD 5, Box 237
San Diego	W6YYM	Mrs. Ellen White	3677 Wightman St.
WEST GULF DIVISION			
Northern Texas	W5BKH	William A. Green	1834 University Blvd.
Oklahoma	W5GVV	Jesse M. Langford	2005 W. Oklahoma Ct.
Southern Texas	W5JFE	Dr. Charles Fermaglich	618 Medical Arts Bldg.
New Mexico	W5NNE	Robert W. Freyman	2255-46th St.
MARITIME DIVISION			
Maritime (Nfld. & Labr. att.)	VE1DO	A. M. Crowell	69 Dublin St.
ONTARIO DIVISION			
Ontario	VE3IA	G. Eric Farquhar	16 Emerald Crescent
QUEBEC DIVISION			
Quebec	VE2GL	Gordon A. Lynn	R.R. No. 1
VALNTA DIVISION			
Alberta	VE6MJ	Sydney T. Jones	10706-57th Ave.
British Columbia	VE7US	Wilf Moorhouse	324 Regina Ave.
Yukon			
PRAIRIE DIVISION			
Manitoba	VE4AM	A. W. Morley	26 Lennox Ave.
Saskatchewan	VE5HR	Harold R. Horn	1044 King St.
			St. Vital Saskatoon

* Officials appointed to act temporarily in the absence of a regular official.

✓ Check up on PR

✓ STABILITY

Stay put with PRs! They're really LOW DRIFT ... without sacrificing high output characteristics. X-ray orientation guarantees uniform cut for maximum low-drift performance ... drift limited to less than 2 cycles per MC per degree.

✓ ACCURACY

Guaranteed accurate within .01 per cent of specified frequency or better. When doubling and quadrupling, accuracy is absolutely necessary. You KNOW where you are with PRs.

✓ POWER OUTPUT

PRs are designed to give maximum power output from the exciter stage. They will stand up under the high voltages and currents common in amateur operation. PRs can "take it" and like it.

✓ ACTIVITY

PRs give you high activity. They "come in" instantly on phone ... key without chirps, even at high bug speeds, without excessive "backing off."



✓ Unconditional GUARANTEE

Every PR Precision CRYSTAL is guaranteed unconditionally by the makers of fine crystals since 1934.


✓ EXACT FREQUENCY AT NO EXTRA COST

You pay no premium for exact frequency (integral kilocycle) within Amateur Bands. PR endeavors to keep its jobbers supplied with EVERY FREQUENCY available to amateurs.

20 METERS, Type Z-3, \$3.75 • 40, 80 AND 160 METERS, Type Z-2, \$2.75

PR

Crystals



USE **PR** AND KNOW WHERE YOU ARE

PETERSEN RADIO COMPANY, INC.
2800 W. BROADWAY • COUNCIL BLUFFS, IOWA

EXPORT SALES ONLY: Royal National Company, Inc., 75 West Street, New York 6, N. Y., U. S. A.

THE AMERICAN RADIO RELAY LEAGUE, INC.,

is a noncommercial association of radio amateurs, bonded for the promotion of interest in amateur radio communication and experimentation, for the relaying of messages by radio, for the advancement of the radio art and of the public welfare, for the representation of the radio amateur in legislative matters, and for the maintenance of fraternalism and a high standard of conduct.

It is an incorporated association without capital stock, chartered under the laws of Connecticut. Its affairs are governed by a Board of Directors, elected every two years by the general membership. The officers are elected or appointed by the Directors. The League is noncommercial and no one commercially engaged in the manufacture, sale or rental of radio apparatus is eligible to membership on its board.

"Of, by and for the amateur," it numbers within its ranks practically every worth-while amateur in the nation and has a history of glorious achievement as the standard-bearer in amateur affairs.

Inquiries regarding membership are solicited. A bona fide interest in amateur radio is the only essential qualification; ownership of a transmitting station and knowledge of the code are not prerequisite, although full voting membership is granted only to licensed amateurs.

All general correspondence should be addressed to the administrative headquarters at West Hartford, Connecticut.



Past Presidents

HIRAM PERCY MAXIM, W1AW, 1914-1936
EUGENE C. WOODRUFF, W8CMP, 1936-1940
GEORGE W. BAILEY, W2KH, 1940-1952

Officers

President GOODWIN L. DOSLAND, W0TSN
Moorhead, Minn.
First Vice-President WAYLAND M. GROVES, W5NW
P.O. Box 586, Odessa, Texas
Vice-President FRANCIS E. HANDY, W1BDI
38 LaSalle Road, West Hartford, Connecticut
Secretary A. L. BUDLONG, W1BUD
38 LaSalle Road, West Hartford, Connecticut
Treasurer DAVID H. HOUGHTON
38 LaSalle Road, West Hartford, Connecticut
General Counsel PAUL M. SEGAL
816 Connecticut Ave., Washington 6, D.C.
Assistant Secretaries JOHN HUNTOON, W1LVQ
RICHARD L. BALDWIN, W1IKE
38 LaSalle Road, West Hartford, Connecticut

DIRECTORS

Canada

ALEX REID VE2BE
240 Logan Ave., St. Lambert, P. Q.
Vice-Director: William W. Hutchart VE6LQ
10740 107 St., Edmonton, Alta.

Atlantic Division

ALFRED C. HECK W3GEG
515 Cedar Ave., Sharon, Pa.
Vice-Director: Charles O. Budgett W3LVF
725 Garden Road, Glenside, Pa.

Central Division

WESLEY E. MARRINER W9AND
844 N. Galena Ave., Dixon 7, Ill.
Vice-Director: Charles F. Reberg W9MVZ
3900 W. 10th Ave., Gary, Ind.

Dakota Division

ALFRED M. GOWAN W0PHR
325 S. Menlo Ave., Sioux Falls, S. D.
Vice-Director:

Delta Division

JAMES W. WATKINS W4FLS
220 N. Howell Ave., Chattanooga, Tenn.
Vice-Director: George S. Acton W5HMM
Plain Dealing, La.

Great Lakes Division

JOHN H. BRABB W8SPF
417 Ford Bldg., Detroit 26, Mich.
Vice-Director: Harold E. Stricker W8WZ
247 W. 5th St., Marysville, Ohio

Hudson Division

JOSEPH M. JOHNSTON W2SOX
423 Monmouth Ave., Bradley Beach, N. J.
Vice-Director: George V. Cooke, Jr. W2OBH
88-31 239th St., Bellerose 6, L. I., N. Y.

Midwest Division

WILLIAM J. SCHMIDT W0OZN
306 S. Vassar, Wichita, Kansas
Vice-Director: James E. McKim W0MVG
1404 S. Tenth, Salina, Kansas

New England Division

PERCY C. NOBLE W1BVR
37 Broad St., Westfield, Mass.
Vice-Director: Frank L. Baker, Jr. W1ALP
91 Atlantic St., North Quincy 71, Mass.

Northwestern Division

R. REX ROBERTS W7CPY
837 Park Hill Drive, Billings, Mont.
Vice-Director: Karl W. Weinkarten W7BG
3219 N. 24th St., Tacoma 7, Wash.

Pacific Division

KENNETH E. HUGHES W6CIS
810 W. Orange Ave., So. San Francisco, Calif.
Vice-Director: Richard F. Czekowitz W6ATO
243 Colon Ave., San Francisco 12, Calif.

Rio Grande Division

WILLIAM H. JACOBS W4CVQ
Route 6, Raleigh, N. C.
Vice-Director: Gus M. Browning W4BPD
135 Broughton St., S. E., Orangeburg, S. C.

Rocky Mountain Division

FRANKLIN K. MATEJKA W0DD
P. O. Box 212, Estes Park, Colo.
Vice-Director: Ramon S. Walker W0QWP
P. O. Box X, Brush, Colo.

Southeastern Division

LAMAR HILL W4BOL
104 Myrtle, Cochran, Ga.
Vice-Director: Ernest W. Barr W4GOR
911 Rosemary Ave., SW, Atlanta, Ga.

Southwestern Division

JOHN R. GRIGGS W6KW
10412 Don Pico Rd., RFD 2, Spring Valley, Calif.
Vice-Director: Walter R. Jook W6EKM
1315 N. Overhill Drive, Inglewood 3, Calif.

West Gulf Division

A. DAVID MIDDLETON W5CA
9 Kay Road, Tijeras, N. M.
Vice-Director: Frank E. Fisher W5AHT/AST
104 E. 11th, Pawhuska, Okla.

"It Seems to Us..."

NEW CHARTER AND BY-LAWS

When the American Radio Relay League resumed activity at the close of World War I, it was operating under a constitution which provided for the government of our affairs by a Board of seventeen directors elected by the membership. But every member of the Board was a director-at-large, elected by popular vote of the entire membership and usually nominated by the Board itself; five of the directors thus elected were also paid officers on the Hq. staff. As the League grew our leaders foresaw the desirability of more democratic government which would provide for regional representation, with each director elected by and responsible to the membership in his particular region or division. This was a cause largely championed by the late Kenneth B. Warner. On December 18, 1923, the Board adopted a new Constitution & By-Laws, drafted by Warner and the Executive Committee to accomplish the desired ends, and the Board in effect voted itself out of office to be replaced by new men nominated and elected by each division.

The 1923 Constitution and By-Laws has served the League, and well, for nearly thirty years. But over that period many minor changes were made here and there by the Board to remedy particular situations — changes in the mechanics and dates of elections, filling of director vacancies, eligibility requirements and interpretations, etc. Although the fundamental principles remained constant, the effect was to build on the sound structure a series of "cupolas" which eventually became confusing and in some cases actually conflicting, were not properly by-laws of a corporation in others, etc. At its 1950 meeting the Board set up a Constitution Revision Committee to study the problem; the Committee, with the assistance of the General Counsel, did its job well — so well in fact that the Board at its 1951 meeting adopted the draft of new Articles of Association almost without change, and at its meeting just held in May completed the job by adopting, effective July 1, 1952, the draft of new By-Laws and supplementary regulations also almost without amendment.

The basic concept of the League's structure

and government remains unchanged. Those principles which are unchanging are embodied in the Articles of Association — the purposes of the ARRL as a non-profit membership association, the government of our affairs by a Board elected by members to represent their divisions, the authority of the Executive Committee (which now includes one director) in the intervals between Board meetings, the barring of membership on the Board to those with commercial interests, and the like. In the By-Laws are those provisions which may need change from time to time to meet our future needs — divisional boundaries, the mechanics of elections, dues rates, meeting dates, standing committees, etc. Supplementary rules and regulations state League policy in matters of conventions and affiliated clubs, and now in process of formation are rules and regulations governing the Communications Department.

Beginning on page 54 of this issue we publish in their entirety the texts of the new instruments of government of your League. They merit your careful reading.

NOVICE PROMOTION

Do you have a friend or acquaintance you're trying to interest in ham radio, but you can't get the bug to bite quite deeply enough? Precisely the push he needs may be furnished by a new promotional booklet the League has just produced, entitled "You Can Be There."

In two colors, and pocket-size for ease in handling and distribution, the booklet points up the Novice Class license not only for the enjoyment of two-way radio communications but also as a stepping-stone to a professional electronics career in industry or military service. Part of the promotional campaign undertaken at the instructions of the Board of Directors, it has had a first printing of 100,000 copies which are currently being distributed in quantities through youth organizations, civic and educational groups, and through electronics manufacturers and distributors.

We call it to your attention not only as information but also so that you may make use of it in your own activities if desired. Should you be promoting amateur radio in a local Boy Scout troop, for example, we'll be glad to send you sufficient copies for individual distribu-

tion. Should you be giving a talk on amateur radio before civic clubs and the like, you might want copies to distribute afterwards to interested members of the audience. Perhaps you will want to contact science instructors in the local schools to see if classes or after-hour clubs would be suitable recipients. Though too expensive to be left in quantity on a public counter as "throw-aways," we'll gladly furnish any reasonable number of copies you request provided you indicate how the booklets are to be used.

We think the booklet does a pretty good job of creating an initial interest in amateur radio on the part of casual readers, and will help accomplish the aim of attracting numbers of new people into our game through the Novice license.

FEED-BACK

In W6OWP's article, "A Beat-Frequency Exciter for Better C.W. Signals," in the June issue, L_1 in the caption under Fig. 1 on page 12 should have a diameter of $\frac{7}{8}$ inch instead of $\frac{1}{8}$ inch. Last-minute revisions in the circuit of Fig. 2 on page 13 conspired to scramble the capacitance values. The caption should read as follows: C_1, C_2 — 100- μ fd. trimmer; C_3, C_6, C_7, C_8 — 0.01- μ fd. disk ceramic; C_4 — 0.1- μ fd. 600-volt paper; C_5 — 100- μ fd. mica; C_9 — 100- μ fd. variable.

Quist Quiz

A tested his 'phone transmitter with a 100-watt lamp used as a dummy load, and observed that the brilliancy of the lamp increased as he spoke. This is proper, he reasoned, because the total output power increases with modulation. However, he notices that the S meter on his receiver stands still on any 'phone signal except those where controlled carrier is used, and he reasons that the S meter should kick up with modulation just as the lamp does, if the S meter is an indication of the power of the received signal. B tells him that the S meter doesn't kick up because it is in a circuit with a long time constant and consequently can't kick up except under sustained modulation. Who is right?

(Please turn to page 110 for the answer)

COMING A.R.R.L. CONVENTIONS

- July 4th-6th — Pacific Division, San Francisco, Calif.
- Sept. 5th-7th — Dakota Division, Minneapolis, Minn.
- Sept. 14th — Vermont State, Burlington, Vt.
- Sept. 27th — New Hampshire State, Nashua, N. H.
- Oct. 3rd-5th — Hudson Division, Albany, N. Y.
- Oct. 11th — Roanoke Division, Richmond, Va.

HAMFEST CALENDAR

ALASKA — Saturday and Sunday, August 2nd and 3rd, at Copper Center Roadhouse, Fairbanks — the All-Alaska Hamfest. Plenty of mobile activity is expected, and a special calling frequency of 3892 kc. has been established for the Hamfest. For further details contact KL7NT.

ARKANSAS — Sunday, July 13th, at Lake Conway, 8 miles south of Conway on U. S. Highway 65 — an Arkansas hamfest sponsored by the Conway Amateur Radio League. The hamfest will be picnic style, and officials of CAP will be on hand to discuss communications in the CAP. For further details, write to WN5TIC, 340 Davis St., Conway.

CALIFORNIA — Saturday, August 9th, at Wieland's Brewery, San Jose — the third annual Central California Barbecue, sponsored by the Santa Clara County Amateur Radio Association. Festivities start at 3 p.m., with dancing at 8 p.m. Registration fee is \$3.00, with a chance at a mobile converter for those who register prior to August 3rd. Make registrations to SCCARA, P. O. Box 6, San Jose.

IDAHO — Friday, Saturday and Sunday, Aug. 2nd, 3rd and 4th, the annual meeting of the WIMU and convention at Big Springs, Idaho. This is the annual get-together of the amateurs in Wyoming, Idaho, Montana, and Utah. A full program is planned, and adequate accommodations are available at dude ranches, lodges and inns. The site of the meeting is near Yellowstone Park, so fit it into your vacation plans. For further information write to Mrs. R. Earl Dawes, Box 663, Bozeman, Montana.

ILLINOIS — Friday, July 4th, at the clubhouse grounds of the Egyptian Radio Club — the Annual Picnic and Hamboore. The club grounds are located one block south of new Chain of Rocks Canal Bridge on highway 66 between Mitchell, Ill., and the Mississippi river. No admission charge. Food and drinks available. Contests and awards.

ILLINOIS — Sunday, August 10th, at Frankfort Park (on U. S. Rt. 45, one-half mile north of U. S. 30) — the Eighteenth Annual Picnic of the Hamfesters Radio Club, advertised as the friendliest get-together in the west. Food, ice cream and beverages available. Treasure hunt and games for the kiddies. Prize table Hamfesters style. For tickets write J. J. Ruth, W9GVO, 4460 Oakwald Ave., Chicago 15, Ill. Donations \$1.50.

INDIANA — Sunday, July 31st, at Brookside Park in Indianapolis — picnic of the Indiana Radio Club Council sponsored by the Indianapolis Radio Club. \$1.00 registration, with games and awards for young and old.

MAINE — Saturday, July 26th, at the Eastland Hotel in Portland — the Fourth Annual Down East Hamfest. Registration will start at 11:00 a.m., with the banquet at 6:30 p.m. The registration fee is \$4.50, and advance reservations should be made with Lee Johnson, W1QIQ, 92 William St., Portland.

MICHIGAN — Sunday, July 27th, at Kensington State Park, 20 miles Northwest of Detroit, near Milford — the second annual picnic of the Inter-County Amateur Radio Club. There will be swimming, games and transmitter hunt, special awards for the ladies and children. A Johnson Viking wired, tested and complete with tubes, will be among the many valuable items awarded. Tickets are \$1.00 each. Bring your lunch and come early. Get your tickets at the picnic or write to W8HYM, 17303 Lenore, Detroit 19, Mich.

VIRGINIA — Sunday, Aug. 3rd, at the Dickey Ridge picnic grounds on the Skyline Drive, near the Front Royal entrance — the second annual hamfest of the Shenandoah Valley Amateur Radio Club. Registration is \$1.00, with a fried chicken dinner available for an extra \$1.25. There will be plenty of activities and awards, and all registrations should be made prior to July 25th. Write the Shenandoah Valley Amateur Radio Club, P. O. Box 139, Winchester, Va.

WYOMING — Saturday and Sunday, July 19th and 20th, at South Fork Camp on Powder River in the Big Horn Mountains — the Annual Wyoming Hamfest for 1952, sponsored by the Casper Radio Amateur Club. The only charge will be for the banquet and lodging. For further details, write to Lial D. Branson, W7AMU, 342 South Elk St., Casper, Wyoming.

A High-Powered Driver-Amplifier for 144 Mc.

An All-Tetrode Transmitter Design for the V.H.F. Enthusiast

BY EDWARD P. TILTON,* W1HDQ

IN the course of the TVI program currently underway in the Headquarters Lab, there arose a need for a 2-meter rig that would be capable of generating something approaching the legal limit of power, to check overload characteristics of representative TV receivers. More than two years' experience with the 450-watt rig at W1HDQ¹ had shown it to be substantially free of TVI on 144 Mc. when operated in the presence of a usable TV signal from our semi-local Channel 6 station. Would jacking the power by another 3 db. make any difference? The 144-Mc. powerhouse shown here was built to find out.

Many hours of tests at up to 800 watts input have shown that it doesn't; that, if reasonable precautions are taken in design and construction, TVI problems are not greatly complicated by the use of high power in the 2-meter station, so long as the rig is not amplitude-modulated. Even with a.m., TVI potentialities do not go up with power as rapidly as one might think. The crux of the matter seems to be that 2-meter TVI is caused not by the 144-Mc. r.f., but by harmonics of lower-frequency stages that fall in the TV channels, and by audio circuit pick-up closely akin to the midget-receiver BCI that has been with us for years. There are high-band image problems in some older receivers, and occasional beats with other frequencies in use locally, but in our experience with current production receivers we've found little evidence of r.f. interference from pure 144-Mc. radiation, even with several hundred watts in a horizontally-polarized

array just a very few feet from the TV antenna.

In most 2-meter work few of us need or even desire really high power. We seldom have to beat down others on the same frequency, but there are times when it's nice to be able to pour it on. In aurora DX work, for example, it has been almost universally true that the high-powered stations work the choice stuff.


If facilities are not available for modulating the full power capabilities of the rig, input can be dropped to 200 watts or less with little change in efficiency. Just because the transmitter is capable of close to a kilowatt input is no reason that it must be run that way. And if we've been in the habit of straining to get the utmost out of 2-meter gear by running it almost to the limit of endurance (and sometimes beyond!), it is comforting to be able to generate a sizable signal with everything running well below its ratings.

Three push-pull stages are used, beginning with a pair of RCA 5763s which triple from 48 to 144 Mc. If a 2-meter rig capable of putting out 5 to 10 watts is already available, this stage can be omitted, and only the two 144-Mc. stages built into the assembly. The first is a dual-tetrode amplifier using an Amperex AX-9903. With some modification of the circuits, an 829B might be used, but the lower input and output capacitance of the 9903 make it preferable. An 832A may be used interchangeably with the 9903, but care is necessary to avoid exceeding its ratings; so the larger tube is recommended. The final stage uses a pair of Eimac 4-125As, with a low-C tank circuit made of copper tubing. The manufacturer's ratings allow slightly over 600 watts input on plate-modulated 'phone and 800 watts on c.w. at 150 Mc.

* V.H.F. Editor, QST.

¹ Chambers, "450 Watts on V.H.F.," QST, September, 1949, p. 22. Also ARRL *Handbook*, 27th, 28th, and 29th editions.

Panel view of the high-powered 2-meter transmitter. At the bottom left are the filament switches and the knob for the screen-neutralizing adjustment. The two knobs, lower right, are the tripler and driver plate tuning, ganged, and the antenna coupling adjustment. Jacks in the tripler-grid, driver-grid and driver-cathode circuits are at the far right. The large knob at the upper center is for turning the plate tuning capacitor.






Fig. 1 — Wiring diagram and parts list for the high-powered 144-Mc. transmitter.

C₁, C₂ — 10- μ fd. per-section butterfly variable (Cardwell ER-6-BF/S. Johnson 10LB15 alternate; see text).

C₃, C₄ — 10- μ fd. mica.

C₅, C₆ — 0.001- μ fd. disk ceramic.

C₇ — 0.005- μ fd. disk ceramic.

C₈ — 50- μ fd. per-section split-stator variable (made from Millen 19140; see text).

C₉ — Plate-line tuning adjustment (made from neutralizing condenser; see text).

C₁₀ — 0.001- μ fd. 5000-volt mica.

C₁₁ — 0.25- μ fd. tubular.

R₁ — 150,000 ohms, 1 watt.

R₂ — 18,000 ohms, 1 watt.

R₃ — 100 ohms, $\frac{1}{2}$ watt.

R₄ — 10,000 ohms, 1 watt.

R₅ — 100 ohms, 1 watt.

R₆ — 10,000 ohms, 10 watts.

R₇ — 5000 ohms, 10 watts.

R₈ — 27,000 ohms. Use only if needed; see text.

L₁ — 1 turn No. 14 enam., $\frac{3}{8}$ -inch diam.

L₂ — 6 turns each side of center, No. 20, $\frac{3}{8}$ -inch diam., spaced wire diam., $\frac{1}{2}$ -inch space at center for L₁ (B & W Miniductor No. 3907).

L₃ — 2 turns No. 14 enam., spaced $\frac{1}{8}$ inch, $\frac{1}{2}$ -inch diam.

L₄ — 2 turns No. 14 enam., spaced $\frac{3}{8}$ inch, $1\frac{1}{2}$ -inch diam.

Electrical and Mechanical Features

The exciter needed to drive the tripler is not shown, as plans call for a general-purpose v.h.f. exciter to be built later. For the present, a small 50-Mc. unit described in the 1952 ARRL *Handbook*² is being used, but almost anything capable of 3 to 5 watts output on 48 Mc. should serve. If the exciter has no stages operating lower in frequency than 24 Mc., a prolific source of TVI in the form of unwanted harmonics can be eliminated.

The tripler circuit is extremely simple, but it supplies the necessary drive for the 9903 amplifier with ease. The plate circuits of these two stages are gang-tuned. They may not track accurately over large frequency changes, but the 2-meter operator seldom jumps around the band extensively, and if a major change is required, the inductances can be altered by spreading or squeezing the turns to take care of tracking. By slight rearrangement of parts the tripler could be tuned by a separate control. Straps of flashing

L₅ — 2 turns No. 18 push-back, close-spaced, inserted between turns of L₄.

L₆ — Loop of No. 14 enam., 4 inches long, inside L₇.

L₇ — Copper strap $\frac{3}{16}$ inch wide and 8 inches overall from grid to grid; see text and bottom-view photograph.

L₈ — Plate line, $\frac{3}{8}$ -inch o.d. copper tubing 12 inches long, spaced $1\frac{1}{8}$ inches center-to-center. Bend on 1-inch radius to make inverted "L" $4\frac{1}{2}$ inches high.

L₉ — Output coupling loop, made from $13\frac{1}{2}$ -inch piece of No. 14 enam. Sides $\frac{3}{8}$ inch spaced. Vertical portion $2\frac{1}{2}$ inches high.

L₁₀ — 5-hy. (min.) choke, 100 ma. or more rating.

J₁, J₂, J₃ — Closed-circuit jack.

J₄ — Coaxial fitting.

J₅ — Crystal socket for output terminal.

MA₁, MA₂, MA₃, MA₄ — External meters, not shown in photographs, 200, 50, 100 and 500 ma., respectively.

RFC₁, RFC₂, RFC₃, RFC₄, RFC₇ — 1.8- μ hy. solenoid v.h.f. choke (Ohmite Z-144).

RFC₅, RFC₆ — 7- μ hy. solenoid v.h.f. choke (Ohmite Z-50).

Si, S₂ — S.p.s.t. toggle switch.

T₁ — 6.3-volt 4-amp. filament transformer.

T₂ — 5-volt 13-amp. filament transformer (Chicago FO-513).


copper $\frac{3}{16}$ inch wide are used for the leads from the 5763 plates to the stator terminals of C₁, to hold down lead inductance.

It will be noted from the bottom view that copper sheets are mounted on the bottom surface of the chassis covering the area of the driver and final stages, to improve grounding conductivity. Only one other element of novelty appears in the driver stage: the grounding of the rotor of C₂ through a 100-ohm resistor, R₅. Originally this butterfly capacitor was mounted on an aluminum bracket, grounding the rotor directly, but the resistor was substituted to stop a 250-Mc. parasitic oscillation. The rotor is now mounted on a polystyrene plate. The rotor of C₁ is grounded directly to the aluminum bracket that also serves as a mounting for the 9903 socket. Note that ventilation holes are drilled through the copper plate and chassis just above the driver tube.

Plate leads for the 9903 should be very pliable material, silver or copper ribbon preferred to braid. The glass seal around the plate pins is fragile, so there should be no mechanical strain.

² ARRL *Handbook*, 29th edition, p. 402.

Rear view of the 4-125A amplifier for 144 Mc., showing details of the parallel-line plate circuit. The 5763 tripler tubes are at the left. Note ventilation holes, below which is mounted the driver tube, out of sight under the chassis.



Standard heat-dissipating connectors must be filed down by about one-third of their total diameter, because of the close pin spacing on the 9903. Cardwell butterfly capacitors were selected for C_1 and C_2 because of their provision for ganging. Should these not be available, other types including the Johnson 10LB15 can be substituted by soldering a ganging extension on the rear end of the rotor shaft of C_2 .

Mounting the driver-plate and final-grid circuits so as to permit direct inductive coupling was ruled out in favor of separated circuits and link coupling, as shown. This reduces capacity coupling and makes the transferring of unwanted harmonics to the amplifier less likely. With low-drive tetrodes, even a small amount of energy (such as the 9th harmonic of a 6-Mc. crystal or the 8th harmonic of a 24-Mc. stage, examples of TVI possibilities in Channels 2 and 9 or 10) can be passed on and amplified if there is appreciable capacity coupling. This precaution can be carried further by providing link coupling between the tripler-plate and driver-grid circuits, and if Channels 9 or 10 are in use in the builder's locality this might be a desirable procedure.

The final stage has several novel features. The relatively high input and output capacitances of the 4-125As rule out conventional coil-and-condenser circuits at 144 Mc., so no grid tuning capacitor is used, and only a very small variable capacitance is used across the plate line. The entire grid circuit is made of $\frac{5}{16}$ -inch copper strip. Two pieces $1\frac{1}{2}$ inches long connect the grid terminals to feed-through bushings that are provided for neutralizing tabs, if needed. The center portion is an egg-shaped loop also mounted on the feed-throughs, as seen in the bottom view. The bushings are mounted near the inner corners of the tube sockets, in holes that are drilled larger than needed to pass the ceramic portions of the bushings, to keep grid-to-ground capacitance to a minimum. More about these later.

The most critical neutralizing adjustment is provided by the variable screen-to-ground capacitor C_3 , a split-stator variable the rotor of which is grounded through a metal mounting

pillar between the two sockets. A modified single-section unit was used because its construction assured a symmetrical path from rotor to ground for each half of the assembly. It can be made from any of several standard single-section variables having ceramic supports at both ends.

A strap of brass or aluminum is first screwed to the metal mounting brackets at each end, tying them together electrically and mechanically. Then the stator bars are sawed in half, leaving an equal number of plates on each side. A Millen double-end-plate variable (19140) was used, but 100- μ fd. models would serve equally well, as the required neutralizing capacitance turned out to be about 30 μ fd. on each side. The 19140 had 9 plates each on the stator and rotor originally. The middle stator plate was cut out, and the front-end rotor plate removed, leaving a split-stator condenser with 4 plates on each stator and 8 on the rotor. The two screen terminals on each socket are strapped together, and connection to the stators is made with copper strap. Symmetry and low inductance are extremely important here.

The screen circuit also includes two solenoid-type r.f. chokes connected directly to the screen terminals. These are under C_3 and do not show in the photograph. Their common connection is by-passed, and a small filter choke is inserted in the screen-voltage lead for modulation purposes. The screen variable capacitor is driven through two universal-joint couplings to bring the drive shaft and knob out to a position that provides a balanced front panel appearance.

At first the amplifier was operated with resistor bias only, but this had certain disadvantages. There was a tendency to hum around the operating frequency during stand-by periods, and there was no means of cutting off the final plate and screen current when excitation was removed. Fixed bias is provided without the use of batteries or an external bias supply by inserting a voltage-regulator tube in series with the grid leak and by-passing the tube with a low-leakage capacitor. When the gas tube fires with application of excitation, C_{11} charges. Removing the excitation stops

the current flow through the VR tube and leaves the charge in C_{11} applied to the 4-125A grids. This is sufficient to cut off the plate and screen current until the capacitor discharges. The length of the cut-off period depends on the leakage characteristics of C_{11} and associated wiring. With an ordinary 0.25- μ fd. paper tubular, there is no plate and screen current for a minute or more. A 1- μ fd. transmitting-type condenser kept the amplifier cut off for several minutes. Some experimentation with C_{11} may be necessary, and there must be very low d.c. leakage losses in the entire grid-to-ground circuit. An external bias source of 90 volts or more may, of course, be substituted.

The construction of the final plate circuit is obvious from the top-view photograph. The tuning device, C_9 , is made from parts of a standard neutralizing capacitor (Millen 15011) mounted on 4-inch ceramic stand-offs (National GS-4) in the center of the chassis. The lead screw on the adjustable plate is extended by means of a short length of $\frac{1}{4}$ -inch diameter brass rod soldered to its end, and this is connected through an insulating coupling and a polystyrene rod to a knob on the front panel. This tuning arrangement provides no logging scale or reset indicator of any sort, but it results in a very worthwhile improvement in tank-circuit efficiency over conventional tuning methods.

The copper tubing tank circuit is mounted in place by means of straps of aluminum wrapped around the lines and fastened to the top of the stand-offs. Connection to the tube plates is made with $\frac{3}{4}$ -inch-wide copper straps that are bolted to the plate lines. No solder is used anywhere in this plate line assembly; the heat dissipated at the tube end of the line would be sufficient to melt soldered connections. The heat-dissipating connectors for the 4-125A plates were cut down to four fins high to reduce plate lead length. Just beyond the stand-off insulators and C_9 the plate lines are bent to a vertical position around a radius of about one inch, the bottom of the line ending about a half inch above the chassis. Here an adjustable strap of flashing copper is wrapped around the lines, and an r.f. choke is connected through a lug to a feed-through bushing carrying the high-voltage d.c.

Details of the antenna coupling loop are visible in the top view. The pick-up loop is made adjustable by mounting it through a polystyrene rod that can be rotated from the front panel. This rod passes through a shaft bearing and a tension adjusting device (National SB and Millen 10061) mounted on a small aluminum bracket. Note that a short length of rod is fastened at the top of the loop, so that no adjustment of the coupling will allow it to come in contact with the line electrically.

Adjustment and Operation

This rig contains its own filament transformer so only plate and screen supplies are external. These should be capable of furnishing 250 volts at 75 ma. for the tripler, 400 volts at 200 ma. for

the driver, 300 to 400 volts at 75 ma. for the final screens, and 1000 to 2000 volts at 400 ma. for the amplifier plates. The screens of the final and the driver plates may be run from the same supply, though a more flexible set-up is possible if the voltage applied to the final screens is adjustable separately.

The tripler should be tuned up first. Plug a low-range milliammeter in the tripler grid current jack, J_1 , and apply grid drive through a coaxial cable and J_4 . Adjust the spacing between the two halves of the grid coil, L_2 , and the position of L_1 , for maximum grid current. This should be 1 to 2 ma. Transfer the meter to the driver grid jack, J_2 , and apply plate voltage through R_3 , tuning C_1 for maximum grid current, which should be between 3 and 5 ma. The inductance of L_3 should be adjusted so that the low end of the band is reached with C_1 set somewhere between the mid-point and the maximum end of its range. Total plate-screen current to the 5763s need not be more than about 50 ma.

Next, tune C_2 through resonance and note whether the grid current changes. Should it dip down at resonance the stage will require neutralization.

This is unlikely with the 9903, however, as this tube is so designed as to be inherently neutralized at frequencies around 150 Mc. Next, plug a 200-ma. meter into J_3 , or connect one externally in series with the plate-screen supply, as shown in Fig. 1, and apply plate voltage, preferably with a lamp load coupled to L_4 . If the stage is working correctly, it should be possible to light a 40-watt lamp to full brilliance. Check for self-oscillation by removing excitation briefly. To protect the 9903, it might be well to make these initial tests at 250 volts or so, increasing to 400 to 500 volts only when the stage is found to be working correctly.

Next, couple the output from the driver stage to the grid circuit of the final, by means of a coaxial cable and L_5 and L_6 . The latter should be the same general shape as L_7 , and mounted inside or just above it, with about $\frac{1}{8}$ -inch separation. The resonant frequency of the grid circuit can be changed slightly by altering the shape of the grid inductance. Squeezing the sides together raises the frequency; making the tank more nearly round lowers it. When the circuit is properly resonated, it should be possible to develop 25 to 30 ma. grid current, measured in series with the VR tube and ground (MA_2 in Fig. 1). The setting of the screen-to-ground capacitor, C_8 , will affect the grid current, but it may be set approximately to the proper point by adjusting it for maximum grid current with the plate voltage off. The total plate and screen current to the 9903 should be 175 to 200 ma. When the coupling loops at both ends of the coax have been adjusted so as to give maximum grid current, adjust the turn spacing of L_4 so that its tuning capacitance will be the same as that of C_1 . The two condensers may then be ganged by means of flexible couplings and an insulating shaft.

Now we are ready to adjust the final stage. Connect a 100-watt lamp at the output terminals and apply about 500 volts to the final plates and 200 or less to the screens, metering both circuits as shown in the schematic diagram. Adjust C_9 for maximum output, watching the grid and plate meters. Move the setting of the screen adjustment in small steps until maximum output, minimum plate current, and maximum grid current all occur at the same setting of the plate tuning. This is the screen adjustment at which the amplifier will operate most stably. Neutralization can also be done by running the amplifier without excitation, adjusting C_8 until there is no evidence of oscillation, but this gives a broader indication than the first method.

Should it be impossible to achieve complete stability by the screen adjustment alone, it may be necessary to add grid-plate capacitance by mounting stiff wires or tabs on the feed-through bushings. In our amplifier, the capacitance added by the feed-through rods alone was just about the right amount, however. This is not the conventional cross-over neutralization, but rather additional grid-plate capacitance. The amount of capacitance added is adjusted in the same way as for triode neutralizing circuits of the crossover type.

Once the amplifier is stabilized at low voltages, we proceed to final checks at normal plate and screen operating conditions. A suitable load for high-power tests is something of a problem, as no lamp combination represents a load that simulates an antenna system at this frequency. A fair load can be made, however, by connecting three or four 100-watt lamps in parallel. Lamps larger than the 100-watt variety are useless for load purposes, as they tend to develop filament hot spots and burn out before reaching anything like normal brilliance.

A method of varying the screen voltage continuously is extremely useful at this juncture, as the final tubes can be made to draw any desired

plate current by suitable variation of the screen voltage. Adjusting a tetrode amplifier is a more complex process than with triodes, and the screen is the critical element. Screen dissipation should be watched closely to see that it does not run much over 20 watts in plate-modulated service or 30 watts on c.w., and it is strongly recommended that a screen-current meter be made a permanent part of the metering system. Efficient operation is possible over a range of 800 to 2500 volts on the plates; the efficiency running better than 50 per cent in our measurements. Power was measured with a u.h.f. wattmeter, so the figures represented the power that can be delivered to an antenna transmission line. Lab tests were made at up to 900 watts input.


The tetrode amplifier with separate screen voltage supply should *never* be operated without load, or with no plate voltage applied. Screen dissipation is certain to be excessive with plate voltage removed. Here we must throw out one of our most cherished indications of amplifier efficiency, the unloaded plate-current dip at resonance. To operate a rig like this without load is to invite tube failure, soon!

Tests with the lamp load should be monitored for freedom from modulation. With some types of chokes for L_{10} , there may be a tendency to oscillation at some audible frequency. Should this develop, it can be damped by loading the choke slightly with a resistor, as shown by R_8 in Fig. 1. The highest value of resistance that will stop the oscillation should be used, if any is necessary. Substituting another choke is a better method. It should have a minimum of 5 henrys inductance, but a wide variety of small filter chokes may be satisfactory.

In prolonged tests in the Headquarters Lab, and on the air at WHDQ, this transmitter has demonstrated its ability to run smoothly at the manufacturer's maximum ratings for the frequency, 600 watts input on 'phone and 750 to

(Continued on page 112)

Looking under the chassis of the high-power 2-meter rig. At the lower right are the components of the tripler stage, with the AX-9903 driver tube just above the aluminum partition. The 4-125A sockets, grid circuit, and screen-neutralization capacitor are at the left. The VR-tube bias system is mounted on the rear chassis wall.



The Siamese Paddle

A Key To Key the Keyer

BY MYRON HEXTER,* W9FKC

ALMOST anyone who has built an electronic keyer has gone through the experience of discovering, usually after completing the electronic part, that the control mechanism—the switch, or key—can be much more of a problem. A glance at the circuit of one of these devices fails to show why an old hacksaw blade wouldn't do the trick. But this is far from the truth. Positive and reliable control requires a considerable degree of mechanical refinement, as attested by the fact that a ham will often chop up a twenty-dollar bug to get the few essential parts he needs. Satisfactory homemade substitutes require greater than an ordinary amount of skill with tools.

However, I recently discovered that there is a very simple solution to the problem. A pair of ordinary inexpensive straight keys can be made into a de luxe keyer control in less than an hour, if you don't insist on trimming it up. It not only supplies a good wobble-free mechanism, but it also provides for convenient adjustment of tension and contact spacing, satisfying the most finicky operator.

As the photograph shows, it is simply a matter of mounting the two keys back to back in a vertical position. The keys shown in the photographs are Type J-38, selling in surplus for as low as 85 cents each, although almost any other type can be adapted. The J-38s are particularly suitable because they come mounted on bakelite bases, one of which can be put to use since most electronic-keyer circuits require insulation for all three terminals of the control.

Construction

First remove the two keys from their bases, strip one of the bases of the remaining hardware and remove the shorting levers from both keys. It may be necessary to lift the key arm out of


• Most of those who have built electronic keyers will tell you that the toughest part of the job is getting a smooth-working keying mechanism. In this article, W9FKC comes up with an answer so effective, and yet so simple, that you will say, "I wonder why someone didn't think of that before."

its bearings to get at the screw holding the lever. Now place the keys on edge, with their bottoms facing, and clamp them together with a 6-32 machine screw through the upper mounting-screw hole. Using another 6-32 screw through the lower mounting hole, fasten a 1-inch hardware-store angle piece on each side with the legs extending outward. (The brass-plated pieces usually found in hardware stores, but less often in dime stores, make a much neater job than the common iron variety.) Make sure that the strap connecting the stationary key contact to its terminal doesn't short against the angle piece.

The front end of the assembly is supported on 1½-inch hardware-store angle pieces. One leg of each of the two pieces is shortened by cutting it off about midway between the two holes. One of these angle pieces is then fastened to the lower terminal of each key, using the terminal cap screw through the top hole in the longer leg of the angle piece. The short legs should point inward.

One of the J-38 bakelite bases is then marked and drilled to fit the holes in the feet of the mounting angles. The key should be placed with the feet approximately centered on the base. The holes should be well countersunk underneath so that flat-head mounting screws do not protrude.

(Continued on page 114)



By simply mounting two standard keys back to back in this fashion you can have a de luxe control for an electronic keyer in less time than it takes to tell about it.

QST for

* Box 73, Ravinia, Ill.

A Phase-Angle Detector for R.F. Transmission Lines

Easily-Constructed Device for Checking Matching and Line Operation

BY G. ROBERT MEZGER,* W2BLL

• Here is another of the many devices that are becoming of greater importance to the amateur as the problems of TVI and of getting the most out of complicated present-day transmitters increase. This simple device not only will tell much about how your transmission line is terminated, but it will do it while the transmitter is operating under full power and as the frequency is shifted.

THE AMATEUR OWES a little thanks, at least, to the TVI problem; for, like so many things that we are doing these days, the work which led to the story of this little phase-angle detector was undertaken simply out of the necessity for it while attacking the greater problem of TVI. To get a low-pass filter working properly in the output circuit of a transmitter, the filter must be inserted in a transmission line that is "flat." And to get a flat line one of the two conditions necessary to describe fully the termination is the requirement that it have unity power factor. Or to put it in other words, the load seen by the line must be purely resistive, with no reactive component. The magnitude of the impedance that is necessary to terminate a transmission line properly is not discussed here, although it is planned finally to build a device that will detect both magnitude and phase angle. It is hoped that such work, if successful, will make this article just an interim report.

The arrangement of equipment at W2BLL is typical. The output stage of the transmitter feeds a length of nominal 50-ohm RG-8/U cable that feeds the antenna tuner. The antenna is a simple 66-foot dipole, fed at the center with feeders 33 feet long, and it is presently used for the 3.5-, 7-, and 14-Mc. bands. The antenna tuner is the usual link-fed parallel-resonant circuit with the antenna feeders tapped on the coil at a point hoped to be the proper one to reflect 50 ohms of pure resistance at the output terminal of the coaxial line feeding the tuner.


A partial solution to the problem has been achieved by utilizing some of the work described in a Naval Research Laboratory Report written by V. True.¹ In connection with its basic subject, *NRL Report 3755* describes two devices for making measurements on radio-frequency transmis-

sion lines, between transmitter and antenna tuner, that should be of great interest to the amateur. One of these, the phase-angle detector, is described here.

The Phase-Angle Detector

The basic circuit of the phase-angle detector is shown in Fig. 1. The general similarity of this circuit to the well-known Foster-Seely discriminator, used for f.m. detection, will be apparent. The significant distinction is that the circuit of the phase-angle detector is untuned, so that it is phase-conscious, rather than frequency-conscious as is the more familiar circuit. Qualitatively, the operation of the phase-angle detector can best be described by reference to the vector diagrams of Figs. 2 and 3.

The voltage across capacitor C_2 is always in phase with the voltage, V_L , across the transmission line. Similarly, the voltage developed across the inductor L_2 is always different in phase from the line current, I_L , by 90 degrees; and if the coil is center-tapped, as here, and if the base of the vector diagram is chosen as the vector E_{C_2} , the voltage across capacitor C_2 , then it may be said that the voltage E_A , across L_A , the left-hand side of L_2 , leads the line current by 90 degrees, while the voltage E_B , across L_B , the right-hand side of L_2 , lags the line current by 90 degrees. Of course, when the inductor L_2 is properly center-tapped, E_A equals E_B . Then, with respect to the voltage and current in the transmission line, the vector diagrams of Fig. 2 describe the conditions.



Although it is easily fitted into a miniature box, the phase-angle detector is a highly useful device for antenna circuit adjustment and s.w.r. monitoring—and can be left permanently in the line with transmitters up to the legal power limit.

*617 Beverly Road, Teaneck, N. J.

¹Naval Research Laboratory Report 3755, "An Automatic Antenna-tuning Unit," by V. True, Nov. 2, 1950. See also: "Automatic Impedance Matcher," by Virgil True, *Electronics*, December, 1951, p. 98.




Fig. 1 — Basic circuit of the phase-angle detector.

On the secondary side, the operation of the phase-angle detector may be described as follows: The voltage across either crystal diode, D_1 or D_2 , will be the sum of the voltage across capacitor C_2 and the voltage across the particular side of the center-tapped coil, L_2 , across which the diode in question is connected. Thus, a change in the phase angle between the voltage across C_2 , which voltage is always in phase with the transmission-line voltage, V_L , shown in Fig. 2, and the voltage across the coil, causes the vector sum of these voltages to change, and the rectified voltages developed across the diode load resistors, R_1 and R_2 , will change.

From the vector diagrams of Fig. 3, it will be seen that when the line current leads the line voltage, the voltage E_{D1} developed by D_1 will be less than E_{D2} , the voltage developed by D_2 , and the output voltage will be positive. Similarly, when the line current lags the line voltage, Fig. 3B, the voltage developed by D_1 will be greater than that developed by D_2 and the output voltage will be negative. At unity power factor, of course, the rectified voltages are equal and the output is zero.

The sensitivity of the phase-angle detector will increase as the frequency increases because

the voltage induced in L_2 will increase with frequency. It may be difficult, therefore, to employ the same detector circuit for operation on both 1.8 Mc. and 28 Mc., but the device described here operates satisfactorily over the range from 3.5 Mc. through 14.4 Mc. Fig. 4 is a plot of the typical operation of the device described here when operated at a frequency of 7200 kc. This plot clearly shows some unbalance, a condition that yet remains to be corrected.

Construction

The circuit of the phase-angle detector used in these experiments is shown in Fig. 5. Since shielding between the r.f. and other circuit components would be desirable,

the device can be constructed by using two ICA "channel-lock" aluminum boxes of the smallest available size, 4 by $2\frac{1}{2}$ by $1\frac{5}{8}$ inches in size. The channels of the two boxes should be fastened together along their 4 by $2\frac{1}{2}$ -inch dimensions using the junction of C_1 , R_1 , and D_1 as one fastening and using C_4 , a feed-through capacitor, as the other fastening. The "top" box should contain the input and output connectors for the coaxial cable, L_1 , L_2 , D_1 , D_2 , C_2 , and R_2 . The lower box should contain R_1 , R_3 , C_3 , C_4 , C_5 , and L_3 .

L_1 is nothing more than the inductance of a straight piece of No. 12 copper wire extending through the box from one coaxial terminal to the other. The capacitor C_1 is the stray capacitance between L_1 and L_2 .

Inductor L_2 is wound, with No. 22 d.c.c. wire, on a rectangular wooden form two inches long by $\frac{1}{2}$ inch high. It is a five-turn center-tapped coil, and it seems to give adequate sensitivity, even at low powers and at low frequencies. Fewer turns could be used for high power and for higher frequencies, but as the number of turns is decreased it becomes more difficult to locate the center tap physically in the exact electrical center of the circuit. L_1 and L_2 are so oriented that the straight wire, L_1 , lies in the plane of the rectangular coil L_2 .




Fig. 2 — Relations between secondary voltage and voltage and current of transmission line.




Fig. 3 — Relations among secondary voltages in phase-angle detector.

Circuit constants given are for use with Type 1N34 crystals. If Types 1N38 or 1N67 are used, R_1 and R_3 may be increased to approximately 0.3 megohm, thereby increasing the sensitivity of the circuit.

It is obvious that resistor R_3 causes a loss in output voltage from the phase-angle detector. It has been used only because of the advantage of small physical size. A 2.5-mh. r.f. choke would be preferable.

Because the output signal developed by the phase-angle detector is developed in a high-impedance circuit, the indicator of that signal must be either a sensitive microammeter or a high-impedance vacuum-tube voltmeter. If a microammeter is used, a zero-center instrument with a range of 100-0-100 microamperes probably will be satisfactory. The work described here has been done using an ordinary vacuum-tube voltmeter on its lowest range with the zero adjustment turned to make it operate as a zero-center instrument.

Operation

In the brief period of time so far available for experimenting with the phase-angle detector, it has been used here only at the antenna-tuner end of the coaxial feed line between the transmitter and the tuner. Thus, it has been employed only in a position chosen to tell us what may be the phase angle of the load seen by the coaxial cable at its termination or, conversely, something of the nature of the load reflected to the termination of the coaxial line by the antenna, through the antenna tuner. This information, of course, has helped give answers to such questions as whether the antenna tuner is tuning out all the reactance of the antenna system, and whether the reflected impedance of the antenna is inductive or capacitive.

A little experience with the phase-angle detector has shown that if, after a thorough check of wiring, the detector fails to indicate a null when the antenna tuner acts as though the antenna were properly tuned, then it is most likely that the antenna tuner is not tuning out all the reactance of the antenna. This difficulty has occurred a number of times, using this little detector. In each case it has been corrected by changing taps on the antenna tuner, changing the length of the antenna feed line, or both. This manifestation of the effect of improper matching

between antenna and transmitter causes us to consider the phase-angle detector as a pseudo-s.w.r. indicator. It is true that when the s.w.r. is unity the phase-angle detector will indicate a null; but it is not necessarily true that when the phase-angle detector indicates a null the s.w.r. is unity. Rather, the phase-angle detector simply shows that the reactance reflected back from the antenna, through the antenna tuner to the feed line from the transmitter, is either present, capacitively or inductively, or is zero. It says nothing about the magnitude of the resistance that the feed line from the transmitter sees when a null is indicated by the phase-angle detector. That is, the phase-angle detector will show when the impedance seen by the feed line from the transmitter has been changed from the general expression $R \pm jX$ to the form $R + j0$, but it will tell nothing about the magnitude of R . This in itself is useful information when attacking the s.w.r. problem, but it is not the complete answer.

Conclusion

In spite of the limitations mentioned in the foregoing paragraph, the phase-angle detector can be usefully employed, in many cases, as a monitor of the s.w.r. If the antenna tuner and its associated load, the antenna, are first matched to the link coil feeding it from the output of the coaxial transmission line so that the line is terminated





Fig. 4 — Plot of typical output of device of Fig. 5 at a frequency of 7200 kc.

properly, by using an s.w.r. bridge, and if the phase-angle detector is installed at the input end of the line, then the phase-angle detector does tell when the s.w.r. is unity or when it departs therefrom. A mismatch of any sort at the antenna tuner will cause the input impedance of the line to have a reactive component. The one exception to this case is when the load is still resistive and the line is an exact multiple of $\frac{1}{4}$ wave in electrical length; this length easily can be avoided. So, after a preliminary matching, the phase-angle detector becomes an s.w.r. monitor, or serves to indicate adjustments at the antenna tuner, as after changing frequency, that will bring the s.w.r. back to a minimum.

The phase-angle detector has proved itself to be a very useful little gadget for tuning a transmitter and the antenna that goes with it. It has, for example, shown that maximum power output is not necessarily the point where final-amplifier-plate current is maximum and everything seems to be "in tune." It has shown the proper amount of coupling to employ with variable-link coils to obtain good power transfer with minimum coupling. It has helped to locate the reason, in specific cases, why tuning capacitors are over because of high standing waves. Because its output potential changes polarity with phase angle, it will identify the reactance present, so that one easily can determine whether the load is capacitive or inductive. And if, after adjusting the load to eliminate reactance, the output voltage of only one-half of the circuit is read, the voltage is an index of output power. In another article² Walt Knoop describes another ingenious and interesting application of this circuit, in this case as the detecting device for an automatic antenna tuner.

It is obvious that the work and the results mentioned here are rather sketchy. That is



Internal layout of the experimental unit. The five-turn secondary coil is concealed by a rectangular piece of cardboard that serves to prevent it from touching the "primary"—the straight-through connection between the two coax fittings. The long sides of the secondary turns are parallel to the primary wire. An alternative method of construction that provides shielding between the r.f. transformer and other components is suggested in the text.




Fig. 5—Circuit of the phase-angle detector.

C₁—Stray capacitance.

C₂—300 μ fd.

C₃, C₄, C₅—1500 μ fd.

R₁, R₃—0.1 megohm, $\frac{1}{2}$ watt.

R₂—27,000 ohms, $\frac{1}{2}$ watt; or 2.5-mh. r.f. choke.

L₁—See text.

L₂—See text.

L₃—2.5-mh. r.f. choke.

because we have been playing with this little gadget for only a very short time; but in this brief period, it has proved so useful and helpful that it seemed more desirable to write a short report describing the basic device, even if the work is only partially completed, rather than wait the long time necessary for more complete exploitation of the possibilities of this circuit.

² "Automatic Tuning of the Antenna Coupler," by W. A. Knoop, to be published in a subsequent issue.

Silent Keys

IT is with deep regret that we record the passing of these amateurs:

W1PCC, Charles J. Crabill, Lowell, Mass.
 W2JGM, Clayton B. Legallez, Slingerlands, N. Y.
 W2NFK, Mario J. Bruscia, Brooklyn, N. Y.
 ex-2RE, Louis G. Pacent, New York, N. Y.
 W2SMP, David Nabutovsky, Trenton, N. J.
 W2YU, Abe Hass, Mt. Vernon, N. Y.
 ex-3MS, C. W. Gilbert, Philadelphia, Pa.
 W4DSY, Robert E. Dawson, Jr., Charlotte, N. C.
 W4DU, Orville R. Cheatham, Jacksonville, Fla.
 W6MUI, Dr. J. Van Beccelaere, San Diego, Calif.
 W6QZN, Albert J. Layos, Hollywood, Calif.
 W6SLT, Edna McGeorge, Los Altos, Calif.
 ex-W7AAO, George M. Ohi, New York, N. Y.
 W7OQK, Merle A. Cook, Boulder City, Nev.
 W7TJH, H. O. George, Tucson, Ariz.
 ex-9AHM, Fred O. Grimwood, Quincy, Ill.
 W9FFV, William A. Markland, Lawrenceburg, Ind.
 W9NYR, George Pabst, Chicago, Ill.
 W9RN, Dr. J. Wilson Gray, Geneva, Ill.
 W8AFQ, John P. Breheny, Keokuk, Iowa.
 W8QYL, Albert P. Smith, Holyoke, Colo.
 W8YKK, William A. Copeland, Woodbine, Iowa.
 G5IQ, R. Frank Speake, Wolverhampton, Staffordshire.
 H1SFA, F. A. Sanabia, Ciudad Trujillo
 ZL4HP, T. E. Neville, Moa Creek, Otago

Getting the Most Into Your Antenna

A Simple Explanation of the Fundamentals Involved

BY RICHARD M. SMITH,* W1FTX

• A frequent stumbling block is the problem of getting the power generated by the transmitter into the antenna. This, the first of two articles on the subject, gives the Novice the basic fundamentals he needs to solve his coupling problems. A subsequent article will describe the construction and use of the antenna couplers he needs to make use of the principles he can learn here.

ANTENNAS and antenna coupling are not "mysterious" subjects. They only seem that way to the Novice because he finds it more difficult to know when he is doing the right thing than in other phases of the hobby. He can tell, for example, when his transmitter is working properly merely by watching the plate milliammeter and listening to the tone of the signal in his receiver. But what does he do when the meter shows him that "everything is working right" but he still doesn't get any answers to his calls? Is his location poor, conditions bad, or what? Admittedly these factors may exist, but in more cases the trouble is that the power just isn't getting into the antenna.

With a half-way efficient transmitter, a mediocre location, and anything but a complete "washout" of radio conditions you'll "get out" if you get the power into the antenna. If you don't, the best transmitter, the best location, and the best antenna in the world won't help you. It is important, therefore, to pay close attention to the antenna coupling system in your station. It can mean the difference between failure and success.

Some Fundamentals

It is easy to get power into an antenna, if the right kind of coupling device is connected to the feed line at the right point. Before you can understand this and thereby learn what to do to make your antenna and its feed line work properly, there are a few basic fundamentals of antenna operation that must be learned. We won't go into all of the theory involved, but will state the more important considerations that must be kept in mind. For more detailed discussion of the theoretical aspects, you can refer to the *A.R.R.L. Antenna Book*.

First of all, the easiest way to get power into your antenna is to start out with an antenna system that is resonant. Coupling problems are then much simpler. When we say "system," we mean all of the wire involved, from the antenna coupler out to the end of the line. To be resonant, the antenna system must be cut to a length determined by the frequency or wavelength at which it is to

operate. A wire is resonant when its length is exactly equal to one half wavelength (or any multiple thereof) at the frequency of operation. Exact figures, in feet and inches, can be computed from simple formulas contained in both the *Antenna Book* and *The Radio Amateur's Handbook*. The main point, so far as this discussion is concerned, is that it is easiest to couple to a resonant antenna system, and to be resonant it must be cut to the correct length.

The next important point concerns the way current and voltage are distributed on an antenna. Again skipping the theory that can be obtained elsewhere, Fig. 1 shows the current distri-




Fig. 1 — Current distribution in three different types of antenna. Note the way the current patterns repeat themselves, but in the opposite polarity, throughout alternate half waves. The dimensions shown are those computed for half-wave antennas operating at 3725 kc., the center of the present Novice assignment in the 3.5-Mc. amateur band.

* Technical Assistant, QST.

bution on three different antenna systems. In sketch A, a random-length wire is shown. Assume for a moment that power is applied to the end of the wire from the transmitter. Current flows down the wire, but when it reaches the end insulator, it must stop. This is the key to all of the various current distribution diagrams that you will encounter in reading about antennas, and it is often overlooked by newcomers. A current minimum, or null, *always* occurs at the end of the wire, simply because it has to. Based on this fact, drawing a diagram of the current distribution on any antenna, resonant or not, becomes a simple matter, because it will follow a regular pattern dictated by the length of the wave at the particular frequency involved. The pattern is always as shown in sketch A of Fig. 1, with current being minimum at the far end of the wire, at maximum one quarter wavelength back toward the source, returning to minimum again one half-wavelength from the far end. If the wire is more than one half-wavelength long, current reaches another maximum three quarters of a wavelength from the end, and is back at minimum again a full wavelength from the end.

Note that the second maximum-current point is shown on the opposite side of the line to the first. This is to indicate that the current flows in the opposite direction in this section of the wire, because the polarities change during succeeding half waves (half cycles). If the wire were to be extended several wavelengths more, the same patterns would exist, with the current maxima and minima occurring regularly a quarter-wavelength apart, and with the direction of flow, or polarity, reversing every half-wavelength throughout.

The distribution of voltage on a wire is exactly opposite to the current distribution curve. Maximum *voltage* points occur at the minimum *current* points, and minimum voltage points correspond to maximum current points. Actually, it is necessary to think in terms of only one, either current or voltage, because we know that when one is at maximum, the other is at minimum. We choose to talk in terms of current distribution here because it is easier to measure current than voltage at radio frequencies.

The Single-Wire Antenna

As shown in sketch A of Fig. 1, a straight length of wire, whether it be cut to a resonant length or not, *can* be used as an antenna. Radiation takes place from the entire length of wire, regardless of where it is installed. Thus, if part of the antenna is low to the ground, surrounded by buildings and trees, as it usually is at the transmitter end, a portion of the power radiated is apt to be absorbed by the surrounding objects. It is better to try to design a system in which all of the radiation takes place from a wire that is supported high above the ground, and away from surrounding objects. This requires some means for getting the power up to the antenna in a feed line that will not radiate, but which will deliver the power to the place from which we wish it to be

radiated. The same current-distribution characteristics that we've been talking about present the solution to this problem. We know that electrical charges of equal intensity and opposite polarity cancel one another. Radiation from a *pair* of wires, spaced a few inches apart, will be negligible, therefore, if the current in the two wires is equal and opposite. This is called a balanced feed line. How the desired relationship between the currents in the two wires is achieved is shown below.

The Zepp Antenna

In this system, one side of a two-wire feed line is connected directly to one end of a *resonant* "flat top," and the other side is left "floating." (It must be insulated from both the flat top and the supporting wire, or rope, as shown in sketch B of Fig. 1.) In order to understand how we can get a balanced feed line out of this arrangement we must consider the current distribution on the flat top as well as the feeders, because the feeders are actually an extension of the flat top, bent down from the plane of the wire in the flat top. This can be seen by following the dotted lines back up to the straight wire shown at the top of Fig. 1. Note that, if the flat top is exactly a half-wave (or any multiple thereof) long, a current minimum occurs at the point of attachment of the feeders, and another current minimum occurs at point C, one half wavelength down the "live" feeder wire. The current distribution on the "dead" feeder is also shown in the diagram, with a current minimum occurring right where it has to, at the insulated end of the wire. This, of course, results in the correct relationship between currents in the two feeders. We have made them equal by cutting the flat top to the correct length, and they are opposite because of the polarity reversal which exists in adjacent half wavelengths of any piece of wire. (The two feeder wires are joined through the antenna coupler.) Being equal and opposite, the radiation from the feeders will cancel, and all the power will go into the flat top. Thus the Zepp will be able to do a better job of radiating than the single wire described earlier.

If the flat top is not cut to the correct length for the frequency of operation, the feed line currents will not be balanced, and the feeders will radiate some of the power in places where we don't want it to be dispersed, namely close to the ground near objects which can absorb it, and often close to some neighbor's broadcast or TV set where it can cause interference. What happens when the flat top is not the right length is shown in Fig. 2. Here the flat top is too short. Starting again at the far end of the wire, there must be a current minimum at the end, with a point of maximum current occurring one quarter wavelength away. The next current minimum occurs not at the junction of the feeders and the flat top, but at a point part way down the "live" feeder, how far down depending on the deficiency in length that has to be made up. Note that the distribution of current on the "dead" feeder is not changed by the fact that the antenna is too short;




Fig. 2 — Current distribution in antennas having less than a half wavelength in the "flat-top." In the case of the Zepp, feeder unbalance results. This is not true of the center-fed antenna, making it the best bet for installation where space for a full half-wave is unobtainable.

the current minimum is right where it always has to be — at the end of the wire. Naturally, the current in this set of feeders will be unbalanced, and some of the power will be wasted on the surrounding objects.

The Center-Fed Antenna

Return now to Fig. 1, and look at sketch C, which shows the current distribution in a center-fed half-wave antenna. The feeders are attached at a point of maximum current, resulting in a situation exactly opposite to the case of the Zepp. The current minima on the feed line occur one quarter wave-length away from the point of attachment to the flat top, and both feeder wires must be considered as extensions of the flat top, not just one.

Let's see what happens when a center-fed antenna is too short. The length of the flat top shown in Fig. 2B is somewhat less than a half wave. Current minima must occur at the insulated ends of the wire, as always. Therefore, starting at either end of the antenna, and apply-

ing the same principles, we see that the current maxima must occur part way down the feed line, a quarter wavelength from the ends of the wire. Assuming that the two halves of the flat top are equal in length, these points will be opposite each other on the feed line, so the currents in the feeders are balanced, and feeder radiation is minimized.

This explains why the center-fed system is considered better than end feed. The advantage is even greater when you consider what happens when the operating frequency is changed. In the case of the Zepp, the feeder currents are balanced only when the flat top is cut to the right length for the frequency in use. With the center-fed antenna, feeder current remains balanced, regardless of the operating frequency, and regardless of whether the flat top is by itself resonant.

Thus, it is not necessary that you have space for a full half-wave antenna. If you use center feed, and there is sufficient wire in the complete system for it to be resonant, you can have an efficient antenna even though the flat top must be shortened somewhat to fit a city lot.

Coupling to the Antenna System

We've talked about the distribution of current and voltage on antennas and their feed lines solely to indicate why the total length of wire involved is important, and to show the differences encountered in various types of antenna. We said at the start that it is easy to get power into an antenna if the right kind of coupling device is connected at the right place. The right place is either a point of maximum current or minimum current. The farther away from these points you go, the more difficulty you are apt to encounter, and the midway points present a coupling problem that is often beyond the capabilities of the usual antenna coupler.

An important thing to remember is that in figuring feeder lengths, the distance from the far end of the antenna to the coupler is what counts, not the distance to the house, or to the transmitter. The coupler can be installed some distance away from the transmitter, if need be, but the length of the link line that connects it to the transmitter cannot be considered as part of the length of the antenna system when you are drawing current-distribution curves.

The type of coupler to use depends on whether you are going to feed power in at a point of current maximum or minimum. If your antenna system is cut so that the end of the feed line represents a current minimum (voltage maximum), you will need a parallel-tuned coupler. A series-tuned coupler is called for to insert power at a point of maximum current. A third type, the pi-section coupler, is recommended if you are forced by circumstances to use a random-length antenna with power applied at one end. All three types are described in detail in the *A.R.R.L. Antenna Book*.

Using the antenna coupler is a simple procedure once you have selected the right type, but

(Continued on page 116)

A Quadriband Mobile Transmitter

Fifty Watts Under the Dashboard

BY CHARLES J. SCHAUERS,* W6QLV

HAVING looked over almost every type of mobile installation, ranging from a 1-kw. rig downward, my ideas had become pretty well crystallized by the time I got around to building one for my own car. For one thing, I wanted to keep the trunk free for the purpose for which it was originally designed. This meant a dashboard job that would operate from a power unit sufficiently reasonable in size to fit under the hood. Therefore, the starting point was the space available under the instrument panel. Measurements showed that a cabinet of approximately 11 by 11 by 8 inches would fit nicely without undue crowding. An enclosure of this size was made by cutting down a standard utility box.

Circuit

Having determined the physical limits, the problem of circuitry was tackled next. The one shown in Fig. 1 was based on the principal requirements that included choice of VFO or crystal, operation in the most-popular mobile bands—10, 11, 20 and 75 (including the MARS frequencies)—and an input of about 50 watts to the final amplifier with 100 per cent plate-and-screen modulation.

When operating at 75 meters, the plate circuit of the 6AG7 crystal oscillator is untuned. This permits working the 6V6 buffer-doubler (and also the 6AG7 when VFO is used) straight through without danger of oscillation. For the higher frequencies, the plate circuit is fixed-tuned, using iron-slug coil forms. For 14-Mc. operation,


• Here is a 50-watt four-band mobile job designed for mounting under the instrument panel where the controls can easily be reached. The fact that an installation of this type leaves the trunk free for other uses is another advantage worth considering.

frequency is doubled in the plate circuit of the oscillator and doubled again in the 6V6, using crystals in the 3.5-Mc. range. Crystals in the 7-Mc. range are necessary only for 10- and 11-meter output, doubling in both stages.

The VFO, shown only in block form in Fig. 1, is a Lysco 381-R mounted on the chassis at the center of the panel. This VFO gives output on either 80 or 40, selectable by a switch. S_1 shifts from crystal to VFO. Since this model VFO is designed for low-impedance output, it was necessary to alter it slightly for high-impedance output by clipping the link coils and making connection directly to the hot end of the circuit. (Lysco also puts out a similar VFO designed for high-impedance output which, of course, would not require this alteration.)

The 807 works straight through on all bands. Excitation can be adjusted to proper value by means of R_1 which controls the screen voltage of the 6V6. The output circuit is in the form of a pi-section network. This circuit has worked out very well on all frequencies and no TVI has been experienced operating the rig as close as practicable to a TV antenna. C_{19} , C_{20} and C_{21} are

* 15 North "G" St., Lompoc, Calif.



The quadriband mobile transmitter installed, showing the panel layout.

QST for





Fig. 1 — Circuit diagram of the quadriband mobile transmitter.

- C₁, C₁₅ — 0.0022- μ fd. mica.
 C₂ — 12- μ fd. silvered mica.
 C₃ — 47- μ fd. silvered mica.
 C₄, C₅, C₆, C₁₀, C₂₀ — 0.001- μ fd. ceramic.
 C₇ — 22- μ fd. ceramic.
 C₈ — 47- μ fd. ceramic.
 C₉, C₁₁, C₂₈ — 0.01- μ fd. ceramic.
 C₁₂ — 75- μ fd. variable (National PSE-75).
 C₁₃ — 100- μ fd. mica.
 C₁₄ — 0.0047- μ fd. mica.
 C₁₆ — 0.001- μ fd. 1000-volt mica.
 C₁₇ — 470- μ fd. 1000-volt mica.
 C₁₈ — 140- μ fd. variable (National ST-140).
 C₁₉ — 100- μ fd. 1000-volt mica.
 C₂₁ — 470- μ fd. ceramic.
 C₂₂ — 330- μ fd. ceramic.
 C₂₃ — 300- μ fd. variable (National STH-300).
 C₂₄ — 500- μ fd. 12-volt electrolytic.
 C₂₅, C₂₇ — 10- μ fd. 25-volt electrolytic.
 C₂₈ — 50- μ fd. 25-volt electrolytic.
 R₁, R₃, R₄ — 47,000 ohms, $\frac{1}{2}$ watt.
 R₂ — 470 ohms, $\frac{1}{2}$ watt.
 R₅, R₁₀, R₁₂, R₂₁ — 47 ohms, $\frac{1}{2}$ watt.
 R₆ — 330 ohms, $\frac{1}{2}$ watt.
 R₇ — 25,000-ohm wire-wound potentiometer.
 R₈ — 22,000 ohms, $\frac{1}{2}$ watt.
 R₉ — 20,000 ohms, 10 watts.
 R₁₁ — 100 ohms, $\frac{1}{2}$ watt (see text).
 R₁₃ — 0.47 megohm, $\frac{1}{2}$ watt.
 R₁₄ — 2200 ohms, $\frac{1}{2}$ watt.
 R₁₅ — 0.1 megohm, $\frac{1}{2}$ watt.
 R₁₆ — 4700 ohms, $\frac{1}{2}$ watt.
 R₁₇ — 0.5-megohm potentiometer (log taper).
 R₁₈ — 560 ohms, $\frac{1}{2}$ watt.
 R₁₉ — 250 ohms, 10 watts.
 R₂₀ — 15,000 ohms, 10 watts.
 R₂₂ — 900 ohms, 20 watts.
 L₁ — Approx. 10 μ h. — 32 turns No. 20 enam. (Millen 69045 iron-slug form, $\frac{1}{2}$ -inch diam.).

fixed condensers augmenting the variable condensers C₁₅ and C₂₂. RFC₅, RFC₈ and RFC₉ are v.h.f. parasitic chokes. The milliammeter MA₁ reads 807 grid current, while MA₂ may be switched to read either modulator or final-amplifier plate current.

- L₂ — Approx. 2.5 μ h. — 19 turns No. 20 enam. (Millen 69045 iron-slug form, $\frac{1}{2}$ -inch diam.).
 L₃ — 45 μ h. — 48 turns No. 26 enam., 1-inch diam., close-wound.
 L₄ — 1.7 μ h. — 14 turns No. 18 enam., $\frac{3}{4}$ -inch diam., 1 inch long.
 L₅ — 0.4 μ h. — 4 turns No. 18, 1-inch diam., $\frac{1}{2}$ inch long (B & W 3014 Miniductor).
 L₆ — 10 μ h. — 32 turns No. 20, 1-inch diam., 2 inches long (B & W 3015 Miniductor).
 L₇ — 2.5 μ h. — 15 turns No. 18, 1-inch diam., 2 inches long (B & W 3014 Miniductor).
 L₈ — 0.7 μ h. — 6 turns No. 18, 1-inch diam., $\frac{3}{4}$ inch long (B & W 3014 Miniductor).
 I₁, I₂ — 6.3-volt dial lamp (see text).
 J₁, J₂ — Female coaxial-cable connector.
 J₃ — 3- or 4-contact shielded connector.
 J₄ — 6-prong male connector.
 MA₁ — D.c. milliammeter, 10-ma. scale.
 MA₂ — D.c. milliammeter, 200-ma. scale.
 P₁ — Male connector to match J₃.
 RFC₁, RFC₂, RFC₃, RFC₄, RFC₆, RFC₇ — 2.5-mh. r.f. choke.
 RFC₅ — 15 turns No. 20 enam., close-wound on pencil.
 RFC₈ — 9 turns No. 20 enam., wound on R₁₁.
 RFC₉ — 19 turns No. 20, $\frac{1}{2}$ -inch diam.
 RY₁ — 6.3-volt relay.
 RY₂ — 6.3-volt d.p.s.t. relay.
 RY₃ — 6.3-volt d.p.d.t. relay.
 S₁ — S.p.d.t. rotary switch.
 S₂, S₇ — S.p.s.t. toggle.
 S₃ — Bandswitch (see text).
 S₄ — Miniature single-circuit 3-contact rotary switch.
 S₅ — Push-to-talk switch at microphone.
 S₆ — D.p.d.t. toggle switch.
 T₁ — Microphone transformer, single-button.
 T₂ — Interstage audio transformer, single plate to p.p. grids, ratio 1:2.
 T₃ — Universal modulation transformer, 30 watts (UTC S-19).

The audio section consists of a two-stage speech amplifier using a single 12AU7 and a 6L6 Class AB₁ modulator. Although sufficient gain is available for a dynamic or crystal microphone, I use a hand microphone fitted with a W.E. F-1 carbon button. Full modulation is



Bottom view of the quadri-band mobile rig showing the general arrangement of major components.

obtained with the gain control backed down near minimum.

A PE-103 dynamotor is used to supply the final amplifier and modulator stages, while a 300-volt 100-ma. vibrator pack supplies all other stages. If the negative side of the battery in your car is grounded, as it is in mine, the polarity of the high-voltage output of the PE-103 can be corrected by reversing the connections to the high-voltage brushes.

Control Circuit

The toggle switch, S_7 , turns on the filaments and the hot side of the car battery to the relays and microphone. It also lights the green indicator lamp, I_2 . Closing the microphone switch, S_6 , operates R_{y2} . The contacts of R_{y2} operate R_{y1} , which I mounted in the VFO unit, closing the VFO plate-voltage circuit and, through connection W, operate the antenna relay, R_{y3} , and the power relay, R_{y2} , in Fig. 2. The latter starts the dynamotor, turns on the vibrator pack via R_{y1} and lights the red indicator lamp, I_1 . A second set of contacts on R_{y3} closes the high-voltage circuit to the final amplifier and modulator.

A switch, S_1 in Fig. 2, mounted on the dashboard, permits turning on the vibrator pack alone for tuning up the crystal oscillator and doubler. In setting the VFO to frequency, S_2 (also added to the VFO unit) must be closed. The VFO can also be used as a b.f.o. in c.w. or s.s.b. reception.

Construction

The important details of construction are shown in the photographs. The chassis measures $10\frac{3}{4}$ by 10 by 3 inches and, in my case, setting the chassis off center on the panel made installation easier. On top of the chassis the VFO unit is

placed against the panel in the center of the chassis. A window is cut in the panel to expose the calibrated dial. The audio tubes and the modulation transformer are lined up along the rear of the chassis. To the left of the VFO are the 75- and 20-meter output coils, L_6 and L_7 , mounted at right angles on stand-off insulators, and the 807 immediately to the rear. The 6V6 is off the right rear corner of the VFO unit. The 6AG7 and its associated plate coils are hidden behind the panel in the space to the right.

Underneath, the bandswitch is at the center. The ceramic wafer at the front, fastened to the panel, is a two-circuit unit carrying the circuits of S_{3C} and S_{3D} . The 10-meter coil, L_8 , is soldered directly between the switch contact and the stator terminal of C_{22} to the left in the bottom-view photograph. C_{13} is the variable to the right. The two remaining bandswitch wafers, S_{3A} and S_{3B} , are of bakelite and are mounted on a bracket which places the sections at almost the exact center of the chassis. S_{3B} is to the rear, with the associated coils, L_3 , L_4 and L_5 , lined up across the rear. C_{12} is to the left, mounted on a bracket. S_4 is panel-mounted close to the control of the bandswitch. The antenna change-over relay, R_{y3} , is mounted against the right-hand edge of the chassis, between the two coaxial connectors, J_1 and J_2 . A short piece of RG-59/U connects the relay contacts to the stator of C_{22} . Small baffle shields are placed between C_{12} and C_{22} , and between the rear section of the bandswitch and C_{13} .

To the rear of the chassis, behind a shielding barrier, are the microphone and driver transformers and small components of the audio section. The control relay, R_{y2} , is mounted to the right on a small stand-off insulator.


On the panel, the two meters are mounted

to either side of the VFO unit. The filament switch, S_7 , and the green signal lamp, I_2 , are below the grid-current meter, MA_1 , to the right, while the meter switch, S_6 , and the red signal lamp, I_1 , are to the left. The microphone connector and audio gain control are below the red lamp. Below the green lamp to the right are the crystal socket and the crystal-VFO switch, S_1 . The tuning control for C_{12} is the small knob to the right of the dial for C_{22} . The excitation control, R_7 , is below the filament switch. The toggle switch above the VFO dial is S_2 in the VFO unit.

Adjustment

Prior to installation, the VFO is tuned up for maximum output, as are the output coils of the crystal oscillator. A grid-dip meter comes in handy for this adjustment. The buffer-doubler is then tuned for maximum 807 grid current and the excitation adjusted by R_7 to give an 807 grid current of 3 to 4 milliamperes. In adjusting the coupling to the antenna or transmission line, C_{22} is placed at some setting and then C_{13} is resonated for the usual plate-current dip. If the resulting plate current is too low or too high, C_{22} is adjusted to a different setting and the circuit reresonated with C_{13} . It should be possible to load the final up to 100 ma. on all bands. I have found it possible to maintain satisfactory loading over a range of about 125 kc. on 75 without readjusting the antenna length or the loading-coil inductance. On this band it is usually necessary to switch in either C_{20} or C_{21} to obtain proper loading.

A small field-strength meter is used for tuning the transmitter for maximum output. This is



Side view of W6QLV's mobile rig showing the mounting of the 20- and 75-meter output coils. The 12AU7 speech tube is the shielded tube to the left.

connected to the regular auto antenna on the cowl and placed on the floor when not in use. The auto antenna is not fully extended. False loading with the pi-section network is avoided in this manner.

The total battery drain with full load to the final runs about 40 amperes, so it is a good idea to keep the motor running while transmitting.

Consistent results have been obtained on 75 up to 300 miles in daylight and stations as far away as 2500 miles have been contacted at night with S5 to "S9-plus-40" reports. Best DX on 20 is Japan, and nearly every station called in reply to a CQ has been raised.




Fig. 2—Power circuits of the quadriband mobile transmitter.

- C_1 —2- μ fd. 500-volt paper.
- C_2 —8- μ fd. 400-volt electrolytic.
- C_3 —4- μ fd. 600-volt electrolytic.
- F_1 —50-amp. fuse.
- F_2 —300-ma. fuse.
- J_1 —6-prong tube socket.
- RFC_1 —2.5-mh. r.f. choke.
- Ry_1 —6.3-volt s.p.s.t. relay.
- Ry_2 —6.3-volt heavy-duty starting relay.
- S_1 —S.p.s.t. toggle on dashboard.

Strays

It was a case of life or death when VQ4CO, Nairobi, and W8LIO of Dorset, Ohio, set an amateur radio chain reaction in motion on the 20-meter 'phone band in mid-May. W4AAM, W4NTZ, W1JCX, W1MB and 5A2TO joined in.

Doctor Gustave H. Hoehn, Seventh-day Adventist missionary-physician, was stricken with polio on May 4th while on duty at Kendu Hospital, 200 miles from Nairobi in Kenya Colony. He continued his work until the 11th when a respiratory paralysis developed. The doctor was quickly transported to a Nairobi hospital where Dr. G. W. Allen, VQ4CO, also a Seventh-day Adventist physician, placed him in a standby "wooden lung." This unit was far from satisfactory and Dr. Hoehn's situation was perilous.

VQ4CO then succeeded in contacting W8LIO who, aided by W4AAM, got word to Seventh-day Adventist headquarters in Washington.

The next step was volunteered by the Surgeon General's Office of the Air Force. A special mission was dispatched by air from Frankfurt, Germany, carrying a portable iron lung and a medical team to Nairobi and thence to the U. S. The 8500-mile trip was completed and at last reports Dr. Hoehn was resting comfortably in Children's Hospital, Boston.

Two-Element Driven Arrays

Adjustable Phasing by a Simplified Method

BY L. A. MOXON,* G6XN

TWO-ELEMENT arrays of the close-spaced parasitic type have achieved a well-deserved popularity in spite of a number of drawbacks, among which are the difficulty of making adjustments after erection, the need for 360-degree rotation, a rather poor front-to-back ratio when adjusted for maximum gain, and the difficulty of making them "multiband." These difficulties can be overcome by driving both elements with a suitable phase difference; although there are no new principles involved it appears that the case for driven *vs.* parasitic arrays is not widely known. The problem of phasing—which is a simple matter if tackled as described in this article—has in the past given rise to a certain amount of difficulty.

Before developing the system described here the author relied for DX contacts mainly on a fixed four-element beam which, aided by steeply-sloping ground, gave very good results over the long route to Australia. However, other directions proved difficult to work. Interest was aroused in the "GSPO antenna" by the large number of VK stations using it, and discussions over the air with GSPO himself, in the person of VK3WU, proved to be the starting point for a detailed theoretical and experimental study of driven two-element arrays.

The GSPO antenna is a two-element driven array with 135-degree phasing and $\frac{1}{8}$ wave spacing. The front-to-back ratio is infinite in theory

• All-driven arrays used by amateurs have almost exclusively been of the type where the phasing is either zero or 180 degrees. Perhaps the principal reason is that such phasings are the easiest to get with certainty. This article describes a method of phasing adjustment, based on a unique property of two parallel elements one-eighth wave apart, that is simple to apply and permits selection of a variety of directional patterns.

and often very nearly so in practice. The theoretical gain is 1 db. less than for a parasitic array and about the same as that of the WSJK antenna. However, the gain is more easily realized since the radiation resistance is nearly four times as high. As the beam is electrically reversible, there is no need to provide more than 180-degree rotation. The phase shift is obtained by having different lengths of feeder to the two elements.

In its original form the GSPO antenna has two main snags; i.e., restriction to single-band operation, and cut-and-try methods of phasing adjustment that do not seem always to lead to equally good results. This is usually due to standing waves on the feeders, and in systems with other than $\frac{1}{8}$ wavelength spacing the situation is further complicated by the fact that, in general, the impedances of the two elements are not equal, and it is therefore more difficult to adjust the individual element currents to the desired values. A theoretical study shows that the impedance inequality does not arise if the transfer impedance (i.e., from one element into the other) is non-reactive. This happens, very conveniently, at about $\frac{1}{8}$ wave spacing, and means that if the elements with their feeders are cut individually to exact resonance and connected in parallel through equal values of reactance the currents in the elements are automatically equal.

Fig. 1 shows calculated curves of power gain and front-to-back ratio plotted against phase angle of the currents in the two elements, for equal current amplitudes in both. These curves are applicable to any 2-element $\frac{1}{8}$ -wave spaced array with driven elements, and it will be noticed that the best gain is obtained with phasing in between that of the WSJK and GSPO systems. The G6XN antenna uses 150° phasing as an optimum compromise between gain and front-to-back ratio. With 150-degree phasing the nominal front-to-back ratio is not as high as with 135-degree phasing, but reference to Fig. 2 shows that the single null directly to the rear (180 degrees on the pattern measured from the optimum direction of radiation) has been replaced by *two*




Fig. 1 — Gain and front-to-back ratio as a function of the phase angle between two equal currents in parallel elements spaced one-eighth wavelength, assuming a copper-loss resistance of 2 ohms per element.




Fig. 2 — Polar diagrams comparing the directive patterns with 135-, 150-, and 180-degree phasing. These figures represent the free-space horizontal-directivity pattern of a horizontal element or array.

nulls at 132 degrees. The nominal figure is therefore misleading, and if we consider the power received "on the back" averaged over 180 degrees on the assumption of uniform angular distribution of interfering stations, the two values of phasing are found to be about equally good.

Phase Shifting with Resonant Feeders

Most readers will be familiar with the WSJK antenna, which makes a convenient starting point for explaining the G6XXN method of phasing. If the feeders coming from the two dipoles are joined together, with one pair crossed over, and if r.f. energy is applied to the junction, we have in effect the WSJK system; the arrangement is perfectly symmetrical, the currents in all elements are equal, and the antenna fires equally in both directions.

Let us assume that each dipole, together with its own half-wave feeder, is exactly resonant. The impedance looking into either set of feeder terminals will then be a pure resistance, as indicated in Fig. 3A, and the resistances will have the same value. Shortening one feeder by a small amount, as in Fig. 3B, is equivalent to putting capacitive reactance in series with resistance and the value of reactance will be dependent upon the amount by which the feeder is shortened. Lengthening the other feeder by the same amount introduces inductive reactance of exactly the same amount, and the resistive component of the input impedance is also exactly the same as in the capacitive case.

Consequently, if we leave the feeders joined together but feed "off center" as shown in Fig. 3C, the system is resonant and the same power is delivered to each dipole. Also, the shortened side is given a phase lead and the current in the lengthened side lags. As a result of this and the crossover in one feeder the system fires in the direction of the side toward which the feeder junction has been moved.

The interaction between the elements depends on the phasing between their currents, and not only affects the radiation resistance but introduces reactances of opposite sign into each element which in turn affects the phasing. Since the impedances of the elements themselves




Fig. 3 — Development of the off-center feed method of phasing. The character of the input impedance seen by a transmission line connected to the terminals is shown at the right. As stated in the text, this is based on $\frac{1}{4}$ -wavelength spacing and exact resonance in each element plus its half-wave feeder.

With 150-degree phasing the radiation resistance of each element is about 18 ohms. The resistance seen by the feed line at the junction of the phasing lines is about 10 ohms, the two reflected resistances being in parallel at this point and stepped up a small amount by the phasing lines. With 180-degree phasing each element has a radiation resistance of about 9 ohms, so that the increase in resistance with 150-degree phasing represents a worth-while increase in efficiency.




Fig. 4—The 14-Mc. system used at G6XN. Each L is 0.25 microhenry and each C is 500 μfd . The 28-Mc. addition shown in Fig. 5 is permanently connected at points A and B . An open position on the reversing switch disconnects the 14-Mc. phasing elements and main transmission line when operating on 28 Mc.

affect the standing-wave ratio on the feeders, and the s.w.r. in turn affects the values of reactance and resistance in the input impedance of the feeders, the proper feed point (junction of feeders) will be farther "off center" than would be the case if changing the current phasing caused no mutual effects between the radiating elements. However, at $\frac{1}{2}$ -wave spacing these effects are practically the same in both elements, so the feeder currents remain equal and the whole system remains resonant, since the phase shifts are equal and opposite.¹

This is true only if the antennas and the connecting line are exactly resonant. For example, if both feeders are too short, the reactance on the capacitive side is increased and the reactance on the inductive side is reduced; the inductive side therefore draws more current. Conversely, excess current on the capacitive side indicates that the feeders are too long. A 20 per cent inequality of currents will reduce the front-to-back ratio (for the G8PO 135-degree phasing) from infinity to about 16 db., although it causes only a slight reduction of forward gain.

¹ In this way a phase angle of 150 degrees is obtained by subtracting 30 degrees from the 180 degrees of the SJK system. As some readers may hasten to point out, one could equally well, in principle, start from 0 degrees (i.e., feeders not crossed over) and add 150 degrees. This is fairly common practice with the G8PO antenna, but with resonant feeders it is quite unworkable except perhaps for spot-frequency working, being too critical. The reason is that in this case the correct feed point is much nearer center than it would be with no interaction, and consequently a very small shift of feed point produces a large phase change.

A Practical System

Reversal of the beam requires the main feeder to be attached at the same distance off center on the opposite side. If preferred, the individual feeders may be kept equal in length, and ordinary lumped capacitances and inductances can take the place of the shortenings and lengthenings. These components can be conveniently mounted on a switch for beam reversal. This is the method used at G6XN, shown in Fig. 4, each feeder being a half-wave long.

The system should ordinarily be adjusted at the mid-frequency of the band or part of the band to be used. If there is an inequality in the feeder currents which favors the capacitive side to the same extent regardless of the switch position, both feeders must be shortened (by the same amount) to the extent required to establish equal currents. Alternatively, if the inductive side is favored the feeders must be lengthened. An adjustment of this type is very likely to be required because end effects make it difficult to calculate the lengths exactly. However, if care has been taken to make the lengths equal it is easy to get them right.

The effect of unequal lengths is best illustrated by an example. Suppose one feeder is resonant (zero reactance) and that the other is too short, giving a capacitive component of 100 ohms. Also suppose that equal and opposite lumped reactances of 50 ohms each are carried by the switch. In one switch position the net reactance of the short feeder is 150 ohms capacitive and the other is 50 ohms inductive; there is a phase difference but the inductive side draws more current. In the other switch position the net reactance of the short feeder is 50 ohms capacitive and the other feeder is also 50 ohms capacitive. The currents are equal but there is no phase shift, so we have the WSJK system. A signal received from the best direction in the first position will therefore be comparable in the second position, so there appears to be no back-to-front ratio. However, the same test on a signal from the opposite direction will indicate at least some back-to-front ratio. The example ignores the interaction between the elements with the change in phasing on operating the switch, but is in good qualitative agreement with what happens in practice if the lengths are not equal.

Once the feeder lengths are correct, the phasing can be adjusted to the desired value by changing L and C , keeping their reactances equal at the mid-frequency. (Equality can be checked by connecting the two together, to form a simple tuned circuit, independently of the feeder system, and making sure that they resonate at the desired frequency.)

Although there is no simple method available for measuring the phase difference, the phasing can be adjusted by the usual field-strength meter, the L/C ratio being adjusted either for maximum forward gain or to put the nulls at the back at

the desired angle with respect to the line of fire.

If meters are not available for checking the feeder currents a flashlight lamp connected to two probes can be bridged across an inch or two of each feeder in turn. Due to the low impedance the feeders can be handled without serious disturbance of the current or danger of r.f. burns, up to at least 100 watts input and probably much more. It is assumed, of course, that proper care has been taken to prevent any possibility, however remote, of high voltage appearing on the feeders.

At 100 watts input the current in each feeder is about $1\frac{1}{2}$ amperes and the phasing condensers should be rated to stand rather more than this because the currents may be higher during adjustment. Ordinary receiving-type mica capacitors have been used successfully but are not recommended because, even with the author's 100 watts, the current is well in excess of the rating. The capacity values are not unduly critical and normal tolerances are acceptable.

Harmonic Operation

Fig. 5 shows an addition to the system that permits operation on 28 Mc. Since on this frequency the spacing of the two elements in wavelengths is doubled, equal feeder currents are obtained only with unequal values of the phasing reactances for the two sides.

The true center of the system should be determined either by careful measurement of lengths or by making the feeder lengths deliberately too long or too short and adjusting the feed point for current equality; the system is then operating correctly on the principle of the WSJK antenna. A displacement of the feed point will now make the currents unequal, but the lengths can be made correct by the procedure already described. The correct lengths will no longer be exactly resonant and the system as a whole will look reactive, but this can be taken care of by the normal process of matching the main feedline from the transmitter.

A displacement of 6 or 7 inches, as shown in Fig. 5, will be found satisfactory when using a 33-foot long, 8-foot spacing system on 28 Mc., although it is not necessarily the optimum value. The 28-Mc. feeder system has no effect on 14-Mc. operation because it offers a high impedance at a point where the 14-Mc. system has low impedance. When operating on the 28-Mc. band the 14-Mc. feeder is disconnected by means of an open-circuit position on the 14-Mc. beam-reversing switch.

Matching of the transmission line running from the transmitter to the switch is independent of the rest of the system and should be left until last, the matching stubs being adjusted according to standard handbook procedure. Any out-of-balance in this main feeder, such as could be produced for example by one wire running very much closer than the other to some grounded object, must be tracked down and eliminated, since it upsets the relative currents in the resonant feeders and spoils the front-to-back ratio.




Fig. 5 — Linear phasing system for 28-Mc. operation with the antenna shown in Fig. 4. Points A and B are connected to the corresponding points in Fig. 4. A separate 600-ohm line runs to the transmitter for this band, as shown.

Performance

As the beam is electrically reversible and has a fairly broad forward lobe, about 140-degree rotation is all that need be provided for reasonable all-around coverage; this means that a very simple control system can be used. At G6XN the two elements are supported from a central cross-arm carrying a pair of control wires and hinged to the top of the mast. To prevent the feeders from fouling the guy wires they are brought in to a sort of "neck" on the mast two or three feet below the cross-arm, and then run out again and down at an angle of about 45 degrees to each other, which appears sufficient to prevent any undesirable interaction between them. The feeders have to be brought together at their bottom ends — i.e., at the switch — so that a diamond pattern is formed. Above the neck the feeders are fairly slack, with plenty of spacers, allowing the system to be rotated through the desired angle without short circuits or appreciable mismatching.

The main support for each element is a 10-foot length of 1 by 2 wood, and there are light bamboo extensions carrying wire elements with no additional insulation. This is not a recommended design but merely an example of what one can get away with; the reader no doubt will have better ideas.

Performance was carefully checked against the fixed beam on VK mentioned earlier, which itself had been checked against a dipole. Taking the average of a large number of consistent reports the fixed 4-element beam (theoretical gain about 7 db.) was $1\frac{3}{4}$ "S" points up on the dipole, and the antenna described here was $\frac{3}{4}$ of an "S" point down on the fixed beam, which is in reasonable agreement with the theory on the basis of 4

(Continued on page 120)

Happenings of the Month

NEW A.R.R.L. PRESIDENT

Gentlemen, we give you our new president — Goodwin L. Dosland, W0TSN!



"Dos" brings to the presidency considerable background in amateur organizational and League affairs. Coming to Chicago in the mid-thirties from his Moorhead, Minn., home to practice law, W0TSN joined the Tri-Town Radio Club where his abilities became quickly apparent and he was shortly elected to head the club. In this capacity he became a delegate to the Chicago Area Radio Club Council which, similarly recognizing his leadership qualities, promptly elected him its Chairman. He thereupon was chosen to chairman the Council organization which ran the very successful 1938 ARRL National Convention. What followed was only natural — Dosland became the choice of the Central Division for its director in 1940 and again in 1942. He was, incidentally, a candidate for Congress and although defeated made a surprising show of strength in a district normally heavily leaning to the opposite party.

With the coming of war Dos relinquished his ARRL directorship upon call to active duty, where he first set up and ran the Navy's radio operator training school at Miami (Ohio) University and then at several other schools. Later he got overseas assignments on both war fronts as communications officer. Postwar he returned to Moorhead to take over the law practice of his deceased father, and became W0TSN . . . president of the Red River Radio Club and . . . you guessed it . . . director of the Dakota

Division in 1948, again in 1950, and again the first of this year.

Our new prexy asks us to relay to all amateurs the following note of thanks:

I take this opportunity to express my sincere appreciation and thanks to the many Amateurs throughout our Country who have been so kind as to send me messages, letters of congratulations, and for their kind offers of assistance.

My only regret is that it is physically impossible for me to answer each of the messages and letters individually, and I sincerely trust that each of you will accept this as a personal message of appreciation to you, from your newly elected president.

I know that we will all work together in harmony and unity for the continuance of the best interests of our League and the furtherance of Ham Radio.

73,

Dos, W0TSN
President, ARRL

CANADIAN RECIPROCITY

For quite some time now there has been hanging fire in Washington a treaty between the governments of Canada and the United States which, among other things, would permit the operation by amateurs of one country in the territory of the other. In mid-May, the U. S. Senate finally having ratified, diplomatic representatives of the two governments met to bring the treaty formally into force. This brings a step nearer the time when we in the U. S. shall be able to operate fixed, portable or mobile in Canada, and when our VE associates will be able to do likewise in our country. It appears now that only minimum additional regulation is required before the privilege becomes a reality — perhaps simply taking the form of specific notification blanks filed with appropriate officials. We'll have all the dope for you when available.

NEW F.C.C. AMATEUR CHIEF

William S. Grenfell, W4GF, on May 19th was appointed Chief, Amateur Branch, Public Safety & Amateur Division, Safety & Special Radio Services Bureau, FCC. Thus he fills the vacancy caused by the recent promotion of Ivan H. Loucks, W3GD, to Assistant Chief of the Industry and Commerce Division in the same bureau. Amateurs everywhere, especially those

ARE YOU LICENSED?

- When joining the League or renewing your membership, it is important that you show whether you have an amateur license, either station or operator. Please state your call and/or the class of operator license held, that we may verify your classification.

who were more intimately aware of Loucks' capable handling of ham affairs, will wish him continued success.

The new amateur branch chief was bitten by the ham bug in 1929 and became W7GE; he got his Amateur Extra First ticket a year later. An EE graduate of Oregon State College, OM Grenfell worked several years for the state highway and police radio system, then in 1940 joined the rapidly-expanding Radio Intelligence Division of FCC. He served on the radar school staff of the Navy, rejoined FCC in 1946 as engineer in the Frequency Allocation & Treaty Division, subsequently becoming assistant chief in the frequency utilization and requirements branch.

W4GF gets around on most of the ham bands from his home in Falls Church, Va., but likes low power; there's a 6- and 10-meter mobile job of 10 watts, and even the home station runs only 30 watts. He participates in the AREC and the local civil defense net activities.



W4GF

EXAMINATION SCHEDULE

The Federal Communications Commission will give amateur examinations during the second half of 1952 on the following schedule. Remember this list when you need to know when and where examinations will occur. Where exact dates or places are not shown below, information may be obtained, as the date approaches, from the Engineer-in-Charge of the district. *Even stated dates are tentative and should be verified from the Engineer as the date approaches.* No examinations are given on legal holidays. All examinations begin promptly at 9 A.M. except as noted.

Albuquerque, N. M.: Oct. 3rd
Amarillo, Texas: Sept. 30th
Anchorage, Alaska, 52 Federal Bldg.: By appointment
Atlanta, Georgia, 411 Federal Annex: Tuesday and Friday at 8:30 A.M.
Bakersfield, Calif.: Sometime in August
Baltimore, Md., 508 Old Town Bank Bldg.: Monday through Friday. When code test required, between 8:30 A.M. and 9:30 A.M.
Bangor, Maine: Sometime in October
Beaumont, Texas, 329 P. O. Bldg.: Monday through Friday, except Thursday only when code test required.
Birmingham, Ala.: Sept. 5th and Dec. 4th
Boise, Idaho: Sometime in October
Boston, Mass., 1600 Customhouse: Monday through Friday 8:30 A.M. to 2:00 P.M.
Buffalo, N. Y., 328 P. O. Bldg.: Thursday
Butte, Mont.: Sept. 18th
Charleston, W. Va.: Sometime in Sept. and Dec.
Chicago, Ill., 826 U. S. Courthouse: Friday
Cincinnati, Ohio: Sometime in August and November
Cleveland, Ohio: Sometime in September and December
Columbus, Ohio: Sometime in July and October
Corpus Christi, Texas: Sept. 10th and Dec. 3rd
Dallas, Texas, 500 U. S. Terminal Annex Bldg.: Monday through Friday

Davenport, Iowa: Sometime in July and October
Denver, Colorado, 521 New Customhouse: 1st and 2nd Thursdays and by appointment
Des Moines, Iowa: Sometime in July and October
Detroit, Michigan, 1029 Federal Bldg.: Wed. and Fri.
El Paso, Texas: Oct. 7th
Ft. Wayne, Ind.: Sometime in August and November
Fresno, Calif.: Sept. 19th and Dec. 19th
Grand Rapids, Mich.: Sometime in July and October
Hartford, Conn.: Sometime in September
Hilo, T. H.: Oct. 7th
Honolulu, T. H., 502 Federal Bldg.: Monday through Friday, 8:00 A.M.
Houston, Texas, 324 U. S. Appraisers Stores Bldg.: Tuesday and Friday
Indianapolis, Ind.: Sometime in August and November
Jackson, Miss.: Sept. 10th and Dec. 10th
Jacksonville, Fla.: Oct. 11th
Jamestown, N. D.: Oct. 8th, 10:00 A.M.
Juneau, Alaska, 6 Shattuck Bldg.: By appointment
Kansas City, Mo., 3200 Federal Office Bldg.: Friday, 8:30 A.M., and by appointment
Knoxville, Tenn.: Sept. 18th and Dec. 18th
Las Vegas, Nev.: Sometime in October
Lihue, Kauai, T. H.: Oct. 21st
Little Rock, Ark.: July 16th and Oct. 8th
Los Angeles, 539 Federal Bldg.: Wednesday, 9 A.M., 1 P.M.
Louisville, Ky.: Sometime in November
Manchester, N. H.: Sometime in November
Marquette, Mich.: Nov. 5th, 10:00 A.M.
Memphis, Tenn.: July 11th and Oct. 10th
Miami, Fla., 312 Federal Bldg.: Thursday
Milwaukee, Wis.: Sometime in July and October
Mobile, Ala., 419 U. S. Courthouse and Customhouse: Wednesday and by appointment
Nashville, Tenn.: Aug. 7th and Nov. 6th
New Orleans, La., 400 Audubon Bldg.: Monday through Friday, except Monday through Wednesday only at 8:30 A.M. when code test required
New York, N. Y., 748 Federal Bldg., 641 Washington St.: Monday through Friday
Norfolk, Va., 402 Federal Bldg.: Monday through Friday except Friday only when code test required
Oklahoma City, Okla.: July 17th-18th and Oct. 16th-17th
Omaha, Neb.: Sometime in July and October
Philadelphia, 1005 U. S. Customhouse: Mon. thru Fri.
Phoenix, Ariz.: Sometime in July and October
Pittsburgh, Penna.: Sometime in August and November
Portland, Maine: Sometime in October
Portland, Ore., 307 Fitzpatrick Bldg.: Monday through Friday; when code test required, Friday only — 9:00 A.M. for 13 and 20 w.p.m.; 1:00 P.M. for 5 w.p.m.
Reno, Nev.: Oct. 17th
Roanoke, Va.: Oct. 4th
St. Louis, Mo.: Sometime in August and November
St. Paul, Minn., 208 Federal Courts Bldg.: Friday
Salt Lake City, Utah: Sept. 13th and Dec. 13th
San Antonio, Texas: Aug. 7th and Nov. 6th
San Diego, Calif., 15-C U. S. Customhouse: By appointment
San Francisco, Calif.: 323-A Customhouse: Advanced Class Monday through Friday; Novice and Technician Classes, Monday, 8:45 A.M.; General and Extra Class, Friday, 8:45 A.M.
San Juan, P. R., 323 Federal Bldg.: Thursday, and Monday through Friday at 8:00 A.M. if no code test required
Savannah, Ga., 214 P. O. Bldg.: By appointment
Schenectady, N. Y.: Sept. 17th-18th and Dec. 3rd-4th
Seattle, Wash., 808 Federal Office Bldg.: Friday
Sioux Falls, S. D.: Sept. 10th and Dec. 10th; Novice and Technician, 10:00 A.M.; others, 1:00 P.M.
Spokane, Wash.: Sept. 16th
Syracuse, N. Y.: Sometime in July and October
Tallahassee, Fla.: July 12th
Tampa, Fla., 410 P. O. Bldg.: By appointment
Tucson, Ariz.: Sometime in October
Tulsa, Okla.: July 21st-22nd and Oct. 20th-21st
Wailuku, T. H.: Oct. 9th
Wash., D. C., 415 22nd St., N. W.: Monday through Friday, 8:30 A.M. to 5:00 P.M.
Wichita, Kans.: Sometime in September
Williamsport, Penna.: Sometime in September and December
Wilmington, N. C.: Dec. 6th
Winston-Salem, N. C.: Aug. 2nd and Nov. 1st

**MINUTES OF 1952 SPECIAL MEETING OF THE
BOARD OF DIRECTORS, AMERICAN RADIO
RELAY LEAGUE,
May 9-10, 1952**

1) Pursuant to due notice, the Board of Directors of The American Radio Relay League, Inc. met in special session at the Hartford Club, Hartford, Conn., on May 9, 1952. The meeting was called to order at 9:30 A.M. EDTST with President George W. Bailey in the Chair and the following other directors present:

Wayland M. Groves, First Vice President
John H. Brabb, Great Lakes Division
Goodwin L. Dosland, Dakota Division
John R. Griggs, Southwestern Division
Alfred C. Heck, Atlantic Division
Lamar Hill, Southeastern Division
Kenneth E. Hughes, Pacific Division
William H. Jacobs, Roanoke Division
Joseph M. Johnston, Hudson Division
Wesley E. Marriner, Central Division
Franklin K. Matejka, Rocky Mountain Division
A. David Middleton, West Gulf Division
Percy C. Noble, New England Division
Alexander Reid, Canada
R. Rex Roberts, Northwestern Division
William J. Schmidt, Midwest Division
James W. Watkins, Delta Division

Also in attendance, as a member of the Board without vote, was General Manager A. L. Budlong. Also in attendance, at the invitation of the Board as non-participating observer, was New England Division Vice-Director Frank L. Baker. There were also present Vice-President Francis E. Handy, Treasurer David H. Houghton, Technical Director George Grammer, Assistant Secretaries Richard L. Baldwin and John Huntoon, General Counsel Paul M. Segal and Quayle B. Smith of his office. The meeting was welcomed and briefly addressed by the Chair.

2) On motion of Mr. Brabb, unanimously VOTED that the minutes of the 1951 annual meeting of the Board of Directors are approved in the form in which they were issued by the Secretary with the addition to Item 45 of those

minutes of the following statement of purpose for resolving the Board into a Committee of the Whole: That the Board resolve itself into a Committee of the Whole to take under consideration the following matters:

a) a report of the Canadian General Manager on the progress that he has made in securing uniformity in the Canadian 'phone regulations to conform with those of the United States, as requested of the Canadian General Manager in a motion unanimously adopted at the 1946 meeting of the Board;

b) a discussion of the present status of the temporary stewardship of amateur radio activities in Canada contemplated in League By-Laws 28, 29 and 30, with a view of determining whether League activities in Canada can be more directly integrated with the League's divisional organization.

3) On motion of Mr. Brabb, unanimously VOTED that the minutes of the 1952 annual meeting of the Board of Directors are approved in the form in which they were issued by the Secretary.

4) On motion of Mr. Roberts, unanimously VOTED that the annual reports of the officers to the Board of Directors are accepted and the same placed on file.

5) On motion of Mr. Dosland, unanimously VOTED that the Board, having examined its mail action in electing Francis E. Handy as Vice President to serve until May 10, 1952 now ratifies this action and decides to take the aforesaid position as of May 25, 1951.

6) Moved, by Mr. Dosland, that the regular order of business be suspended and that the meeting take up, as Item 4b of the agenda, the ratification and approval of the actions of the Executive Committee during the past year. But, after discussion, during which the General Council stated such action is no longer required under the new Charter, with unanimous consent, Mr. Dosland withdrew the motion.

7) On the reception of reports of committees: Without objection, ordered that the report of the Finance Committee goes over for consideration later in the meeting. Mr. Noble read the report of the Planning Committee; whereupon, on motion of Mr. Johnston, unanimously VOTED to receive the report. There was no report from the Policy and Review Committee. Upon the request of Mr. Noble, without objection, ordered that the report of the Constitution Revision



The ARRL Board of Directors and League officials at the annual meeting of the Board in Hartford on May 9th. Seated around the table, *l. to r.*: Director Watkins, Delta; Director Griggs, Southwestern; Director Hughes, Pacific; Vice-President Groves; Director Roberts, Northwestern; Director Schmidt, Midwest; Vice-President Handy; Counsel Smith; President Bailey; General Manager Budlong; Asst. Secretary Huntoon; Treasurer Houghton; Director Reid, Canada; Director Noble, New England; Director Matejka, Rocky Mountain; Director Brabb, Great Lakes; Director Marriner, Central. *Rear, l. to r.*: Vice-Director Baker, New England; Technical Director Grammer; Director Dosland, Dakota; Director Middleton, West Gulf; Director Hill, Southeastern; Director Heck, Atlantic; Director Jacobs, Roanoke; Director Johnston, Hudson; Asst. Secretary Baldwin.

Committee goes over for consideration later in the meeting. Mr. Griggs reported briefly for the Membership and Publications Committee; on motion of Mr. Johnston, unanimously VOTED to receive the report.

8) On motion of Mr. Hill, unanimously VOTED that the annual reports of the directors to the Board of Directors are accepted and the same placed on file.

9) At this point, supplementary oral reports were rendered by the officers of the League. During the course of the General Manager's report, he and the General Counsel discussed at length the relationship of the League to the various government agencies in Washington dealing with amateur matters.

10) During the course of the above, the Board was in recess from 11:14 A.M. to 11:24 A.M.

11) On motion of Mr. Dosland, unanimously VOTED that the regular order of business be suspended and that the meeting proceed to take up at this time Item 14 of the agenda, Consideration of recommendations of the Constitution Revision Committee.

12) After discussion, moved, by Mr. Dosland, that the following By-Laws of The American Radio Relay League, Inc., be adopted

[The text of the By-Laws appears in a separate article in this issue and is not repeated here. — Ed.]

The yeas and nays being ordered, the question was decided in the affirmative: Whole number of votes cast, 16; necessary for adoption, 11; yeas, 16; nays, 0. All the directors voted in the affirmative, except the President and First Vice-President, who abstained as required. So the By-Laws were ADOPTED.

13) Moved, by Mr. Noble, to adopt the following resolution: The Board of Directors, having, at its 1951 meeting, effectuated Amended Articles of Association and having at the present meeting adopted new By-Laws, be it now RESOLVED, that the Constitution and By-Laws of The American Radio Relay League, Inc., as published June 1, 1951, and entitled, "Constitution and By-Laws of The American Radio Relay League, Inc., Revised to June 1, 1951," be and they hereby are repealed, effective July 1, 1952. The yeas and nays being ordered, the question was decided in the affirmative: Whole number of votes cast, 16; necessary for adoption, 11; yeas, 16; nays, 0. All the directors voted in the affirmative except the President and First Vice-President, who abstained as required. So the resolution was ADOPTED.

14) On motion of Mr. Noble, the following Rules and Regulations Concerning American Radio Relay League Constitutions were unanimously ADOPTED:

[The text of the regulations appears along with the Charter and By-Laws in another article in this issue, and is not repeated here. — Ed.]

15) On motion of Mr. Noble, the following Rules and Regulations Concerning Affiliated Societies were unanimously ADOPTED:

[The text of the regulations appears along with the Charter and By-Laws in another article in this issue, and is not repeated here. — Ed.]

16) Moved, by Mr. Noble, the adoption of the following resolution: Be it RESOLVED that, pursuant to Article 7 of the Amended Articles of Association, F. E. Handy is hereby designated and appointed a member of the Executive Committee to serve as such for the 53-week period ending May 16, 1953. The yeas and nays being ordered, the question was decided in the affirmative: Whole number of votes cast, 16; necessary for adoption, 9; yeas, 16; nays, 0. All the directors voted in the affirmative except the President, who abstained as required, and the First Vice-President. So the resolution was ADOPTED.

17) Moved, by Mr. Noble, the adoption of the following resolution: Be it RESOLVED that, pursuant to Article 7 of the Amended Articles of Association, David H. Houghton is hereby designated and appointed a member of the Executive Committee to serve as such for the 53-week period ending May 16, 1953. The yeas and nays being ordered, the question was decided in the affirmative: Whole number of votes cast, 16; necessary for adoption, 9; yeas, 16; nays, 0. All the directors voted in the affirmative except the President, who abstained as required, and the First Vice-President. So the resolution was ADOPTED.

QSL MANAGERS THANKED BY BOARD

At its May meeting the League's Board of Directors took time to express its thanks to the QSL Bureau Managers in the U. S., its possessions, and Canada. These Bureau Managers have continued to give unstintingly of their time and energy in order that the DX cards from overseas stations may be delivered to the addressees. We can all add our thanks to those of the Board by writing a note of appreciation to the Manager who serves our particular call area. And when you send him that note, don't forget to include at least one stamped and self-addressed envelope which is about 4 by 9 inches in size. Your call letters should be printed in the upper left-hand corner, with your name and address in the usual place. If you will send these envelopes, your QSL Bureau Manager will be very grateful.

18) The Board was in recess for luncheon from 12:05 P.M. to 1:34 P.M.

19) On motion of Mr. Jacobs, after discussion, unanimously VOTED that the General Manager is authorized to reimburse SCMs for travel within the limits of the division in which they reside, provided this meeting is called by the director of the division for the purpose of considering League matters, and provided further that SCMs shall attend not more than one such meeting each calendar year and that said trips shall be considered one of the SCM annual trips otherwise provided for elsewhere by the Board, and provided further that nothing in this authorization shall permit travel into or out of the continental United States as a unit, or Canada as a unit.

20) Moved, by Mr. Jacobs, that By-Law 6, just adopted, be amended to read as follows:

6. Every officer, director and vice-director of the League shall serve and continue in office until his successor shall have been elected and qualified; provided, however, the President shall not succeed himself in office a second time.

The yeas and nays being ordered, the question was decided in the negative: Whole number of votes cast, 16; necessary for adoption, 11; yeas, 3; nays, 13. Those voting in the affirmative were Messrs. Griggs, Jacobs and Middleton; all the other directors voted in the negative except the President and First Vice-President, who abstained as required. So the motion to amend was rejected.

21) Moved, by Mr. Matejka, that the Secretary of the League be instructed to request, in the name of the American Radio Relay League, a suballocation in the 7-Megacycle band for 'phone from 7225 to 7300 kc. Moved by Mr. Dosland, that the motion be amended to strike out the frequencies 7225-7300 kc, and substitute therefor 7200-7300 kc. The yeas and nays being ordered, upon request, the amendment was decided in the affirmative: Whole number of votes cast, 16; necessary for adoption, 9; yeas, 15; nays, 1. All the directors voted in the affirmative except Mr. Hughes, who voted opposed, and the President, who abstained as required, and Mr. Reid, who also abstained. So the amendment was ADOPTED. The question then being on the motion as amended, the same was decided in the affirmative: Whole number of votes cast, 16; necessary for adoption, 9; yeas, 16; nays, 0. All the directors voted in the affirmative except the President, who abstained as required, and Mr. Reid, who also abstained. So the motion, as amended, was ADOPTED.

22) Moved, by Mr. Matejka, that the Secretary be instructed to request of the Federal Communications Commission, in the name of the American Radio Relay League, that the 'phone sub-band at 3.8 Megacycles be extended to

read 3750-4000 kc. But, after discussion, unanimous consent being given, Mr. Matejka withdrew his motion.

23) On motion of Mr. Dosland, unanimously VOTED, at 2:25 P.M., that the Board does now resolve itself into a Committee of the Whole in order to consider the entire subject of frequency allocations and suballocations in the amateur bands in the United States. The Chair appointed himself Chairman of the Committee of the Whole. The Board, sitting as a Committee of the Whole, was in recess from 3:37 P.M. to 3:46 P.M. and from 5:37 P.M. to 5:42 P.M. The Committee arose at 5:42 P.M. and Mr. Bailey, as Chairman of the Committee, laid before the Board the report of the Committee.

24) On motion of Mr. Matejka, unanimously VOTED, Mr. Reid abstaining, that the General Manager is directed to request of the Federal Communications Commission in the name of the American Radio Relay League, that the frequencies 21,250-21,450 be authorized for 'phone operation.

25) On motion of Mr. Matejka, unanimously VOTED, Mr. Reid abstaining, that the General Manager is directed to request of the Federal Communications Commission in the name of the American Radio Relay League, that the possession of Advanced Class license, or higher, be continued as a requirement for 'phone operation in the 3.8- and 14.2-Mc. sub-bands.

26) On motion of Mr. Matejka, unanimously VOTED, Mr. Reid abstaining, that the General Manager is directed to request of the Federal Communications Commission in the name of the American Radio Relay League, that issuance of the Advanced Class license be continued after December 31, 1952.

27) On motion of Mr. Matejka, unanimously VOTED, Mr. Reid abstaining, that the General Manager is directed to request of the Federal Communications Commission in the name of the American Radio Relay League, that the present operating privileges for Novice licensees in the 26.96-Megacycle band be retained.

28) On motion of Mr. Matejka, unanimously VOTED, Mr. Reid abstaining, that the General Manager is directed to request of the Federal Communications Commission in the name of the American Radio Relay League, that A-0 emission be authorized for the frequencies 51-54 Megacycles.

29) On motion of Mr. Matejka, VOTED, 14 votes in favor to 2 opposed, Mr. Reid abstaining, that the General Manager be directed to request of the Federal Communications Commission in the name of the American Radio Relay League, that f.s.k. emission, teletype only, be authorized on the sub-band 7150-7200 kc.

30) On motion of Mr. Matejka, unanimously VOTED, Mr. Reid abstaining, that the General Manager is directed to request of the Federal Communications Commission in the name of the American Radio Relay League, that the frequencies 7150-7200 kilocycles be authorized for Novice operation, A-1 emission only.

31) On motion of Mr. Matejka, unanimously VOTED, Mr. Reid abstaining, that the General Manager is directed to request of the Federal Communications Commission in the name of the American Radio Relay League, that Novice Class licensees be authorized to operate on the frequencies 51-53 Megacycles, A-1 and A-3 emission, for a trial period of one year.

32) On motion of Mr. Matejka, unanimously VOTED, Mr. Reid abstaining, that the General Manager is directed to request of the Federal Communications Commission in the name of the American Radio Relay League, to amend the amateur rules so that the 'phone authorization in the 28-Megacycle band shall read 28,250-29,700 kc.

33) The Board was in recess for dinner from 5:57 P.M. to 7:51 P.M.

34) Moved, by Mr. Matejka, that the General Manager be directed to request of the Federal Communications Commission in the name of the American Radio Relay League, that the 'phone suballocation in the 3.8-Megacycle band be amended to read 3750-4000 kc. The yeas and nays being ordered, on request, the question was decided in the negative: Whole number of votes cast, 16; necessary for adoption, 9; yeas, 7; nays, 9. Those voting in the affirmative were Messrs. Dosland, Hill, Matejka, Middleton, Noble, Watkins and Groves; those voting in the negative were Messrs. Brabb, Griggs, Heck, Hughes, Jacobs, Johnston, Marriner, Roberts, and Schmidt. The President abstained,

as required, and Mr. Reid also abstained. So the motion was rejected.

35) Moved, by Mr. Matejka, that the General Manager is directed to request of the Federal Communications Commission in the name of the American Radio Relay League, that mobile 'phone operation be authorized on the frequencies 3775-3800 kc. Moved, by Mr. Jacobs, to amend the motion so that 'phone is authorized on these frequencies with no reference to mobile. The yeas and nays being ordered, on request, the question on the amendment was decided in the negative: Whole number of votes cast, 16; necessary for adoption, 9; yeas, 7; nays, 9. Those voting in the affirmative were Messrs. Dosland, Jacobs, Matejka, Middleton, Noble, Watkins, and Groves; those voting in the negative were Messrs. Brabb, Griggs, Heck, Hill, Hughes, Johnston, Marriner, Roberts and Schmidt. The President abstained as required and Mr. Reid also abstained. So the motion to amend was rejected. The question then being on the original motion, and the yeas and nays being ordered, on request, the same was decided in the affirmative: Whole number of votes cast, 16; necessary for adoption, 9; yeas, 14; nays, 2. All the directors voted in the affirmative except Messrs. Griggs and Hughes; the President abstained, as required, and Mr. Reid also abstained. So the motion was ADOPTED.

36) The Board of Directors was informed by Mr. Hill of the death on April 17, 1952 of Dr. Orville Cheatham, W4DU, of Jacksonville, Florida, a friend to amateur radio and a true friend to the many radio amateurs who had the privilege of his acquaintance or the joy of his friendship. Whereupon, on motion of Mr. Hill, the following resolution was unanimously ADOPTED:

RESOLVED: That on behalf of amateur radio the Board expresses its deep regret at the loss of Doctor Cheatham, a true leader, a true friend, and a true amateur; that the Board expresses its deep and sincere sympathy for Doctor Cheatham's family; and that the President of the League is requested to express these sentiments to Doctor Cheatham's family and to transmit to them a copy of this resolution.

37) Mr. Middleton read a letter from Mr. C. Fermaglich, the SCM of Southern Texas, requesting, on behalf of the Houston Amateur Radio Club and members of the West Gulf Division, that the Board of Directors of the American Radio Relay League authorize a National Convention of the League in Houston in 1953. Whereupon, on motion of Mr. Middleton, unanimously VOTED that the Board of Directors authorizes the Houston Amateur Radio Club to hold an ARRL National Convention in Houston in 1953, subject to the terms of a satisfactory contract to be executed between the Club and the League, similar in tenor to that for previous National Conventions.

38) Moved, by Mr. Middleton, that the Editor of QST be instructed to publish in QST, in the earliest issue possible, any material forwarded to QST by any ARRL elected official, when such material pertains to any phase or phases of Amateur Radio or the ARRL. Such material (not more than 250 words per issue) to be signed with the name and title of the authoring ARRL official. After discussion, on motion of Mr. Dosland, VOTED to amend the motion by prefaceing it with the words "When so ordered by the Board of Directors.". The question then being on the motion as amended, the same was unanimously ADOPTED.

39) Moved, by Mr. Middleton, that the ARRL Headquarters Staff establish and publicize a policy on TVI by means of a nationwide educational program directed to TV manufacturers, servicemen and repairmen, and TV set users, such a program to be implemented by suitable literature together with other media that will assist said program. Moved by Mr. Johnston to amend the motion by striking out the text and substituting therefor that the Board commends the management staff of ARRL for the excellent manner in which it has attacked the TVI problem; but there was no second, so the motion to amend was lost. On motion of Mr. Dosland, VOTED to amend the motion by deleting the words "That the ARRL Headquarters Staff" and substituting therefor "That the Board compliments the Headquarters Staff on the work that it has done and directs it to continue to." The question then being on the motion as amended, the same was unanimously ADOPTED.

40) On motion of Mr. Middleton, the following reso-

lution was unanimously ADOPTED:

RESOLVED, that the Board of Directors of the American Radio Relay League does hereby express to Mr. Phil Rand, WIDBM, its thanks and appreciation for his untiring efforts on behalf of amateur radio in connection with combating TVI.

41) Moved, by Mr. Middleton, that the ARRL Technical Director be instructed to make (or to secure a qualified testing laboratory) a thorough evaluation of both high-pass and low-pass TVI filters currently available on the commercial market and that this data be published without delay in QST, referring to various filters as "Type A—low-pass three-section M-derived" etc. together with their respective block diagrams. No mention shall be made of the manufacturer's type or brand name in ARRL publications in this connection. And that this program of investigation and publication of the results be continued in order to acquaint the buying amateurs with the technical facts regarding the relative merits of this type of manufactured units as compared with those hand-built units described in ARRL publications. But there was no second, so the motion was lost.

42) Moved, by Mr. Middleton, that this Board of Directors direct and order that full and complete lists of all affiliated clubs in any and all divisions be furnished to any group of ten (10) or more ARRL members or to any affiliated club upon request, if the request is accompanied by a statement that the lists will not be used for commercial purposes. But there was no second, so the motion was lost.

43) Moved, by Mr. Middleton, that the Editor of QST be instructed to print the once familiar and time-honored ARRL guarantee covering space advertised products in each issue of QST; but unanimous consent being given Mr. Middleton, with the permission of his second, withdrew the motion.

44) Moved, by Mr. Middleton, that the ARRL sponsor a "Technical Scholarship" which will lead to a year's paid employment in the ARRL Laboratory at Headquarters for an amateur who has not yet reached his twenty-first birth date and who, in the decision of the judges (to be selected by the Board of Directors), has most clearly demonstrated his inherent ability, interest and enthusiasm towards the technical side of Amateur Radio, through his contribution to Amateur Radio in the year 1952, such "Technical Scholarship" to be a continuing yearly award with job offers made to the winners. On motion of Mr. Dosland, VOTED to table the motion and refer it to the Planning Committee relative to the cost of such a program.

45) Moved, by Mr. Griggs, that the ARRL Technical Director be instructed to make (or to secure from a qualified testing laboratory) an immediate and searching investigation of representative types of TV receivers relative to their capability to reject amateur signals and also to determine the extent of their radiated interference as affecting amateur communications, and that the Editor of QST be instructed to supply the results of these unbiased engineering reports to League members upon request. After discussion, moved by Mr. Dosland to amend the motion to read that the General Manager of the League have the League's technical staff, to the extent practicable, make an investigation of representative types of TV receivers, etc., with the engineering reports referred to be supplied League members upon request, the information to be cleared through the office of the General Counsel. But the motion to amend was rejected, 4 votes in favor to 7 opposed. The question then being on the original motion, the yeas and nays being ordered upon request, the same was decided in the negative: Whole number of votes cast, 17; necessary for adoption, 9; yeas, 3; nays, 14. All the directors voted in opposition except Messrs. Griggs, Middleton and Watkins, and the President, who abstained as required. So the motion was rejected.

46) On motion of Mr. Heck, unanimously VOTED that the General Manager of the League is instructed to conduct a continuing survey looking toward expansion of maritime mobile privileges.

47) On motion of Mr. Heck, the following resolution was unanimously ADOPTED:

RESOLVED, that the Board of Directors, on behalf of Amateur Radio request its Secretary to convey to the Chairman of the Federal Communications Commission this expression of their appreciation of the

meritorious and unstinting service of the members of the Field Engineering and Monitoring Bureau of the Commission.

48) On motion of Mr. Marriner, unanimously VOTED that the Technical Editor of QST is commended on the excellence of the technical material appearing in QST during the past year. Mr. Grammer spoke briefly in appreciation. (Applause)

49) Moved, by Mr. Marriner, that QST should, from time to time, stress the existence of the Ragchewers Club, A-1 Operators Club, etc., and the requirements for them, etc. But there was no second, so the motion was lost.

50) On motion of Mr. Johnston, the following resolution was unanimously ADOPTED:

WHEREAS, on March 21, 1952, Ralph T. Beaudin would have completed twenty-five years of continuous service to the American Radio Relay League, as Assistant Circulation Manager and more recently also as Production Manager, and

WHEREAS, the Board of Directors of the American Radio Relay League is deeply grieved at his sudden passing on February 15, 1952,

Now, therefore, be it RESOLVED, that the Board of Directors, meeting at Hartford, Connecticut, on May 9, 1952, in recognition of Ralph T. Beaudin's untiring efforts on behalf of the League, does hereby express its deep appreciation of his loyalty, fidelity and intelligent devotion to the best interests of amateur radio, and expresses its deep sense of loss at his passing.

51) On motion of Mr. Johnston, the following resolution was unanimously ADOPTED:

Whereas the QSL Bureau Managers of the United States and Canada have continued to render valuable service to their fellow amateurs, without material compensation, BE IT RESOLVED that the Board does hereby commend the QSL Bureau Managers for their faithful service.

52) The Board was in recess from 9:37 p.m. to 9:45 p.m.

53) Mr. Roberts' position on the agenda having been reached, he reported to the Board receipt of the following resolution:

RESOLVED, by the sixth National ARRL Convention assembled at Seattle, July 29, 1951 that the ARRL requests of the Federal Communications Commission what should be considered good engineering standards in the reduction of TVI.

On motion of Mr. Dosland, unanimously VOTED that this resolution be received and filed.

54) On motion of Mr. Jacobs, after discussion, unanimously VOTED that the General Manager is hereby authorized to reimburse division directors for actual expenses incurred by them during the year 1952 in the proper administration of ARRL affairs in their respective divisions up to amounts as follows:

Canadian Director	\$ 350
Atlantic Division Director	600
Central Division Director	850
Dakota Division Director	600
Delta Division Director	800
Great Lakes Division Director	800
Hudson Division Director	700
Midwest Division Director	800
New England Division Director	300
Northwestern Division Director	800
Pacific Division Director	600
Roanoke Division Director	200
Rocky Mountain Division Director	400
Southeastern Division Director	600
Southwestern Division Director	950
West Gulf Division Director	1000

55) On motion of Mr. Griggs, unanimously VOTED that the General Manager is hereby authorized to pay expenses for the operation of ARRL committees during the year 1952 but not to exceed the amounts as follows:

Planning Committee	\$2000
Finance Committee	\$ 200

56) On motion of Mr. Roberts, unanimously VOTED

that, to continue the Board policy of reimbursing SCMs and QSL Managers for certain travel via the shortest commonly-traveled route, the General Manager is hereby authorized to pay during the year 1952 a total amount not exceeding three thousand dollars (\$3000) under the conditions specified in Minute (52) of the 1951 meeting of the Board.

57) On motion of Mr. Roberts, unanimously VOTED that the Constitution Revision Committee, its work having been completed, is hereby dissolved with the deep appreciation of the Board for the excellent work done in revising the League's Charter and By-Laws.

58) On motion of Mr. Roberts, unanimously VOTED that the General Manager is hereby authorized to reimburse, at the rate of seven and a half cents per mile or actual rail or bus fare, Section Emergency Coordinators to a maximum of ten trips each per year per section, throughout their respective sections in United States and Canadian territory only, via the shortest commonly-traveled route for the pre-arranged meetings or contacts, for the purpose of close contact with Emergency Coordinators and through meetings, selling clubs and individuals on the necessity for emergency corps work, and contacting duly constituted civil defense officials, relief and appropriate local agencies, subject to submission and approval of a full report to the Communications Manager. If one SEC replaces another and the section quota of trips has been exhausted by his predecessor, he may with a written concurrence of his director and the Communications Manager request advance approval of subsequent reimbursement for specific travel (but not more than five trips) under the provisions above. In cases where official meetings or other official contact with state or regional civil defense authorities makes travel for attendance in adjacent sections especially desirable, an SEC may in each case be authorized such travel exceptionally, as one of the authorized trips, but only after coordination with the division director and by advance permission of and at the discretion of the ARRL Communications Manager; no reimbursement in such special cases, however, may cover any travel to points more than 100 miles beyond the boundary of his own section. The total amount covered by this motion for travel during the year 1952 shall not exceed two thousand five hundred dollars (\$2,500).

59) On motion of Mr. Griggs, unanimously VOTED that the General Manager is hereby authorized to pay, during the period between January 1, 1953 and the 1953 meeting of the Board, expenses against usual authorizations for administrative and committee operations, in no greater amounts than 1952 authorized amounts.

60) On motion of Mr. Griggs, the Board recessed at 10:35 P.M. under order to reassemble at 9:30 A.M. on the morning. The Board reassembled at the same place on May 10, 1952 and was called to order by the Chair at 9:30 A.M. with all directors and other persons herein before mentioned in attendance except Messrs. Segal and Smith, who entered the meeting at 9:55 A.M.

61) Moved by Mr. Middleton, that the Editor of QST be instructed to print the once familiar and time-honored ARRL statement covering space-advertised products in each issue of QST. On motion of Mr. Reid, VOTED 13 votes in favor to 3 opposed to amend the motion so that it shall read that the Editor of QST be instructed to print the once familiar and time-honored ARRL statement covering space advertised products from time to time at his discretion, subject to the approval of the League's General Counsel. The question then being on the motion as amended, the same was ADOPTED.

62) On motion of Mr. Brabb, unanimously VOTED that. Whereas the majority of Canadian amateurs have indicated their unselfish cooperation by refraining from operation in the portion of the spectrum 3725-3750 kilocycles, it is the sense of this Board that it expresses its thanks.

63) On motion of Mr. Brabb, unanimously VOTED that this Board expresses its thanks to the League's General Counsel for his excellent handling of recent municipal ordinance cases affecting Amateur Radio.

64) On motion of Mr. Brabb, unanimously VOTED that the Board hereby expresses its deep appreciation for the services being performed in the name of Amateur Radio and the League by the Section Communications Managers, Section Emergency Coordinators, Emergency Coordinators, and members of Emergency Radio Nets.

65) Mr. Hughes drew the attention of the Board to the

fact that Treasurer David H. Houghton had this year completed 30 years of service with the League, whereupon all those present tendered Mr. Houghton a standing vote of applause.

66) On motion of Mr. Groves, unanimously VOTED that the Board does hereby express its appreciation to John Cann, W1RWS, of the Headquarters staff for the efficient manner in which he has been handling DXCC awards.

67) Moved, by Mr. Griggs, that the Board direct the Communications Manager to establish an appointive field position of interference coordinator in each section, to be appointed by the SCM. After discussion, moved, by Mr. Hughes, to amend the motion to specify that such appointments shall be made only in areas where such appointments have not already been made. After further discussion, on motion of Mr. Matejka, unanimously VOTED to further amend the motion to provide that the Communications Manager is to give consideration to such an appointive position in preparing the Rules and Regulations of the Communications Department. The question then being on Mr. Hughes' amendment, as amended, the same was unanimously ADOPTED. The question then being on the original motion as amended, the same was unanimously ADOPTED.

68) On motion of Mr. Jacobs, the following resolution was unanimously ADOPTED:

RESOLVED, that this Board sincerely appreciates the loyalty of the individual employees of the League at our Headquarters offices and does hereby express our sincere thanks to them for their valued services to the League and Amateur Radio.

69) Moved, by Mr. Jacobs, that a committee of two directors be appointed to study the many questions and requests from clubs and individuals pertaining to contests, etc., conducted by the League and report its recommendations to the General Manager prior to December 31, 1952. For the purpose of financing this committee one thousand dollars is hereby appropriated; monies made available shall be used for the expense incurred by directors only. But, after discussion, the motion was rejected.

70) On motion of Mr. Johnston, VOTED, 13 votes in favor to 3 opposed, that following the completion of directors' motions, the regular order of business be suspended and item 19 on the agenda, election of officers, be made the next order of business.

71) On motion of Mr. Noble, unanimously VOTED that affiliation is granted to the following societies:
Texoma Amateur Radio Club, Sherman & Denison, Texas
Richland Amateur Radio Club, Richland, Washington
Augusta Emergency Amateur Radio Unit, Augusta, Maine
The Band Hoppers Radio Club, Ferguson, Missouri
Longhorn Amateur Radio Club, Austin, Texas
Stonewall Jackson Amateur Radio Club, Inc.

Weston, West Virginia
Florence Amateur Radio Club, Florence, South Carolina
Calumet High Radio Club, Calumet, Michigan
Haverford Township Emergency Radio Net
Havertown, Pennsylvania

Minnedosa Amateur Radio Club
Minnedosa, Man., Canada
Needham Amateur Radio Association
Needham, Massachusetts

Carrollton Radio Club, Carrollton, Georgia

72) On motion of Mr. Noble, unanimously VOTED that in the event Board action on new draft language comprising the Rules and Regulations of the Communications Department is not completed by July 1, 1952 that the Communications Manager be guided in conducting SCM elections and other matters by the policies presently effective in old By-Laws 6 to 9.

73) On motion of Mr. Noble, unanimously VOTED that the Board of Directors, to continue to acquaint itself with the current status of field organization and radio operating matters, will continue to expect to receive an annual report on these matters from the Communications Manager.

74) The Board was in recess from 10:53 A.M. to 11:00 A.M.

75) Proceeding now to the election of officers, the Chair then APPOINTED Messrs. Hill and Matejka as tellers.

76) Nominations for President being in order, Mr. Johnston nominated Mr. Bailey, Mr. Griggs nominated Mr. Dosland. Whereupon, on motion of Mr. Brabb, unanimously VOTED that the nominations are closed.

(Continued on page 120)

YL NEWS and VIEWS

CONDUCTED BY
ELEANOR WILSON,* W1QON

In response to requests, when space permits, we plan to publish the regular operating times and frequencies of YLs who handle large amounts of traffic and/or who are very active in one way or another on the amateur bands. There are several reasons why it may be of value to know where and when these YLs operate — to facilitate the exchange of traffic; to work toward WAS/YL; to observe some good operating procedure; or to enjoy a bit of rag-chewing. Most of the YLs who are on extensively are first-class operators — efficient, courteous, and capable!

We'll launch the project with information about the following well-known YLs who operate several hours each day (all times EST):

W1OAK — Ann Chandler: 3740 kc. — 1815, Mon. thru Fri.; 3520 kc. — 1900, Mon. thru Fri.; 3605 kc. — 1945 and 2130, Mon. thru Fri.

W2BNC — Helen Law: 3970 kc. — 1645 to 1800, Mon. thru Fri.; 3595 kc. — 2000 to 2045, Wed.; 14,255 kc. — 1200 to 1500, Mon. thru Fri.

W2BTB — Jeanne Walker: 3845 kc. — 0545 (!) to 1200; 3920 kc. — early afternoons; 3970 kc. — 1700 to 0100 (the next day!).

W2RUF — Clara Reger: 7150-7200 kc. — Days, Mon. thru Fri.; 3615 kc. — Evenings, Mon. thru Fri.

W3CUL — Mae Burke: (Record traffic-handler Mae wrote that a listing of all her schedules and frequencies would consume the YL Department's space allotment for this issue!)

W3NHI — Marion Kurtzner: 7120 kc. — 1030; 7280 kc. — 1230; 3610 kc. — 1830; 3620 kc. — 2400.

W9UJ — Peggy Coulter: 7100-7150 kc. — 0630 to 1630; 3636 kc. — 1700 on.

In future columns, space permitting again, the regular operating times and frequencies of YLs will simply be listed without introduction. We don't mean to overlook anybody, so let us know whom you think should be added to the list.

Keeping Up with the Girls

WNFOU, Rosemary Parenteau, and **WN8FKK**, Helen Young, both patients at O'Reilly Veterans Hospital in Springfield, Missouri, would like to hear from other YL.

(Continued on page 124)

* YL Editor, QST. Please send all contributions to W1QON's home QTH: 318 Fisher St., Walpole, Mass.

Pilots Alice Picard, **W2WP**, left, and Helen Wright, **WN1UPZ**, shown here with Alice's Cub, are two of a number of YLs who successfully mix amateur radio and flying. Alice received her ham ticket in 1930 and became one of fewer than 100 YLs in the world. While Helen is a comparatively new YL, she has an extensive background in various radio organizational activities.



Here are nine YLs who let the world know that the ten-meter band is open to the Canal Zone. These **KZ5** YLs are charter members of the Canal Zone **QRMarys**, a club recently organized to coordinate and further **KZ5** YL activity. Besides DXing on ten, the girls handle traffic and conduct periodic net drills. Seated, *l. to r.*: Grace, **KZ5DG**, club secretary; Angie, **KZ5AC**, president; Lois, **KZ5LM**, v.p. Standing, *l. to r.*: Bess, **KZ5CN**; Dee, **KZ5NN**; Bess, **KZ5BM**; Kay, **KZ5KA**; Carol, **KZ5GQ**; and Martha, **KZ5ML**, club activities.



These are members of the newly-formed Ladies Amateur Radio Klub (LARK) of Chicago. The girls meet on the last Thursday of each month, and every Tuesday at 10:00 p.m. CST on 29 Mc. they conduct a ten-meter net. Bottom row, *l. to r.*: Bernice, **WN9RWV**; Helen, **W9EZO**; Grace, **W9GME**; and **WN9SEZ**. Top row, *l. to r.*: Gladys, **W9MYC**; Chris, **W9LOY**; Bobby, **W9KXL**; Helene, **W9BCB**; and Verona, **WN9QYG**.



On the Air with SINGLE SIDEBAND

ANY of the readers of this column who don't know how to tune in a s.s.b. signal (and we certainly hope there are a few, attracted by the superior quality of the prose!) can get some practice in our own 21-Mc. band. There are some Argentine s.s.b. commercial stations still operating there, in English, and their signals offer excellent opportunities for practice. They run a slight residual carrier. In case you don't know the technique, first center the receiver on the signal by tuning for maximum "kick" of the S meter. Then reduce the r.f. gain, switch off the a.v.c., switch on the b.f.o., run the audio volume at maximum and increase the r.f. gain until you begin to hear the beat against the residual carrier. Slowly tune the b.f.o. control until you have zero beat with the residual carrier, and you will hear the speech. Of course most amateur s.s.b. signals don't use a residual carrier, and when you come to them you have to tune the b.f.o. carefully until the speech is the most understandable. The Argentine signals allow you to demonstrate receiver overload, too, since if you let the r.f. gain run too high in the receiver, you can't possibly clear up the speech. But reducing the r.f. gain to a correct setting will eliminate the overload, just as it will with amateur signals. These signals are usually pretty potent, so when you tune into them with the a.v.c. on and the r.f. gain wide open, you will observe the same receiver-generated "splatter" that has been reported on 75 and 20 on one or two occasions.

In strictly amateur circles, a nice note from W5PWO/4 tells about Tennessee's W4CVM and W4ONX. CVM uses an Edmunds (W1JEO) exciter ending in a pair of 807s that drive a linear 304TL, and ONX uses an Edmunds into a pair of 6146s driving a pair of 304TLs. W5PWO/4 will be on soon with an Edmunds ending in an 829B. All rigs use voice control.



Here is Bob Ehrlich, W2NJR, of West Orange, N. J., and his neat shack and rig. The rack at the right houses the 833A final and its power supplies, while on the table the left-hand rack carries the exciter and its 807 driver-amplifier, with a BC-348 receiver in the right-hand rack. The table at the rear carries a 'scope and some 2-meter gear (not s.s.b., yet). Bob is one of the early-birds in s.s.b., and authored that excellent article on linear amplifiers in the May issue.

First s.s.b. maritime-mobile rig we've heard of is operated by Bob Wilson, W9RNL, aboard the SS *North American* on the Great Lakes. Prompted by receiving experiences last year, when s.s.b. was found to be copiable when all 75-meter a.m. signals were completely taken out by QRN, both natural and man-made, W9RNL/MM uses a crystal-filter job involving features from several sources. The filter itself is a single-section lattice à la Weaver-Brown, following a Pierce 6AU6 crystal oscillator and 6AK5s balanced modulator. The speech is 6AU6-6C4-12AU7, the 12AU7 screen-modulating the 6AK5s across 27,000-ohm resistors. Voice control, taken off the 12AU7 plates, consists of a 6AL5 rectifier and 6AG5 control tube that works a 5000-ohm relay. Following the filter a 6AG7 mixer (and 6J6 crystal oscillator) converts to 75 and drives a push-pull 6AG7 output amplifier. The single-lattice filter was found to be adequate for the job when good isolation between input and output circuits is




This is the gang that did such a splendid job of presenting s.s.b. to the multitudes at the recent R.S.G.B. Exhibition, and the equipment that was displayed and demonstrated. L. to r.: G3BVA, G2NXX, G3CWC, G8RC, G3CU, G3FHL, and G3FDG.

QST for

Fig. 1—The VE6CN revision of the Edmunds exciter.

C_1 —8- μ fd. 450-volt electrolytic.
 C_2, C_7, C_8 —0.005- μ fd. mica.
 C_3, C_4 —100- μ fd. mica.
 C_5, C_6 —0.25- μ fd. paper.
 R_1 —47,000 ohms.
 R_2 —33,000 ohms.
 R_3, R_4 —0.15 meg-ohms.
 R_5 —2500-ohm potentiometer.
 T_1 —450-ke. i.f. transformer.
 T_2 —Small Class B input transformer.



maintained, and it is simple to align when a balanced modulator is used. Look for W9RNL/MM around 3995 this summer.

VE6CN Balanced Modulator

G. O. Kincaid, VE6CN in Calgary, sends along the interesting balanced-modulator circuit he uses in his version of the Edmunds exciter. Shown in Fig. 1, it has the additional feature of providing for p.m., just in case one wants to revert to it for some reason. The oscillator circuit starts faster than the original, and it can be "pulled" by tuning, for better alignment with the filter. The filter is first aligned by removing the oscillator crystal, introducing a BC-221 signal across C_4 , and using the original alignment procedure.

Then the oscillator crystal is replaced and the oscillator frequency trimmed by adjusting the trimmer in the primary of T_1 .

The p. m. is obtained by tuning the secondary of T_1 until the voltage fed to the carrier-amplifier tube is 90 degrees different than that applied to the balanced modulator. For p.m., the crystal filter must be out of the circuit, of course, since the p.m. signal is obtained by combining the two sidebands (less carrier) with a carrier that has been shifted 90 degrees. Checking with a scope, one simply sets the trimmer in the secondary until there is minimum amplitude change on the carrier with modulation. The two circuits of T_1 "pull" a little, so the complete adjustment may require several trial runs.

—B.G.

Strays

B. C. Twinn, G3CGL, and F. B. Singleton, G3CGM, are consecutive in the *Call Book*.

"Television was introduced in Denmark last fall and may soon be shut down . . . only 400 sets have been sold so far." —*Chicago Daily News* via W9ZMY. Have you applied for your OZ calls yet, fellows?

culating harmonic suppression also is included.

A limited number of reprints is available, and copies may be obtained by addressing a request to the Collins Radio Company, Cedar Rapids, Iowa.

STAFF VACANCY

ARRL has a vacancy to be filled in its Communications Department staff. This post involves correspondence on and responsibility for the handling of DXCC Awards. It's also a job that takes knowledge of and background in the many phases of amateur operating. Experience in League field work, traffic, DX, organizing, also a background of some operating in contests such as the DX Test, Sweepstakes and Field Day is desirable but not specifically a requirement as to how much in a given branch. Essential: age 20-30, personable, appropriate experience, accuracy, skill, typist, ability to keep records and formulate statements or reports from time to time for *QST*. Starting salary around \$3000. Preference given single man. Personnel form sent on request. Be sure to attach snapshot of yourself, indicating age, license, experience, jobs held past and present, availability. Any information will be restricted to use in connection with prospective employment.

Antenna-Mast Loading and Guying

Considerations in the Use of Pipe Masts for 10-Meter Beams

BY CHARLES KANDEL,* W2VOU

WHILE some amateur antenna masts are installed after careful calculation of the factors involved, the large majority are probably worked out using the "by-guess-and-by-gosh" principle. The author had occasion to work out the stresses and loads for a number of different heights of pipe and tubing supports for 10-meter beams, for a talk before the N. Y. Radio Club, and it was thought that the tabulated results might be of interest to other amateurs who are contemplating similar installations.

All of the designs are based on a simple pipe or tubing mast, guyed three-quarters up the mast by a set of three guy wires or cables arranged 120 degrees apart. There is no advantage in using

four guy wires instead of three, because the guys are used primarily to take up wind loads, and with a four-wire guy system there will be times when all of the load is taken by one wire. The same is true, of course, for the three-wire system.

A typical antenna mast is shown in Fig. 1, with the antenna omitted for simplicity. The antenna mast, of course, be included in the calculations, because it represents the major portion of the wind load. The term "counter pull" is a mathematical convenience, the horizontal component of the force acting on the guy wire. The other forces and dimensions are obvious, and are shown to enable one to understand the tables quickly.

Table I shows the forces and stresses that exist in typical installations. Two types of 10-meter beams were included — wide-spaced 4-element beams on 20-foot booms, and close-spaced 3-element beams on 10-foot booms. Elements of $\frac{3}{4}$ -inch and $\frac{5}{8}$ -inch diameter were assumed. Calculations are based on a maximum wind force of 40 pounds per square foot (90 m.p.h.). The "combined stress" consists of two factors, the maximum bending moment (usually occurring at the point where the guy wires are tied to the mast) and the compression stress on the mast metal (caused by the vertical component of the guy-wire tension). The "combined stress" does not include any "dead" load, such as the weight of the beam, motor or mast itself, since the combined total of these is insignificant for ordinary installations, even when the dead load total adds up to a few hundred pounds. If the dead load is substantially greater, the amateur should have a structural engineer design the mast, as he should also in any case where the wind resistance of the mast is more than 10 or 15 times the resistance of the beam, since other design factors are involved.

In all cases, it is assumed that all guy wires are made up equally snug with turnbuckles, but *not too tight*. They should be adjusted seasonally with major temperature changes. Very tight guy wires may cause the mast to be pre-stressed to the point exceeding the maximum wind load. In such a case, when the full wind load is added to the existing stresses in the mast, the combined stresses will cause the mast to buckle and fail.

Table II illustrates how using an antenna with anchorages farther out from the base of the mast will result in reduced guy-wire tension. While everyone knows this intuitively, the actual order of magnitude of the reduction can be readily appreciated by a study of the table.

Anchoring the Guy Wires

The above data cover mast installations for a flat area or peaked roof with timber beams into which the lag screws would be driven after drilling




Fig. 1—Typical mast of the type discussed in the text. For simplicity, it is drawn without the 3- or 4-element beam mounted on the top.

TABLE I
Dimensions for Masts and Guy Cables To Support 10-Meter Beams at Desired Height

1	Type of Beam	4-el.	4-el.	4-el.	4-el.	4-el.	4-el.	4-el.	3-el.	3-el.	3-el.	4-el.	3-el.	3-el.
2	Boom Dimensions (inches \times feet)	2 \times 20	2 \times 20	2 \times 20	2 \times 20	2 \times 20	2 \times 20	2 \times 20	1 1/2 \times 10	1 1/2 \times 10	1 1/2 \times 10	2 \times 20	1 1/2 \times 10	1 1/2 \times 10
3	Beam Wind Load ¹ (pounds)	200	200	200	200	200	200	200	200	200	100	200	100	200
4	Mast Wind Load ¹ (pounds)	204	141	140	89	93	53	56	21	12	15	6	27	12
5	24ST Tubing Mast ^{2,3} 1/8-in. Wall (in. diam. \times feet long)			3 \times 20		2 1/2 \times 16		2 \times 12	1 1/2 \times 6	1 1/2 \times 9				1 \times 5
6	Steel Pipe Mast ² standard weight (nominal diam. \times feet long)	3 \times 25	2 1/2 \times 21		2 \times 16		1 1/2 \times 12				1 \times 5		1 \times 9	
7	Guy Point on Mast ⁴ (feet above base)	18 3/4	15 3/4	15	12	12	9	9	4 1/2	6 3/4	3 3/4	6 3/4	1 1/2	3 3/4
8	Guy Anchorage ⁴ (feet from base)	7	5 1/2	5 5/8	4 1/2	4 1/2	3 3/8	3 3/8	1 7/8	2 1/2	1 1/2	2 1/2	7/8	1 1/2
9	Thrust at Base (pounds)	1125	976	930	864	876	801	810	740	386	740	400	724	375
10	Tension on Each Guy (pounds)	1150	1041	998	911	935	854	860	790	386	790	436	762	400
11	Diameter of Guy Cable ⁵ (inches)	1/2	1/2	1/2	1/2	1/2	7/16	7/16	7/16	3/8	7/16	3/8	7/16	3/8
12	Lap-screw Size for Guy Anchor (inches)	1/2 \times 6	1/2 \times 5	1/2 \times 5	1/2 \times 5	1/2 \times 5	1/2 \times 4 1/2	1/2 \times 4 1/2	1/2 \times 4 1/2	3/8 \times 4	1/2 \times 4 1/2	3/8 \times 4	1/2 \times 4 1/2	3/8 \times 4
13	Combined Stress on Mast Material (lb. per sq. in.)	10,300	13,400	20,200	18,900	20,200	23,800	24,000	22,600	22,000	24,300	22,000	24,500	24,000

¹ Based on 40 lb. per sq. ft. \times 0.7 for round tubing, thus 2-inch diam. tubing has a wind load of $40 \times 0.7 \times 2/12 = 4.7$ lb. per lineal foot. Double the wind load for square tubing. Thus 2-inch square tubing has a wind load of $40 \times 1/12$ diagonal of tube = 9.4 lb. per lineal foot.

² Mast length not to be increased even with a beam of lower wind resistance, because the permissible slenderness ratio would be exceeded.

³ For wall thickness less than 1/8 inch, use beam having wind load proportionately less than shown on line 3.

⁴ These dimensions may not be reduced without noting their effect upon items in lines 9, 10, 11, 12 and 13.

⁵ Dimensions are for common steel, galvanized. Smaller diameter may be used for high-strength cable.

TABLE II
Examples of Reduced Guy Tension and Reduced Thrust at Base of Mast Resulting from Use of Beams with Lower Wind Load and/or Use of Wider Guy Anchorage Base

1	Type of Beam	4-el.	3-el.	4-el.	4-el.	3-el.	3-el.	3-el.	3-el.	3-el.	3-el.
2	Beam Dimensions (inches X feet)	2 X 20	2 X 10	2 X 20	2 X 20	2 X 10	1½ X 10	2 X 10	1½ X 10	1½ X 10	1½ X 10
3	Diam. Elements (inches)	¾	¾	¾	¾	¾	¾	¾	¾	¾	¾
4	Beam Wind Load ¹ (pounds)	200	150	200	200	150	100	150	100	100	100
5	Guy Anchorage ² (feet from base)	4½	4½	6	8	6	4½	8	6	8	12
6	Counter Pull	329	264	329	329	264	195	264	195	195	195
7	Thrust at Base (pounds)	876	672	660	492	528	520	396	390	293	195
8	Tension on Each Guy (pounds)	935	743	737	590	590	559	475	435	351	276
9	Reduced Tension, Each Guy Cable (%)	—	20	20	37	37	40	50	52	62	72
10	Combined Stress on Mast Materials (lb. per sq. in.)	20,200	19,300	18,900	18,900	19,300	15,600	19,300	15,600	15,600	15,600

¹ Mast for all beams: 2½-inch diam. 24ST tube 16 feet long, ¼-inch wall, or standard-weight 2-inch steel pipe 16 feet long.

² Guys attached to mast 12 feet above base.

an undersized pilot hole and filling it with roofing compound. No lag screw should be placed less than 27 inches from the end of a timber beam when the guy pull is 500 pounds, or 36 inches if the pull is over 500 and less than 1000 pounds. This will insure that the lag screw is in the center of a square large enough to take the strain.

For a mast that is guyed from points on the ground, each guy wire should be anchored to a "deadman" — a galvanized cast steel plate with ribs (available commercially in various sizes) to which a long galvanized eyebolt is attached after the plate has been set in the ground. The recommended procedure for installing a "deadman" is to dig a hole with a vertical side toward the mast and a sloping (45-degree) side away from the mast. The eyebolt is then driven into the undisturbed ground from the mast side at a 45-degree angle down to the bottom of the hole, where the plate can be slid down the sloping side

of the hole and into the ground until the eyebolt can be installed and secured with a nut. This puts the eyebolt in undisturbed ground with the plane of the plate at right angles to the line of the bolt. The excavated material should be replaced in batches, and each batch should be tamped firmly in place.

Table III gives the recommended sizes of bolts and plates to be used with various guy-wire pulls. For heavier loading than shown, merely increase the area of the plate and the diameter of the bolt, the length of the bolt and the depth of excavation need not exceed the maximum figures shown.

The table applies to sandy soil with good drainage. Soil consisting of firm clay will stand about 50 per cent more pull, while hardpan (a soil which can be broken up only by the use of a pick or crowbar) will carry 100 per cent more than sandy soil. However, soil that is wet and soggy to a considerable depth most of the time cannot be depended

upon to take the full pull, and due allowance must be made for this condition by using a larger plate and a longer eyebolt.

The "deadmen" commercially available and widely used by power companies are cast steel (galvanized) about ¼ inch thick, with ribbed stiffeners cast into them. If ordinary steel plate is used, it should be somewhat thicker and prepared conveniently

(Continued on page 126)

TABLE III
Guy Anchor Data

Guy Pull (pounds)	Plate Size ¹ (inches)	Bolt Diam. (inches)	Bolt Length ¹ (inches)	Depth to Plate Hole (inches)
500	6 X 6	¾	36	25
800	6 X 6	¾	36	25
1100	6 X 7	¾	42	29
1500	6 X 7	¾	48	33
2300	6 X 8	1	60	42
3500	6 X 9	1¼	72 ²	52

¹ Minimum.

² Maximum.

Constructing Safety Interlocks from Standard Parts

BY RONALD L. IVES *

ALTHOUGH interlock switches are recommended on all radio equipment so that when the cabinet door is opened all high-voltage circuits are de-energized, such switches are not readily available, and many of the small commercial models are not in accord with local electrical codes.




Fig. 1 — Microswitch mounting for service as rack-cabinet interlock.

A neat and relatively inexpensive interlock switch that is quite safe and which will pass most electrical inspectors can be constructed easily from a Microswitch and a few standard fittings. Constructional details are sketched in Fig. 1. Because all electrical parts are standard UL or AN fittings, and all fit together without alterations, appearance is quite workmanlike and neat. Mountings for most rack cabinets are quite simple, requiring only straightforward machine work, with no highly-critical dimensions.

Length of spacers, for Par-Metal rack cabinets of the ER-223 series, should be about 1 1/4 inches. The switch is held in place by two 10-32 rack standard mountings include a right-angle bracket

screwed to the rear frame of the cabinet, and a bracket to support the switch from the rear of a convenient chassis. Best location for the switch is so that the actuating button is operated by the door catch housing when the cabinet door is latched. This eliminates any tendency of the switch to warp the cabinet door.

A satisfactory electrical location for a safety interlock switch is between the main fuse and the main system switch, as in Fig. 2A. If extra safety is desired, the interlock can be used in conjunction with an electrically self-holding relay, as shown in Fig. 2B. This prevents accidental or intentional turning on of the power by manual operation of the interlock. Once the circuit is broken by S_2 , it is necessary not only to close the interlock, but also to close the "start" or "on" push-button switch before the system is electrically live. Since this requires the use of both hands when the cabinet is open, the chance of shocks is at a minimum.

Whatever circuit is used, some sort of safety interlock should be incorporated in every rack cabinet. Safety measures are much cheaper than funerals!





Fig. 2 — A — Simple interlock circuit. The switch is simply plugged in series with the a.c. line. B — Circuit using interlock in conjunction with a locking relay. The switches are push-button type. S_1 (on) is normally open, while S_2 (off) is normally closed.

*5415 Main St., Williamsville 21, N. Y.



• As W4JJX points out here, a VFO doesn't have to be so elaborate if you are interested in 75-meter operation only. The simple unit described should be entirely adequate for this purpose.



This small VFO unit designed primarily for 75-meter 'phone work requires little chassis space. The tuning shaft is extended to the dial on the transmitter panel.



Simple VFO Construction for the 75-Meter 'Phone Band

BY CHARLES McDOWELL,* W4JJX

I AM not disputing the fact that the more complicated and elaborate VFO units which appear from time to time in *QST* have their proper place. Too much care cannot be used in the electrical design and construction of the oscillator when its multiples are to be used for operating in the higher-frequency bands. However, many of the refinements featured in such units are unnecessary and disproportionately expensive for the ham who asks only for something with which he can shift frequency in the 75-meter 'phone band. In such a case, simplicity and physical size become more important factors.

In searching about for a simple but reliable circuit, the one shown for the "Coffee-Can"¹ VFO in a previous article appealed strongly to this rock-bound character for several reasons. The circuit, shown in Fig. 1, is simple. It requires relatively few components so that the unit can be made small enough physically to fit, in many instances, on the chassis of an existing rig. A reasonable amount of isolation is provided by the buffer stage. Also, in working 'phone in a crowded band, frequency drift is one of the most important considerations and the Clapp circuit used in the "Coffee Can" excels most others in this respect.

Only two essential changes were made in the

original circuit. A 6AG7 was substituted for the 6V6 in the oscillator, more or less as a matter of personal preference, and the tuning range was restricted to cover only slightly more than the 75-meter 'phone band for better bandspread. However, the original full-band coverage can be easily retained, if desired, simply by using a 75- μ fd. tuning condenser.

Construction

The parts are assembled in a standard 3 \times 4 \times 5-inch box. The tubes are mounted externally on top of the box to keep most of the tube heat away from the tuned-circuit components, minimizing drift. All of the components, except the three tuning condensers, C_3 , C_4 , and C_5 , and the coil, L_1 , are mounted on the underside of the top cover. Thus, most of the wiring and soldering can be done before assembling the box.


The coil is fastened to the side of the box. The tuning condenser, C_4 , is mounted on the front. The paint is scraped away from around the condenser shaft mounting hole to provide a good ground contact for the condenser rotor. The negative-temp trimmer, C_5 , and the zero-temp padder, C_3 , are mounted directly across the terminals of the tuning condenser. The bottom end of the coil can be connected to the tuning-condenser stator before the top and bottom plates are attached. The connection from the other end

* 2021 Lee Terrace S.W., Birmingham 11, Ala.

¹ Hayward, "The Coffee-Can VFO," *QST*, Aug., 1949, p. 22.

Fig. 1 — Simple VFO circuit.

C_1, C_2 — 0.001- μ fd. silvered mica.
 C_3 — 150- μ fd. zero-temp. ceramic (Centralab TCZ-150).
 C_4 — 50- μ fd. variable for "phone band" only (Bud I.C. 1644); 75- μ fd. for entire 3.5-Mc. band (Bud I.C. 1645).
 C_5 — 45- μ fd. neg.-temp. trimmer (Centralab 822-BN).
 C_6, C_7, C_{10} — 100- μ fd. mica.
 C_8, C_9 — 0.01- μ fd. disk ceramic.
 R_1 — 0.1 megohm, $\frac{1}{2}$ watt.
 R_2 — 47,000 ohms, $\frac{1}{2}$ watt.
 L_1 — Approx. 12 μ h. — 23 turns No. 16 enam. $1\frac{1}{2}$ -inches diam., close-wound.
 RFC_1, RFC_2 — 2.5-mh. r.f. choke.



of the coil to the junction of C_2 and C_6 is made by leaving the coil lead long enough to reach a 3-terminal lug strip on which C_1 and C_2 are mounted, and soldering the connection while the plate is held about a half inch from its regular position. This procedure was necessary because the large and not so deft hands of the author are not well suited to working in such small quarters. The power leads and the output lead are brought out through grommets holes in the side or bottom to suit the transmitter layout.

I use a National type AM vernier dial which gives an easily handled tuning rate.

Adjustment


The VFO should not be mounted in the transmitter until the frequency range is checked with the bottom plate in place. Shielding affects the inductance of the coil, and if the frequency is set with the bottom plate removed, the frequency will not be the same with the plate in place. It is necessary to set C_5 , attach the bottom plate, and

then check the frequency limits. If the range is not as desired, remove the plate, readjust C_5 , replace the plate and check again until the right range is obtained. An alternative, of course, would be to mount the trimmer in such a position that the trimmer adjusting screw can be reached through a hole in the side of the box.

Performance

This VFO works well at a plate voltage of 100 or less and gives a healthy output at 175 volts. I use it to drive a 2E26 buffer amplifier, the VFO operating from a tap on a voltage divider across the 400-volt supply for the 2E26. Reports from many stations worked show that drift is negligible. Despite the fact that c.w. performance was a secondary consideration, T9 reports are often received when keying the 2E26 in the cathode circuit. Although I have not had occasion to try it, since I do not feel the need for rapid break-in, it seems probable that the oscillator itself could be keyed with reasonably good characteristics.

Most of the components for the simple VFO are assembled on the top cover plate. Only the tuned-circuit components are fastened to the box walls.



A 200-Watter for 160

Compact Construction for Restricted Space

BY ROBERT M. RESCONSIN,* WITRF

A FEW MONTHS ago I decided to try the 160-meter band, just to see what it was like. My medium-power 10-meter transmitter was too much of a problem to get down to frequencies that low, so I threw together a haywire-style rig for the trial. After only a few nights of operating, I knew I was there to stay and immediately began to lay plans for an outfit more in keeping with the facts. When the ham shack has to be in the dining room, haywire and unnecessary bulk lives on borrowed time if the XYL has anything to say about it — and she usually does! Aside from the considerations of compactness and appearance, I wanted to run the legal nighttime limit on power, have VFO control and utilize the power supply and modulator from the 10-meter rig. Last, but certainly not least, the unit had to be well shielded for TVI because the activity on 160 is usually at its best during TV hours. All of this, of course, called for much planning and checking. But, in the end, the results were all that could be desired in a transmitter for 160 meters.

Circuit

The circuit I finally decided upon is shown in Fig. 1. A 6AG7 is used in the series-tuned VFO which works on 160. The oscillator plate circuit, which is untuned, is capacity coupled to another 6AG7 in the buffer stage. Cathode bias is supplied to the buffer stage by R_3 . The buffer screen voltage is taken from the regulated source that supplies the VFO section. The buffer operates straight through and is coupled to the final-amplifier grid by C_{14} . An 813 was chosen because of its low drive requirements and its adaptability to a wide range of plate voltages — you can run an input of 200 watts with a plate voltage as low as 1200. The stage is neutralized by means of a simple homemade condenser, C_{17} . It will be noticed in Fig. 1 that the conventional neutralizing connection, shown in dotted lines, was not used in this instance. Apparently, stray wiring capacitances are such that the circuit is "over-

neutralized," requiring the introduction of positive, instead of negative, feed-back for neutralization. Therefore, the neutralizing capacitance is directly from grid to plate. It should be borne in mind, however, that the use of different components, or a slightly different layout, may require the conventional connection shown in dotted lines, rather than the one used.

Fixed bias is supplied to the final amplifier by a 50-ma. selenium rectifier and a small filament transformer, T_2 , working in reverse from the 6.3-volt filament supply. A VR-150 is used to stabilize the biasing voltage. Screen voltage is supplied from the high-voltage source through R_8 and R_9 to provide a simple means of modulating both plate and screen.


Although the output circuit is designed primarily for 160 meters, reasonable efficiency is possible in doubling to 80 meters in the final when using

the 3.5-Mc. tank coil specified in Fig. 1.

Construction

The transmitter is constructed entirely on a standard 10 × 17-inch chassis with a 10½-inch panel. The VFO portion is built on the left-hand side of the chassis and will be described first. The 6AG7 socket is inverted so that the tube extends below the chassis. This method allows all of the wiring on the socket to be enclosed within the shield. C_3 , C_4 , C_5 and the grid resistor, R_1 , are all soldered directly to the socket, and the filament by-pass condensers, C_{23} and C_{24} , as well as the screen by-pass condenser, C_7 , are soldered directly to ground from their respective pins. Shielded power wires are brought into the compartment through rubber grommets. The r.f. plate lead to the coupling condenser, C_8 , is

• In this article, WITRF describes his 200-watt 160-meter rig. The simple 3-stage circuit includes a built-in VFO and ends up with an 813. While designed primarily for 160, it also perks on 80.



A front view of the 160-meter transmitter, showing the panel layout. The VFO is directly calibrated for 160 and 80 meters on the National SCN dial. The lower row of controls are, left to right, keying jack, buffer plate tuning, meter switch and the filament switch. To the right of the two meters are the final plate-tuning and the swinging-link controls.

*215 Main St., Rocky Hill, Conn.




Fig. 1—Circuit diagram of the 200-watt 160-meter transmitter.


- C₁—100- μ fd. variable (Millen 22100).
 C₂—50- μ fd. variable (Millen 19050).
 C₃, C₈, C₁₄—100- μ fd. mica.
 C₄, C₆—680- μ fd. silvered mica.
 C₆, C₇, C₉, C₁₁, C₁₃, C₁₅, C₁₆, C₂₃, C₂₄—0.01- μ fd. disk ceramic.
 C₁₀—140- μ fd. variable (Millen 19140).
 C₁₇—Neutralizing capacitance; see text.
 C₁₈, C₂₀, C₂₁, C₂₂—0.001- μ fd. 5000-volt mica.
 C₁₉—Dual-section variable, 200- μ fd.-per-section (National TMC-200-D).
 C₂₅, C₂₆—8- μ fd. 250-volt electrolytic.
 C₂₇, C₂₈, C₂₉, C₃₀—0.1- μ fd. molded.
 R₁, R₂—22,000 ohms, $\frac{1}{2}$ watt.
 R₃—220 ohms, 1 watt.
 R₄—10,000 ohms, 10 watts, adjustable.
 R₅, R₆, R₇—100 ohms, 2 watts.
 R₈—25,000 ohms, 50 watts, adjustable.
 R₉—25,000 ohms, 50 watts.
 R₁₀—500 ohms, 2 watts.
 L₁—100 μ h.—96 turns No. 30 s.s.c. close-wound on 1-inch form.
 L₂—70- μ h.—96 turns No. 24, 1-inch diam., 3 inches long (B & W 3016 Miniductor).

- L₃—1.8 Mc.—90 μ h.—56 turns No. 16, 3-inch diam., 6 inches long over-all, $\frac{3}{4}$ -inch space at center for L₄ (B & W 160TVII or TVL with mounting for plug-in link).
 3.5 Mc.—40 μ h.—38 turns No. 14, 3-inch diam., 6 inches long over-all, $\frac{3}{4}$ -inch space at center for L₄ (B & W 80 TVII or TVL).
 L₄—5-turn variable link (B & W 3555).
 MA₁—D.c. milliammeter, 50-ma. scale.
 MA₂—D.c. milliammeter, 500-ma. scale.
 RFC₁, RFC₂, RFC₃, RFC₄—2.5-mh. r.f. choke (National R-100-S).
 RFC₅, RFC₆—7- μ h. r.f. choke (Ohmite Z-50).
 RFC₇—4-mh. r.f. choke (National R-152).
 RFC₈—Line-filter choke (Ohmite Z-21).
 S₁—Single-wafer double-pole 3-position ceramic rotary.
 S₂—S.p.s.t. toggle.
 SR—50-ma. selenium rectifier.
 T₁—6.3-volt 3-amp. filament transformer (Stancor P-5014 or equiv.).
 T₂—6.3-volt 1.2-amp. filament transformer (Stancor P-6134 or equiv.).
 T₃—10-volt 5-amp. filament transformer (Stancor P-6139 or equiv.).

made of a short piece of RG/59-U coaxial cable and this also is brought up through the chassis along with the power leads. L₁, the VFO coil, is close-wound on a 1-inch Millen form and is mounted on a half-inch cone insulator. The ends of the winding are soldered directly to their connections so that they are held quite rigid. Two half-inch spacers are used to hold the VFO tuning condenser, C₂, above the chassis so as to line the shaft up with the drive mechanism of the National SCN dial. The oscillator paddler, C₁, and its mounting bracket are bolted firmly to the chassis. A 3 \times 4 \times 5-inch aluminum utility box is used to cover the VFO circuit. A small opening cut in the front cover allows the tuning dial to turn freely. After all of the leads are brought through to the underside of the chassis we go on to the buffer stage.

The oscillator plate choke, RFC₂, and the buffer grid choke, RFC₃, are mounted vertically. The choke terminals are used as tie points for the coupling condenser, C₈, and the buffer grid resistor, R₂. The buffer tuning condenser, C₁₀, is mounted directly in front of the tube socket on the vertical bracket supplied with the condenser. A B & W 3016 Miniductor, just as it comes in the box, has just about the right inductance for L₂.

The 813 socket is mounted directly on the chassis to the right of the buffer-tube socket, with the coupling condenser, C₁₄, placed so that the leads are as short as possible. RFC₅, the 813 grid choke, is in front of the tube socket, near the grid-meter shunt. The meter shunting resistors for the buffer plate and the 813 grid circuits are fastened to a pair of two-terminal lug strips. The 813 screen-current shunt is mounted on two small



Top view of the 160-meter chassis removed from the cabinet. On the rear edge of the chassis are the two filament transformers and the VR tube for the bias supply. T_2 is underneath. In front of the transformers are the 6AG7 buffer tube, the VR-150 for the VFO and the aluminum box shielding the oscillator section. To the left of the 813 are the final tank condenser and the swinging-link assembly. Along the rear of the chassis are the high-voltage connector, the 115-volt input connector, the grounding post and the exciter low-voltage connector.

cone insulators and is connected with high-voltage insulated wire, since the screen voltage rises to the supply value when the tube is not being driven. All external power leads have v.h.f. filters. The components are placed in the enclosure formed by the aluminum barrier shield running the length of the chassis.

The neutralizing "condenser," C_{17} , consists of a strip of aluminum about a half inch wide and 2 or 3 inches long, bent at right angles and mounted on a feed-through insulator near the socket grid terminal. The feed-through is connected to the grid terminal and neutralizing is adjusted by altering the length of the strip or by bending it closer to, or farther from, the tube.

The output tank condenser, C_{19} , is mounted above the chassis on half-inch cone insulators. The shaft is connected to the tuning dial through a ceramic-insulated shaft coupling. The jack bar for L_3 is supported on National GS-1 pillar insulators and mounted alongside the tank condenser. Another insulated shaft coupling is used to extend the shaft of the swinging link to the panel. A length of coaxial cable is run from the link assembly to the antenna terminal along the left drop of the chassis.

The shielding barrier is spaced 3 inches from the rear. This enclosure contains all of the a.c.


wiring, the line chokes and the bias supply. The high voltage to the final is routed through a feed-through in the shield. L_2 is cemented between two ceramic cones on the other side of the barrier.

Adjustment

After turning on the low-voltage supply, the slider on R_4 should be adjusted to the point where the VR tube just stays ignited with the key closed. At resonance, the buffer plate current should be about 22 ma. and screen current approximately 8 ma. This should produce an 813 grid current of 18 or 20 ma. When the key is opened, the buffer plate current should drop to about 12 ma. while the screen current is reduced almost to zero. If there is any variation in buffer plate current as the tank circuit is turned through its range with the key open, a check should be made for parasitic oscillation, as discussed in the ARRL *Handbook*.

In tuning up the final amplifier, the screen resistor, R_8 , should be adjusted to leave about 20,000 ohms in the circuit and quarter or half maximum plate voltage applied. A dummy load should be connected and the output tank tuned to resonance. As the load is adjusted to take current, the plate and screen voltages can be

(Continued on page 126)



Bottom view of the 160-meter transmitter. R_4 is to the left. The inverted 6AG7 oscillator tube is just to the left of the buffer tuning-condenser shaft. In front of the 813 socket are the meter-shunting resistors and the meter switch. R_8 and R_9 are to the right of the 813 socket. The final plate choke is mounted on the right drop of the chassis. All power wiring is done with shielded wire to suppress v.h.f. harmonics.

QST for

Arkansas-Tennessee Tornadoes

Amateurs in "Tornado Alley" Provide Emergency Communication as Twisters Destroy Power and Wire Lines

BY GEORGE HART,* WINJM

TORNADOES are not exactly rarities in the Southern and Midwestern states, but the series of twisters that leapfrogged over Arkansas and western Tennessee, to say nothing of other storms in the surrounding states of Mississippi, Alabama and Missouri, in late March set a record of destructiveness and fury that is unsurpassed in the long tornado history of this area. One cannot be sure whether the various funnels which became apparent on and after March 21st were separate storms in themselves or different visitations of the same over-all clash of warm- and cold-air "fronts" which, combined with other atmospheric conditions, were conducive to the formation of whirling air funnels of terrific speed and strength which cut swaths of destruction through Arkansas and Tennessee.

We amateurs, although not too well versed on the cause of the tornadoes, are certainly aware of their effects in terms of broken communication and power lines coupled with what this means to our emergency establishment. And but for the quick activation of amateur stations in most of the affected areas, the suffering felt by the populace would certainly have been greater and spread over a longer period of time than it was. This is the story of that amateur participation, compiled from the thick sheaf of reports from Emergency Coördinators and participating amateurs which has been received since the incident.

Arkansas


The tornadoes in Arkansas started in the southwestern part of the state with a funnel at the little town of Dierks. This particular twister progressed northeastward, as did they all, and then disappeared. Very shortly afterward, however, additional funnels formed at England, at

Georgetown and at Searcy, each progressing northeastward and finally disappearing after spreading its quota of destruction. Later that night tornadoes struck points in Western Tennessee.

The destruction at Dierks, although great, was only a harbinger of disaster to come upstate. Shortly after the twister struck at 1515 and moved on in the general direction of Little Rock, W5AQF offered to set up a station at Dierks but was told there was no real need, since the town still had communication. It was not until Saturday afternoon, the day after the tornado, that W5AQF was requested to set up a station, which was accomplished on Sunday morning with the aid of W5EGY. Set up at Red Cross Headquarters, the station handled traffic for Western Union and the Red Cross. W5JTR was the Shreveport contact, from which point WU traffic normally comes into Dierks, and outgoing traffic was handled through W5ICS at Fort Smith. Others who assisted included W5s APW, BJH, EA, FPD, JIC, KKM and W9UID. Operation was buttoned up at 1730. Nine messages were received and 21 sent on behalf of the Red Cross.

The biggest and most destructive of the Arkansas tornadoes hit Searcy at 1730 on Friday, March 21st, and passed along to lay waste the small towns of Judsonia and Bald Knob. Six mobiles from Little Rock drove toward the area and for a time maintained contact with Little Rock, but it was not reliable due to skip conditions. W5STV put 100 watts on the air from Searcy and handled 8 or 10 messages, but at daylight it was impossible to reach Little Rock. A group of five amateurs headed by W5DVI left Little Rock about 2230 Friday night with a 1500-watt a.c. gasoline-driven generator and enough gear to establish a 100-watt station. This station was set up in the Methodist Church, one of the few able remaining buildings in Judsonia.

The set-up at Judsonia, W5DVI/5. Looking out the window, one can see the roof blown off the parsonage next door to the church in which the station was established. The rig was a Collins exciter driving a pair of 4-125As to 500 watts input — the amount of power needed to get through the QRN. James Girdley, a prospective ham, holds the mike while W5DVI and W5OCX prepare messages in proper form for transmission.



in which there was no heat, communications or power. Rain and lightning heralded the arrival of this group, and unheard-of QRN marked the initial operation of W5DVI/5.

Within 45 minutes of the time of arrival, W5DVI/5 was on the air, this in spite of transmitter difficulties. Contact was established with W5BCZ, and this contact was maintained throughout the night, although relays were necessary at times due to skip. Red Cross and town officials assisted in setting up a routine and priority system for outgoing traffic. Persons wishing to send messages had to file them at a desk set up for that purpose, although medical and Red Cross personnel filed theirs in the radio room for priority handling. The traffic was brought to the radio room six or eight at a time, and the station never got more than 30 minutes behind in its traffic handling.

But the boys had their troubles. In addition to transmitter troubles, there was QRM from a.c. generators (not their own, which was effectively silenced) and ear-splitting QRN. Low power would have been useless, and even the 100 watts they were using was hardly sufficient.

At 1700 the next day three relief operators arrived from Little Rock with new transmitting equipment, and at that time the station was moved to a higher and drier location, since there was a half inch of water on the floor of the original location. Actually, W5DVI/5 was off the air less than ten minutes in changing locations. The only means of communication, this station handled traffic for Red Cross, Western Union, U. S. Post Office, National Guard, Salvation Army, Weather Bureau and the Governor. In the first 24 hours of operation, traffic was sent to the loudest station heard, to be filed with Western Union at that point. After that, amateur channels were used for welfare traffic, both incoming and outgoing, although in many cases it was not possible to get information in answer to incoming inquiries. W5PHP in Searcy was one of the reliable contacts. W5MRD/M and W5BDR/M represented Bald Knob until W5KBH was set up.

On Sunday morning (Mar. 23rd) W5DVI's half-kilowatt rig was brought to Judsonia, and this transmitter was used for communication with the outside until Wednesday at 1900, by which time a temporary switchboard had been installed. The traffic total handled by W5DVI/5 was 422, 277 of which were outgoing. Dr. George Bean, W5DVI, and the group which assisted him have been publicly praised for their services. The people of Judsonia, to say nothing of the various agencies served, will not soon forget that these amateurs supplied the only communication out of and into Judsonia for several days.

The little adjoining town of Bald Knob was also hard hit on Friday. W5RWJ of Jonesboro, upon hearing of the disaster and learning of the need for communications out of Bald Knob, transported his station the some 90 miles to Bald Knob, with the assistance of W5MSH. W5RWJ/5 was on the air from the City Hall from 1800 Saturday until 2000 Sunday; they were the only

means of communication until Sunday, when wire and telephone service were again available. Some 122 messages were handled for the National Guard and Red Cross on 3885 kc. On Sunday evening W5KBH and W5OCX arrived to relieve W5RWJ and his crew. They operated W5KBH/5 until there was no further need for their services.

One of the most outstanding stations in the Arkansas group was W5PHP of Searcy. This station was the first on the air after the tornado side-swiped Searcy, doing comparatively little damage, and then roared into Judsonia and Bald Knob, and W5PHP was designated by the Red Cross as its collecting point for welfare traffic. He operated for three days continuously, had relief for four hours and was back on again for another 24-hour shift. W5PHP gained the respect of all who worked with him by his persistence and efficiency under extremely trying conditions.


W5QIP, 4EC for Conway, assisted by W5S STU, ARH, TIC and TID, set up a BC654 station in Searcy about 2245 Friday (Mar. 21st) and another in Judsonia shortly after midnight. Due to the heavy atmospherics which always accompany tornadoes, these low-power units were not too effective, and the Judsonia station was dismantled when W5DVI and his crew arrived on the scene.

Tennessee

The fact that the terrific tornadoes which struck Dyersburg and Henderson, Tenn., followed by only a few hours those which twisted across Arkansas in that same direction lends credence to the probability that they were part of the same disturbance, which later also alerted parts of Kentucky and West Virginia and came close to creating panic in some places. But by the time the disturbance which begets tornado conditions got this far north the winds had died down and all that was left was drenching rain.

In their dying throes, the tornadoes that hit Arkansas in the afternoon lashed out in renewed fury that evening at western Tennessee. The first town hit was Moscow, and then Henderson was all but levelled. Further north Dyersburg felt the force of another twister, killing scores of people, injuring hundreds and wreaking property destruction into the millions of dollars.

In Henderson, RM W4AGC contacted W4EDC immediately after the blow, and the latter went to Jackson to obtain an emergency power supply, which was not available locally. When he returned, it was found that the Jackson Radio Club was setting up facilities in Henderson. Failing to establish contact between W4HXC/M and W4HPO in Jackson, the group put W4EDC/4 on the air about 0545 Saturday (Mar. 22nd). This station operated with fair success until a second emergency generator was put on the air at 1715 Saturday, using the call W4AGC, who immediately called the Tennessee Net on 3635 kc. Within 15 minutes, 25 stations had reported in and the traffic began to flow. W4AGC alone handled over 300 messages through the facilities of the Tennessee c.w. and 'phone nets, the Fifth



and Ninth Regional Nets of NTS, and ARRL Trunk Line J. The session lasted until 0130 March 23rd (Sunday), then was resumed again at 0900 and operated until 2300. W4JU and W4BAQ maintained liaison with Arkansas 'phone and c.w. nets.

W4AKJ, EC at Crockett Mills, reported into the Tennessee Phone Net at 0850 Saturday morning (Mar. 22nd), having heard of the emergency at Dyersburg. Later, having collected some traffic for Dyersburg, he visited that town to deliver it, and visited Western Union, telephone company and the Red Cross to see if any assistance was needed. The need did not seem to be particularly urgent; nevertheless, he contacted W4OFX to see what facilities were available, and after taking inventory they got W4STX to come down from Newbern with a small rig. With low power and transmitter difficulties, however, contact was not satisfactory and most of the traffic was carried from Dyersburg to be originated at W4AKJ, handled mostly through the Tennessee c.w. net on 3635 kc.

Miscellaneous

The emergency nets operating in Arkansas and Tennessee received considerable assistance from other nets outside these two states in facilitating their long haul traffic and conducting traffic relays necessitated by skip conditions, which were especially prevalent on 75 and 80 meters, the two bands most used in the emergency. The Transcontinental Relay Net (TCRN) on 7042 kc. remained in session to assist with traffic to and from the storm area, and a new net was formed on 7090 kc. by W0GBJ, W8DLZ and W5TOE, the latter in Little Rock. Stations in this net would comb the band for traffic and bring it or the stations having it to the 7090 frequency for clearance. The National Calling and Emergency Frequency, 7100, was especially monitored.

W0EBE of Springfield, Mo., cleared a considerable amount of traffic with the Arkansas storm area on 75 and 80, while Trunk Line J

(Ninth Regional Net) and the River Forecast Net under W9TT handled much traffic with the tornado-stricken areas in Tennessee by conducting special sessions and maintaining contact with W4AGC, with W9LZI and W4MWX turning in especially noteworthy performances. Approximately 100 messages were handled. The NTS Fifth Regional Net held a special session but was not called upon to assist in traffic relay.

Each amateur group is its own worse critic, and the Arkansas-Tennessee tornado emergency was not exceptionable in this instance. In spite of this, all agencies, both government and private, which were assisted during the tornado — and there were a lot of them — are singing the praises of the organized radio amateur who makes his time, facilities and sweat available to the public in time of disaster.

In all, several hundred amateurs participated in this emergency, both in the disaster area itself and outside in supporting roles. All are deserving of the highest praise for their efforts. It should be obvious from the above that no particular effort has been made to list the call letters of those who participated, but most reports received included long lists which we have not included for space reasons. To all these, our felicitations for a good job well done. And one last thought — they also served who stood by *without transmitting* so that those handling emergency traffic could do so that much easier and quicker.

Strays

Coaxial or feed-through condensers of the type used in suppressing automotive noises as specified in "Automotive Radio Noise Elimination," by Brooks H. Short, W9DPI, (April, 1952, *QST*, p. 17) are now available from Sprague Products Company, North Adams, Mass., and Cornell-Dubelier Corporation, South Plainfield, N. J.



ARTICLES OF ASSOCIATION

Be it known that we, the subscribers, do hereby associate ourselves as a body politic and corporate pursuant to the statute laws of the State of Connecticut regulating the formation and organization of corporations without capital stock and the following are our Articles of Association:

Article 1:

The name of our corporation shall be *The American Radio Relay League, Incorporated*. Our corporation commenced its corporate existence as the American Radio Relay League, Incorporated, when its Articles of Association were approved by the Secretary of the State of Connecticut on January 29, 1915. The original Articles of Association were subscribed by Hiram Percy Maxim, Clarence D. Tuska and Lawrence A. Howard. The affairs of the corporation have since that time been continuously administered by a Board of Directors selected by the membership; and the present Directors, subscribers hereto, are the lawful successors and associates of the incorporators.

Article 2:

The purposes for which our corporation is formed are the following: the promotion of interest in amateur radio communication and experimentation; the relaying of messages by radio without charge; the furtherance of the public welfare; the advancement of the radio art; the fostering and promotion of intercommunication by electronic means for the personal benefit of the members and without pecuniary gain; the fostering of education in the field of electronic communications; the dissemination of knowledge and information by electronic means; the printing and publishing of documents, books, magazines, newspapers and pamphlets necessary or incidental to any of the above purposes. No part of the assets or income of our corporation shall be the property of the members or any of them, but such assets and income shall be devoted exclusively to the purposes herein set forth.

Article 3:

The corporation is located in the town of West Hartford, County of Hartford and State of Connecticut and the address of the principal office is 38 LaSalle Road.

Article 4:

The name of the agent upon whom process may be served is A. L. Budlong and his address is 38 LaSalle Road, West Hartford, Connecticut or upon his successor as Secretary of the Corporation.

Article 5:

The affairs of this corporation shall be governed by a Board consisting of not less than five, nor more than seventeen Directors who shall be elected by the members for terms of two years.

The present Board of Directors and the expiration date of the term of each Director, are:

Alexander Reid, 240 Logan Avenue, St. Lambert, P. Q., January 1, 1952
John H. Brabb, 417 Ford Bldg., Detroit 26, Michigan, January 1, 1952
Victor Canfield, P. O. Box 965, Lake Charles, Louisiana, January 1, 1952
Goodwin L. Dosland, Moorhead, Minnesota, January 1, 1952
John R. Griggs, 10412 Don Pico Rd., RFD 2, Spring Valley, Calif., January 1, 1953
Lamar Hill, 104 Myrtle, Cochran, Georgia, January 1, 1952
Kenneth E. Hughes, 810 W. Orange Avenue, S. San Francisco, Calif., January 1, 1952
William H. Jacobs, Route 6, Raleigh, N. C., January 1, 1953
Joseph M. Johnston, 423 Monmouth Avenue, Bradley Beach, N. J., January 1, 1953
Alvin G. Keyes, 1201 Merchants Nat'l Bank Bldg., Cedar Rapids, Ia., January 1, 1952
Wesley E. Marriner, 844 North Galena Avenue, Dixon 7, Ill., January 1, 1953
Walter Bradley Martin, 1033 Arbutha Road, Abington, Pa., January 1, 1952
Franklin K. Matejka, P. O. Box 212, Estes Park, Colo., January 1, 1953
A. David Middleton, 9 Kay Road, Tijeras, N. M., January 1, 1953
Percy C. Noble, 37 Broad Street, Westfield, Mass., January 1, 1953
R. Rex Roberts, 837 Park Hill Drive, Billings, Mont., January 1, 1953

Their successors shall be elected by mail vote in accordance with rules and regulations prescribed by the Board of Directors in the By-Laws. Directors may be elected to represent specific geographical areas as may from time to time be prescribed in the By-Laws. The Board shall meet annually during the first quarter of each year at a time and place to be fixed by the President upon at least forty days' notice. Special meetings of the Board shall be called by the President upon written request of at least one-half the membership of the Board as then constituted.

Article 6:

At the time of the election of each Director there shall also be elected a Vice-Director who shall have power of succession to the office of Director as hereinafter prescribed. No person shall be eligible for the office of Vice-Director who does not possess the qualifications herein specified for the office of Director.

Article 7:

During the intervals between meetings of the Board of Directors the affairs of the corporation shall be administered by an Executive Committee consisting of the President, the First Vice-

President, the General Manager and one member of the Board of Directors designated by the Board. The Board of Directors, in its discretion, may also appoint from amongst the officers, directors, or employees of the League not more than three additional members of the Executive Committee to serve for fixed terms between regular meetings of the Board of Directors. The Executive Committee shall meet at the call of the President, but no less often than bi-monthly. The Executive Committee may in its discretion submit for determination or decision by the members of the Board of Directors by mail vote any proposal pending before the Executive Committee. When such submission is made, it shall be made in precise terms embodying the text of a proposed resolution. Such resolution shall be deemed adopted upon the receipt of the affirmative mail votes of at least 60% of the members of the Board. Otherwise, it shall be deemed rejected. Such action shall be binding upon the Executive Committee.

Article 8:

A vacancy in the Board of Directors shall be deemed to occur upon the death, resignation or refusal to act of any Director. Upon the occurrence of such vacancy, the Secretary shall proclaim it and thereafter the duties of the Director shall be assumed by the Vice-Director, and the Vice-Director shall hold the office of Director for the remainder of the term for which he was elected Vice-Director. Should the office of both Director and Vice-Director be vacant, the vacancy shall be filled by appointment of the President.

Article 9:

The officers of the corporation shall be a President, not more than three Vice-Presidents, a Secretary and a Treasurer who shall be elected by the Board of Directors at their meeting in 1952 and biennially thereafter.

Article 10:

The Board of Directors may from time to time adopt By-Laws not inconsistent with these Articles and may alter, amend or repeal such By-Laws.

Article 11:

The membership of the League shall consist of (a) full members who shall be entitled to all rights and privileges of the League and (b) associate members who shall be entitled to all rights and privileges of the League except the right to vote for Directors and Vice-Directors and the right to hold office. The Board of Directors shall by appropriate By-Laws specify the requirements for membership and classes of membership provided, however, that the Board of Direc-

tors shall not terminate or reduce the rights of any member except for the lapse or termination of a condition now required as precedent to the exercise of such rights. Nothing herein contained shall preclude the Board of Directors from expelling a member upon good cause shown and after notice and an opportunity to be heard.

Article 12:

No person shall be eligible for the office of Director, Vice-Director or President who has not been a member of the League for at least four years or who does not hold a valid authorization as a radio amateur in accordance with the applicable federal laws and regulations prevailing at the time of his election. No person shall be eligible for the office of Director, Vice-Director or President who is commercially engaged in the manufacture, sale or rental of radio apparatus capable of being used in radio communication, or is commercially engaged in the publication of radio literature intended in whole or in part for consumption by radio amateurs.

Article 13:

The Board of Directors shall employ a General Manager who shall hold office for a term and upon such compensation as the Board and he may agree upon. The General Manager shall manage the affairs of the League under the direction of the Board of Directors. He shall be deemed a member of the Board, but without vote. He shall attend all meetings of the Board. He shall collect all monies due the League and turn them over to the Treasurer. He shall certify the accuracy of bills or vouchers on which money is to be paid and shall draw and countersign all checks. He shall have charge of the books and accounts of the League and shall furnish to the Board of Directors from time to time such statements as may be required. He shall conduct the general correspondence of the League and shall keep full records. He shall be in responsible charge, under the Board of Directors, of all property of the League. He shall, under the general direction of the Board of Directors, employ such personnel as may be necessary for the effective accomplishment of the purposes of the League. He shall be the General Manager of the League publications. He shall prepare and submit to each annual meeting of the Board of Directors a comprehensive report of the progress and status of the affairs of the League. He shall perform such other duties as may be assigned to him by the Board of Directors. His entire time shall be devoted to the affairs of the League. He shall furnish a bond satisfactory to the Board of Directors, the expense of the same to be borne by the League.

• On these pages we reproduce the new Articles of Association of The American Radio Relay League, Inc., adopted by the Board of Directors at its 1951 meeting. On the following pages are the new By-Laws and supplementary regulations just adopted by the Board at its May meeting to become effective July 1, 1952.



BY-LAWS

Members

1. Pursuant to Article 11 of the Articles of Association, the following membership requirements are established:

(a) To be eligible for full membership an applicant must be a resident of the United States or its possessions or of Canada and must be either:

(1) the holder of either an amateur radio station license or an amateur radio operator's license, issued by the administration of the country of which he is a citizen. Such full membership shall be granted for no longer than one year at a time, and the holding of an amateur radio license must be demonstrated before each renewal for an additional year; provided, however, that if such a full member becomes without amateur radio license during a year for which he has been accepted as a full member, he shall continue to possess the rights of a full member until the expiration of the year; or

(2) a person who has held continuous and unexpired membership in the League since May 15, 1934.

(b) Any person interested in amateur radio shall be eligible to associate membership. Upon attaining possession of an amateur license, an associate member shall be transferred to full membership upon his application therefor, if he is otherwise eligible.

2. Applications for membership shall be submitted to the Executive Committee and a majority vote of this Committee shall elect to membership. The Committee shall not elect any applicant whose character, reputation or conduct would make him, in its opinion, an undesirable member. The Committee may delegate the ministerial function of granting (but not denying) applications for membership as to which no question is raised or suggests itself under these By-Laws.

3. The Secretary shall notify members of the expiration of their membership not less than thirty days in advance thereof.

4. The dues of members of any class shall be \$4.00 per year in the United States & Possessions, \$4.25 in the Dominion of Canada, payable annually in advance.

5. Provided that a full member is without sight, or is the husband or wife, brother or sister, son or daughter, father or mother of another full member living at the same address paying dues at the rate of \$4.00 per year in the United States & Possessions or \$4.25 in the Dominion of Canada, he may at his request pay dues of \$1.00 per year, in advance, but without the right to receive "QST"; said membership to be concurrent with that of the member receiving "QST".

General Provisions as to Officers and Directors

6. Every officer, director and vice-director of the League shall serve and continue in office until his successor shall have been elected and qualified.

7. All officers, directors and vice-directors shall serve without compensation in any form. This shall not preclude the reimbursement, and the League shall reimburse the reasonable and necessary travelling expenses of officers and directors from their homes to the place of meeting of the Board of Directors or of the Executive Committee and return to their homes. This section shall not be construed to prevent the employment, for agreed compensation, of the Secretary, the Treasurer, and any Vice-President other than the first Vice-President, by the League in other capacities.

8. No person shall be an officer, director or vice-director of the League unless at the time of his assuming office he is a member of the League.

Directors

9. The members of the Board of Directors shall be the President, the Vice-Presidents, one director from each of the several territorial divisions of the League and the General Manager.

10. The President, the Vice-Presidents and the General Manager shall possess all of the rights and duties of directors save the right to vote, provided, however, that the President shall be required to cast a vote on any matter as to which a tie is found to exist.

11. Without restriction of his rights and duties as prescribed by the Articles of Association, the Canadian Director is requested not to vote on any matter involving recommendations or expressions of attitude concerning the exercise of the power of the Federal Government of the United States of America in the regulation of radio communication, or in matters of purely domestic United States interest.

12. Each director shall keep himself informed as to conditions and activities in his territorial division and as to the needs and desires of the members therein in order that he may faithfully and intelligently represent the true interests of such members. He shall attend all meetings of the Board. At least twenty days prior to each annual meeting of the Board of Directors each director shall file with the Secretary a written report on the status of the affairs of the League in his division, together with a statement of his recommendations as to any actions required for the effective administration of the objectives and affairs of the League.

13. On any date not later than noon of the twentieth day of September of an election year in

any division, nominating petitions signed by ten or more full members of a division and naming a full member of the division as candidate for director, may be filed with the Secretary. The Secretary shall solicit such petitions in the August and September issues of "QST" in each election year by a notice that will show the name of the incumbent.

14. The Executive Committee shall delete the name of any nominee who may be ineligible to election and the name of any who may withdraw by written communication. The remaining names shall be listed on a ballot, in alphabetical order. If there be but one eligible nominee, the Executive Committee shall declare him elected without balloting by the membership. If there be more than one eligible nominee, then during the first week of October the Secretary shall send by mail to every person who on the twentieth day of September of that year was a full member of the League in the divisions in which elections are being held, a ballot listing the candidates for director in his division, and a return envelope, soliciting a vote for one name. The ballot shall contain a copy of By-Laws 13 and 15.

15. The Executive Committee shall appoint a committee of three tellers and shall arrange to have a certified public accountant present to certify the results of the balloting; but any member of the League who shall deliver to the Secretary on or before the first day of October of election year a written petition signed by at least ten full members of a division, stating their desire that he witness the counting by the committee of tellers of the ballots from that division, shall be permitted to do so and shall be accorded reasonable opportunity to satisfy himself of the correctness of the count reported by the committee. Ballots, to be counted, shall reach the Secretary not later than noon of the twentieth day of November of election year. No outer envelopes marked as containing ballots shall be opened until the meeting of the committee of tellers held for the purpose of counting the ballots. The committee of tellers shall meet at the headquarters office of the League as soon thereafter as possible and in the presence of each other shall open the envelopes containing ballots and shall count the vote, after first eliminating the ballot of anyone disqualified from voting. They shall forthwith prepare and sign in the name of the Executive Committee a report of the results of the vote, declaring duly elected as new directors the candidate in each division receiving the greatest number of votes therein; and they shall turn over all their records and ballots to the Secretary for presentation at the next annual meeting of the Board of Directors.

16. If there be no eligible nominee, the procedure provided for in By-Laws 13, 14 and 15 shall be repeated three months later and if there again be no eligible nominee, the person then holding the office of director shall continue in office (subject to the provisions of Article 8 of the Arti-

cles of Association), until the next regular election established by these By-Laws for the division.

17. Simultaneously with each election for director of any division there shall be held an election for vice-director of that division. All of the provisions of By-Laws 1, 13, 14 and 15 shall be applicable to the election for vice-director. Should it appear that any one person is nominated for the office of director and vice-director, his nomination shall be deemed for director only and his nomination for vice-director shall be void.

18. A director and a vice-director shall be elected in each even-numbered year in each of the following divisions: Central, Hudson, New England, Northwestern, Roanoke, Rocky Mountain, Southwestern and West Gulf. A director shall be elected in each odd-numbered year in each of the following divisions: Atlantic, Canadian, Dakota, Delta, Great Lakes, Midwest, Pacific and Southeastern. The term of each director shall be for two years.

19. The terms of all directors and vice-directors shall begin at noon on the first day of January of the year after that in which they are elected.

20. Meetings of the Board of Directors shall be held at West Hartford at a place to be designated by the President and notified by the Secretary. Meetings may be held at places other than West Hartford provided that specific provision is made thereby by appropriate action of the Board of Directors or of the Executive Committee at least sixty days prior to the date of the meeting.

21. Special meetings of the Board of Directors may consider or act upon only those matters which are set out in the request provided for in Article 5 of the Articles of Association. The call for any such meeting shall specify the matters to be considered.

22. A majority of the members of the Board of Directors or of any committee shall constitute a quorum at any meeting of the Board or committee.

23. Prior to any regular meeting of the Board of Directors, the Secretary, upon consideration of the reports of the officers and directors, shall establish an agenda for the meeting. Proposals for amendment of the agenda or for the deletion or addition of items shall be the first order of business.

24. On questions of order and procedure not otherwise determined by these By-Laws the provisions of the current edition of *Robert's Rules of Order* shall prevail.

25. In accordance with the provisions of Article 5 of the Articles of Association and for the purpose of By-Laws 9, 12, 13, 14, 15, 17 and 18, the following territorial divisions are established:

ATLANTIC DIVISION, those portions of the states of New York and New Jersey not included in the Hudson Division, the states of Pennsylvania, Maryland and Delaware, and the District of Columbia; CANADIAN DIVISION, the provinces

of Nova Scotia, New Brunswick and Prince Edward Island, Ontario, Quebec, Saskatchewan, Manitoba, Alberta, British Columbia, and Newfoundland, Labrador, the Northwest Territories and the Yukon Territory; CENTRAL DIVISION, the states of Illinois, Indiana and Wisconsin; DAKOTA DIVISION, the states of Minnesota, North Dakota and South Dakota; DELTA DIVISION, the states of Louisiana, Mississippi, Arkansas and Tennessee; GREAT LAKES DIVISION, the states of Kentucky, Michigan and Ohio; HUDSON DIVISION, the counties of New York, Bronx, Richmond, Kings, Queens, Nassau, Suffolk, Westchester, Rockland, Putnam, Orange, Ulster, Dutchess, Columbia, Green, Albany, Rensselaer and Schenectady of the state of New York, and the counties of Bergen, Passaic, Morris, Essex, Union, Middlesex, Monmouth, Hudson and Ocean of the state of New Jersey; MIDWEST DIVISION, the states of Nebraska, Iowa, Kansas and Missouri; NEW ENGLAND DIVISION, the states of Maine, New Hampshire, Vermont, Massachusetts, Rhode Island and Connecticut; NORTHWESTERN DIVISION, the states of Washington, Oregon, Montana and Idaho, and the Territory of Alaska; PACIFIC DIVISION, that portion of the state of California not included in the Southwestern Division, the state of Nevada, the Territory of Hawaii and the United States Possessions in the Pacific; ROANOKE DIVISION, the states of Virginia, West Virginia, North Carolina and South Carolina; ROCKY MOUNTAIN DIVISION, the states of Colorado, Wyoming and Utah; SOUTHEASTERN DIVISION, the states of Georgia, Florida and Alabama, the United States Possessions in the Caribbean, and the Canal Zone; SOUTHWESTERN DIVISION, the counties of Imperial, Inyo, Los Angeles, Orange, Riverside, San Bernardino, San Diego, San Luis Obispo, Santa Barbara and Ventura of the state of California, and the state of Arizona; WEST GULF DIVISION, the states of Texas, Oklahoma and New Mexico.

Officers

26. The President shall preside over all meetings of the Board of Directors. He shall, subject to instruction from the Board of Directors, represent the league in its relationships with the public and the various governments, governmental agencies and officials with which the League may be concerned and shall be the official spokesman of the Board of Directors in regard to all matters of League policy.

27. In the absence or disability of the President, the First Vice President shall preside at meetings of the Board of Directors and in general act in his stead. No Vice President other than the First Vice President shall have this power of succession. Should the First Vice President be also absent or unable to act, the Board of Directors shall designate an Acting President, provided that no special meeting shall be called for this purpose.

28. The Secretary shall record the proceedings of all meetings of the Board and of the Executive Committee. He shall promptly furnish copies of the minutes of these meetings to all officers and members of the Board and publish them in "QST". He shall be responsible for the maintenance of the corporate status of the League and the filing of all reports and certificates which may be required of the League under the corporation laws of the State of Connecticut. He shall be the archivist of the League and for the performance of his such duties may call upon the General Manager for such clerical and stenographic assistance as he may require. To the extent that may from time to time be required by law, he shall act as agent for the service of process, but only while present in the State of Connecticut, and he is not authorized to accept service of process elsewhere.

29. The Treasurer shall be the recipient of all monies of the League and shall deposit the same in the name of the League in a depository specified by the Board of Directors. He shall sign checks drawn by the General Manager in payment of obligations known by him to be proper and authorized. He shall make a report at the annual session of the Board of Directors and shall attend meetings of the Board. He shall furnish bond satisfactory to the Board, the expense of such bond to be borne by the League. He shall be *ex officio* a member of the Finance Committee provided for in By-Law 30 and shall, on consultation with and subject to the general supervision of the Finance Committee, invest and reinvest the surplus funds of the League in securities of the variety in which a life insurance company is authorized by law to invest.

Standing Committees

30. The following standing committees are established:

Finance Committee
Planning Committee

31. Each such committee shall consist of three members, one of whom shall be specifically designated as Chairman. Appointments shall be made by the President during annual meetings of the Board of Directors and shall be for a term of one year. Standing committees shall make written annual reports at least thirty days prior to each annual meeting of the Board of Directors.

32. The Finance Committee shall act as advisor to and supervisor of the Treasurer in regard to the investment of the League's funds. The Chairman of the Finance Committee may direct from time to time that the business of the committee may be transacted by mail.

33. The Planning Committee shall act as a reference body to which the Board may from time to time by resolution refer problems requiring special study, planning and recommendation. Any such resolution of reference shall describe with particularity the problem to be studied, the

general character of the investigation required and the scope of the report desired.

Official Publication

34. There shall be an official publication maintained by the League, in the form of a monthly magazine, the name of which shall be "QST". A copy of this magazine shall be supplied each month to every member of the League in good standing. The general management of this magazine shall be in the hands of the General Manager. The policy of the magazine shall be determined by the Board of Directors.

Amendments

35. These By-Laws may be amended by a three-quarters vote of the directors present at any meeting; or (provided due notice of the proposed amendment shall have been submitted to every director at least thirty days in advance), they may be amended by a two-thirds vote.

36. Without changing their import, the Secretary may from time to time, on notice to the members of the Board of Directors, renumber these By-Laws so as to serve the purpose of ready reference.

37. The present By-Laws shall become effective July 1, 1952.

RULES AND REGULATIONS CONCERNING AMERICAN RADIO RELAY LEAGUE CONVENTIONS

1. An American Radio Relay League convention is defined as a meeting of persons interested in amateur radio, of any regular American Radio Relay League Division or of any State or Province therein, when such meeting has been authorized and is conducted as hereinafter provided.

2. Neither the name of the American Radio Relay League, nor the initial letters thereof, nor its emblem, shall be used in connection with any meeting or convention, or in the advertising thereof, save such as above defined.

3. Before such a convention is held, the parties desiring to conduct the same shall obtain the approval of the director of the division in which the convention is to be held, by an application setting forth the place and date of the proposed convention, the territory to be embraced, the particular purpose to be served thereby, the clubs, associations or groups who propose to sponsor it, and the names and addresses of the officers chosen to conduct it. When the director is satisfied that the approval of such convention will be in the

best interests of the League, he shall submit the application to the Executive Committee for its formal approval. Upon such final approval the headquarters shall notify the chairman or secretary of the convention group. The management, program and financial plans of every such convention shall be subject to the approval of the director of the division in which the convention is to be held.

4. Notwithstanding the foregoing provisions the Board of Directors may, at any meeting, authorize or direct, upon such terms as it may prescribe, the holding, as a National Convention, of a meeting of persons interested in amateur radio from throughout the operating territory of the League.

5. The General Manager, with the approval of the Executive Committee, is also authorized to provide (upon the request of the directors affected), for the holding of a State Convention designed for amateurs residing in any state which lies partly in each of two divisions.

RULES AND REGULATIONS CONCERNING AFFILIATED SOCIETIES

1. It shall be the policy of the League to affiliate with itself local non-commercial amateur radio societies of kindred aims and purposes with a view to forming a homogeneous organization for unity of action in matters affecting amateur welfare.

2. Any such society which suitably expresses its sympathy with and allegiance to the aims and policies of the League in accordance with regulations determined by the Communications Manager with the approval of the Executive Committee, and which upon investigation is found to be worthy and well qualified, may be declared duly and truly affiliated with the League by the Communications Manager with the approval of the Executive Committee and a certi-

ficate shall thereupon be issued the society in token thereof. The Executive Committee shall have the authority to refuse affiliation to any society if in its opinion such affiliation would be harmful to the best interests of the League.

3. The affiliation of any society may be terminated and its charter recalled by the Executive Committee at any time for any cause deemed prejudicial to the best interests of the League.

4. At least 51% of the voting members of an affiliated society must be full members of the League.

5. At least 51% of the members of an affiliated society must be licensed radio amateurs.

6. The Communications Manager shall be

(Continued on page 128)

• Technical Topics —

"How Come No 160?"

Most of us of pre-World-War-II days' operation can recall the fine QSOs on 160 meters, but since the war very little activity has been noticed. The 160-meter band has extremely good possibilities and promises a great deal of enjoyment and experimentation. The author has been operating mobile on 75-meter 'phone since two days after the go-ahead signal for mobile operation on all bands and, like many other hams, has had an immense amount of enjoyment and opportunity for experimentation with the low-frequency antenna systems required for mobile operation.

Daylight operation on 75 is quite limited with the average mobile installation of about 20 watts, and, after reference to various textbooks, the reasons for the limited signals are readily understood. Attenuation of the ground signal in the 2- to 4-Mc. region is quite pronounced. For instance, tests were conducted on both bands, with a given output of 20 watts on 'phone. The receiving end indicated the following signal levels: on 3980 kc. the signal was 1500 microvolts at approximately 7 miles from the transmitter, and on 1920 kc. the signal was 10,000 microvolts at 7 miles from the transmitter. This experimentation was conducted at various times and under various conditions, but good engineering practice was used and the above figures were compiled as an average of the findings. Near the salt water or any areas of exceptionally moist and good ground such as marshes, etc., the over-all gain was much more pronounced. But over average terrain these were the readings. It should also be brought out at this time that the antenna used on 160 was the same home-brew antenna that had been grid-dipped to 3965 kc., complete with capacity hat. Even though the antenna was not resonant to the 160-meter band, the antenna loaded in fine style by adding a variable series inductance.

Although fine communication on 75 mobile 'phone has been experienced in the daylight hours, it was the complete *kaput* of contacts in the evening that prompted this look into the possibilities of 160 mobile.

About a year ago the rig was placed on 160 and, for a receiver, the low-frequency end of the car's broadcast receiver was modified by removing a few turns from the oscillator coil and then re-peaking the receiver at about 1900 kc. For normal broadcast reception the receiver with the extra-good ham antenna is fine, and this little receiver, a cheap auto radio in comparison to existing types on today's market, has turned out to be very excellent, and a good number of mobile QSOs have been realized on the 160-meter band.

Two facts have been mentally recorded while operating on 160 that make the band ideal for mobile and in some respects superior to 75 meters. Excellent contacts of about twice the distance for ground wave have been noticed on 160—over 75-meter operation,¹ and a QSO in the evening is excellent on 160 whereas on 75 it's *kaput* because of the gallons of r.f. in the air.

The two reasons for good operation on 160 that have just been brought out are fine, but of course all is not gold that glitters, and the disadvantages to be encountered are as follows: The QSOs obtainable on 160 mobile are reduced, of course, because of the limited activity on the band. So let's get on the 160 mobile and fixed band. There's a well of enjoyment here, and already about 25 stations active in this area.

—R. A. Roberge, W6OZS



July 1927

... Boyd Phelps, 2EB, and Technical Editor Robert S. Kruse "formally opened" the amateur $\frac{3}{4}$ -meter band with gear brought to the Hudson Division Convention.

... E. M. Guyer and O. C. Austin, 9AKR, recount their investigation into 5-meter techniques. Both are constructing new gear for operation at one meter and lower.

... Chester W. Rice discusses phenomena associated with short-wave transmission and reception and explains the "skip" effect in a detailed analysis.

... Ross A. Hull's "Some Light on Transmitter Tuning" features a handy "Growler" monitor built into a completely-shielded container of the hardware-store variety.

... "A Constant-Frequency Transmitter," by W. H. Hoffman, 9EK-9XH, contends that crystal control is not the only approach to signal stability.

... To minimize transients, a wave is interrupted by varying the capacities of coupling condensers in the novel keying system of A. G. Shafer, 3ACF.

... A laboratory instrument capable of measuring capacity, power factor, resistance and inductance is the subject of an article by J. Katzman.

... An "852 holder" is among new available equipment, marketed by Radio Engineering Labs of New York City to facilitate use of this popular tube.

... Amateurs cooperated with the Army and Navy in Atlantic Coast maneuvers wherein a Black Force mounted an attack by sea on a defending Blue Force.

... Putnam Baffinland, Wilkins Arctic, University of Michigan Greenland, Borden-Field Arctic and Marshall-Field Alaska expeditions are utilizing amateur radio.

... Enthusiasm for Twenty runs high as reports continue to pour in concerning amazing low-power daylight DX contacts made throughout the world.

... Outstanding amateur stations pictured and described are those of Edward G. Raser, 3Z1, Trenton, N. J., and H. G. Pearce, 6DDO, Los Angeles, Calif.

¹See, also, Beers, "The Wavelength Factor," QST, February, 1952.



CONDUCTED BY E. P. TILTON,* WHDQ

It was just a year ago that FCC touched off an unprecedented march on its examining rooms by opening up for business on the Novice and Technician classes of license. We don't have complete figures for the year, of course, but present licensing rates make it certain that well over 12,000 new hams will have been brought into our hobby through these new licensing avenues alone, when the June and July figures are in.

We need only listen above 3700 kc. to see what all this has meant to occupancy of the 80-meter band. That 50-kc. Novice segment is literally boiling with signals, around the clock. The effects on the world above 50 Mc. are less obvious, but perhaps no less important. Two-meter operators in or near our more densely-populated regions have seen a marked change in operating habits and occupancy already, and the effects are still on the increase. Where there was universal complaint over lack of activity a year ago, today we find use of the 2-meter band approaching the saturation point in some spots, and almost everywhere there is more doing on 2 than at any time since the simple modulated oscillator and superregenerative receiver went out of style some years ago.

Most noteworthy is the reversal of the trend toward low-end crowding. No longer is it necessary to be in the bottom 500 kc. of the band to get contacts. We're tuning the whole band again, and the 145-Mc. low end of the Novice assignment is responsible for it.

As will be seen from the minutes of the recent ARRL Board Meeting, printed elsewhere in this issue, our Directors have petitioned FCC to open 51 to 53 Mc. to Novice use. If FCC acts favorably on this request, we may expect a similar expansion in utilization of that band. All of us agree that 6 could stand it. There has been a growing tendency on the part of 6-meter men to become DX hunters exclusively, making use of the band only when it is open, or expected to be. There is regular use of the band here and there, but the total occupancy is all too small a percentage of what the band is capable of accommodating. DX hunting on 6 is fun, and our efforts in that line have resulted in some noteworthy contributions to the store of wave-propagation knowledge, but the band should not live by DX alone. It is too useful a hunk of spectrum for local communication to be allowed to lie almost unused for nine months in the year!

The most frequently voiced objection to Novice operation on the v.h.f. bands runs something like this: "Sure, that's all well and good to promote activity on the v.h.f. bands, but how is the Novice going to build up his code speed to the

General Class level if he yaks away his first year on 'phone?" This line of reasoning ignores the fact that thousands of beginners have made the grade in years gone by without having c.w. operating experience. They learned the code by listening, and by practice with others who were learning.

Which brings up a possible use of the v.h.f. bands that has yet to be fully exploited — the formation of Novice nets for code-practice purposes. Surely the swapping of formulas, in the manner of the usual 80-meter QSO, is not the ideal form of code practice. An hour's work each evening with A2 emission, chewing the rag with nearby associates on 6, 2, or 1½ would do a lot more good. It would be more fun, too, in view of the congestion of the Novice segment of the 3.5-Mc. band. Some of us who have been around a few years could stand the code practice, too. When do we start?

Here and There on the V.H.F. Bands

The May issue of *QST* had not been out long before we heard about a couple of errors in the tabulation of scores for the V.H.F. Sweepstakes. We did W6GCG dirt by listing his score as 34 instead of 340. Getting it right moves him up from 9th to 4th place in the Santa Clara Valley Section listing. Worse yet, we transposed two figures in the score of W2DLO, listing him as having 846 points instead of the 864 he actually rolled up. What's so important about 18 points, do we hear someone ask? Well thereby hangs a tale, for that slight change put W2BNX (850) just a hair above W2DLO, and we listed him as winner in the Lake Success Radio Club standing. This didn't feel too well, as W2BNX was the fellow who promoted the club members into turning out in force for the Contest! We're really sorry, boys; we do try to check contest scores carefully, but things like these happen once in a while.

Would anybody like to work Chile on 50 Mc.? It's never been done from this country, despite valiant efforts in that direction by CE1AH. Now the fellow all 6-meter men knew so well as HC2OT is going to have a try at it. Steve, W5BR, ex-W5DNN-HC2OT-CO2JF, is soon to leave for an assignment that will keep him some time in a likely location in Northern Chile. Though the solar cycle offers little chance for F₂ DX, Steve will be taking gear for 2 and 6 meters, as well as for 10, 15, and 20. It is an amateur axiom that we never know what we can or cannot work until we try, and many paths have been worked when available facts made it seem useless to try. One thing's sure — if 6-meter DX can be worked from Northern Chile, the man who made 6-meter history in Ecuador and Cuba is the fellow to do it! And we know that CE1AH will be glad to have some company on 6 and 2 meters.

DX of another sort, but hardly less desired by 6-meter men who need Nebraska for 50-Mc. WAS, should be available from June 29th to July 12th, when W9EET/Ø will be operating in Lincoln, Neb. The rig will run at least 50 watts, and Gordon hopes to have a beam up. Frequency will be 50.7 Mc.

Up to the end of May, the 50-Mc. DX season was well below par, but all hands are hoping at this writing that this is only a matter of delayed action. There is difference of opinion as to the relation, if any, between the sunspot cycle and incidence of sporadic-E ionization. Some observers see inverse correlation, while others feel that E_s is more prevalent in years of high sunspot number. We are passing through

* V.H.F. Editor, *QST*.

the low years at present, so the next few years should shed light on the subject. Of interest in this connection is the summary of the DX season enjoyed by our friends in the Antipodes, as reported by Cliff Betson, ZL1MQ, V.H.F. Editor of the NZART publication, *Break In*.

Cliff says that things got underway late, and the season was shorter than some, but conditions were excellent while it lasted. The first good openings came in early December, corresponding to our June. VK9XK, Papua, was a star performer, working nearly every 50-Mc. ZL until he left the band in the middle of January. He worked 147 stations, 75 per cent of them ZLs, winning the ZL WAD award. ZL to VK9 is equal to or greater than W1 to W6 DX! ZK2AA on Nuie worked 4 ZLs using a 2E26 doubler and a 10-meter beam. On Dec. 30th, the peak day of the year, all ZL districts, VK2, 3, 4, 5, 6, 7, 9, and ZK2AA were all workable on the band at the same time. This session covered from 115

degrees East to 170 West, or 75 degrees longitude, and extended over 38 degrees latitude, from 8 to 46 south. (U.S.-Canadian activity covers 58 degrees longitude and 24 latitude!) From VK6 to ZL1 and 2 is 2500 miles, yet the VK6s were in solid for hours. If June 30th is as good here, most Ws and VEs will be well satisfied!

Ever notice how few fellows you hear making use of the opportunities for v.h.f. DX that a good aurora opening affords? W2ORL, Lockport, N. Y., says that the 2-meter aurora gang would make a good club—you hear the same calls time after time. The only trouble is, says John, there aren't enough members, particularly in certain states, like Maine, New Hampshire, Vermont, Rhode Island, and Delaware, for instance. There is at least some 2-meter activity in these states; doesn't anyone there have a horizontal array, or know the code?

In watching for aurora members of the "club" overlook few bets. They watch their TV screens, or have their families and friends do so and let them know when those streaks appear. (This one is particularly good if you have to aim north or south for your TV reception, and are at least 35 or 40 miles from a low-band station.) They monitor WWV for the propagation warnings at 19½ and 49½ minutes past the hour. They get the advance dope by listening to W1AW regularly. They watch for wavy signals on 75, or the short-wave broadcast bands. They know that better than average signals on 10, with the band staying open for DX later than usual in the evening, are an almost certain tip-off. And they don't just aim north in looking for aurora signals. Some openings, including the widespread one of May 26th, brought in signals best with beams here in the East aimed almost west, while W0EMS, Adair, Iowa, says that his reception is usually best at about NNE.

The boys who work the aurora for all it's worth think it one of the most intriguing angles in the whole v.h.f. game. We feel that the fellows who don't go in for it are missing something. What's more, they are passing up a chance to help in a scientific study. Are you contributing reports for the Cornell University Aurora Project? If not, we invite you to send for reporting forms now, and join in the fun. A card to the writer will start forms on the way.

W2NLY, Oak Tree, N. J., reports aurora DX on 144 Mc. five nights in a row, beginning with April 29th. The May 3rd session was the best, with W9UCH, Ft. Wayne, Ind., reaching 88 on peaks, and W9EHX, McLean, Ill., worked, extending Jim's best 2-meter DX to 795 miles.

Nowhere is "what's going on" at the local level better reported than in the hundreds of radio club papers. You find these everywhere, and they run all the way from single-sheet mimeographs to beautifully-printed jobs gotten out by some of the larger radio-club councils. Most of the outfits producing them are ARRL-affiliated clubs, so many of them pass across our desks here at Headquarters. Noteworthy to the writer is that, in the last few months, almost every club bulletin we've seen has at least some v.h.f. news, and not a few of them devote a goodly portion of their space to it.

In QRM (Puget Sound Council of Amateur Radio Clubs) we find a list of 43 2-meter stations active in Longview and Portland, Oregon, and Seattle and Tacoma, Wash., contributed by W7PXB. He reports that the VE7 activity is now all horizontal, and there are stations on every night looking for more business. Activity gets underway as early as 6 p.m. Olympia, Wash., got its first shot of 420-Mc. interest recently as the result of operation on that band by W7s KNV, HPJ, and CMX.

Working on 2 around Philadelphia must be unhealthy these days. Now we understand, from W2QED, that W2PAU is having a session in the hospital. Don't be long, Brownie, this is the wrong time of year for good v.h.f. men to be out of circulation!

One of the elaborate c.d. communications set-ups for 2-meter work we've heard of is the Orange County station of the Zone 3 New York State Civil Defense System, described by W2PCQ. Located 1385 feet above sea level about 10 miles from Middletown, N. Y., the station covers all seven counties of Zone 3, and other points in Eastern New York, New England, Northern New Jersey, and Eastern Pennsylvania with ease. There is emergency power for operating two 2-meter transmitters, with a choice of high-gain or coaxial antennas. Operation is on 145.5 and 144.8 Mc.

Doings on 220 and 420

Until recently, the 220-Mc. band has been something of an orphan, with most of the experimenters skipping over it

2-Meter Standings

Call			Call			
States	Areas	Miles	States	Areas	Miles	
W1HDQ	16	6	650	W8SWV	7	2
W1IZY	15	6	750	W5FBT	6	2
W1MNF	14	5	600	W5IRP	6	2
W1BCN	14	5	580	W5ONS	5	2
W1DJK	13	5	520	W5FSC	5	2
W1CTW	12	4	500	W5DFU	5	2
W1KLC	12	4	500	W5JLY	4	2
W2BAV	21	7	1175	W6ZL	2	2
W2NLY	18	6	795	W6WSQ	2	2
W2PAU	16	6	740	W6JFA	2	2
W2AZL	16	6	—	W6GCG	2	2
W2SFK	13	6	—	W6EXH	2	2
W2DFV	13	5	350	W6ZEM	1	1
W2CET	12	5	405	W6GGM	1	1
W2DPB	12	5	500	W6YGY	1	1
W2QED	12	5	365			
W2FHH	12	5	—	W8WJC	21	7
W2QNZ	12	5	—	W8BFQ	21	7
W2BVU	12	4	260	W8WRN	19	7
W2ORI	11	6	620	W8WVX	18	8
W2UTH	10	6	—	W8UKS	18	7
				W8EP	17	7
				W8WSE	16	7
W3NKM	19	7	660	W8RWW	16	7
W3RUE	18	7	760	W8BAX	15	6
W3QKI	17	7	820	W8FQK	13	7
W3KWL	15	7	560	W8CYE	12	6
W3LXA	14	7	720	W8CPA	12	6
W3GKP	14	6	650			
W3OWW	13	6	600	W9FVJ	20	7
W3KITX	12	5	575	W9UCH	20	7
W3PGV	12	5	—	W9SVU	19	7
W3LMC	11	4	400	W9EQC	18	7
				W9BOV	15	6
W4MRJ	16	7	665	W9WOK	15	5
W4HHK	15	6	660	W9MBL	14	—
W4JDN	13	6	—	W9AFT	14	—
W4JFV	13	5	830	W9NFK	12	7
W4IKZ	13	5	650	W9TIA	12	7
W4JFU	13	5	720	W9GTA	11	5
W4OXC	13	7	500			
W4CLY	12	5	720	W0EMS	15	6
W4JHC	12	5	720	W0IHD	15	6
W4OLK	12	5	720	W0NFM	14	7
W4FJ	12	5	703	W0ZJB	12	7
W4LRR	5	2	900	W0WGZ	11	5
				W0HXY	8	3
				W0JHS	7	3
W5JTI	14	5	670			
W5QNL	10	5	1400			
W5CVW	10	2	1180	VE3AIB	12	6
W5MWW	9	4	570	VE1QY	11	4
W5AJG	9	3	1290	VE3BOW	8	5
W5ML	9	3	760	VE3BQN	7	4
W5ERD	8	3	570	VE3TN	7	4
W5VX	7	4	—	VE3BPB	6	4
W5VY	7	3	1290	VE3AQG	6	4
W5FEK	7	2	580	VE3DER	6	4
W5ABN	7	2	450	VE3EAB	5	4

from 144 to 420 Mc. The Technician Class license is resulting in some signs of life on 220, however. It is somewhat easier to get equipment working efficiently on the lower frequency, and the band is working out nicely for local ragchewing. According to W2IQR, each Sunday morning at 11 finds around a dozen stations on 220 in the New York area. These include W2s DZA, IQQ, MLX, BQK, KQ, ESW, BOD, HRN, QOX, KON, LWN, BZJ, IHV, IQR, and WG. W2IQR also operates from a summer location on the North Shore of Long Island, near Huntington, from which point he has worked as far as High Point, N. J., some 90 miles distant. He would like to arrange schedules with W1s, particularly the group known to be working on 220 in the Boston area. He has a crystal-controlled rig with an 829B final on 220.5 Mc. A 12-element vertical array is used.

On 420 the prospects are bright for the best summer season yet. Not only are many more stations ready to go, but the quality of much of the equipment is vastly improved over that used in former years, particularly in the receiver department. Here are some of the better set-ups: W1CLS, Waltham, Mass. — 9903 tripler-amplifier on 432.38 Mc., 24-element horizontal array, crystal-mixer converter with HRO i.f. W1HDF, Elmwood, Conn. — 9903 tripler-amplifier on 432.1 Mc., 16-element horizontal array, crystal-controlled converter (described in June QST). W1HDDQ, Canton, Conn. — 9903 tripler-amplifier on 432.4 Mc., 24-element horizontal array, crystal-controlled converter. W1PBB, Monroe, Conn. — low-power crystal control on 436.4 Mc., 40-element array, horizontal or vertical, crystal-mixer converter. W2EH, Collingswood, N. J. — 9903 tripler, 40-element array, APS-13 converter ahead of 2-meter receiver. W2QED, Seabrook, N. J. — 9903 tripler-amplifier, 435.6 Mc., 32-element horizontal array, 6/4 r.f., APS-13 converter into 2-meter receiver. W3RKK, Wilmington, Del. — 9903 tripler-amplifier. W3BSV, Salisbury, Md., same. W3KFM, Baltimore, Md. — 9903 tripler on 433.5 Mc., 16-element horizontal with screen reflector, converted taxi receiver with 6/4 r.f. amplifier. W9ZHB, Zeining, and W9MBI, Coleta, Ill. — 9903 tripler-amplifiers, 430.6 and 434 Mc., both with crystal-controlled converters and 16-element horizontal arrays.

There is considerable 420-Mc. activity around Toronto and Hamilton, Ontario, according to VE3EAB, writing in the *Mohawk Journal*. He says that the local (Hamilton) record is held by VE3AQQ, as the first to work W2ORI, Lockport, N. Y. VE3DAL is the first Hamilton station to use crystal control on 420. Other VEs now on 420 include AIB, AXT, DAN, and BQN. W2PSC, Lewiston, N. Y., is also on and working across the lake.

W4HHK, Collierville, Tenn., has a 9903 tripler, and indoor 16-element array, and a crystal-mixer converter ahead of his HFS-183 lineup. He is working crossband with W4BYN in Memphis, who replies on 144 Mc. Paul had a misfortune with his first 9903 that might well serve as a warning to other users of this tube. The 9903 is built with only the glass seals at the top of the envelope supporting the plates. This design results in low output capacitance, making the tube really outstanding for operation on 420 Mc., but it also makes it break very easily. The tube will stand normal usage OK, but don't put any strain on those plate pins. Use very flexible ribbon for plate leads, and be careful not to hit the pins in handling.

OES Notes

W3NNV, Colwyn, Pa., would like to know of someone nearby who could help him in getting set up for teletype operation on 144 Mc.

A request in this space for skeds on 6 by W4FLW, Dresden, Tenn., brought results. He is now checking regularly with W4JAG, Princeton, Ky., 75 miles to the northeast,

Phasing the "Twin-Five"—Correction

An error was made in the drawing of the 5-over-5 array on page 56 of the June issue. As shown, the two sections of the array are out of phase. Where the off-center matching is used, the phasing line must be transposed. Additional work is being done on this design, and details will be given in a later issue.



W0ZJB.....48	W4FNR.....39	W8LBH.....39
W0BJV.....48	W4HJ.....38	W8BFQ.....39
W0CJS.....48	W4BEN.....35	W8LPD.....37
W5AJG.....48		
W9ZHL.....48	W5VY.....47	W9ZHB.....48
W9OCA.....48	W5GNQ.....46	W9QUV.....48
W6OB.....48	W5JTI.....44	W9HGE.....47
W0INI.....48	W5ONS.....44	W9PK.....47
	W5ML.....44	W9VZP.....47
W1HDDQ.....47	W5JLY.....43	W9RQM.....47
W1CLS.....46	W5JME.....43	W9ALU.....47
W1CGY.....46	W5VV.....42	W9QKM.....46
W1LLL.....44	W5FAL.....41	W9ULA.....45
W1KHL.....44	W5NHD.....41	W9UNS.....45
W1HMS.....43	W5FSC.....41	
W1LSN.....42	W5HLD.....40	W9QIN.....47
W1EIO.....41	W5HEZ.....38	W9DZM.....47
		W9NFM.....47
W2RLV.....45	W6WNN.....48	W9TKX.....47
W2BYM.....44	W6UXN.....47	W9KXF.....47
W2IDZ.....43	W6TMI.....45	W9HYW.....45
W2AMJ.....42	W6IWS.....41	W9JOL.....44
W2MEU.....42	W6OVK.....40	W9JHS.....43
W2FHL.....41		W9PKD.....43
W2GYV.....40	W7HEA.....47	W9MYG.....41
W2QVH.....38	W7ERA.....47	W9IPT.....41
W2ZUW.....35	W7BQX.....47	
	W7FDJ.....46	VE3ANY.....42
W3OJU.....45	W7DYD.....45	VE3AET.....35
W3NKM.....41	W7JRG.....44	VE1QZ.....32
W3MQU.....39	W7BOC.....42	VE1QY.....31
W3JVI.....38	W7JPA.....42	XEIGE.....19
W3RUE.....37	W7FIV.....41	
	W7CAM.....40	
W4FBH.....46	W7ACD.....40	
W4EQM.....44		
W4QN.....44	W8NSS.....46	
W4FWH.....42	W8NQD.....45	
W4CPZ.....42	W8UZ.....43	
W4FLW.....42	W8YLS.....41	
W4MS.....40	W8CMS.....41	
W4OXC.....40	W8RFW.....41	

Calls in bold-face are holders of special 50-Mc. WAS certificates listed in order of award numbers. Others are based on unverified reports.

and W4JL, Rome, Ga., a 265-mile hop to the southeast. During the summer Harry monitors the 50-Mc. band and makes calls at 7 to 7:30 A.M., 11 A.M. to 1 P.M., 5 to 5:30 P.M., and 9:30 to 10 P.M. regularly.

W0CFL, Los Angeles, wonders why it is that superregens for 420 Mc. and up exhibit such variable performance. He has one for 420 that works perfectly, while another that appears to be a duplicate seems to be almost useless. When you get the answer to that one, Tuck, let us know. We've wondered the same thing since our first experience back on 5 in the early '30s!

W8FKC, Hudson, Ohio, reports that activity on 2 in the Akron area is increasing steadily, with at least 6 Novice calls heard regularly. Around Cleveland there is interest in 220, with W8IY, North Olmstead, on 220.7 Mc. and W8JG, Cleveland, on 220.3. Ralph suggests a buzzer with a quarter-wave antenna as a noise source for receiver adjustments. He has been able to hear the buzzer on a superregenerative receiver for 420 Mc. He and others in the area would like to acquire some R80 ARN's glide-path receivers; condition not important, so long as the coaxial tank elements are in usable condition.

W9GSY, Selma, Ind., reports considerable increase in number of 2-meter stations. A net operates on 145.86 Mc. each Monday at 8 P.M.

A trouble frequently encountered with crystal-controlled converters is the leaking through of signals on the intermediate frequency. W9KQX, Springfield, Ill., solved this (Continued on page 110)



U. S. N. R.



Tennessee Tornado

A tornado struck Henderson, Tennessee, on the night of March 21-22, 1952. At the request of the ARRL Emergency Coordinator, W4GEH, the Naval Reserve Training Center at Jackson, Tennessee, furnished TCS radio equipment and a gas-driven generator for a radio station at the Henderson County High School. This station served the Red Cross headquarters and the Red Cross emergency hospital which had been established in the high school. A circuit was set up between the high school and the city's central emergency radio station. Operators from the Naval Reserve Training Center and from Naval Reserve Organized Surface Division 6-75 were assisted by W4STB.

Iowa Flood

During the recent flood in the Des Moines and Council Bluffs, Iowa, area, G. F. Binnall, RMNC, USNR, W3RRH/5, traveled approximately 500 miles from Eureka Springs, Arkansas, to assist in the flood emergency. Binnall arrived at the emergency control center at Council Bluffs, Iowa, on Tuesday, April 15, 1952, and brought with him Navy TCS equipment from Naval Reserve Organized Electronics Company 8-6 of Eureka Springs. A former resident of Iowa, W3RRH/5 was welcomed with outstretched arms.

Code Practice

The Naval Reserve master control station at Seattle, Washington, NPD, transmits on the following training schedule, Monday through Thursday of each week:

Pacific Standard Time	Speed
1900-2000	10 w.p.m.
2000-2030	14 w.p.m.
2030-2100	18 w.p.m.

All transmissions are made on 5295 kc. and 434 kc., keyed simultaneously.

Here and There . . .

Chief Radioman George A. Lewis, W5LNV, USNR, of the 8th Naval District Headquarters radio station NDF, has passed the examination for amateur Extra Class license.

Doris L. Nash, RMSN, USNR(W), a member of Organized Surface Division 8-88, Naval Reserve Training Center, Galveston, Texas, recently passed the FCC examination for an amateur license.

N. A. Partridge, W1BWR; Frederick Best, W1BIG; and Zina Corliss, W1RJD, are taking an active part in amateur and reserve activities at the Naval Reserve Training Center, Augusta, Maine.

Philip Roy Kennedy, W9AKP, and Richard M. Mays, W9AJY, are reservists located in the Indianapolis, Indiana, area.

J. R. Yost, W4DNE, is a member of the Charleston Naval Shipyard Radio Club, Charleston, S. C.

Charles P. Robart, jr., WN2EVL, of Pleasantville, N. J., is now in active service in the Navy.

Lt. Comdr. E. W. Zimmerman, USNR (W4DMP), is now assigned to duty with the Electronics Division of the Bureau of Ships, Washington, D. C.

Richard R. Kerns, ET3, USNR (W5OUZ), is now on active duty.

T. M. McGauley, PHG2, USNR, of the Naval Receiving Station, Washington, D. C., recently passed the FCC examination for a Novice Class amateur license. McGauley is an active member of the Hobby Shop Amateur Radio Club (W3SWN).

Recap—DX Contest High Claimed C.W. Scores

Last month's c.w. scores Preview for the 18th ARRL International DX Competition was incomplete through inadvertent omission of some of the high claimed tallies. We present below a more inclusive tabulation which will convey a clearer picture of claimed results. Apparently conditions weren't quite so bad as they were painted! Following are top W/VE totals (station, score, multipliers and contacts):

W5ENE	255,732	202	422	W1AXA	104,805	132	250
W8JIN	237,390	193	410	W3GRF	104,538	131	266
W3BES	228,984	188	406	W6TT	103,752	132	262
W3DHM	220,458	181	406	W6YRA	103,678	133	258
W2WZ	205,740	180	381	W1BFT	98,010	121	270
W4KFC	196,116	177	371	W3IYE	96,384	128	251
W8WZ	194,840	180	361	W3KT	94,815	129	245
W3JTC	186,732	171	364	W6FSJ	93,000	124	250
W3LTU	184,212	172	357	VE4RO	92,400	110	282
W4BPD	174,104	164	362	W6AIW	90,678	119	254
W6AM	167,562	174	321	W8DX	90,506	118	256
W9LM	162,771	161	337	VE2WW	88,293	119	249
W8BTI	158,110	155	340	W9DUY	87,750	117	250
W4ESK	156,006	162	321	W4HQN	87,462	129	226
W4BGO	155,925	165	315	W3BYN	86,346	123	234
W6MVQ	150,174	162	310	W8DUS	86,204	124	232
W4BRB	142,749	153	311	W6PYH	85,668	118	242
W4CEN	138,600	150	315	W6WB	85,233	119	239
W3BXE	136,335	149	305	W4ACE	84,870	115	246
W3PDX	134,505	147	305	W2GGL	81,720	120	227
W6NIG	134,505	147	305	W6EPZ	81,396	119	228
W5ZD	127,458	146	291	VE3ZW	80,678	107	252
W1LOP	123,954	146	283	W1TX	74,015	113	219
W3GHS	120,555	141	285	W6PB	73,776	116	212
W6LDJ	119,328	132	302	W4NNH	69,960	106	220
W5CKY	118,854	142	279	W7HXG	69,642	106	219
W1NMP	114,840	132	297	W4KE	69,264	104	237
W0DAE	110,970	135	274	W6RBQ	68,970	110	209
W3FQZ	109,692	132	277	W8CVU	68,364	108	211

High claimed scores outside W/VE:

KV4AA	541,890	90	2015	ZL1MQ	76,200	50	508
KG4AF	518,833	83	2085	DL4EF	71,706	37	651
KH6IJ	331,918	78	1427	ON4QF	69,042	37	622
KH6AEX	275,724	74	1242	G5RI	65,286	39	558
KH6MG	260,570	71	1228	ZE3JP	61,920	43	518
VP7NM	190,038	57	1114	KH6FX	59,643	47	427
CO2BC	177,954	57	1043	KH6ER	57,684	46	418
KP4KD	169,443	67	843	ZK2AA	57,290	40	481
XE2OK	131,372	56	789	VP9AL	54,694	41	452
KH6PM	124,551	63	659	OQ5RA	51,356	37	467
KH6DK	110,925	51	725	KP4OD	45,072	36	414
CN8EX	100,758	42	805	E1SC	43,224	24	637
KP4JE	80,370	57	470	VP9OO	35,800	25	478

Other non-W/VE scores over 15,000: KL7WC 33,390, FA9RZ 32,085, GC4LI 31,724, VR2CG 30,293, OZ1W 28,196, DL1DX 28,179, CE4AD 28,117, FF8AG 26,340, OZ4KX 24,544, KL7NXI 23,600, KL7ANJ/KL7 22,968, DL2RO 22,794, HC2OS 20,631, G6GN 18,262, PA0KW 16,874, CT1AL 16,692, OH6NR 16,200, PA0VB 15,900, VK3AHH 15,892, OZ7BG 15,387.

All claimed scores will be subject to checking prior to the announcement of final results.

SWITCH TO SAFETY!



How's DX?

CONDUCTED BY ROD NEWKIRK, * W1VMW (Ex-W9BRD)

How:

Last month we sorta waxed neuralgic and sedimental about DX doings of yore and present. Jeeves thought it proper this month to wrap on his turban, haul out his xtal ball and give us a peep at a page of "How's DX?" circa 1975. We don't know who's conducting it, but a few paragraphs look interesting. Let's peek over our Swami's shoulder. . . .

... W8SAI, HB9AW and ON4QF are off to Neptune with radio gear. . . . QSLs are rumored coming through from F8IHH and FM8AD. . . . W1FH now has racked up double-TVDXCC. . . . W1VMW has almost licked his TVI. . . . XF1A and KV4AA converted their W/VE QSL files to microfilm after their shack floors buckled. . . . W1DX needs Jupiter for s.s.b. WAP. . . . μ 80 is the new prefix for Arcturus. . . .

Then the darned thing QSBd. Jeeves wiggled the knobs frantically and DX column paragraphs for a 2002 QST momentarily came into view:

... W8SAI and HB9AW sent ON4QF back for another 807. . . . QSLs are rumored coming through from F8IHH and FM8AD. . . . W1FH reached the Color-TVDXCC 800-mark. . . . W1VMW has almost licked his TVI. . . . XF1A and KV4AA bought more land for their QSL files. . . . W1DX's Jupiter QSL was bounced by W1RWS; Jupiterian ink disappears in our atmosphere. . . . W4GVU is now μ 80GVU. . . .

PING-G-G! Excessive crystal current fractured the quartz sphere. Too bad — there was an interesting article in that issue by W1TS on spacecraft mobile rigs and another on synthesized ionospheres by Larson E. Rapp, jr., WN1OU.

What:

Short skip makes twenty sound a little more lively these warm days and the night shift is once again getting in some DX ticks. EA9DC, for instance, was doing business with W/VEs almost around the clock, 'phone and c.w., dishing out first Ifni QSOs to a multitude. . . . Another lulu with quite an entourage, ZC2MAC put Cocos Islands QSOs within reach of many while working mainly the low end of 20, c.w. . . . ZS8D (14.020) has a new 75-watter on the air and tells W7PVZ he looks for Ws in the African mornings and evenings. . . . Continuing on the c.w. subject, WN4TVQ became W4TVQ and lost no time in hitting 20; OE13RN, PY3QX and some Europeans were worked first day. . . . VE3RXY made away with OX3s BI (020), UD (100), VP's 6CDI (090), 9HH (050) and CX4CZ (020). . . . Another ex-WN, W2INE knocked off some fast countries on 14 Mc., including OE13HP and KT1OC. . . . W9NN made the grade for WACE and added MI3US, VESRG, EL2A and ZE4JT to boot. . . . ZB2I (097) answered Chas at W1AW and W2EY ran into KV4BA (086). . . . W4REZ reports QSLs already on hand from VP1AA, YS1EM, VPTNM, YN4CB, F08AC, 954AX (010) and KW6AR. . . . KZ5WZ raised ZC2MAC (020) who said he'd be in those islands for some three months. This juicy one runs 35 watts to a long-wire radiator. Wally adds KC6DX on Truk (080), 120 watts and a long wire. . . . School work has been hampering W0AHH's

DXing but Paul managed HZ1MY (006), KW6BB (042), VR2AS (072), VS6CK (065), VU2EJ (032), VK9DB (065), YU3AT (030) and EA9DC. . . . DL4JZ (W2FRE) worked 56 countries out of 85 heard in his first month in Germany. The latest include CE1DC, CX1BZ, EA8BK, FA9IO, FF8AG, FQ8AP, GD2FRV, IS1EHM, KG6ACY, MI3LK, MP4BBD, OD5AM, OQ5PE (050), SU5EB (070), SV0WW, TA2EFA, VU2JV (025), VSs 1CZ, 6CG (050), VQs 3BM (060), YU1CX (070), ZBs 1BL, 2A (100), ZCs 2MAC, 4RX, 6UNJ, ZD6DU, ZS3K, 4X4BN (065) and 5A2TP. . . . HE9LAA (035), HC8GJ, ZK2AA (160) and FD8AB (027) look good in W5KUF's log. Charlie's latest QSLs include those of ZD6DU, Y13BZL, ST2GL and EA0AB. . . . KX6AO speaks of a 24-hour ragchew roundtable with VQ4BU, VQ4CO and OQ5BR — that's the life. . . . W5KUC's West Gulf DX Club DX Bulletin pins down this c.w. activity: A.M. — C3MC (036), DU1s GB (100), MB (090), EA9YY (042), FK8AI (069), F08s AB (082), AG (150), GD3UB (042), KR0s AI (074), HX (060), IG (038), KX0AH (078), KW6AZ (080), OQ5RA (008), OE13USA (060), SU1BN (015), VKs 1RG (049-072), 9BI (095), 9GW (037), 9XK (112), VP3VN (018), VQs 4BY (030), 4CM (025), 8CB (018), VSs 1BN (056), 1ER (040), 2CY (065), 7GQ (005), 7NG (103), ZP5AY (070); P.M. — CU3YY (1) (052), DU1s 1AL (085), 9VL (080), EAs 9BF (095), 9AC (075), EL2R (070), FF8s AE (048), AJ (100), F08AF (040), FK8s AB (069), AE (046), FKS8BC (028), F08s AF (050), AG (010 t6), HC2OM (090), KS6AA (045), W7L-DY/KS6 (135), LBs 6XD (021) on Jan Mayen, 9Q (082), LZ1KAB (032), MI3ZX (063), OA4EK (055), OK3AOS (048), TF3MB (047), TG9LC (018), VP6s 2GH (083) in the Windwards, 3TY (023), VQ2s GW (060), HC (061), VR1A (074), VS1CO (070), YUs 1AD (035), 1AS (034), 2AK (070), YV5AK, ZC4XP (050), ZDs ISS (007 t9c), 2HAH (070), 9AA (032), ZS3HX (070), 5A2s TL (072) and TS (030).

On twenty 'phone, XE1AC pounced on EA9DC like DDT on a taterbug. Al added KB6AO (14.257), VQ4BU (167), ZK2AA (308) and EA8AC (123). . . . YA3TU (095), LZ1KSR (200), M1B (160), ISUF (230) and 4U4J (200) helped fatten G4ZU's roster. . . . ZP4s AF (175) and BB (195) are highly recommended by W0AHH. . . . School restricts W4REZ to week-end DXing but he did well with FG7XA, HRs 1KS, 2JM, YN1WC and HI6EC



* DX Editor, QST.



Jimmy Taylor, GM2DBX, has accomplished 'phone DXCC with this layout in Fife. GM2DBX is a pharmacist by trade.

..... W4GXB reports W5SGH/FKS raising havoc for a week or so. He and W5MPG were among the early birds to catch EA9DC on voice..... The DX Bulletin and W5KUC/UCQ account for the A3 activities of CS3AC (310), DUs 1AL (201), 1J1 (147), 1VVS (182), 7SV (238), 9VL (153), EAs 8BC (120), 9AR (305), FQ8AK (100), GD3s GBC (315), UB (220), HC8MM (120-398), H16TC (280), HH3L (140), HZ1MY (155), W0EGY/KJ6 (272), W6HKH/KM6 (230), KM6AY (250), KG6DX (210), KW6s BD (230), CB (250), MI3DW (324), MP4KAC (180), ODSAB (300), SP9KAA (110), ST2GL (250), TAs 2EFA (170), 3AA (315), VK9DB (150), VR2CG (312), VR1s A (065), B (130), VSS 1AJ (257), IDS (128), IES (304), IAX (337), 2BS (170), 2CY (130), 6BA (145), 7FG (147), VU2s ARCI (155), ET (324), XZ2s KN (307), SS (270), ST (302), YU3AC (190), ZK1BC (308), ZE3JY (275), ZS2MI (137), 3V8BB (318) in the a.m.; CNs 2AD (337), 8EI (304), 8FF (337), 8GD (320), CRs 4AC (175), 9AH, CFIAM (155), DU6IV (152), EAs 8AP (342), 8AZ (175), 9AA (308), EL9A (345), FB8BE (100), FF8CB (350), FQ8AI (135), H18WF (200), HK1DZ (310), IT1s BNH (203), BXX (187), KV4BB (295), MF2AA (320), MI3s RC (310), RR (192), US (070), ODSAC (320), OE13s SC (285), USA (313), OQ5s CF (105), PE (045), VP (215), WW (145), TF3SG (150), VK9YT (330), VPs 2GX (165), ZLE (335), 3LF (170), VQs 2DC (145), 3CH (335), 3CP (135), 4AA (160), 4AC (100), 4AQ (180), 4BU (167), 4CO (135), 5AU (156), 5BVF (100), 5DO (120), 8CB (319), VR2AP (170), YI3BZL (330), YU3AC (190), ZB1GKU (177), ZC6UNJ (305), ZPs 2BB (125), 2DD (105), 4AK (125), 5A2TO (323) in the evenings. Note how the VU2s have slipped out of the picture this month.

We find that Uruguay's amateurs have had fifteen available since 1949. Australian hams can now use the band and overseas U. S. military personnel may be in positions to add more countries to 21-Mc. activity. MI3s and 5A2s are among this group and are especially on the lookout for Ws. KZ5WZ says W6AM is the loudest 15-meter signal down his way. Wally has been looking stuff like KG6QY, CE3AX, VP6CDI, CM9AA, KV1AA, HPIAW, VK4s HR, SN, ZB, PYs 1ADA, 2HT and KI6YL. Europeans were active but their chief path was to South America.

Forty is still worth a try. OY2Z (7005) told W3RFA theirs was the first W-OY 7-Mc. contact. OY2Z uses 30 watts, a dipole and a 4-tube superhet. Chas. of W1AW hopped on VP8AJ (015) and W2EYF raised KG6FAA (023) who is plenty fast with a pasteboard. G3IAD and PA0ERC were W2LSJ's first DX QSOs. W2N1Y collected HZ1MY (025) and heard ODSAB (025) who is ex-ARRAB. YU1s 1AND, ICX, HKs 1GE, 4DP, 5CR, KG4AO, CT3AB, YSIO, ZS8P and sundry PYs were

gathered by W9ESQ. Lou had to work nine HHs on 40 before one (HH2CL) came through with a QSL. W5YGR has no better luck with HH cards although ELs 2R and 7A came through promptly. Jack garnered VP2SC (090) in the Windwards. VP5BH (001) in the Caymans, YV6AO (072) who likes to switch to 'phone, VP6FM (001) and TI2PZ were buttonholed by W4REZ.

Alaskan Novice WL7AOC's 70-watter raised ZLIADU (3710) for some unusual work on eighty. WN4USQ worked VP7NT (3750) c.w.-to-'phone and states that the DX bug really has him cornered. Six W116s have been worked at WL7AOC. These Novices are really beginning to get around on 80! W4REZ found 'phones HR1BG (3792) and VP5BP available on seventy-five.

A 2E24 at 28 watts does well for W6NZX on ten 'phone. Bob mailed KX6AO, KJ6AR, HP1HO, HC1KV, ZL2CC, PJ5ZO, CX7BA, ZSe 1JZ, 6DW, VP6CJ and VK4HD. A 3-element close-spaced beam was probably responsible. KZ5WZ scared up VP2GX (ex-VP2AC) on voice while a c.w. QZ surprised W4REZ by raising PJ5NH.

Nothing much cooking on one-sixty this time of year but the dust is still settling after last season's efforts. W1BB reports that W1LYV has received SWL cards from Czechoslovakia and Russia. The OK listener's report concerned '52 activity while the U.S.S.R. card pertained to January, 1951, operation.

Where:

W0YXO desires it emphasized that he does not handle QSL matters for ZK2AA. We printed info to the contrary over a year ago and Ken still gets requests for QSP. So far as we know, the Call Book address for ZK2AA is perfectly okay. Bear in mind the 4X4 QSL bureau has instructions that all ZC6 operation is illegal and therefore will not handle cards for stations bearing that prefix.

CN8FF	Sgt. L. W. Geldner, Hq. 5th Air Div., Box 11, APO 118, % Postmaster, New York, N. Y.
DL4JZ	PFC R. Friederich, 97th Sig. Ogn. Bn. Radio Co., APO 46, % Postmaster, New York, N. Y.
EA9DC	(QSL to EA8AW)
EL2A	Ed Yarborough, Firestone Plantations Co., Harbel, Liberia
FB8BE	Box 86, Tamatave, Madagascar
FB8ZJ	(QSL via FB8S or F9LQ)
FF8AJ	Yves Bijault, Box 230, Bamako, F. W. A.
ex-JA2DK	M/Sgt. Don E. Kitchen, AF-6780509, 71 Clarke Ave., Langley Air Force Base, Va.
KS6AA	Art R. Fillebrown, Pago Pago, American Samoa
ex-KZ5GT	Gordon T. Henderson, KL7AOS, Shuyak Island, % CAA, Kodiak, Alaska
MI3RR	R. Reimund, Field Stn. 8604-AAJ, APO 843, % Postmaster, New York, N. Y.



In the patio adjacent to PY2CK's shack are Mrs. W1ZD; John M. Wells, W1ZD; Capt. Fowler, a companion; PY2CK; and Mrs. PY2CK. The W1ZDs were visiting in Brazil and decided to pay a visit to one of the world's ace 'phone DXers.

OA4V	Inter-American Geodetic Survey, % U. S. Embassy, Lima, Peru
OD5AJ	Elias M. Raffoul, P. O. Box 352, Tripoli, Lebanon
OY2Z	Johan Ziska, Box 71, Torshavn, Faeroes Islands
SV0WW	Skip Gross, USASG, APO 206, % Postmaster, New York, N. Y.
ex-VE8RY	John W. Smith, VE3DCQ, Box 538, Wingham, Ontario, Canada
VP2MD	Cyril Volney, Monserrat, Leeward Islands, B.W.I.
V87RSC	Radio Society of Ceylon, Box 907, Colombo, Ceylon
W2AOS/KG6	ex-W3ENK (QSL via W3KT)
YA3UU	(QSL via R8GB)
ZC2MAC	(QSL via R8GB)
ZC6UNJ	UN Mil. Obs. Gp., APO 206-B, % Postmaster, New York, N. Y.
ZD4BF	J. R. S. Innes, Box 7, Takoradi, Gold Coast
ZE5JA	C. Jordaan, P. O. Box 17, Bindura, Southern Rhodesia
Z83U	W. V. Helasingen, P. O. Box 49, Gobabis, South West Africa
3A2AM	Marcel Ardissou, 28 rue Grimaldi, Principauté de Monaco
4UD	UN Radio, Jammu, Kashmir, India
5A2TV	Box 66, Tripoli, Tripolitania, Libya

W1s FTX IKE ODW RWS, W2s TXB ZQW, W3RFA, W5s EGK KUJ, W8SYC, W9CFT, W9AII, OVSV's OEM and USKA's *Old Man* take credit for our roster this issue.

Tidbits:

ZC6UNJ is located in a "No Man's Land" between Israeli and Jordanian outposts. Operator W5LLQ has at his disposal a Temco-600 rig running 150 watts, an NC-340D receiver and folded dipoles. He reports regular reception of U. S. mobiles on 20' phone. VE3CJ, taking another crack at an ARRL DX Test as VP5BP in the Caymans, was assisted ably by VE3HC. A 1-kw. generator powered a 32V2-75A1 combination which managed a total of 924 contacts with 775 stations; 731 QSOs were on 20 meters, 116 on 10 and 77 on 75—all QSOs 'phone. VE3DGG was the only station worked on all three bands. VP5e EM and FR provided the Ontario boys unlimited hospitality in traditional ham fashion. Notes re Lebanon, courtesy W1IKE: Their government has informed ITU that amateur operation is now recognized as legal; however, proper notification must go through appropriate channels before Ws are permitted to resume communication with Lebanese stations. By the way, amateurs in Lebanon now use the OD5 label in lieu of AR8. Exams there are held twice yearly and license fees are approximately thirteen bucks. Operation on 14, 21, 28, 144 and 420 Mc. is permitted. Setting up of a QSL bureau is pending upon the formation of a responsible national radio society. W3PYH and KV4BB are separately contemplating possible rare-DX operating excursions. Some of the DL gang, nationals and DLAs alike, have formed an amateur radio club which looks forward to close cooperation with IARU, ARRL and DARC. DL4GI was elected president, DL3DC vice-president and DL4EA secretary. An excellent spirit of cooperation between American and German amateurs is evident. W3ENK closed down his station at Silver Spring, Md., on January 31st and since April 9th has been active as W3ENK/KG6 with 75 watts on 14 and 7 Mc., c.w. He intends to add 10- and 20-meter 'phone to his repertoire and assures 100-percent QSL. Charles has also held the calls W2AOS and KZ5CB. "Haven't missed [sending] a QSL in 32 years!" W4BRB offered to hire Jeeves if, in addition to his regular duties, he'd keep an eye on W2QHH and fill in at center field on Gene's ball team. [How about my playing fourth base, Boss? I'm always catching it, anyway. — Jeeves]. QSLs for 984AX mailed to W1NWO



The entire ham population of the Caymans is gathered here. From the left: D. Tibbetts, VP5BD; H. M. Coe, VP5BE; Noel B. Eaton, VP5BP (VE3CJ); and A. H. Hanlan, VP5BH. This Cayman quartet assembled during VE3CJ's operational excursion to the islands for the '52 ARRL DX Test.

will be acknowledged but the 984 does not verify QSOs unless and until cards are received. 984AX finds this policy expedient in view of the fact that his W QSOs now number into the thousands. ON4NC, who still needs Nevada for WAS, would like to know of a way to procure ET3AF, VO2G, VO4L, EQ1RX, EQ2L, VQ8WU and W4FV1/KX6 QSLs, these stations worked in the period '46 through '49. From KH6WW we hear that KC6QY (ex-KH6QY and KH6QY/KC6) is putting together a 1000-watt for operation on 80, 40 and 20 meters. On 40 he uses a ground-plane skyhook built around a big bamboo pole. KH6AFS amazes locals with a QRP pipeline into Europe on 7 Mc. Invisible rhombics? Ex-W2MVP is now K2CW, a fact we couldn't seem to get straight in a recent column. Three guys currently on Macquarie Island are VK1RG (VK5RG), VK1EM and VK1RR. Ex-VK1BS is now VK2EG and says he has received but 128 QSLs from over 400 Ws worked at VK1BS. Bill worked 40 United States and 75 countries and will round out his QSLing 100 per cent. He writes further, "I would advise anyone contacting a VK1 amateur to send the card to the bureau or to a QTH given by the station. Do not send them to the island if . . . not sure as to the mail facilities or mail closing dates. . . . Reception is very poor on both islands owing to the high absorption down there." W6NMC is to journey around the world on a freighter and will take along a rig and receiver for possible work on all bands 80 through 10 meters. W6AM says he may get a shot at CR8, FN8 and FL8 operation. Along with a big batch of eagerly waited QSLs, ZM6AK sends word that he's about to fire up his prewar rig at ZL1FT. "Don't think there will be much, if any, ZM6 activity now as ZM6AA and I were the only ones who took QSL seriously." HE9RDX, DX editor of USKA's *Old Man*, writes that all cards received for 3A2AD operation have now been answered. His records indicate that over 400 stations worked did not bother to QSL—the demand for 3A2 must be in good part satisfied! Etienne would like to take a fling at HV work but the possibility at present seems remote. "ON4QB told me all about his [new] projected expedition, but I swore not to tell," writes Bob Schoening. A plague on all Ws ending

(Continued on page 188)



It looks as though a big wave could sweep KW6AR's shack right off Wake Island into the Pacific. Ivan has one of the biggest signals to come out of this part of Oceania.



Hints and Kinks

For the Experimenter



SIMPLE CODE-PRACTICE AID

THE gadget shown in Fig. 1 is a simple means for using any receiver equipped with a b.f.o. as a code-practice "oscillator." Simply plug P_1 into the 'phone jack on the receiver, a key into J_2 , and the 'phones into J_1 . Close the key and tune in a steady signal, such as WWV or the carrier of a broadcast station. Open the key and the 'phones go dead, close it and the signal comes through again. From here on, use the unit as you would any oscillator.




Fig. 1—Here's the way one Novice solved the problem of obtaining a code-practice oscillator. J_1 and J_2 are open-circuit 'phone jacks, and P_1 and P_2 are ordinary 'phone plugs.

The two jacks and the plug are mounted on a small bracket made of sheet aluminum. The two jacks must be insulated from the bracket. The entire gadget cost me only 95 cents, and was well worth the time it takes to build. —George B. Jeffrey, WN9OXH

CONVENIENT ENTRY "BUSHING" FOR TWIN-LEAD

A ONE-INCH diameter cork can be used to make a weather-tight bushing for the hole through which Twin-Lead enters the shack. Cut a slot deep enough to permit the Twin-Lead to be sandwiched in the cork. Then drill a hole a little smaller than the diameter of the cork. Push the cork in the hole, and it will squeeze the Twin-Lead tightly, holding it securely in place. At the same time the cork successfully plugs the "leak" in your window or wall to keep out the weather. —K. F. Triggs

ANOTHER CRYSTAL-GROUNDING HINT

PREVIOUS attempts to change the frequency of a crystal frequently resulted in diminished activity or complete failure to oscillate. The probable cause was that the grinding surface was not perfectly flat. Much of the so-called plate glass does not have a truly flat surface. As an excellent substitute the good old-fashioned razor hone was pressed into service, and since then results have been far better.

When rapid cutting is desired, grinding compound may be used with water in the usual manner. Putting the grinding compound in an old

salt shaker and using a medicine dropper to add water when needed cuts down on the messiness of the operation. For finishing, the hone is used alone with plain water for slower cutting.

The hone used here is of the hard-surfaced type, and measures 3 by 5½ inches. Figure eight strokes utilizing as much of the surface as possible were used. Approximately 500 such strokes moved an 80-meter crystal about 125 kc., depending on the pressure exerted. It is wise, of course, to check results frequently so that you don't overshoot your goal. —Harry H. Heinrich, W9KPG

SAFETY INTERLOCK FOR CABINET RACKS

THE sketch shown in Fig. 2 is a simple, inexpensive method of making it impossible (or at least difficult) to open a cabinet rack without killing the power first. Terminate all transmitter a.c. supply leads at a male chassis connector in the side of the rack near the back, as shown.




Fig. 2—Here's an inexpensive interlock system devised by W2PFJ.

Feed this connector with a convenient length of heavy rubber-covered cord clamped across the door, with a female connector on the end of the cord. Leave only enough excess cord here to make the connection when the door is closed. The rest of the cord should be clamped down the hinged corner of the cabinet, leaving a small loop at the turn so that the door can be operated without undue flexing of the cable. It will then be impossible to open the door without first unplugging the power cord. —R. M. Girdler, W2PFJ



Correspondence From Members-

The Publishers of *QST* assume no responsibility for statements made herein by correspondents.

MOBILE

822 West 22 St.
Kearney, Nebr.

Editor, *QST*:

Mobile operation is increasing by leaps and bounds. Pending specific legislation, why don't all of us become "mobile helpers" by not ruthlessly invading, with our fixed stations of much higher power, those frequencies near the band edges of our "phone bands. If we allowed 10 kc. for mobiles at each end of the 75- and 20-meter bands it would serve two purposes. First, hundreds of mobile operators would be perfectly happy. Second, FCC notices for out-of-band operation by fixed stations would be a rarity.

— Glen H. Byars, W0BNF

TVI AND PUBLIC RELATIONS

241-02 86th Road
Bellerose 6, N. Y.

Editor, *QST*:

... Your timing in contacting the various manufacturers while the TVI groups all over the country were working on the problem was perfect.

What greater reward can the amateur who is making an honest effort to cooperate receive than to hear his neighbor say "Well done." And when it comes from one who may have been a little reluctant at first to accept your explanation, it is music to the heart; it makes all the disappointing cases seem worth while.

There are other rewards to be gained in this effort to bring about friendlier relations between the amateur and his neighbor. By getting together and discussing the problem in a sensible manner, we find that they are real people after all — interested in their home, their family and much the same things that we too are interested in. We may never have met them even though they were just around the corner if it were not for TVI. Had we elected to brush him off with some curt technical explanation he would still be our neighbor, but no longer a friendly one. Ours would have been the loss.

In working with the manufacturer, the amateur has much to learn also. We have found them to be most cooperative when approached with a sound business proposition that concerns the future growth of their organization as well as good public relations. Many pleasant associations have been made and a wealth of knowledge gained by cultivating the friendship of the field forces sent out to investigate reported cases.

I would like to recommend to all amateurs that they adopt the FCC plan for elimination of TVI and that they first analyze the problem from the TV owner's point of view and then go to work keeping that view ever before them.

— Russell S. Miller, W2DIC
Secy., TVI Organization
of New York

RAPPORT

42 Parkwood Dr.
E. Syracuse, N. Y.

Editor, *QST*:

In reference to Larson E. Rapp's perspicuous article in April *QST*, I would like to offer several suggestions toward improvement of the over-all system.

In recent experiments I made numerous changes in the transmitter design but any improvement over the original was to no avail. Mr. Rapp, bless his soul, has touched greatness. I seriously doubt if anyone will overshadow his basic circuits.

As to the suggestions: The receiver adapter circuit is of sound design but I did make minor changes in components. It is not necessary to use a linear taper control for R_5 —

much better performance will be obtained if a fixed gaffer is installed here. The center smolk should be grounded. As for the roans, let it float! Much greater sensitivity and improved limiting action can be obtained by using the new improved 1Z2Z in place of the present used 1N2N. There is a 1C2C on the market at a higher price but the difference in performance does not merit the added cost. If it's a choice between the 1Z2Z and the 1C2C I would pick the 1Z2Z every time over the 1C2C. Why? Gentlemen, it's easier to pronounce!

— John F. Cleary, W0VSP

HOW TO BECOME . . .

226 Clifton Avenue
Staten Island 5, N. Y.

Editor, *QST*:

Every now and then you'll read an advertisement in *QST* of a fellow requesting aid from experienced amateurs to help him with theory and the code. Also, during the past six months since I became a ham operator, I have met several persons who desired to be amateurs but gave up because, as they told me, they couldn't get anyone to assist them. Brother, let me tell you something; you don't need any help if you really want to join this great hobby.

I am a middle-aged man with a family and, until a little over a year ago, all I knew about radio was to turn on and off a broadcast receiver. To show you my ignorance of electronics, the first time I looked inside of a receiver I wondered why they used prongs on a tube instead of screwing it in place like a light bulb.

Today I hold both the Novice and Technician tickets and a first-class commercial "phone ticket. The first day of my vacation I'll be at the FCC office to take the test for the General Class ticket. I feel confident of passing the test because more than a month ago I received my 15-w.p.m. endorsement sticker from the ARRL.

Here is how to do it. Read the *Handbook* over and over again until you fully understand it. Read it every chance you have, while eating your lunch and riding to work. I must have read each chapter in the *Handbook* at least a dozen times. The code I must admit was tough for a while. I did get some assistance there from WIAW each night at 9:30 EST but you can get that too. Copy, copy, and copy everything you hear over the air but never more than for an hour at a time. It took me six months because my skull is a little thick in places but you may do it in half the time. No sir; you don't need help from a licensed amateur if you really wish to become a ham operator and join the greatest gang in the world. I did it and so can you. By the way, I wonder what this u.h.f. is all about.

— Frederick H. Scheuter, W21PA

MOTORCYCLE RIGS NEEDED

811 S. Union Ave.
Los Angeles, Calif.

Editor, *QST*:

Civil defense seems to be a popular subject nowadays. Yet the ARRL, which should know better, seems to have neglected publicizing the most important mobile asset of civil defense units — radio-equipped motorcycles.

Motorcycles can navigate rough, rugged mountain country, can cross streams, get over bare slivers of ruined bridges, and go 70 miles on a gallon of gas. Long after autos have been arrested by bogged roads, the cycles will continue to travel, to observe and inform.

How in the world did such a valuable piece of gear get pushed into the background?

Yet, motorcycle radio has problems peculiar to itself which should be discussed in the pages of *QST*. Let's get hot on it!

— Lee Lamasus, W8JQP
(Continued on page 130)



Operating News



F. E. HANDY, WIBDI, Communications Mgr.
JOHN E. CANN, WIRWS, Asst. Comm. Mgr., C.W.
GEORGE HART, WINJM, Natl. Emerg. Coordinator

J. A. MOSKEY, WJMY, Deputy Comm. Mgr.
L. G. McCOY, WICP, Asst. Comm. Mgr., Phone
LILLIAN M. SALTER, Administrative Aide

Loose Talk and Security. Though some contacts are crosstown, it is well to remember that signals on some frequencies go many thousands of miles when conditions are favorable. Propriety rightly keeps many of our intimate, personal, club, and argumentative matters off the air and in the club and organization meetings where they properly belong. Our amateur sense of responsibility similarly is more important than specific rules of what can and cannot be said. From the national security standpoint, whether key or mike is used, it is important that amateurs avoid discussing any matters that might provide missing information in the picture puzzle which the intelligence services of unfriendly nations are continually working over, to ascertain the state of our national morale, and the state of civilian and military defense preparedness. FCC and ARRL place high reliance in your discretion and cooperation in such matters. Let there be no loose talk. Keeping on the subject of *our own radio technique* is a safe course. The following seven Operating Precautions reprinted from an earlier *QST* may serve as a rough guide when operating:

- 1) Sign each transmission with your assigned call.
- 2) Do not permit unlicensed operators to use equipment.
- 3) Contact no unlicensed stations.
- 4) Follow each FCC regulation with scrupulous care.
- 5) Do not discuss any happenings that might have military intelligence or political significance.
- 6) Limit on-the-air discussions to radio technique and personal matters.
- 7) Watch for any possible signs of radio activity that do not belong in our bands, strange or subversive or suspicious. Report all such to the Field Engineering and Monitoring Division of the FCC without delay for any necessary study or investigation.

Note that last point especially. We must spare no efforts to keep our amateur radio *clean*. Perhaps you read with some pride those recent *Satevepost* articles covering FCC monitoring of radio as illegally employed by gambling and race-track enterprises, and where amateur know-how was the helpful key to the tip off and successful execution of duty by FCC officers. FCC is cultivating the reputation monitoringwise of always getting it man! It has the tools to work with and law on its side. Should any amateur operator, through approach or tuning the different frequencies run across the track of bookies, gamblers or racketeers generally, and especially those subversive possibilities named in point seven, report the facts appropriately and quietly to the FBI or FCC for instructions, or investigation by them as case may seem to warrant.

On Informative CQs. W6LDJ writes to suggest more use of additional types of informative CQs. Let us record his ideas and ask all of you who feel a need in these directions to give them a try.

Call	To Indicate
CQ RC	Station calling desires ragchew; answer only if so inclined.
CQ T	Station calling desires to test or experiment. Do not want to ragchew. Answer only if so inclined.
CQ QRK	Station calling desires a series of QRK reports at various points; answer only if you don't object to short quick signal report exchanges.

"The above is now sometimes accomplished in amateur 'phone work by calling 'CQ for a short check' which may indicate the need for such procedures. Example, one finishes a portable rig wants some checks on the keying or signal strength at a few points — not a long harangue about the weather, handle, etc., which a simple CQ call might bring. Nothing against ragchewing, of course, great in its place when both parties are agreeable."

A Nine-Point Self-Rating System. There's always high interest in self-rating systems. One applicable to the division of operator activity in *amateur radio* will be something for you to try on at the same time we add 'em up! This list was devised by the St. Paul Radio Club and published in its bulletin the *Ground Wave* to help the SPRC members, then putting the new call letter plates on their cars, to devise ready answers about the why of their license plates, against those who will allege political privilege. The *Ground Wave's* suggestion is applicable to each and every amateur. This is that all amateurs run through a nine-point consideration of how we stand in justifying our amateur authorizations, at the same time we enjoy our hobby. The SPRC credits toward a possible 100%: (1) home stations in operating condition, 30%; (2) mobile operation, 20%; (3) emergency-portable equipment, 20%; 5% each for (4) amateur Radio Emergency Corps membership, (5) emergency power supplies, (6) traffic handling and nets, (7) cooperation with civil defense, (8) cooperation with Red Cross, (9) active club training program.

If one's score is less than 70% we suggest the list be used as a start on widening amateur activities during the coming year. Amateurs with whom we have discussed the list would emphasize that it isn't just *having equipment* so much that makes for communications performance, as it is the actual *active participation* in nets and AREC.

On Using Break-In. Break-in should be a "good operating habit." If using 'phone we may want to call it "push to talk." Whether for 'phone or c.w. every constructor should consider building the capabilities for full break-in into his station. The traffic man is most often accustomed to using break-in as part of his standard high-grade procedure. W9LQE finds that the rag-chewer could profitably use the same technique to make more pleasant and effective QSOs possible and he writes to that effect.

The operating technique of using break-in is simple. In traffic handling, we break by sending BK, or a series of dashes or a series of dits. When the station being broken stops sending, we know he has heard us breaking, and that we can go ahead with the last word received correctly. C.w. break-in, if working properly, can be used exactly like talking on a telephone, where one person can interrupt the other at will. W9LQE suggests the operator *being broken* acknowledge with a "BK," pausing to receive any advice on receiving conditions or rate of speed, since adverse conditions may make new instructions to the transmitting operator, by the receiving operator, necessary.

Frequency Observance Important. In recent months reports from several ARRL Official Observers have indicated a possible ignorance or disregard for frequency band limits! The 20-meter 'phone is mentioned most often in observer reports in that connection. Confirming checks made from W1AW disclosed some W-stations with carriers 5 to 35 kc. beyond the 14.2 and 14.3-Mc. points, for example. Of course we amateurs should constantly remember that the individual reputation as well as that of the fraternity for clean operating depends on *close adherence to frequency authorizations*. FCC monitoring stations are on the job enforcing the rules.

Drifting v.f.o. trouble, some lack of appreciation of the problem may be mixed in with some intentional disregard for the sub-band edge. W0TKX offers some thoughts about the recent dubious frequency observance:

Violators range from fellows who zero beat *everyone* they call from force of habit to hard-shelled oldtimers risking a pink ticket to get through the QRM. A W5 was heard remarking toward the end of a round-table with VEs, "Well, I had better not hold it too long, since I am outside the band here."! Some 10-meter hams suddenly presented with Advanced Class licenses find the 14-Mc. band too restricted for their "loose" VFOs? Perhaps those "tolerance" questions in the Advanced examination were just figures and formulae to be memorized without conveying a meaning, or too quickly forgotten? An amateur *mobile* heard on 14.193 was working with a fixed amateur station on this frequency. The latter must have set his frequency without looking at either transmitter or receiver dials. A W2 was logged two days in succession just outside the high end chatting with South African stations. . . .

Quite a few amateurs may be right on the verge of being caught up with the inevitable FCC Monitoring Notice! With all that has appeared on the stabilization of oscillators, calibration methods, etc., reference to the *Handbook* and running QST file will give a wealth of information on the evaluation of drift and equipment precautions to be observed. . . .

OOs only send Cooperative Notices to invite an amateur to look into his own situation and

responsibility to help him avoid FCC trouble. Such information is for investigation and evaluation, not for purposes of rightness or arguments. The dangers of indiscriminate zero beating, the values (magnitude and direction) of warm-up drift, stand-by drift and frequency changes during high and low power operation, the similar drift in receivers and standards (too few hams make these a part of their stations) should be known and considered by all. The limitations of crystals themselves depending on temperature, holder and circuit capacity and other conditions are things with which every amateur should be familiar. This is an *individual* responsibility between each amateur and FCC in the final analysis. A system of check-back against WWV is our final word of advice, or else lacking such provisions, we personally should not flirt with the band edges. — F.E.H.



This certificate has been awarded for the year 1952 to each of the clubs listed in the ARRL Affiliated Club Honor Roll that appeared on page 64 of June QST. Issuance was based on membership information obtained from the 1952 Annual Club Information Survey. There will be an additional QST Honor Roll published later this year to include those clubs reporting results of ARRL membership drives being conducted currently. Clubs that qualify for the second 1952 listing will also receive 100% certificates following publication of the Honor Roll.

ARRL ACTIVITIES CALENDAR

July 12th: CP Qualifying Run — W6OWP
 July 18th: CP Qualifying Run — W1AW
 July 19th-20th: CD QSO Party (c.w.)
 July 26th-27th: CD QSO Party ('phone)
 Aug. 3rd: CP Qualifying Run — W6OWP
 Aug. 18th: CP Qualifying Run — W1AW
 Sept. 5th: CP Qualifying Run — W6OWP
 Sept. 10th: Frequency Measuring Test
 Sept. 16th: CP Qualifying Run — W1AW
 Sept. 20th-21st: V.H.F. Contest
 Oct. 4th: CP Qualifying Run — W6OWP
 Oct. 11th: Simulated Emergency Test
 Oct. 15th: CP Qualifying Run — W1AW
 Oct. 18th: CD QSO Party (c.w.)
 Oct. 25th: CD QSO Party ('phone)
 Nov. 9th: CP Qualifying Run — W6OWP
 Nov. 13th: CP Qualifying Run — W1AW
 Nov. 15th-16th, 22nd-23rd: Sweepstakes Contest



The lessons learned by amateurs participating in emergency communications are of little value to the fraternity as a whole if they are not publicized. There has never yet (and probably never will be) an emergency in which all AREC operation was so perfect that no implied vows were made concerning improvement "next time." Lessons coming out of recent emergencies will be noted in this column from time to time as a sort of "Hints and Kinks for Emergency Operation," so that progressive local AREC units will have the opportunity to learn through the experiences of others. Here are a few:

1) Operating conditions during or after an emergency are generally anything but favorable, and it is necessary to operate emergency setups with as high power as is obtainable, especially when using 'phone.

2) Noise limiters and clippers on receivers are a definite asset, in addition to hash filters on your own emergency power source. Noise from generators being used for lighting and other non-communications purposes can be a great drawback unless your own receiving equipment makes provision for suppression of such noises.

3) A pre-prepared antenna on a suitable reel should be kept available for emergency use, since it requires time to cut, erect and load up an antenna in a disaster situation; along with your portable rig, you should have a portable antenna.

4) Our business in an emergency should be to handle the communications which agencies being served require us to handle; nothing else. However, in exceptional cases it may be necessary for an AREC official to decide which type of message shall receive priority handling. In this connection, we have to divide message traffic into two categories, as to whether they pertain to (a) the general public welfare or (b) the welfare of an individual. Concerning the former, we have to decide which require immediate action, which have a time limit for delivery and action, and which are of a non-urgent nature. Concerning the latter, it should be obvious that outgoing messages containing assurances of safety or notification of death or injury should receive priority over incoming traffic of a "worry" or "agony" nature. In the final analysis, each emergency has its own peculiar ramifications. We amateurs should avoid having to designate priorities on messages we are given to handle; if we cannot do so, the above may serve as a general guide.

5) Perhaps the greatest lesson learned in all emergencies is the necessity for more preparedness and official contact as a corollary to emergency planning. Most of the difficulty in setting up facilities and getting these facilities used and trusted by agencies needing them is directly traceable to lack of previous contact with or knowledge about them on the part of officials concerned. We should make sure that the things about an emergency situation that irk us communicators are not basically our own fault.

A large area of the City of Swift Current, Sask., was threatened by flood waters in April from the Swift Current

Creek. Radio contact had been established between the dam at Duncrain and Swift Current by army units, but this contact was interrupted and amateurs were asked to establish contact immediately. We were alerted at 2130 and at 2200 were told to proceed. A spare 100-watt transmitter from VE5JG, powered by a 1500-watt lighting plant, left Swift Current after midnight with VE5BQ and was on the air and in contact with base station VE5JG at 0230. An hourly schedule was arranged. The local Department of Transport range station arranged to monitor the emergency transmitter frequency continuously, so we did not have to keep a continuous watch at the base station. VE5BO was alternate base station. VE5FP loaned his 50-watt transmitter as a standby at the dam. VE5OH relieved operators at VE5BQ while VE5AZ assisted at VE5JG. VE5BQ never missed one schedule from the time of its arrival at 0230 April 21st to 1045 April 23rd. Signals from VE5BQ were reported from the West Coast to Winnipeg, operating on 3770 kc. Wonderful cooperation was extended by all hams in keeping our channel clear, offering equipment and personnel for our assistance, and also maintaining a watch on the frequency.

— VE5JG, EC Swift Current, Sask.

On the morning of May 11th a tornado hit the little town of Alapaha, in southern Georgia, destroying about 75 per cent of the town. All power and communications were out and the water supply was cut off. W4PFF at Dublin was first to learn of the disaster and call in on the frequency of the Georgia Cracker Emergency Net (3995 kc.) to contact W4LXE, net manager. W4LXE alerted the net and sent two mobile units, W4ACH and W4OIL, to Alapaha. When the mobile units arrived they found the city without communications. City officials used the mobile and the net to contact the Red Cross office in Atlanta, requesting a water wagon, tents, cots, blankets and food. This was delivered to the American Red Cross in Atlanta and the answer was returned to our mobile units in Alapaha advising that the equipment was on the way. Our mobile units stayed in Alapaha until the telephone circuit was completed and their services were no longer needed.

Stations participating in this emergency were: W4s ACH BIW FBH IAO IFQ KIJ LXE MZO OIL OTD PFF PGK PKT PYM (W4NS at the mike) SCR and ZD. The Red Cross Director praised the hams for the fine job they did in handling traffic for him and keeping him informed.


— W4ZD, SCM Georgia

On November 4, 1951, Rhode Island conducted the first statewide CD test in its history. Incidents prepared beforehand lent color and realism to the drill. Certain areas surrounding Providence were serviced by 10-meter mobile units: W1s KKE LZY OOX PTF RAM RVQ SGA and SIK. W1MIJ handled the control mike for the mobile networks. W1HEH also assisted. The traffic handled by these amateurs sent hundreds of firefighting trucks, ambulances and police into the fight. Numbers assigned to each car greatly speeded up the action. W1FNM was "Control." Frequent use of proper procedure within the time limits required prevented any confusion. Announcements to the effect that the messages were "simulated" were made with each message from the control station.

A 2-meter network was also in operation, embracing all the larger towns surrounding Providence and using equipment furnished by the State. W1s AFO CPV JND JP LCP

The AREC groups of the Greater Hartford (Conn.) area got together in a cooperative project to establish this Amateur Radio Civil Defense center at the Alert America exhibit held in the West Hartford Armory in early March. Contact was maintained with control stations in each of the towns in the 15-town mutual aid area, as well as with the many mobile units in operation in the area. A small amount of traffic was also originated. Most operation was on 10-meter 'phone and 80-meter c.w.

QST for



MCP OJE PAZ and SKT participated, with BGM at the control mike.

The 75-meter band took care of our long-haul traffic in compliance with the Ten-State Mutual Aid Plan. Although aerial aid was not requested from the other states over the air, informational messages were transmitted to the two adjacent states. This network included Wls BBN BVY CPT JZJ JRZ KMY OIL OUR PVY SBP and TJR.

WJFF, EC of Newport and his crew did a wonderful job at working two, ten and seventy-five. The Newport and Middletown networks were credited with being the first to flash the news of a Navy jet crash into a Newport home. Aiding WJFF were Wls MMX, PXI, W4PAE/1 and WNls TXE and TXL.

Firefighting apparatus from other states also participated, particularly from Fall River, Mass. In order to recall this apparatus quickly if necessary a separate network was established and coordinated by WIAHP, aided by WIDQ. WIGDJ/M followed the fire trucks wherever they were dispatched to keep in touch with home. WICRN/M also aided. In calling the operation a success, the Governor of Rhode Island made special mention of communications. The whole communications undertaking was headed by WINZR, director of radio for the State Council of Defense, and his assistants WIKKE and WIMLI who is also Chief of Amateur Radio for CD. — WIMLI, SEC R. I.

Seventeen SECs submitted reports for March activities, an increase of four over February. So the steady climb upward continues. March reports add up to representation of 3150 AREC members. New reporters for March were the SECs of S. N. J., S. Dak., W. Mass. and Wash. Forty-four SECs monthly reports have been received from 21 different SECs in the first quarter of 1952. We're still not bragging, but the uptrend is most encouraging.

CODE-PROFICIENCY AWARDS

Have you received an ARRL Code Proficiency Certificate yet? Twice each month special transmissions are made to enable you to qualify for the award. The next qualifying run from WIAW will be held on July 18th at 2130 EDT. Transmissions will be made simultaneously on 1887, 3555, 7120, 14,100, 28,060, 52,000 and 146,000 kc. The next qualifying run from W6DWP only will be transmitted on July 12th at 2100 PST on 3580 and 7248 kc.

Any person may apply; neither ARRL membership nor an amateur license is required. Send copies of all qualifying runs to ARRL for grading, stating the call of the station you copied. If you qualify at one of the five speeds transmitted, 10 through 35 w.p.m., you will receive a certificate. If your initial qualification is for a speed below 35 w.p.m., you may try later for endorsement stickers.

Code-practice transmissions are made from WIAW each evening at 2130 EDT. References to texts used on several of the transmissions are given below. These make it possible to check your copy. To get sending practice, hook up your own key and buzzer and attempt to send in step with WIAW.

Date	Subject of Practice Text from May QST
July 2nd:	<i>The Truth About the Vertical Antenna</i> , p. 11
July 8th:	<i>A 50-Mc. Transmitter-Receiver for Civil Defense Use</i> , p. 17
July 10th:	<i>A Car-Mounted 10-Meter Beam</i> , p. 22
July 14th:	<i>A Midget Fifty-Watt</i> , p. 27
July 16th:	<i>The Wavelength Factor — II</i> , p. 32
July 22nd:	<i>Tools and Tricks</i> , p. 36
July 25th:	<i>How To Test and Align a Linear Amplifier</i> , p. 39
July 28th:	<i>Tuning Two Meters on the Car Receiver</i> , p. 49
July 31st:	<i>Technical Topics</i> , p. 52

BRIEFS

WN1VNN was the first Novice to operate Maxim Memorial Station WIAW. While visiting the station he contacted WIKOW on 144 Mc. and WN2HCZ on the Novice 80-meter band.

"CQ, CQ, CQ." called A1/C Dan Peters of DL4TH. He combed a dead band for answers to no avail and made ready to pull the switches for the night. Answering a hurried knock at the door he heard a breathless voice inquire, "Did you call the CQ?" It happened that the 1807th AAC's Wing's Charge-of-Quarters responded because of a case of BCI in his desk-top a.c.-d.c. broadcast set three floors below. How would you log that one? — DL4JC/W8KKQ

DXCC NOTES

When the first LU1ZA cards appeared in DXCC applications, ARRL was confronted with the problem of whether to count only VPS confirmations from the Falkland Islands Dependencies or to credit cards from the LU and CE7 stations operating in that area as well. Information was obtained from the sources usually approached in DXCC Countries List problems, and it was indicated that the Falkland Islands Dependencies were generally recognized as British-owned. On that basis ARRL has accepted only VPS cards from the South Shetland, South Georgia, South Sandwich, South Orkney, and Falkland Islands, and the portion of the Antarctic continent including Palmer Peninsula. Since this policy was inaugurated, so many inquiries have been received that it was decided to consult our highest authority, the United States Government, and to let our policy be guided by that of our government. This correspondence now having been completed, we have found that no claims of individual countries to the Falkland Islands Dependencies or any part of the Antarctic mainland are recognized by the U. S. Government. Therefore, a ruling by the ARRL, to be consistent with our government's stand, should provide for the crediting of all confirmations from this area, without regard to prefixes or nationalities of stations. Accordingly, QSLs from LU and CE7 amateurs in the Antarctic region, previously rejected, will now be accepted for DX Century Club credit.

DX CENTURY CLUB AWARDS

HONOR ROLL

W1FH	247	W6AM	234	W1BPD	230
W8HJW	242	W6GHD	234	W6GRL	229
W3BES	242	W3CPV	233	W3EVW	229
W0YXO	239	W2BXA	231	W2QKS	229
W6VFR	238	G6ZO	231	W6SN	229
G2PL	238	W3JTC	231	W9RBI	225
W6ENV	238	W3KT	230		

RADIOTELEPHONE

W1FH	216	XE1AC	211	W1JCX	193
PY2CK	215	W5HGW	200	W2BXA	190
VQ4ERR	213	W9RBI	199	W3LTU	187
		WINWO	195		

From April 15 to May 15, 1952, DXCC certificates and endorsements based on postwar contacts with 100-or-more countries have been issued to the amateurs listed below.

NEW MEMBERS

GW3FSP	151	ZS1FR	106	ZS6OS	101
VQ4SGC	129	SM3AKM	106	W5DMR	101
W1ZW	117	DL3BJ	105	VE1EX	101
G2CNW	112	DL1YA	104	W7NIN	101
DL1VU	110	PY2DV	104	W1PKW	101
F3MS	108	GM3DZB	103	W6DBT	100
V86AE	107	OH60A	103		

RADIOTELEPHONE

W1BLF	114	EA4CM	107	W1DSC	100
		GM3DZB	100		

ENDORSEMENTS

PY2CK	222	W6EYR	180	ZL3AB	138
PY1AJ	220	KZ5CP	179	G6XA	135
W6TT	220	W8KPL	171	W0AIIH	132
W2WZ	214	G3YF	170	W4CKB	131
W6CUQ	211	W1BLE	166	IS1FIC	130
W0PNQ	211	CP5EK	160	W3AFU	127
W2QHH	210	ON4NC	152	W1QV	121
PY1AHL	201	W2LV	143	VE7KC	119
W5KUC	200	H1UA	141	W4OG	119
W6TI	200	G3DOG	140	EA4BH	118
G6QB	194	G4ZU	140	GM2DBX	112
LU7CD	190	G8KUC	140		

RADIOTELEPHONE

W6AM	181	ON4PJ	140	F9PH	113
W9ROQ	176	H1TA	140	GM2DBX	111
W3DHM	170	W3EVW	140	G3HD	110
W1LMB	160	CT1PK	136	F8MY	110
W5EFC	150	W5KUC	121	F9RM	110
W8GZ	150	PY2JU	120	PY4VX	110
		ZS9G	114		

BRASS POUNDERS LEAGUE

Winners of BPL Certificates for April traffic:

Call	Orig.	Recd.	Rel.	Del.	Total
W6HQX	53	3296	3266	30	6645
W3CUL	253	2465	1952	456	5126
W6HK	192	2622	365	136	3315
W6KYV	279	1364	402	960	3005
W9JLJ	31	1265	1201	28	2525
K6FAA	782	817	527	249	2375
K9FAE	97	1074	1072	41	2284
W6GYH	839	762	96	23	1720
K4WAR	215	624	568	56	1463
W2BNC	13	633	613	20	1279
W4PJU	6	599	554	45	1204
W5QHI	69	517	571	12	1169
W7IOQ	37	499	542	36	1114
W7CZY	7	550	545	4	1106
W8ZGT	10	504	488	16	1018
JA8AB	140	385	291	94	910
W6NCP	46	425	421	8	900
W2BTB	32	383	397	21	833
W6BAM	39	364	262	100	765
W6GKM 6	686	7	59	7	759
W6HPT	5	369	341	28	743
W8AUJ	11	376	322	25	734
W7MLJ	10	361	355	6	732
K5FBB	366	163	137	45	711
W5MN	26	340	261	79	706
W8SCA	6	357	339	1	703
W2RUF	16	338	225	86	665
W7II	27	312	298	14	651
W2RO	10	275	310	41	636
W1SJO	8	304	247	53	612
W8BDR	3	305	294	7	609
W9TT	16	295	241	49	601
W4SHJ	225	166	141	17	549
W8ARO	37	254	106	146	543
W3BIP	6	272	245	7	530
W7PKX	3	262	260	2	527
W5MRK	8	257	230	30	525
Late Report					
JA2KW (Mar.)	3540	172	14	158	3884

The following made the BPL for 100 or more origination-plus-deliveries:

W4FOR 231	W5FOG 125	W3RIT 106
W5QVY 214	W2VNJ 123	Late Report
W9NZZ 210	W5VHY 118	W1QKM (Mar.) 148
W7BA 174	W4TRC 116	
W6GJP 143	W2AEE 114	

A message total of 500 or more or 100 or more origination-plus-deliveries will put you in line for a place in the BPL. The Brass Pounders League is open to all operators who qualify for this monthly listing.

TRAFFIC TOPICS

Most amateur nets are open to all comers, and this is as it should be in view of the voluntary nature of our work. Some nets which aim at high efficiency and speed have found it necessary to restrict the QNTs to a certain membership, and accomplish this objective by "calling the roll" so that only these stations will report in. There are other nets, also, which move along at high speed and refuse to slow down for the casual participant who cannot maintain the pace.

Emily Post probably never participated in a traffic net, but if she had perhaps she would come up with a set of rules of conduct similar to the following:

(1) Before reporting into a net in which you are a stranger, or not a regular participant, first listen to determine whether the particular net is "closed" or "open," or somewhere in the middle.

(2) Do not report in unless you have traffic which can be handled by that net, or unless you have some reason to believe that you can provide an outlet which they do not already have.

(3) Wait until you know the call letters of the NCS before reporting in. Don't break in and inquire.

(4) Wait for a "break" in the traffic handling before reporting in. Don't do so in the middle of a message.

(5) Use their procedure when reporting to their NCS. If you do not know their procedure, listen until you get onto it.

(6) When reporting in, indicate your location or what traffic you can take briefly. Indicate your traffic, if any, in as brief and concise a fashion as possible. The extent to which the NCS has to ask you questions is the extent to which you have failed to report in properly.

(7) Once you are in the net, stay off the air except when told to transmit by the NCS. If he needs any "help," let the regular net members do it.

(8) Don't feel offended if your traffic is not handled right away. Many nets have a policy of handling traffic to and from their regular members first, visitors last.

(9) Stay in the net, once you report in, until the NCS excuses you (QNX).

(10) If you don't feel like abiding by the above, don't report into the net in the first place.

National Traffic System. Copies of a new release bearing the designation CD-24 and entitled *The ARRL National Traffic System* have been mailed out to some 600 amateurs. This release explains in detail what the NTS is and what it does. Every NTS participant should have a copy of this for reference, and anyone interested in NTS participation is invited to drop us a line or radio message asking for a copy. The initial mailing consisted of a selected list of net control and liaison stations, but we suspect that there are a great many interested amateurs who have not received this information. While it is not feasible to distribute these at random on a "throw-away" basis, we do want to make sure that anyone interested is informed. So if you want a copy and have not received one, just let us know.

One of the new features of NTS which is now on trial is the Transcontinental Corps (TCC). At this writing, applications are beginning to pour into Headquarters in response to formal invitations to participate which were mailed out to selected amateurs whose services it was felt could best be used. There are openings for a maximum of some 65 amateurs to participate in TCC functions each week, and all positions are at this writing a long way from being filled. The principal need is for long-haul stations which can operate at odd hours, particularly located in the Mountain or Pacific Time Zones. Such participation need not tie you down more often than one night a week, contrary to the belief and opinion which have been expressed by many. There are a great many good traffic men who do not have either the ability or inclination to handle traffic every night of the week. Here is their opportunity to become a vital part of NTS in accordance with their limitations.

April reports:

Net	Sessions	Traffic	High	Low	Average	Most Consistent
1RN	32 ¹	263	68	0	8.2	E. Mass., W. Mass
2RN	44	635	79	0	14.5	JN
3RN	38	350	41	0	9.2	All
4RN	39	464	32	2	12.0	Fla.
RN5	39 ²	497	41	0	13.0	Okl.
(Feb.)						
RN6	54	1341	72	2	24.8	
RN7	52	306	33	0	5.0	Wash.
SRN	30	143	21	0	5.0	Mich.
9RN	26	1169	96	4	45.0	All
TEN	43	1277	87	5	29.7	La., Kans., Minn.
TRN	44	85	15	0	1.9	Ont.
EAN	22	730	67	2	33.2	2RN, 3RN
TLCN	22	350	32	5	15.9	
(la.)						
QIN	60	1067	54	1	17.0	
(Ind.)						
¹ Out of 44 sessions held.						
² Out of 42 sessions held.						

Daylight Saving Time has done its usual excellent job of messing up the NTS time schedule. The only way to handle a situation of this kind is for all NTS nets either to remain on Standard Time or change to one hour earlier. Unfortunately, once again this has not appeared to be feasible, with the result that some nets changed and some did not, and most of those which did have not notified us so in many cases we no longer know when a net is operating. In the

Eastern Time Zone, most regional nets and the area net have continued on Standard Time, but pressure from participants may make it necessary for some to rearrange their operating schedule. Things are rough all over.

Second Regional Net: 2RN will have one session only at 1945 EST during the summer months.

Third Regional Net: Certificates have been issued to W3s AD AAX COK KUN QLZ and UHN. 3RN will attempt to continue throughout the summer months on EST. Section net members of the EPA and WPA nets (discontinued for the summer) are invited to participate in 3RN.

Fourth Regional Net: W4AKC is the new 4RN Manager, although resigning Manager W4ANK will continue as a 4RN member. W4AKC's appointment was effective May 1st.

Seventh Regional Net: RN7 has shifted to 7225 kc. for its first session, remaining on 3575 for the 2130 PST session. Certificates have been earned by W7s AWG LVU HKA and PKX.

Eighth Regional Net: Len sent us a copy of his very FB April Eighth Regional Net News bulletin. The following stations have earned 8RN certificates: W8s BWK FYO RJC and ZLK.

Ninth Regional Net: 9RN will remain on CST all summer, six nights per week. W9EHS has earned a 9RN certificate. W9TT points out that Kentucky was not included in the 9RN roster in the recent Emergency and Traffic Bulletin. Our apologies!

Tenth Regional Net: Manager W9ITQ wants a Manitoba contact by c.w., 'phone or smoke signals.

Thirteenth Regional Net: TRN will remain on EST, but probably on a restricted schedule.

Eastern Area Net: W8SCW says that long-haul liaison troubles are more a result of conditions than lack of personnel.

MEET THE SCMs

Nebraska SCM Guy R. Bailey, W9KJP, became interested in ham radio in 1919, obtaining his first license in 1931 with the call W9KJP.

Holder of ORS and OPS appointments, Guy enjoys handling traffic, is NCS of the Nebraska 75-Meter Net. He's a member and past vice-president of the Ak-Sar-Ben Radio Club and a member of the Council Bluffs Radio Operators Club. For his noteworthy work in the Nebraska blizzards of 1948 and 1949 he was awarded Public Service certificates. He also holds RCC and WAS certificates.

The transmitting tube line-up at W9KJP: BC458 VFO-T40-p.p. HK54s final; modulator, 811s with Splat-ter Choke and negative peak clipper. Input generally runs about 275 watts on c.w. or 'phone. Receiver is an NC-173 and the antenna in regular use is a half-wave doublet cut for 3700 kc. Operation is conducted on 40, 75, and 80 meters.

Guy's favorite recreation aside from amateur radio is bowling; his pet sports are baseball and football. A retired blacksmith foreman, SCM Bailey is now employed as a salesman by the N. P. Dodge Corp.



APRIL CD QSO PARTIES

Top score in the c.w. section of the April CD QSO Parties was chalked up by W7BSU. Elmer, you will recall, also was high man in the January shindig and deserves a big hand for maintaining his standing against some very keen competition. Second place honors were taken by W6WOO, who showed considerable improvement by climbing from eighth place in the previous party. W4KFC came through with the third highest c.w. score and rates special mention for tallying more contacts than any other participant. In the 'phone party a dark horse, W3AD, showed up in first place with a comfortable lead on the rest of the field. W4NYN and W4FV, regular high scorers in many previous parties, turned in the second and third

highest point totals. Listed below are other high claimed scores. The figures following each call indicate the claimed scores, number of contacts and number of ARRL sections worked. Final and complete results will appear in the July CD Bulletin.

C. W.

W7BSU	147,280-290-56	W1EOB	48,750-188-50
W6WOO	110,922-214-57	W3PZW	47,840-204-46
W4KFC	103,455-356-57	W9ADM	44,500-173-50
W3FQB	94,335-324-57	W1AW	43,470-183-46
W7UTM	87,618-187-51	W1CRW	38,880-162-48
W8NBK	79,430-278-57	W9NH	38,880-156-48
W7GHT	78,768-179-48	W0PHR	38,720-176-44
W3JSH	76,850-283-53	W2MHE	38,270-178-43
W7JGZ	71,900-157-50	W2AQT	35,875-175-41
W4HQN	68,320-237-56	W2KEL	35,100-149-45
W3KUN	66,480-270-48	W3PDJ	34,960-179-38
W4NH	65,455-247-53	W2CPN	34,230-163-42
W3BIP	65,070-234-54	W0UNC	34,185-153-43
W2COU	58,250-226-50	W7KWC	33,300-100-37
W1QIS	56,750-220-50	W2HTH	32,625-145-45
W5AQE	56,650-200-55	W3AXA	31,675-176-35
W3JHW	56,160-227-48	W4CKB	31,590-162-39
W6GEB	54,943-126-47	W9ERW	31,175-139-43
W8EXZ	54,825-208-51	W6CMN	30,711-87-37
W7MLL	53,712-120-48	W3LVE	30,450-145-42
W4AKC	52,875-225-47	W9KXX	30,140-134-44
W2GFG	52,825-210-45		

'PHONE

W3AD	9425-58-29	W2ILI	2250-30-15
W4NYN	6370-49-26	W1FZ	2175-24-15
W4FV	5390-44-25	W1RDV	2100-30-14
W2MHE	4510-41-22	W3EAN	1750-20-14
W1MX	3995-44-17	W4KMS	1650-22-15
W2ZVW	2775-30-15	W4DLX	1560-19-13
W6CHV	2688-18-14	W4KFC	1500-16-12
W1GKJ	2520-31-14	W5PBX	1500-20-15

"Blue Dolphin" — W2BZD/MM

The schooner *Blue Dolphin* will again cruise in northern waters this summer. Bruce Wald, W2BZD, will operate and has asked for special FCC authorization permitting maritime-mobile work in the lower amateur frequencies.

Daily watches will be kept June 20th through September 10th in accordance with the following: (If no calls are noted in five minutes, alternate frequency will be tried.)

Mode	Time GCT	CST	Frequency
A-1	1430 and 2030	0830 and 1430	14,075 (14,107 kc. alt.)
A-3	2045 and 2340	1445 and 1740	14,260 (14,240 kc. alt.)
A-1	0000	1800	14,075 (14,107 kc. alt.)
A-1	0100	1900	7065 (7115 kc. alt.)

NATIONAL CALLING AND EMERGENCY FREQUENCIES

C. W.

7100 kc. (day)	3875 kc.
3550 kc. (night)	14,225 kc.
14,050 kc.	29,640 kc.
28,100 kc.	

'PHONE

During periods of communications emergency these channels will be monitored by stations of the National Emergency Net for personal-inquiry traffic. At other times, these frequencies can be used as general calling frequencies to expedite general traffic movement between amateur stations. Emergency traffic has precedence. After contact has been made the frequency should be vacated immediately to accommodate other callers.

The following are the National Calling and Emergency Frequencies for Canada: c.w. — 3535, 7050, 14,060; 'phone — 3815, 14,160 kc., 28,250 kc.

Station Activities

• All operating amateurs are invited to report to the SCM on the first of each month, covering station activities for the preceding month. Radio Club news is also desired by SCMs for inclusion in these columns. The addresses of all SCMs will be found on page 6.

ATLANTIC DIVISION

EASTERN PENNSYLVANIA — SCM, John H. duBois, W3BXC — SEC: ISE, RMs: AXA, BIP, E. Pa. Net: 3610 kc. On May 3rd, the Lancaster Radio Transmitting Society held its annual banquet, with the following officers for the coming year being announced: ITD, pres.; GJA, vice-pres.; OY, secy.; SNI, treas. Our Director, GEG, was the guest speaker. RQY, the Abington Township ARA station is regularly reporting into the E. Pa. Emergency Net on Mon., 2030 EST, frequency 3610 kc. In addition, RQY is transmitting Philadelphia Area Council of Radio Clubs news, announcements, etc., on 28-Mc. phone. New officers of the Lehigh Valley SRA are: DPK, pres.; QGZ, vice-pres.; RCG, secy.-treas. The Lehigh Valley Net meets Tues. at 2100 on 146.8 Mc. and includes nine mobiles. The Northeast RC (Philadelphia) is planning to increase its membership. Those interested should contact RZO, secretary. The *Delaware News*, a new monthly paper published by the Delaware Lehigh ARC, does a fine job covering items of club interest and local activities. The Phil-Mont Mobile Club had a very successful e.d. demonstration on March 30th. This group also is compiling a "bible" on automobile noise elimination, which would be a worthwhile contribution to the art when complete. During the Daylight Saving Time period the E. Pa. Net will meet at 1830 EST and the second session will be combined with 3RN on 3590 kc. at 2130 EST. CUL and BIP make BPL this month. OQG is at Signal Corps radio school at Fort Devens, Mass. WN3TEC now is running 20 watts on 144 Mc. and 35 watts on 3.7 Mc. Several members of the Frankford RC "boiled the owl" and opened the 21-Mc. band at 0300 EST on May 1st. QLZ is adding 200-watt final. BIP, RCG, and SNI are going to higher power. LCK and SGB are active on 420 Mc. QLI is running 140 watts, 80 to 10, c.w. and "phone." FPC is installing 10-meter mobile rig. The Beacon Radio Amateurs now is in its 16th year and elected DYL, pres.; and ETA, secy.-treas. as officers at its last meeting. LVM is building a new VFO. QMP continues activity at Sampson Air Force Base. SBE dropped the "WN" after making first Novice WAST Traffic: (Apr.) W3CUL 5126, BIP 530, AXA 99, PYF 85, QLZ 74, AD 56, OML 53, VR 45, FDJ 42, RCG 22, QMB 16, BXE 17, QLI 11, BFF 7, CAU 6, CDT 6, DUL 5, PUY 4, BES 3, BYB 2, (Mar.) W3OML 40, QLI 14, (Feb.) W3QLI 32, (Jan.) W3QLI 20.

MARYLAND-DELAWARE-DISTRICT OF COLUMBIA — SCM, James W. John, W3OMN — The Chesapeake Amateur Radio Club has changed its meeting place to the American Legion Hall, Towson. At its April 14th meeting Lt. E. S. Maloney demonstrated "Crystal Grating" and on April 28th Jim Gordon, LNK, discussed "FM Transmitters." The Washington Radio Club held a successful auction on April 14th and on May 10th movies were shown. On April 21st FQR and GHX explained single sideband principles to the Baltimore Amateur Radio Club. The BARC will hold its 5th Annual Hamfest Picnic at Triton Beach Club on Sunday, August 10, 1952. On April 25th the Rock Creek Amateur Radio Association heard Dr. George Sterling, speak on the subject "Old-Timers." GHX, FQR, and HKJ presented an interesting program on single sideband for the May 9th meeting. QZC completed his 19-tube receiver and is trying it out as EAN liaison for 3RN on Tuesday evenings. Kent County, Delaware Amateur Radio Club, had a civil defense display booth in Dover for "Dover Day." MCD/3 was used for handling traffic. The Delaware Civil Defense Net meets Sundays 9 a.m. EDST on 3993 kc. Traffic: W3PZW 257, LZM 241, CVE 185, QZC 84, ONB 48, JHW 42, MCD 18, NOE 14, HC 10, QCS 9, IL 8, NNX 6, FQB 1.


SOUTHERN NEW JERSEY — SCM, Lloyd L. Gainey, W2TCV — The Cumberland Radio Association has formed a TVI committee to cover a large portion of the Club area. Full cooperation of all Club members will be necessary for this group to succeed. The published results of the V.H.F. Contest were enthusiastically received by the v.h.f. oper-

ators of the SJRA. The Club took first prize with a wide margin over its nearest competitor. ZI received the first amateur Extra Class license in the Trenton Area. The April meeting of the Cumberland Radio Assn. featured a film on radar presented by JAV. YRW is in civvies again after his release from the armed forces. Mr. J. Wilson, of Coles Lab., Ft. Monmouth, gave an exceptionally interesting illustrated lecture on captured North Korean and Russian radio equipment at the April meeting of the SJRA. Various pieces of the equipment were on hand for inspection by the Club members. KBR now is going strong on 144 Mc. Traffic and news for this column must be received no later than the seventh of each month to meet the column deadline. How about some news from the Jersey Shore areas? Traffic: W2RG 264, K2BG 219, W2ZVW 193, ZI 19, FLW 10, HAZ 8.

WESTERN NEW YORK — SCM, Edward G. Graf, W2SJY — SEC: UTH, RMs: RUF and COU, PAM, GSS, NYS: 3615 kc. 8 p.m. NYS: 3595 kc. 9 p.m. NYS: 3980 kc. 6:30 p.m. NYS C.D.: 3970 and 3509.5 kc. Sunday 9 a.m. GSS has been appointed Net Manager of the New York State Traffic and Emergency 75-Meter Phone Net by ILL, Eastern New York SCM, and SJV, Western New York SCM. PVB is home from the hospital and back on 75 meters. RJJ has 150 watts on 7, 14, and 28 Mc. and 40 watts on 3.5 Mc. CBA is mobile on 28 Mc. with clamp-tube modulation and tri-band. New club rooms have been completed by the Lockport Radio Club. Gadget Night and a quiz program were held at the last two KBT meetings. BDK has Navy 120 transmitter available for e.d. work. If you are a member of IA-IP, 6BA or would like to see your call for listing in the IA-IP publication, K2DQ, JR, and QQ received Extra Class licenses. E. Merrian, former service manager for RTMA, spoke at a RAWNY meeting on TVI. FCG resigned as AC for Zone 5 e.d. and the NYS office of e.d. has appointed PWN as Zone Coordinator. VIQ and RJJ are active in NYS traffic. WZM is home on leave from the Navy. FCG lost his sixteen-element 144 Mc. beam at Upper Lisle because of the wind. SEW is on 420 Mc. and QSOed Scranton, Pa. On April 5th the first annual get-together of v.h.f. men in the vicinity of Binghamton, Ithaca, and Sidney was held at Whitney Point. The Rochester DX Assn. was very active in the ARRL DX Contest. FBA, QJM, REF, TXB, SAW, DOD, ICE, and BJH have reported. SGI, TEX, and ZEL installed a bedside rig for THK. Zone 9 and 10 have established 2-meter Zone nets for e.d. The Erie County AREC manned a radio booth at the Alert America C.D. Show in Buffalo. JEY won an award for his operating at the North Central New York Science Fair in Watertown. Also operating were JWU, WZQ, and CVH. RJL and DNE are on s.s.b. with TMI exciter. The Rochester v.h.f. group met at the home of VVG. A e.d. meeting in Binghamton was attended by BGO, BTB, DEX, GSS, LQM, OUT, PWN, QY, RJL, ROL, RZF, SDA, SDX, SJV, TQY, UTH, ZOL, and WN2MSY. GSS and UTH visited the SCM to talk over and plan activities for W.N.Y. New appointments: GSH and STJ as OOL, RJJ as ORL, UAD as OES, GSS as OPS. RUF made BPL on both deliveries and total. COU received WAS award. BTB is back on the air after being in the hospital. Traffic: W2BTH 833, RUF 665, ZOL 378, WAI 327, COU 279, DJF 128, GSS 123, VIQ 57, CPN 43, SJV 35, RJJ 16, K2DG 12, W2QAA 10, EMW 4.

WESTERN PENNSYLVANIA — SCM, Ernest J. Hinesky, W3KWL — The following have had appointments cancelled: RIS, LSS, LGM, QYL, LIW, LQQ, and YA. Please send your monthly reports so that they reach this office by the end of each month. The Fort Nessity Radio Club staged a STAG Gabfest on June 7th at Uniontown. The Upper Ohio Valley Emergency Net now has gone v.h.f. under the watchful eyes of RXT/KWH, the 144-Mc. band is humming each Wed. at 8 p.m. WN3SHX has worked 36 states (all confirmed) on 80 meters. WN3SIV, of Kittanning, has 29 states and wants to get acquainted with the local boys. NRQ was Field Day chairman of the Steel City Amateur Radio Club. OOB is a new member of the Club. NKM says his handswitching VFO is swell. OKU is working single sideband and 160 meters. RSL now has an 829-B final. We understand MPO and CTN have State level nets and Sat. at 7 p.m. for all Westmoreland and ex-Westmoreland County hams. Congrats to NJH and the new jr. operator. AER, our DX man first-class, says 14 Mc. is very poor and that his son now has his own station and is active with the call WN3TQL. KNQ reports TVI receivers are

(Continued on page 78)



Pardon us, but here's a complaint letter that we could not resist publishing.

December 12, 1951

THE NATIONAL COMPANY
MALDEN, MASSACHUSETTS

Gentlemen:

I am writing you about something that has just gone wrong with my HRO. It's a plain HRO, not one of the fancy new ones from the post-war era. It was built by you and purchased new by me in October 1939, and now, after all these years, the filter condenser in the power supply has blown. This is its first really major failure. Two years ago I replaced a couple of resistors and the r.f. gain control because their values had changed more than 10% from recommended circuit design. I still use the old "pot" in another rig.

Incidentally, your advice of a decade or so ago has more than proven its worth. I have forgotten exactly when, but you will remember recommending leaving the heaters on continuously to decrease failure from thermal strains. Except for the few times the set has been moved, this policy has been rigorously followed. The net result has been replacement of only a handful of tubes in more than twelve years. A majority of the original ones are still in there punching.

In these days when reliability is the keynote of modern electronics, it might be well to go back and examine some of the design practices that have stood the test of time. Those in my HRO certainly have.

It is seldom one has a chance to praise a failure. I am happy to register my "complaint" about the filter condenser and at the same time congratulate you on the superb record established by this fine old set.

Sincerely yours,

JAMES M. BREARLEY (W3GZQ)



spoiling his traffic sessions. Up Erie way QN sends in his usual fine report via paper clippings. We are sorry to learn that NXK had an accident. We are happy to report OTE is home and convalescing very nicely. LKJ reports excellent progress on the emergency trailer. BPP does a swell job in his Sunday newspaper editorials concerning amateur radio and all phases of radio operation. The 75-meter net of the Lake Erie Emergency Net will be discontinued. TMK is a new one in Erie. A report from QN, Erie County Emergency Coordinator, shows 25 full members and 4 supporting and 40 per cent have emergency power. Traffic: (Apr.) W3GEG 198, NCD 125, UHN 64, KUN 30, AER 9, (Mar.) W3GEG 154, AAX 40, AER 14, (Feb.) W3GEG 92.

CENTRAL DIVISION

ILLINOIS — SCM, H. F. Lund, W9KQL — Section Nets: IEN, 3940 kc.; ILN, 3515 kc. SEC: QLZ, Asst. SEC: HPG, RM: BUK, PAM, UQT, Ex-K6GGC is on 20-meter c.w. from Hillsboro with the call SFD. MBI and ZHB are conducting daily 420-Mc. tests in an attempt to correlate propagation conditions with weather and barometric pressures. KQX says the 2-meter VDX eight-element "Long-John" is just another good 144-Mc. coming in for IFA but 30 Mc. remains a dead issue. After going house cleaning ICF still is hunting his 20-meter coils, spare crystals, and mike which he had hidden behind the sofa. NSL has new doublets for 14 and 7 Mc. The Midway Club at Zion has begun code and theory classes. DOR received his last-class 'phone ticket. STZ's daughter married and Pop has his new son-in-law studying for a Novice class license. OCG got rid of TVI and now he can't get a signal out of his back yard. A new Novice in Chicago is WN9REP; with 5 watts Jim is working out well. BA/mobile was NCS during the massed emergency disaster mobilization of 24 fire departments at Mascoutah Lake. Thirty-five pieces of fire-fighting apparatus were mobilized. Mobile units reporting fire trucks at they passed certain positions were KTH, JSQ, GFN, and KVC. Others assisting were QJY, QJY, PAM, MIB, CJJ, QQA, UXY, PKUJ, and SHHC.9. WN9RUW is on 80-meter c.w. and 2-meter 'phone in Peoria. Traffic: (Apr.) K9FAE 2284, W9FBX 269, CSW 255, UQT 236, SXL 145, BGN 95, CEE 69, BUK 67, LKJ 43, STZ 40, KQL 39, LGR 29, DOR 21, CTZ 10, MEI 8, LIN 3, (Mar.) W9LIN 1, NN 8.

INDIANA — SCM, Clifford C. McGuyer, W0DGA — The DARA mobile unit race placed spatter information with regular telephone service and tied. NH schedules 7JU on 160-meter c.w. NZE still handles the Arctic traffic. DKR is building new rig. New Novices in Martinsville are SWM, SYG, SWC, and SSQ. KTX handled urgent traffic with reference to obtaining watermelons for a sick child in Chicago. JCL is the new manager of the Central Area Net, in addition to QIN. APG has new HRO and is building new transmitter. DAG is working Novices on 80-meter c.w. EVR works 7 Mc. New officers of the Kokomo Club are YDP, pres.; WN9PUK, vice-pres.; WN9QBD, secy-treas.; DKR, rep. at large. YDP has received his WAC. HQF has 110 sticker for his DXCC. DKR has TVI-proofed his transmitter. ORZ is building new v.h.f. antenna. CEB has returned home after 18 months of Naval service. The Calumet Emergency Net is operating on a frequency of 1805 kc. and the Net Manager is DRJ. UKT is building new mobile rig. New EC for Howard County is DKR. LZL has installed a voice-controlled relay for 'phone operation. TT is a new REC. DLI and EUJ work 80-meter c.w. from Hobart. Total IFN traffic for April was 151. On April 27th the Indiana Radio Club Council held its meeting at Frankfort. Eleven clubs were represented by 31 delegates. QLW has recovered from a case of the hives. The XYL of DKS now is WN9ULW. GSY changed his cascade receiver to coax input for 144 Mc. V.h.f. operators, please forward your call to the SCM. FJI is studying for his Advanced Class license. New members of the Lake County ARC include JRY, PKF, JDM, PJW, DRJ, PAS, PKG, FVE, and Novices QPR, QBN, RES, and QNJ. If your county does not have an EC, make recommendations to the SEC. LZL JBQ reports RFN traffic for April as 131. Traffic: (Apr.) W9UJ 2525, TT 601, JBQ 363, NZZ 330, DGA 182, TG 149, BKJ 130, KTX 105, LZL 97, JTX 95, KDV 78, FZW 68, DHJ 64, PYM 58, RCH 48, DOK 40, WBA 3D, JGB 19, QJW 19, DKR 18, MUR 15, ZIB 6, GSY 4, NH 3, YVS 1, (Mar.) W9JTX 78, IFR 8, IZC 3.

WISCONSIN — SCM, Reno W. Goetsch, W9RQM — SEC: OVO, PAM: ESJ, RM: IQW, CBE. C.w. net (WIN) 3625 kc., 7 p.m. daily; slow speed at 6:30 p.m. 'Phone net (BEN) 3950 kc., 6 p.m. daily. WJH worked Waukesha on 144 Mc. GFL is trying out net 1830. HHD/MY is working 1RT in Indiana for a nice haul with the mobile rig. OOD is Asst. EC for Beloit. SGG is using TV beam and lead-in as 1/2-wave vertical top-loaded on 3.5 Mc. SBQ received his Extra Class license, one of the first in the section. RYA has a new Viking transmitter. Approximately 350 were in attendance at the Wausau Hamfest on April 26th. IDVJ, Asst. Secretary of ARRL, was guest speaker. The newly-formed Wisconsin Council of Radio Clubs elected JXY, pres.; ART, vice-pres.; ONY, secy.; BCC, treas. Communications for the 32nd Div. Memorial Day Autocades were provided through facilities of MRAC, many State EC nets and mobiles, and 1 BEN stations. IFS is new OHS. WLZ renewed EC appointment.

If there is no EC appointed for your county, OVO, would appreciate information on eligible candidates to complete state-wide Emergency Corps coverage. Don't forget the BEN picnic at Sturgeon Bay. KKK took a vacation trip, visiting HQF, HUZ, and other DXers en route. CFP uses SCR-522 on 144 Mc. with folded dipole for antenna. FAN took in several April 144-Mc. openings to Illinois, Indiana, and Michigan. The following Novices are active on 144 Mc.: OOW, RNJ, RNI, and RXL. TQ is working on new circuit to relieve the SCR-522. PGF has new mobile in operation. LED's auto has a new Morrow converter decorating the interior. FPE is on 144 Mc. from Willard week ends. LEE is looking for Green Bay 144-Mc. stations every Monday night along with his regular skeds. NYS is having antenna and converter trouble. EYN has a new mike. Traffic: W9ERW 175, SFL 84, IQW 73, CXY 72, IFR 65, SDR 29, DR 18, OVO 10, RQM 9, CFT 8, FDX 8, CFP 6, SHG 6, OOD 5, LSK 3, IZE 2, KKK 2, OVO 2, SGG 2.

DAKOTA DIVISION

NORTH DAKOTA — SCM, Everett E. Hill, W0VKP — 1 Grand Forks hams really are going to town on a new club. The Sioux Amateur Radio Association has 46 charter members. Officers elected were: GZD, pres.; RGT, vice-pres.; OGZ, act. mgr.; BKB, secy.; and TSB, treas. The Club will have a permanent shack in the new NDU Engineering Building. Plans are for a kw. rig on all bands. Grand Forks now has 18 Novices as a result of its training program. The Williston Amateur Club now has 25 members. BKZ has a training program in mind and is writing out the laws. The founders and officers of the above clubs are to be commended on their excellent work. Clubs should be formed in all the towns in which there are two or more hams. They can lend much needed assistance to the newcomer. Mayville is a fine example of assistance with 15 hams there. Your SCM can give you assistance on organizing clubs. Be sure and affiliate your club with the ARRL and make use of the ARRL. Traffic: W0JVP 26, GSR 10.

SOUTH DAKOTA — SCM, J. W. Sikorski, W0RRN — SEC: GCP, RM: OLB, ZIQ, Sioux Falls, has been discharged from the Army and is back at his old stand at Power City Radio. Winners in the Sioux Falls ARC 5-watts-or-less WAS Contest were BLZ, PHR, and MPQ. UVL, Pierre, announces that the 75-meter 'phone net will operate Sunday, 9:30 a.m. (CST) during the summer months. The Radio Club members are building several 2-meter rigs. UVL has teletype ordered and is the first South Dakota member reporting that activity. The SFARC held an auction of parts donated by KSOO. Two activity reports were received this month, and none from clubs. Traffic: W0EHO 78, PHR 37, RRN 32, UVL 6.

MINNESOTA — SCM, Charles M. Bove, W0MXC — The Mobile Amateur Radio Corps of Hennepin County had 15 minutes on TV. They showed the inner working of their station, PZT, and a demonstration of the operation of their pack sets and mobile set-up. Well LI finally did it. Her call is WN0IRD and she will run 75 watts into an 812 on c.w. VE4KM was a visitor to the Twin Cities and made a visit to the MARC transmitter at the Hennepin County sheriff's radio station. KOW is building a mobile rig for 75 and 10 meters. BYQ now is operating mobile portable 8 in Michigan. AME has been operating portable while out smelt fishing. KYE paid a visit to the Twin Cities for a check-up at the hospital. JVV has purchased a new HRO-50 receiver. The Duluth Radio Club held a combined field day and picnic with a BC-437. The Marshall Red Cross disaster committee asked the Marshall Radio Club for a ham station at its headquarters in case of flood. SKQ, BGJ, UUY, FFO, QIQ, QEI, and FLE responded and set up a station on 10 and 75 meters. BGJ and QIQ now are on 75-meter mobile. DXY now has his General Class license. The Minnetonka Radio Club is a new club at Excelsior. Officers are QZ, pres.; WQF, vice-pres.; and NSE, secy.-treas. WQF is doing a fine job conducting code classes at Excelsior. Traffic: W0UCV 129, AA 92, HE0 85, AII 32, TJA 26, TKX 25, BUO 20, MXC 20, DQL 15, KNR 15, BRA 13, RXL 9, K0AW 8, W0JNC 4, OPA 4, YUN 4.

DELTA DIVISION

ARKANSAS — SCM, Dr. John L. Stockton, W5DRW — The meeting at Eureka Springs was well attended with more than a hundred amateurs making a grand total of 214 present. Our thanks to AAE for a grand job and for making the hamfest possible. See you in Eureka next year. TNM is new EC for Fayetteville and has organized a good emergency plan. EA has been QRL working on 2nd-class 'phone ticket. MET is MM again and has been working the DX. BAB has new 37-ft. tower for his 20- and 10-meter beams. PUN is at San Diego in the Marines. I wish to take this opportunity to thank all of the hams that have sent in

(Continued on page 80)

world's toughest transformers

wear these exclusive **ONE-PIECE DRAWN-STEEL CASES**



the only complete*, versatile** line with
tough Sealed-in-Steel construction

When tougher transformers are made, CHICAGO makes them—in rugged, streamlined drawn-steel cases that provide the fullest enclosure and protection, that look well with other modern electronic components and enhance the appearance of the equipment. The exclusive CHICAGO one-piece drawn-steel case (no seams or spot welds) is the strongest, toughest type of mechanical construction. Further, the one-piece design provides a continuous electrical and magnetic path which means better electrostatic and magnetic shielding. Seamless construction assures maximum protection against adverse atmospheric conditions—means longer, more dependable transformer life.

Whether your transformers must pass the most rigid MIL-T-27 specifications or are intended simply for average, normal applications, it's wise to choose CHICAGO "Sealed-in-Steel" Transformers (the world's toughest) for that extra margin of dependability under all operating conditions.

Free "New Equipment" Catalog

Get the full details on CHICAGO'S New Equipment Line—covering "Sealed-in-Steel" transformers designed for every modern circuit application. Write for your copy of this important catalog today, or get it from your electronic parts distributor.



Write for
CHICAGO'S
"New Equipment"
Catalog
Today

***COMPLETE.** There's a CHICAGO "Sealed-in-Steel" unit for every application: Power, Bias, Filament, Filter Reactor, Audio, MIL-T-27, Steppeddown, Isolation—all in one-piece, drawn-steel cases.

****VERSATILE.** Available in 3 constructions to meet most requirements—a type for every application.

H-Type. Steel base cover is deep-seal soldered into case. Terminals hermetically sealed. Ceramic bushings. Stud-mounted unit. Meets all MIL-T-27 specs.

S-Type. Steel base cover fitted with phenolic terminal board. Convenient numbered solder lug terminals. Flange-mounted unit.

C-Type. With 10" color-coded stripped and tinned leads brought out through fibre board base cover. Flange-mounted unit.

CHICAGO TRANSFORMER

DIVISION OF ESSEX WIRE CORPORATION

3501 ADDISON STREET • CHICAGO 18, ILLINOIS



reports during my term as SCM. I also would like to urge each and everyone to report to the new SCM, LUX. Let's give him all the cooperation that we possibly can to make his job more pleasant. Also a special thanks to EA, our SEC, who, in addition to doing a good job, never missed reporting.

73. Traffic: WSRW 150, EA 46, LUX 45, DRW 37.
LOUISIANA — SCM, Robert E. Barr, W5GHF — FYZ has just been appointed EC and holds OBS and OPS appointments. KRX, recommended by our RM, NG, becomes the latest ORS. LDH/LXX is an OES besides carrying on his duties in promoting the Amateur Radio Emergency Corps as Emergency Coordinator. Aetna reports are needed from all stations. Send them to the SCM.

MISSISSIPPI — SCM, Norman B. Feeham, W5JHS — 9080/5 is a new OBS and ORS appointee. ARRL bulletins will be sent at slow speed on 3700 kc. at 1930 CST and repeated on voice immediately after on 3975 kc. This is good practice for the Novice who can check his copy on the voice transmission. VME is on 7 Mc. PFC, TDO, and SYR are new calls in Jackson. PFC is on 75 meters and is a member of the GCH Net. Jackson mobile stations made a very good showing in the Civil Defense Parade. There are now 17 mobile stations operating on a net frequency of 28.592 kc. HIDA is working DX with A.C.-D.C. rig running 6 watts. FRY and SNQ are in the services. TLAP has closed down for the summer but WZ has a net to take traffic from the area. K5FBB checks into GCH, Tenn. 'phone, PX, RN5, OON, and TCPN Nets, which accounts for the FB traffic total. PGF has given quite a few hams throughout the State their first aeronautical mobile contact. Traffic: K5FBB 711, W5JHS 113, W2 102, RIM 101.

TENNESSEE — SCM, D. G. Stewart, W4AFI — This being the last report from your net, I am going to take this opportunity to thank each and everyone for your most excellent cooperation. It certainly has made the job easier and is truly appreciated. It has been a genuine pleasure to have served you. I am sure you will find CXY a capable, friendly, and willing successor and urge that you give him your wholehearted support. IIB recently received MARS Station of the Month Certificate for April of '51. This is quite an accomplishment. ELW demonstrated emergency gear and gave a talk on c.d. to the local Rotary Club. NNH is interested in 6 meters and is building crystal converter for that band. NPS is getting back into the swing on both 'phone and c.w. OGG, operating from Sewart AFB, turned in a nice traffic total. TRC, operated by KARC, made BPL on origination for seven months. New officers of the KARC are PJD, pres.; KJY, vice-pres.; SWW, sec.; CBU, net. mgr. UVP is active on 3.5 and 7 Mc. W4TJB, UQV, VVY, and USN are active in Johnson City. Traffic: W4CXY 150, OGG 149, ODR 128, TRC 116, IIB 91, PMR 16, RHO 16, AFI 14, SZI 12, FLW 11, NPS 10, NDC 2.

GREAT LAKES DIVISION

KENTUCKY — SCM, I. W. Lyle, jr., W4KKG — TAV and Nep send in a nice report on traffic. TAV says DX is not so hot. The band is always dead when she's on! Hi, FR delivered a lot of messages from overseas this month. JUA again makes top rating in Frequency Measuring Tests. JUA makes W4S. Congratulate URF is going up for Gen. Class ticket. CDA is working on new 20-meter final. WBG makes BPL with a nice total. VP received Extra Class ticket. Congrats. Doc. MGT works four nets! SSQ operates on 40 Mc. in Corbin. SZL keeps daily slack with TYP. MKJ is NCS of the 144-Mc. net along with TUV, TLU, OXC, NWT, and MMM. LVP, KMX, MOP, CNE, and KKG of Southern Bell, have been QRL with work. They handled microwave link for the Derby telecast. They know how it feels now to operate on 7000 Mc! Summertime is here again and everybody is getting sunburned. Take time out from that lotion application to drop me a line for the report, if it's only to lie about that string of fish you caught! Traffic: KAWBG 432, W4TAV 365, MGT 244, MWR 136, CDA 49, WQDDT 4 37, W4MKJ 28, KTA 27, VP 13, KKG 11, SZL 1.

MICHIGAN — SCM, Norman C. MacPhail, W8DLZ — Asst. SCMs: R. B. Cooper, 8AQA, and J. R. Beljan, 8SCW. SEC: GJH. RMs: YKC, UQV, and ELW. PAM: UTH. New appointments: EC (Benzie County) to JKE; ORS to HKL. AXP reports he and MHIL, ZWM, JGP, and WSNEL took part in the 4-hour CAP test of plane-spotting. The test took place Sunday, April 20th, and we understand it was very successful, with the amateur stations doing the long-haul traffic. GEH advises a new club is being organized in Zeeland with the Ottawa County gang reactivating the Monday night emergency net at 8 p.m. on 28.700 kc. TQP is trying out phase modulation. Sounds good. HKT still is drooling over his visit aboard the USS Courier, where he got a good, long look at the 150-kw. Voice of America station. NQ still is active on MARS nets. RJC says overseas traffic has slowed up a bit. THG says the OCD meetings in Detroit were very FB. Many Michigan amateurs attended the entire course. New officers of the Central Michigan ARC are ECL, pres.; TCY, vice-pres.; CKK, sec.; SCW, treas., with FSZ and TLJ on the board of directors. GJB advises the Great Lakes Emergency Net on 160 meters will be closed until Oct. 1st. UES took the big jump. When will the new XYL get her ticket, Don? EXZ is up to his grid leak, building new rigs for 21 and 420 Mc. ZGT made BPL for the third

straight month. This gal really moves it, and is the first one to top 1000 points in a long, long time. FNH is no longer a bachelor. We need more news items and club notes on those traffic reports — please! Traffic: (Apr.) W8ZGT 1018, IJC 410, URM 273, SCW 210, QBO 193, JYJ 169, DAP 142, T2D 132, ZLK 126, WNO 109, NZZ 101, ELW 77, NOH 75, CPB 66, RTN 59, AXP 53, COW 50, SPF 50, DLZ 43, THG 41, LR 36, IV 31, HKT 29, EGI 25, SJF 25, DQI 22, ILP 17, UGD 17, AQA 15, GJB 15, JPY 10, QIX 10, WVL 10, TBP 6, FX 5, KSL 4, LLD 4, PUV 3, TIC 3, CES 2. (Mar.) W8NOH 123, DAP 103, CPB 37, NZZ 30, T2D 16, UGD 15, IKX 14, DOI 6, YMO 2.

OHIO — SCM, John E. Slinger, W3AOW — Asst. SCMs: C. D. Hall, 8PUN, and J. Erickson, 8DAE. SEC: UPB. PAM: PUN. RMs: DAE and PMJ. Apparently the warmer weather has torn several of the lads away from their rigs, judging by the decrease in reports this month. ARO again made BPL, the "easy" way and also the "hard" way. Newly-appointed ECs are HON and QZC. IZD has been made OO, Class I. PEZ is AEC in Lorain and YFB the same in Elyria. ARO is arranging with 3CUL to handle overseas traffic during the summer shutdown of TLAP. BN needs outlets in Akron and Youngstown. GAV is closed down for rebuilding. TLW is working on SCR-522 gear for use on USCG auxiliary frequency. YGR participated in all campaigns of BN. LBH is struggling for his first 2-Mc. contact. W8KRAL is a new Case Tech in a small town. The 25th Anniversary Banquet of the BSWRA held on May 2nd was a great success, with almost 100 attending. Congratulations to RSP and UKS for their FB 88 scores. Local winners in the Cuyahoga County 10-meter groundwave contest were AJW and EMZ, while out-of-county awards were taken by DPH and BSR. CACARE has formed a TVI steering committee which is cooperating with the FCC. Detroit office TZO has rebuilt and now is on with 250 watts. AEB has taken over DAE's spot in SRN. CHI is temporarily off traffic nets while rebuilding. W8JYN QSOed 12 states his first week on the air. New OCARC officers are AUN, pres.; EYE, vice-pres.; WRL, sec.; and AL, treas. WRL is taking care of Ohio amateurs for the license plate issue set for next week. He can be contacted on Monday evenings on the Dog House Net frequency of 3860 kc. at 6:00 p.m. EST. YHH has been appointed director of CARA to replace HAM, who has left the State. According to reports, UPB is doing his usual spectacular job in c.d. work. ET has replaced BWC as West Park delegate to the CACARE. The latter has left Ohio. CARA's TVI Committee has been formed and now is functioning in grand style. AQ is trying to get his mobile rig to percolate. Springfield's Q5 tells us that JNK has a 522 transmitter on 2 meters. EPA received a JA card for WAC. DCJ has a new mobile rig, and IMQ passed his General Class test. The latest recipe to appear in Toledo's *Stack Gossip* is for orange cookies. Other notes state that GRJ received his Advanced Class license after only a three-day wait. AZB will operate portable W5 from Camp Polk, and CNI and ZNU are attending radio school in Pennsylvania. It is noticed that some of the older boys have become a bit lax in reporting. Let's oil up those creaking joints and get on the ball so that the younger bucks won't be showing you up too badly. Oh yes, another double traffic tie this month. Let's see what can be done. Traffic: (Apr.) W8ARO 543, EYO 361, DAE 140, CTI 126, YCP 95, AL 46, QIE 44, LG 35, TLW 32, YGR 30, RN 18, EQN 16, PMJ 10, AJW 6, ET 4. (Mar.) W8RN 46, TLW 14, EQN 12, GAV 11, AQ 8, IZQ 7.

Hudson Division

EASTERN NEW YORK — SCM, Stephen J. Neason, W2ILI — RM: TYC. PAMs: IJG, JQI, and K2CA. VP qualified for Extra Class license and is going for commercial. DVZ has just tied the knot. BTV expects DX with his new conical beam on 14 Mc. LEL has been maritime mobile and has just returned from Rotterdam. The Rip Van Winkle Club participated in Field Day activity. Two rigs were in operation using both A1 and A3 emission. The following calls were Novice, but now are General Class: KHQ, KJK, and IHL. EWO attended the YL get-together dinner held in Boston. Dolores is active on 1.8 and 3.5 Mc. NYS meets on 3615 kc. at 7 p.m., and NYSS meets on 3595 kc. at 8 p.m. These nets will remain on Eastern Standard Time. Novices interested in a section net are urged to drop a card to the SCM. Keep your appointment effective; check your endorsement date now. Albany County AREC did a fine job in the recent c.d. test held at Albany. The group was under the leadership of ECs AWF and SUL. HF recently moved to Pleasantville. BRS has been inactive since October because of high water in his cellar. Trafficators' Attention: Don't let the other fellow carry the load, pitch in and give him a hand. NYS and NYSS need your help and support. The present interest of HTH is DX traffic. The AARA has standard QSL cards and is planning a new year-book. A Ladies' Auxiliary now is associated with the Club. BNC again makes BPL. Please note Helen's total. Phil Rand, IJBM, was guest speaker at AARA. ETC is mobile on 144 Mc. UKA is QRL because of the illness of his XYL. Recent appointments: HF as ORS, K2CA as PAM, HEI as OBS. Endorsements: HTH as ORS, LRW as OPS. Traffic: (Apr.) W2BNC 1279, LRW 300, TYC 216, EFU

(Continued on page 82)

An important message for Amateurs in TV fringe areas

Television interference, particularly in fringe areas, despite the manifold work of hams, has continued to keep thousands of us off the air. Reputable television receiver manufacturers have, by and large, improved the design of their sets. But, as rapidly as the art has permitted, television viewers have stretched the range of TV transmitters. Pictures that are far from acceptable in an engineer's laboratory, somehow seem to satisfy TV fans.


TV and TVI

And, there is a large group of accessory manufacturers who have complicated our TVI problem, unwittingly perhaps, by selling television boosters or preamplifiers—some good, many mediocre. We, at Electro-Voice, make television boosters, and are mighty proud of them. They are *engineered* with the same skill and search for perfection that has been the hallmark of Electro-Voice products for over twenty years. But, as a result, we hams at E-V have contributed our share to the TVI problems by pressing on the frontiers of TV still further . . . a lot further than the average booster previously made possible!

How We Are Helping

We have tried to make a good product, and it has brought pleasure to thousands of families. Now through E-V, boosters are going to be better than ever . . . for customers and for hams. Every E-V booster is equipped with an integral high-pass filter where it can do the most good . . . right at the input of the amplification stage.

The E-V Booster was the first fully automatic, broad-band booster to be marketed. The E-V Tenna-Top Booster is the only broad-band, all-channel, antenna-mounted booster made. All E-V boosters incorporate a lesson learned long ago by amateurs, that high gain without low noise is useless. So, all our boosters have gain *plus* an extremely low noise factor.




E-V Boosters are going to continue to give a hefty boost to TV signals, but they will work equally hard to keep interference, ham and otherwise, out of the television receiver. Recommend an Electro-Voice booster to your neighbor! You will be doing him a favor and yourself too.

W9IOP


Electro-Voice

404 CARROLL STREET • BUCHANAN, MICHIGAN


Export: 13 E. 40th St., New York 16, U.S.A. Cables: Arlab



Model 3010 Super Tenna-Top TV Booster. List. \$88.00



Model 3012 Tenna-Top TV Booster. List. \$59.50



Model 3000 Super Tune-a-Matic TV Booster. List. \$57.50




Model 3002 Tune-a-Matic TV Booster. List. \$39.50

MICROPHONES • HI-FI SPEAKER SYSTEMS • PHONO-CARTRIDGES • TV BOOSTERS • TV DISTRIBUTION SYSTEMS



**More Safety...Less Guesswork
When You Use
-PRECISION-
TEST EQUIPMENT**



**Stay On The Air
With "PRECISION"
SERIES 85
AC-DC
Circuit Tester
(20,000 Ohms per Volt)
SELF-CONTAINED TO
6000 volts,
60 Megohms,
12 Amperes, + 70DB**

A compact, laboratory type, high sensitivity test set indispensable for test and maintenance of modern amateur communications equipment.

20,000 Ohms per Volt D.C. — 1000 Ohms per Volt A.C.

VOLTAGE RANGES: 0-3-12-60-300-1200-6000 A.C. & D.C.

CURRENT RANGES: 0-120 microamps; 0-1.2-12-120-MA;
0-1.2-12 Amps D.C.

RESISTANCE RANGES: 0-6000-600K-6 Meg-60 Megohms.

DECIBEL RANGES: From -26 to +70DB.

Complete with batteries and test leads.....**\$39.95**

PLUS superior physical features:

- ★ 4½", 50 microamps, Easy Reading Meter.
- ★ Heavy duty bakelite case 5½" x 7½" x 3".
- ★ Deep etched, anodized aluminum panel.
- ★ Recessed 6000 volt safety jacks.
- ★ Only two pin jacks for all standard ranges.

LC-1 LEATHER CARRYING CASE—Custom designed, top-grain cowhide case with tool and test lead compartment. **\$9.50**
See Series 85 and other famous "Precision" instruments, on display at leading radio parts and ham equipment distributors. Write for latest catalog.

Precision Apparatus Co., Inc.

92-27 Horace Harding Blvd., Elmhurst 13, N. Y.

88, ILLI 45, PHO 35, WN2APH 17. (Mar.) W2BNC 452, VP 19, HEI 17.

NEW YORK CITY AND LONG ISLAND—SCM, George V. Cooke, jr., W20BU—Asst. SCM, Harry J. Dannels, 2TUK, SEC, KTF, RM: TUK, PAM: YBT, The Tu-Boro and Nassau Clubs are setting up skeds around the country to handle traffic for the Ninety-Niners Women's Air Race over the July 4th week end. Favorable publicity should be gained from this endeavor. Your SCM noted the presence of BOT, QYZ, and B8P at the DVRA Old Timers Night in Trenton. YOT writes from AF base in Korea that he has itchy fingers for a key and hopes to be back again in October. KTF replaces SYW as SEC for the section. Good luck, Chuck, and we hope to have Ray contact us from Germany this summer, where SYW will be stationed with PAA. DRD was the first to report QSOs on the 21-Mc. band and worked a few locals despite heavy TVI to his own set. VFI, VSN, and WN2MRD are the latest members of the New York Radio Club and in the same club AMB, CYK, IXE, and ZKJ have received their Extra Class licenses. DRD has been appointed Brooklyn Alternate EC under BIV, Borough Coordinator, and the Brooklyn AREC boasts 110 members and held 22 drills during the month. BO will be in W6-Land for the summer. AEE, the Columbia University Club, is becoming active and setting up gear on all bands and using the call 8C/TS/2 until its new call letters are issued. EC reports the TLAP will maintain modified summer skeds on Mondays, Wednesdays, and Fridays at 1830 EST on 7260 kc. The Williston Park C.D. Radio Club was formed and elected OBE, pres.; QAN, sec.; IRY, vice-pres.; and VQY, trustee; and the Club awaits its new call. The Tu-Boro Club has revived its bulletin, *Sparks*, and is celebrating its 17th anniversary and creating activity by issuing certificates to members contacting five other members on any band or mode. DID attained OBS for the Smithtown Area nets. ZNM now is stationed in Washington, D. C. operates K4USA often and works at NSS as electrical technician. EEE became a member of the A-1 Operators' Club. AOD now is using automatic CQ tone wheel on 420 Mc. along with MWB and both Q80 QBM regularly. KAC is working Wls and 3s with three-element beam on mobile, on 144 Mc. on band openings. FI, Nassau EC, reports county control c.d. station was set up with good coverage over the entire county on all bands used. PRE, Manhattan EC, boasts 12 mobiles and 10 fixed stations, mostly on 10 meters. TUK, NLI Traffic Net RM, reports the net handled its season's high with 239 messages and 34 different stations active and states the net will remain on DST during the summer on 3630 kc. at 1930. LPI is maintaining 10 schedules a week and trying hard for BPL. GIO has received OES appointment for activity on 420 Mc. and will put a 420-Mc. TV signal on that band with its own sync. and blanking generators. 420-Mc. activity is lively in all parts of the section except Brooklyn and Richmond. Maybe a section 420-Mc. round table could be arranged. AAC and DIC are the newest OES appointees, along with DGF, who plans TV with a flying spot scanner. Traffic: (Apr.) W2BO 636, VNJ 349, AEE 232, EC 186, OBU 174, LPJ 156, GP, BIV 120, DZK 64, DRD 50, TUK 49, BGO 37, LRI 31, ZKJ 24, OUT 18, YBT 14, IN 13, BQJ 12, LKJ 12, DID 10, PF 9, W2KRY 6. (Mar.) W2PZE 10, IAG 7.

NORTHERN NEW JERSEY—SCM, Thomas J. Ryan, jr., W2NKD—SEC: VQR, RM: CGG, PAM: CCS. For the summer N. N. J. traffic nets are operating on Standard Time. "JN" meets at 8 p.m. daylight time. The Second Regional Net meets at 7:30 p.m. for the first session and at 8:45 p.m. for the second session. Anytime you have traffic, put it on JN and it will be on its way through the Second Regional Net. A very nice report was received from DRA concerning the organization in Rutherford. Headquarters station NPC is located in Borough Hall. DRA's staff includes LWW, NCQ, MJC, ODA, DBW, ANW, BLS, CDG, CPJ, NYI, IET, JJR, JLZ, LMQ, NDY, NEL, OV, QKT, and UZC. CUI came through with a 241 traffic total for the month. QPS, late of Maplewood, now is on 144 Mc. from Livingston. COT is running 200 watts on 144 Mc. The Livingston Club completed 144-Mc. converter project. A committee to investigate cases of TVI has been formed by the Northern New Jersey Radio Association. ADB is chairman, assisted by AQT, DOZ, JUO, and ZBY. The NNJRA has the following new members: WEC, TYW, IML, XJE, HEI, MOB, and K2DD. OUS is sending off Official Bulletins on 146 Mc. at 6:15 p.m. and on 1889 kc. at 6:18 p.m. on Tues., Thurs., and Sat. NIY received "Worked Canal Zone" certificate. LFI moved to Metuchen. VPL is studying sunspots and calling the turn on 144 Mc. LRO is the proud puppy of a YL. GRZ again is living in Highland Park. EKU is using a Twin Yagi on 144 Mc. CWK has 99 countries confirmed. ABL reports his son, ZEP, formerly a regular on JN and now in the Air Corps, is stationed at Keesler AFB, Miss. DXD now is mobile on 10 and 75 meters. LSH is new EC of Kearny. Area #3 in civil defense, as well as Essex County for ARRL, now is under the leadership of KLA. We strongly urge all Essex County amateurs to keep him informed of their progress with AREC and c.d. activities. Traffic: W2ANG 243, CUI 241, LMB 172, CGG 135, DXD 122, EAS 171, MTV 106, OUS 6, CJX 4, ABL 2, CWK 2, NIY 2.

(Continued on page 84)

MALLORY HAM BULLETIN

WHAT TO LOOK FOR IN A UHF TV CONVERTER

Dear OMI:

Many communities are preparing to welcome UHF television for the first time. As a result it is probable that you will be called upon by friends, neighbors, and relatives for technical advice regarding the possibility of using a VHF television receiver for the reception of UHF channels.

For your information, UHF reception is entirely possible from a conventional VHF TV receiver provided a suitable onboard Converter is employed ahead of the set. In such a combination, the original TV receiver functions as an i.f. amplifier, and UHF tuning is accomplished solely by means of the Converter.

Unfortunately, the effectiveness of this arrangement depends almost entirely on the skill with which the Converter was designed and manufactured. It is true that a well-designed Converter will tend to overcome some of the deficiencies of a mediocre TV set. On the other hand, it is just as true that a poorly designed Converter will always produce inferior results no matter how good the TV set might be. In view of this, a very deliberate study of every angle of UHF Converter design is justified before recommending purchase of this or that UHF Converter.

One of the points which must be considered is the tuning range of the unit. Does it provide reception of all UHF channels? Or does it limit the user to a choice of only a few of the available channels?

Does it have antenna pre-selection? (The answer to this question is exceedingly important to the amateur, because of the ever possible TVI as a direct result of poor input selectivity!)

Can it be employed with any conventional VHF TV set? Can it be installed without special tools and by non-technicians?

Is it stable in operation? Is it easily tuned, so that even a child can enjoy UHF television?

Does it have built-in low-noise i.f. pre-amplification to guarantee the best possible signal-to-noise ratio at all times? Is it complete? Does it have its own power supply?

Strictly from an operating standpoint, the size and appearance of a UHF Converter is of little importance. However, it is a well-known fact that recommendations to wives, mothers, daughters, sisters, and aunts must be made in good taste. So, the question of appearance must be considered!

Your analysis of a UHF Converter suitable for unqualified recommendation to associates should result in clear-cut affirmative answers to each of the above. Anything less, means that you haven't examined the characteristics of the Mallory TV 101, Inductuner® equipped, UHF Converter. The TV 101 design definitely includes each of the above . . . plus. Your QSL, letter, or msg. directed to TV 101 Bulletin, P. R. Mallory & Co. Inc., Box 1558, Indianapolis 6, Indiana, will get you additional information.



73,

Your Mallory Reporter

P. R. MALLORY & CO. Inc.
P. O. Box 1558 Indianapolis 6, Indiana

P. R. MALLORY & CO. Inc.
MALLORY



**Mighty
Midget**

of the Service World

Mighty Midget of all the V-O-M's! Slips into your pocket for making spot-analyses of D.C. and A.C. Voltage, Current, and Resistance. Has quick-reading scale, only one switch, 50" leads — alligator clips, banana-type jacks, self-contained snap-in type batteries, and plenty of ranges on the one-knob 14-position switch. Remarkable stability on voltage ranges. Completely insulated molded case. Get yours today! Triplet Electrical Instrument Co. • Bluffton, Ohio, U.S.A.

Model 666-HH Volt-Ohm-Milliammeter

ONLY \$24.50 AT
YOUR DISTRIBUTOR
(Price Subject to Change)

FOR THE MAN WHO TAKES PRIDE IN HIS WORK

Triplet

TRIPLET ELECTRICAL INSTRUMENT COMPANY • BLUFFTON, OHIO, U.S.A.

MIDWEST DIVISION

IOWA — SCM, William G. Davis, W0PP — Asst. SCM, Dr. Albert J. Ploog, 8SCA, SEC: VRA, RM: QVA, SCA, HMM, BDR crowded SCA for top traffic honors for April with 609 handled. Top activity in Iowa was that of the gang at Sioux City and Council Bluffs during the Missouri River flood, but reports from those participating are practically nil. The fellows did a great job and NXW, XYI, was in there pitching with the boys. BDR now has his Advanced Class license. DFD now is in New York teaching NFL is home on boot leave. SEF is EC for Harrison and Shelby Counties. YTA has his new VFO made and has received his appointment as Asst. Mgr. of TEN. New on TLCN is JMX. PZO has a new QTH and again is active on TLCN. BDL has a new final using 813. FDL reported that the fellows along the Mississippi all organized in anticipation of a flood. At a recent election YUA was elected NCS for the Iowa 75 Phone Net, with IYW, VCM, GIM, and NTB as alternates. PP is honorary NCS and the board of directors is as follows: PP, chairman, FRB, NTB, YRR, and DWD. Traffic reports were fine but news reports were very scarce this month. Traffic: W0SCA 703, BDR 609, YTA 204, QVA 131, BBZ 74, NYX 41, SEF 32, WMU 26, DIB 24, DFD 17, ATA 14.

KANSAS — SCM, Earl N. Johnston, W0VCV — SEC: PAH, RM: FDI, PAM, HEC. The QTH Net is doing real well at its new meeting time, 2030, Mon., Wed., and Fri. on 3610 kc. The Kansas 75 Phone Net is functioning on regular schedules handling quite a bit of traffic. Practically all drills have mobiles reporting in. We also notice new Acting Net Controls. W0HIAW, an ARRL member and also an RCC member, tells us that EZT now has General Class ticket. The Missouri Valley Emergency Net reports 90 traffic points. The Mo. Valley Radio Club was busy during April preparing for Field Day. IWS and CWG, of Atchison, monitored 3.9 and 28 Mc. during the flood and handled flood traffic when needed. WIT and NCV, of Topeka, have a 100-watt all-band mobile rig to go into Doc's car. It uses 829Bs in the final and also in the modulator. SWR, on 75 meters, and GCD, on 10 meters, are now mobiles in Topeka. Members of the KYRC "Steering Wheel Net" of Topeka recently drove to Lawrence for breakfast holding their session en route. The boss of the SWN, ECF, is a busy man. One Monday night his chinchilla population increased by three and the next night he was the proud papa of a 7-lb. YL jr. operator, and he hasn't missed an SWN drill. On Apr. 6th the Coldwater Amateur Radio Club held a hamfest attended by 50 licensed amateurs. Prizes were won by QNJ, for the farthest QTH, CKV, as holder of the oldest ticket, and W0HPF, as holder of the newest ticket. Traffic: W0BLI 220, NYI 217, FDI 33, PB 15, ICV 5, KXL 4.


MISSOURI — SCM, Clarence L. Arundale, W0GBJ — SEC: VRF. The St. Louis Amateur Radio Club met on April 18th and viewed the civil defense film "A Voice Shall Be Heard." This film has been shown at a number of clubs and is a very fine example of civil defense. Guest speaker at the April 18th meeting of the HARC was Mr. P. N. Powell, HGB, manager of the Precision Products Company. During the April floods in the Missouri River Valley, the Kansas City Red Cross Station, RVG, was active for a two-week period. Mobile stations were used at different points along the river and fixed stations frequently were used as relay stations. Stations reported to have participated in this emergency work were AWII, LBM, RVG, BGP, RDR, NDS, CBS, VRF, DNF, ITX, NNU, PCY, CBR, FHI, WHK, and K0FAY. Missouri was well represented at the "hamfest" sponsored by 5AAE at Eureka Springs, Ark. Harry Paston, from Headquarters, gave a fine talk to the gathering. The following additional stations handled traffic during the March Arkansas storm disaster: BCD, BGQ, BVL, DEQ, JXJ, LNK, RDR, NDS, NXJ, and VRF. K0WBD has a Viking I on the air, however a BC-610 is expected to be in operation soon. QXT and INI are active on 420 Mc. UBR has a new jr. operator. BVL reports the Early Bird Net is off the air until October. K0FAY makes a nice traffic showing. ZLN is running 500 watts to a BC-610 and makes first traffic report. EBE has rebuilt his new exciter and improved its efficiency. CXE is operating Viking I with Viking VFO. WAP is back on the air. QXO ranked No. 1 in the amount of traffic handled during 1951 in Missouri. New appointments: ZBR as EC, PML as OPS, and IQY as OPS. Traffic: (APR) K0FAY 223, W0BVL 195, GBJ 186, PME 144, CFL 132, K0WBD 105, W0ZLN 75, OUD 47, EBE 40, KIK 31, HUT 27, CXE 16, CKQ 10. (Mar.) W0IQY 117.

NEBRASKA — SCM, Guy R. Bailey, W0KJP — About 150 amateurs from this and adjacent areas took part in the flood emergency this month and YMU, who spent many hours in organizing and directing their work, is to be commended. ACH is building a new final for his rig. YOF is putting up a new antenna. GJI now is a cadet in the merchant marine. CC is building a TV camera. COY is reporting in the 75-meter net. The Ak-Sar-Ben Radio Club had a party Mar. 29th. The Club's c.d. mobile unit was the nucleus of the flood emergency operators. AQJ has a new HRD-30, and LRD is sporting a 75A-2. BXJ is doing a nice job as OO, and is having fun getting back on c.w. after his many years on 'phone. The c.w. nets are folding up for the season be-

(Continued on page 86)

*Any Way You Look
At It...*

....the Eimac 4-125A is
designed for economical,
outstanding performance.



TYPICAL OPERATION

(Frequencies below 120 mc.)

Radio Frequency Power Amplifier and Oscillator Class C Telegraphy or FM telephony (key down conditions, one tube)	
D-C Plate Voltage	2500 volts
D-C Screen Voltage	350 volts
D-C Grid Voltage	-150 volts
D-C Plate Current	200 ma.
Driving Power	3.8 watts
Plate Power Input	500 watts
Plate Dissipation	125 watts
Plate Power Output	375 watts

Long service, low replacement costs, high output with low driving power and all-around outstanding performance are some of the reasons why Eimac's 4-125A is the most popular 125 watt tetrode. This power tetrode enables the use of simple circuit design and minimizes TVI grief. Through the extremely low grid-plate capacitances of the 4-125A neutralization problems are non-existent in most cases. Two 4-125A's in typical class C telegraphy or FM fone operation, with five watts of driving power, will handle a kilowatt input—or a pair in high level modulated service will take care of 750 watts input. Rated at a maximum plate dissipation of 125 watts, the 4-125A is excellent for use as an oscillator, modulator or amplifier. If you're rebuilding or planning a rig, you'll find the 4-125A a money saving way to get top performance.


The 4-125A has the Eimac features of a pyro-vac plate, controlled emission Y3 grid wire, low inductance leads and input-output shielding. Get further information from your Eimac dealer.

EITEL-McCULLOUGH, INC.
San Bruno, California

Export Agents: Frazar & Hansen, 301 Clay St., San Francisco, California

Eimac
TUBES

Why all this Junk?



**WHEN
YOU CAN
HAVE
A
Harvey-Wells**

BANDMASTER

40 TO 50 WATTS

THE WORLD'S MOST VERSATILE X'MTR FOR MOBILE
OR FIXED OPERATION. NOVICE OR EXPERT
BANDMASTER SENIOR . . .

A complete ready-to-go phone transmitter including new crystal-oscillator — vfo switching circuit — Phone or CW — 100% break-in operation — Eight bands: 80, 40, 20, 15, 11, 10, 6 and 2 meters — No plug-in coils — completely wired and tested. Tubes: 6AQ5 Crystal Osc., 6AQ5 Buffer Mult., 807 Final, \$111.50
2-6L6 class B Modulators. Sturdy Steel Cabinet 12" x 8" x 8".

BANDMASTER DELUXE . . .

The last word in a versatile small transmitter for amateur, civilian defense and commercial use. Has built-in three tube preamplifier for use with crystal mike PLUS all the features of the Bandmaster Sr. \$137.50

Your Bandmaster is protected by a continuing Technical Service. It provides methods of adding new features as they are developed. No Bandmaster becomes obsolete or outmoded.

SEND NOW FOR LATEST CATALOG

Harvey-Wells Electronics, Inc.
SOUTHBRIDGE, MASSACHUSETTS
Export Dept. 13 East 40th Street, New York
Canadian Distributor: Canadian Marconi Co.
861 Bay St., Toronto, Ontario

cause of QRN. It is hoped to have many new operators next fall as the Novices find out the fun of handling traffic. JDJ is doing a fine job as SEC. and put in many hours along with HQQ and BXJ in coming up from Lincoln to work during the emergency. NVE and UVU, from Fremont, and VPR, from Lincoln, worked long hours away from their regular business. The SCM wishes to thank all of those who were active during the emergency, also the many Iowa hams who participated. Traffic: W0JDJ 126, FQJ 106, CBH 53, LJO 43, AUBS, BXJ 26, QHG 40, JED 10, HQQ 9, UFD 7, VPR 6, YMU 6, HXH 4, YSK 4, WKP 2, LRF 1.

NEW ENGLAND DIVISION

CONNECTICUT — SCM, Roger C. Amundsen, WHYF SEC.; LKE, PAM: STU, RM: KYQ, CPN, 3580 YLF; CN, 3640 kc.; CEN, 29,680 kc. With the advent of Daylight Saving Time activity has started its summer slump and very little of interest has trickled through in the nature of reports. TIB has its new Viking on the air. ODW has been working all bands from his comfortable position in bed recuperating from his recent operation. DHO works LO-NITE with his one-half watt crystal rig. EMF reports that he now has a Class B ticket and operates 29,680 kc. with a TBS-50. BVB still is busy with his OO work. BHM, ZL, and KV renewed ORS appointments. BHM is getting squared away in new location. RWD is finishing the c.d. station in Woodbridge. BVB is building a new rig that he hopes will be TVI-proof. Thanks for the traffic reports this month, but unless you include some news with them this space is going to be quite empty. It is impossible for any one person to report all the news of our section and it will have to be forthcoming from each and every amateur in the section or there just will not be any. So send along anything that might be usable and it will be digested and used to the best possible advantage. Traffic: (Apr.) WISJO 612, KYQ 263, EMF 178, AY 54, HXJ 50, NBS 45, LIG 43, BDI 39, RFJ 27, HYF 26, KV 26, BVB 24, HUM 24, RWS 14, ODW 11, NEK 8, RRE 7, DHO 2. (Mar.) WILIG 29.

MAINE — SCM, Orestes B. Brackett, WPTL — SEC: BYK, RM: LKP. Net frequencies and time: Pine Tree Net, 3596 kc., at 1900 DST, Mon. through Fri. The Sea Gull Net closed for the summer. AUG has been awarded the Extra Class license by virtue of the grandfather's clause. Others we know of who have Extra Class licenses are MJR, EBJ, TO, CBV, PMY, and DPJ. New Advanced Class licenses we know of are TLK, TAU, and SWR. General Class licenses are UPQ (XYL of LER), UZR, and VBV, a twelve-year-old boy from Belfast. VV has been ill and now is in Portland trying to get his strength back before returning to his work at Bingham. Sea Gull Net certificates were issued to EZR, LN, EBJ, PIZ, GLZ, SCS, and GMH. Traffic reports and news probably will be running light during the summer months but we sure would appreciate anything of importance that comes up for the Maine news. The radio club at Auburn still is growing, with two new members, Hank Martineau and Ray Small. Apologies to Vernon Burgess, of Caribou, for forgetting the nice report on the Aroostook County Radio Club, which held a meeting at Limestone with a fine chicken-pie dinner served by the Limestone gang. Those attending were JSY, SIL, UWT, SYU, TMY, 0DIE, VDL, HUL, HXQ, LYR, SFL, ILU, JPC, FDL, Alton Brindley, Sterling Tibbets, Gene McLaughlin, Clarence Benjamin, Milton McRae, George Lauman, and George Morris. Traffic: WISEJ 70, LKP 73, PTL 44, OHT 41, HXQ 18, EFR 13, QEK 11, OLQ 10, IXC 9, GKJ 3.

EASTERN MASSACHUSETTS — SCM, Frank L. Baker, Jr. WIALP — New appointments: ECs — RDV Sharon, ADM Canton, JXM Avon, RQZ Abington, QVN Randolph, MB, Scituate. OBS — MME, NFD, RDV. ORS/OPS — RDV. Appointments endorsed: OBS — RQZ, ECs — JSM Waltham, HKG Malden. PAM for 6 meters — AWA, OES — JSM, PKH, MEG, BHD, OPS — GDY, DJ, OOs — NF, AVG, ORS — DMS, GM and ALP attended the Norfolk County Radio Assn. banquet and the following officers were elected: NOV, pres.; GDY, vice-pres.; TJJ, secy.; AYI, treas. HSB has moved to Riverside, R. L. The Braintree Radio Club elected RDV, pres.; KPX, vice-pres.; AUU, secy.-treas. The South Shore Radio Club elected MME, pres.; OOO and QMD, vice-pres.; OTZ, secy.; TZQ, treas. Nat. Hallenstein, ex-LIMA, is the new engineer in charge of W1-Land. Sorry to have to announce the death of PCC. NBT now is in Quincy. QVK is living in Holbrook. TVV has a new beam on 144 Mc. and an antenna for 3.5 Mc. The Hingham Radio Club has the call VPR. Active on 144 Mc.: DSY and NWK Bridgewater, JQH Stoughton, WN1VOU Weymouth, WN1UMC mobile. QGH is back on the air on 28 Mc. TSB has TBS-50C and SX-71 on 28 Mc. JSM is active on 144, 3.5, 7 Mc. AXA is communication coordinator for Swampscott. UTT is Bob Morse of Haverhill. The Gypsy Radio Club had HP, GLN and QVY at the Great Bay Radio Club chowder party. Theory classes are given each Thurs. by REI. FEC, Middleboro EC, has station checking in on net on 1.8 Mc. The Quapanowitt Radio Assn. has a net on 29 Mc. Wed. at 7:30 p.m. BB, Winthrop EC, puts out a very nice bulletin. The South Shore Club had HDQ as a speaker. The Eastern Mass. Club and the Quapanowitt Radio Assn. had PKW as a speaker. QV has rig on 1.8 Mc., a 50-watter; also a rig for 50-Mc. mobile

(Continued on page 88)

Be Sure of Your Installations...Next Year
Use

Aptitude-Tested **MIKE CABLE** *Now!*

• Now, you can be sure of your installations with Belden Microphone Cables. They are *Aptitude-Tested* and rated to give you safe and complete knowledge of their characteristics. Furthermore, Belden Mike Cables are built for maximum service. Put them to work for you now—and be sure...specify Belden.

Belden Manufacturing Co., 4621 W. Van Buren Street
Chicago 44, Illinois

To You,
Belden's Golden Anniversary
Means

—product performance that can come only from a "know-how" that has grown through actual service since the inception of Radio.

—an ability to co-operate in pioneering new wires to meet or anticipate industry's growing needs.

In the years that follow

This Belden
Program Is—

—TO BE
CONTINUED



No. 8411

Nominal Capacitance 37 mmf per ft. Use particularly for lapel microphone.

No. 8401

Nominal Capacitance 25 mmf per ft. For crystal, ribbon, carbon microphones.

No. 8422

Nominal Capacitance 32 mmf per ft. Use specially for carbon microphones.

No. 8410

Nominal Capacitance 33 mmf per ft. For crystal, ribbon, carbon microphones.

No. 8412

Nominal Capacitance 68 mmf per ft. Use specially for carbon microphones.

No. 8423

Nominal Capacitance 54 mmf per ft. Use particularly for carbon microphones.

No. 8424

Use for interconnecting power cable for all electronic uses. Also microphone cable.

Belden *Radio WIRE*

The
Aptitude-Tested **LINE**

3 MICROPHONES DESIGNED FOR YOU...

BA-109... Flat frequency response from 40 to 10,000 cps. Nondirectional in the horizontal plane... output of 54 db below 1 volt/dyne/cm². Fits standard stand. List... \$22.50.



BA-106... Essentially flat frequency response from 40 to 6,000 cps. Output level—50 db below 1 volt/dyne/cm². List... \$19.75.



BA-116... Hand or desk model. Can be used with standard stand if desired... uniform response from 50 to 6,000 cps. Finest of the low priced microphones. List... \$14.75.



No matter how good your ham rig, your P. A. system or your tape recorder, you can only get out of it what your mike puts into it. You want a sensitive, wide range mike with flat response, yet you want a mike that is sturdy and trouble-free.

Brush had you in mind when they designed their line of microphones. Each Brush mike is engineered to do an outstanding job in its class. All use the exclusive Metalseal Crystal® which assures protection from both high and low humidity.

The 3 Brush microphones illustrated as well as the Brush Vibromike® and the Brush Lapel microphone are available from your local radio parts jobber.

Brush headphones—for the first time combine all the most wanted headphone features. See them at your dealer.

*T. M. Reg.

THE

Brush

DEVELOPMENT COMPANY
3405 Perkins Avenue • Cleveland 14, Ohio

PIEZOELECTRIC CRYSTALS & CERAMICS
MAGNETIC RECORDING EQUIPMENT
ACOUSTIC DEVICES
ULTRASONICS
INDUSTRIAL & RESEARCH INSTRUMENTS



and has Extra Class license. DJ is active on 50 Mc. The T-9 Radio Club held a meeting at CVM's QTH. BB reports RK, DDO, NWO, BCR, PBQ, QFO, MGP, 90WB, K/L, and GENE/1 on 21 Mc. the first day. URR, Woburn, is on the air. SS furnished field stations at the foot and on the top of Mt. Ascutney, Vt., for Conn. Sports Car Hill Climb. RLF has Class A. BHD has walkie-talkie for 28 and 144 Mc. CTR has 829B on 144 Mc. BB has new 32V-3 for portable emergency work. BGH has a new antenna. PU reports that the Deep Sea Dragnet is on at 11:45 A.M. MME is in this Net and also in T-9N. UE has a rig on 14 Mc. AKN is going to Charleston, S. C., with his boy, 48RA. EPE is active in Eastern Mass. Net. The Old Colony Amateur Radio Assn. had a radio booth at the Rotary Club's Exhibit with QKM, FGT, SE, HPV, and SCR assisting. WN1UPZ will be Net Control for the Novice net on 3725 kc. The South Shore Club's call, 1A, is being used for v.e.d. work in Quincy, with a station on at the Police Station. A meeting of Sector 5, Region 5, was held in Quincy with FWS, KWD, KCT, SH, OEJ, MD, OVK, ALP, QKY, ADM, CQN, MME, EKG, and Dedham civil defense director present. A net is going to be on Tues. at 8 p.m. each week. DMS has mobile rig on 28 Mc. PEX has BC-191 on 1.8, 3.5, and 7 Mc., also a BC-342N receiver. DWO put up antenna for NYL, TUD, on 1.8 Mc. TVZ is on 28 Mc. ICU is new EC for Amesbury, with RPB assisting him. New hams: VJL, ex-3NRF Boston, JVO Winthrop, VJQ Saugus, VJY, ex-WN0ELJ, WNs VKB Newton, VKD Newton, VKE So. Boston, VWL Revere, VLX Lexington, VLZ Weymouth, VMM Falmouth, VMO Salem, VKJ Boston, VKK Somerville, VKL Wilmington, VKO Falmouth, VKP Brighton, VKM Malden, VKR Weymouth, VKS Newton, VKT Lawrence, VMD Lynn, VMJ Watertown, VMU Braintree, VMV Cambridge, VMX Holbrook, WN1MA Newton. The New England Emergency Net on 1.8 Mc. wound up the season when Daylight Saving Time started with the following active: RQR, TKP, LSN, PNJ, QZR, QWP, TFE, MUJ, FEC, FVD, LAS, MGP, NWL, RSV, TOA, TTV, and LYD, with SS as NC and JFS Asst. NC. MLZ is on 28 Mc. TYP has mobile rig. RVK has HQ-129X receiver and beam for 28 Mc. KCP-UDF is out of the Army. OLP is a member of Walpole Propagation Society on 28,592 kc. Mon. at 7 p.m. HB is on duty at Charleston, S. C. The Eastern Mass. Club members were guests of the Yankee Radio Club in Salem. ENB has Tech. Class license. NWO is on 21 Mc. Traffic: (Apr.) W188 301, EMG 296, NUP 230, MME 147, JCK 133, UE 104, TY 87, EPE 67, DMS 28, PU 28, BB 15, RDV 15, AKN 14, AVY 13, BY 9, CTR 9, LM 7, PEX 6, DWO 4, QON 3, BGH 2, URR 2. (Mar.) W1QKM 150.

WESTERN, MASSACHUSETTS—SCM, Victor W. Paoonoff, W1EOB—SEC, JYH, PAM, RDR, RM, BVR. The summer schedule of West Mass. Net on 3725 kc. is Mon., Wed., and Fri. at 7 p.m. RHU placed 13th nationwide in the Westinghouse talent search. He is making plans to further his education at M.I.T. Extra Class licenses were obtained by HHQ, NY, and UD. New homes with new lawns, gardens, etc., are keeping many of us off the air, including COI, EOB, and JYH. Listen for BDV's 10-watt mobile from his York Beach, Maine, vacation-land. TZA would like to spend all his waking hours handling traffic. Wish the same interest could be aroused in a few more of our gang. Removing the TVI from a rig can be a tough job, but BVR has turned the trick. He says that ham radio was never like this before. SWJ is converting Command transmitters for 10 and 20 meters. This summer undoubtedly will result in a lot of station improvements. During this period I would like you to give serious consideration to the problem of improving our Western Mass. Net performance and participation. What can be done to reinterest you old-timers, and what is necessary to bring new blood into the net? Will you please drop me a line and let me know of your opinions and suggestions? A happy vacation to all of you. Traffic: (Apr.) W1BVR 55, TZA 31, TAY 28, EOB 22, SDT 12, BDV 10, RHU 10, GVJ 5, RRX 3, WN1TVJ 3, QJN 1. (Mar.) W1TZA 56, RHU 36, QJN 11, GVJ 8.

NEW HAMPSHIRE—SCM, Norman A. Chapman, W1LXN, RM, CRW. The N. H. N., 3685 kc. meets at 1900 Monday through Friday. The Merrimack County Emergency Net, 28.6 Mc. meets Tuesdays at 6:30 p.m. TNO reports he has made WAS. Ted says that Utah was the tough one. CNX is back on the air with a souped-up Harvey-Wells and a couch-spring antenna. The Great Bay Radio Club put on another "Good Time" at Hampton Beach. Cal Hadlock, from National Company, was guest speaker. The Concord Brassponders enjoyed a steak and lobster feed at the summer QTH of BFT, COC, TTU, and WN1VAU were initiated into the Club. The Fourth N. H. QSO Party was a huge success. Twenty-eight stations have now qualified for WNH certificates, with certificate No. 18 going to KP4KD, San Juan, Puerto Rico. If you missed the fun, be sure to make a date for the next one. Anybody working the DX on 21 Mc. yet? Traffic: (Apr.) W1GMMH 38, JNC 27, QJX 16, FZ 6. (Mar.) W1HHS 18.

RHODE ISLAND—SCM, Ray B. Fuller, W1CJH—SEC: MIJ, RM: BTY, PAM: BFB, RIN meets Monday through Friday at 1900 on 3540 kc. I am happy to announce the appointment of RVQ as Assistant SCM of this section. AI is an ardent and very active ham and can be contacted


(Continued on page 96)

GATES

10KW COMMUNICATIONS TRANSMITTERS...

5

Models to Choose From



The popular GATES HF-10 High Frequency Transmitter is available in five different models for applications in broadcast, voice communications, high speed telegraphy or combinations of these services. These fine transmitters have gained world wide recognition for their complete reliability and excellence of signal quality. They are daily handling a sizeable quantity of the intercontinent communications between nations, both government and private.

High level Class B modulation is employed for all voice or broadcast models. The low plate voltage (5000 volts) assures

reliability in line with high efficiency. Rated at 10 KW (telegraph) from 2-22 Mc. and 8 KW (telegraph) at 24 Mc., or 10 KW 100% modulated 2-18 Mc., 7½ KW at 22 Mc. and 6 KW at 24 Mc. These rugged transmitters are worth investigating for your future. Write for full descriptions and specifications.



Center cubical of GATES HF-10 Transmitter illustrates husky tank circuit design for high efficiency coverage over entire frequency range.

GATES

GATES RADIO COMPANY • QUINCY, ILLINOIS, U.S.A.
manufacturing engineers

2700 Polk Avenue, Houston, Texas • Warner Building, Washington, D. C. • International Division, 13 E. 40th St., New York City
Canadian Marconi Company, Montreal, Quebec

**Gm. 2000 umhos at only
45 Volts B Supply—
2.7 ma. plate current**



*These Performance Features
make the*
RAYTHEON
SUBMINIATURE
FILAMENTARY PENTODE
1AD4

**FIRST CHOICE OF HAMS FOR
PORTABLE BATTERY OPERATED GEAR**

For the best battery operated Class A RF Amplifier at 160 Mc. choose the Raytheon 1AD4. Thanks to its rugged, precision construction and its unusually efficient and dependable performance, this filament type subminiature tube approaches cathode type performance.

The Raytheon 1AD4 is another outstanding example of Raytheon's ability to engineer, develop and manufacture all types of electronic tubes—an ability that has made Raytheon subminiature, miniature, hearing aid, reliable, radiac, microwave, voltage regulator, rectifier and transmitting tubes, crystal diodes and transistors standards of quality the world over.

*Ask your Raytheon Tube Supplier to give you
information on the complete line of
Raytheon Special Purpose Tubes*



Excellence in Electronics
RAYTHEON MFG. CO.

Receiving Tube Division
Newton 58, Massachusetts

RELIABLE SUBMINIATURE AND MINIATURE TUBES
GERMANIUM DIODES AND TRANSISTORS • RADIAC TUBES
RECEIVING AND PICTURE TUBES • MICROWAVE TUBES

on most bands any evening. As his business takes him to all parts of the section, make yourself known to him and have a personal contact with a Communications Department official. NAARO held its first all-emergency power drill. The Club station was powered by a gasoline-engine-driven generator in the basement and six mobiles were in the field. Some flaws appeared that will be cured. That is the importance of drills in discovering weaknesses in emergency set-ups. NCX is the new president of NAARO, elected to fill the vacancy occurring because of the departure of KNE. LWA is active again on 10-meter mobile. DXer KG6GU now is residing here and awaiting a W1 call. BBN is recovering from surgery. His big traffic count is missed in this report. Traffic: W1TRX 56, 01K 30.

VERMONT—SCM, Raymond N. Flood, W1FPS—PAM: AXN. RM: OAK. Asst. RM: TAN. The Vermont-to-Outside QSO Party was a success despite the shortage of publicity. Forty-three Vermont stations participated, although some were limited for time. Watch for this next year. It will be bigger and better! JLZ reports a new Novice in St. Johnsbury, the Rev. Father Jean Paul Laplante, WN1VMC. Many Novices have taken General Class exams, those passing that I know of are WN1UBL and WN1UET. FB, girls! The Vermont C.W. Net went on summer sked May 20th. Look on 3520 kc. Mon., Wed., and Fri. at 7 P.M. EDST. The Vermont Slow-Speed Net will QRT for the summer. NDB/1 is a new c.w. net member. PZX, AHN, SS, SCE, and SIO supplied communications for the Magnet Auto Hill Climb of Mt. Ascutney. Traffic: W1OAK 181, RNA 132, AVP 118, FPS 43, IT 36, TXY 15, SVT 4.

NORTHWESTERN DIVISION

ALASKA—SCM, Glen Jefferson, KL7NT—Acting SCM, Jack M. Walden, KL7BK. NT has returned from an extended trip Outside, and will assume SCM duties from now on. The Fairbanks Club has done a fine job in getting communications set up for c.d., with its system inaugurated by Gov. Gruening. The Club also is getting well organized on the hamfest coming up Aug. 2nd and 3rd at Copper Center and is hoping for lots of mobile activity. 3892 kc. has been chosen for the calling frequency. A fixed station at the hamfest site will guard this frequency. Let's have a good turnout from the whole gang this year. The Fairbanks gang promises lots of fun for all. The Anchorage Club is growing steadily, with 60 members at present. AGU, AOT, AEE, and UM volunteered as a committee to try to trace down some of the extremely bad QRN in the Anchorage Area. They find that trying to locate anything definite reminds them of the proverbial needle-in-haystack situation. Best wishes to NT as SCM, and 73.

IDAHO—SCM, Alan K. Ross, W7IWU—Mountain Home: Application for AREC was received from PCZ, major at the Mountain Home AFB. Call at the AFB is K7FBL. IY from Grandview, visited me recently. He is on 80- and 40-meter c.w., but operates on 160-meter 'phone at times. Grangeville: Our new EC is KOG. W7NRKY applied for AREC and hopes to have his General Class ticket soon. Lewiston: IDZ is new OPS. ONP's third harmonic has appeared—a boy. OOW checks into the FARM, OEN, and WARTS Nets. Lewiston-Clarkston Radio Club officers are DJT, pres.; OOW, vice-pres.; OWP, secy. pres., and IFG, Assistant EC. FRM is EC. Blackfoot: LQU is on the FARM Net and also MARS. Rupert: IEY reports he is moving to Empire, Ore. While OBS, Louie has put out 368 bulletins since Jan. 1st. Thanks for your help in the Idaho section and good luck for the future. Boise: The Gem State Radio Club is holding summer picnics.

MONTANA—SCM, Edward G. Brown, W7KGJ—Special thanks go to GSV, who set up emergency equipment April 4th and 5th and handled emergency traffic for the Red Cross during the flood disaster at Havre, Mont. Other stations that worked hard handling this traffic were JDZ, CPY, LBK, OGY, IWW, HFW, BIS, FTV, MVD, JFR, NPV, EOL, FTO, BXL, 6HMA, 5OPQ, 4XJ, 0HOC, and K7FAR. WBSWTV is settled in Billings and has his rig fired up on 80 meters. Norval, better known on the air as Hank, is announcing for KGHL. BNU was in Billings shopping for a house trailer. Deck plans to retire soon and spend some time seeing the sights and meeting hams he has worked. The Rocky Mountain College Campus was the site for the Billings Club Field Day activities. Charles Crouter spent a 14-day leave at home with his mother and OM. CT. Charles is in the Naval Electronics and has just completed boot training. Sure would appreciate a few more activities reports. Traffic: W7JDZ 141, CT 57, KGJ 51, LBK 19, BNU 8.



OREGON—SCM, J. E. Roden, W7MQ—ESJ invites amateurs to contact him if interested in MARS, and he will answer all inquiries with no obligations. If again makes BPL with a score of 651. LAA is touring the Northwest, being on an extended vacation from his new California home. HSL says that OEN 3600-kc. Net is progressing satisfactorily but more stations still can be used to added advantage. MLJ is high score man in Oregon this month with a score of 732 and also makes BPL. LYN has been busy playing with radio-controlled boat and is quite pleased with results. RNU is a new Novice in Pendleton. He is the son of MQ, the SCM. Congratulations are in order for GNJ, who

(Continued on page 92)

HAMMARLUND

PRECISION-BUILT CAPACITORS

Hammarlund Capacitors, backed by 42 years of design, engineering and production experience, are today recognized by the military services, electronic manufacturers and research engineers, as the finest quality capacitors available. Since the founding of the Hammarlund Manufacturing Company in 1910, it has designed and developed capacitors that today are standard in industry. Millions of them are in use by almost every important manufacturer of electronic equipment.



NOW AVAILABLE!

1952

CAPACITOR CATALOG

This detailed and illustrated 12-page catalog is yours for the asking. It will be a valuable addition to your library of radio parts suppliers, for it includes complete diagrams and electrical and mechanical specifications covering the broadest selection of standard variable air capacitors available to the electronic industry.

FOR YOUR FREE COPY of the 1952 Hammarlund Capacitor Catalog write us today. All capacitors listed in this catalog are stock items which can be purchased from jobbers, dealers everywhere.



HAMMARLUND

MORE THAN 40 YEARS EXPERIENCE COUNTS!

THE HAMMARLUND MANUFACTURING CO., INC.

460 WEST 34th STREET • NEW YORK 1, N. Y.

for the high-power man!



MERIT HIGHPOWER Filament Transformer P-2943

Designed for highpower use in both Amateur and industrial applications.

Specifications: Sec. Volts, 5 — Sec. Amp., 30 — Insulation Volts, 3000 — Center tapped with primary taps for 110-115-120 volts, 60 cycles—Dimensions, 3 3/8 H. x 3-3/16 W. x 4 3/8 D.—DL Mounting . . . Will handle a pair of 250 TH's . . . 4—250 A's . . . 4—125 A's . . . 4—400 A's, etc.

Net Price — \$6.60

Merit Transformer Corporation
4427 North Clark Street
Chicago 40, Illinois



BURTON BROWNE ADVERTISING

has been selected as the outstanding radio amateur in Oregon for the year and was awarded a beautiful cup at the annual OARA Convention at Eugene. MQN, a new ham, has moved to Pendleton and is with Forest Service as radio technician, having replaced MRJ who has left to take a new position with RCA Laboratories. HAZ wants all who can to attend the big hamfest at Baker about the middle of June. This is an annual affair which seems to be growing each year and draws amateurs from 3 states. IM is new EC for Lakeview Area. HSL is a new ORS. SF also is new EC for the area between Oregon City and Salem. MLIJ maintains a radio with Japan and handles a lot of traffic from the boys overseas. Traffic: W7MLJ 732, 11 651, OJG 373, APF 222, HDN 96, GNJ 71, MQ 62, JLU 39, FY 33, ADX 32, LVN 30, HJU 28, HSL 27, KYO 26, NOB 23, KTG 19, BDN 18, HSL 17, IEJ 14, NFU 12, EUG 11, KLE 6, EDU 4.

WASHINGTON — SCM, Laurence M. Sebring, W7CZY — SEC, BTY, RM, FLX, PAM, NRB, KTL has Motorola installed in new car and now is 10-meter mobile. Clark County had a nice set-up for Field Day. KCU is against the FCC proposal to eliminate Advanced Class license. CWN has low-power phone on 3.9 Mc. to work mobiles. ESM is attending Mount St. Michaels in Spokane. New stations reporting into WSNet are BAQ, CZX, HNA, KZ, OHY, PYW, QCH, and QLE. EYW operates 2nd-3-meter rig with the Tacoma Emergency Net. FRU is on the mend after a serious illness. MSI finally has mastered TVI and is enjoying traffic work. AIB is busy with antenna experiments. JWE moved to new location with the same address. GVC built sound-powered phone system to aid in emergency work. RT, DL, ETK, LY, and others took in the OARA Convention. G blew up his transmitter and sent it to the factory for repairs. NSI is working on MBY's 2-meter rig trying to get 24-Mc. rock to oscillate on the over-tone. NTU is new OPS. Under the managership of BAQ a new net has been formed for newcomers to traffic ranks. Named "Washington Oregon Net" (WON) it will operate on 3585 kc. at 1600 PST Mon. through Fri. This is a restricted speed net, 15 w.p.m. maximum. Newcomers to traffic from Oregon and Washington are invited to join. PHO moved from Three Tree Point to Lake Burien and works 80 and 40 meters and holds sked with brother, QLE. NLT has 833A final on 20 meters. MKI is building half-kw. rig for all bands. Newest member of VARC is QGB, who just advanced from Novice to General Class. PFZ passed Advanced Class and received 2nd-class commercial ticket. QEQ is stationed at the Tacoma Naval station and works 10-meter phone. The Valley C.D. Net now has 3 mobile and 6 fixed stations on 29,510 kc. New Novice in Puyallup is RED. OIH is ready for action with his mobile rig. PHP has 80-meter portable rig. NNQ is rebuilding his 75-meter mobile. MCU is with the Coast Guard in Florida. JJK is at Camp Hood, Tex. OEB is Puyallup outlet on WSN. The VARC had a fine set-up Field Day. BAC is moving to San Diego and is putting up a 20-meter beam for GVT on the way. PGY and BA have new HRO-50-1 receivers. JNC and JXR are building all-band mobile rigs with VFO. PHV works for SERAD. FKL rejoined the ACS. LAF has beginners' radio class at Riverton Hts. AWP has 75-meter mobile with VFO in a 4 x 5 x 6 inch box. Traffic: W7IOQ 1114, CZY 1106, BA 410, EVL 248, FLX 154, MSI 95, KCU 71, AIB 56, FWD 56, ETO 40, ETO 40, ETO 27, OEB 23, PGY 18, MBY 16, EAU 14, KTL 10, NWP 9, JWE 8, EYW 7, GVC 6, GAT 4, NRB 3, ZU 3, NTU 2.


PACIFIC DIVISION

HAWAII — SCM, John R. Sanders, KH6RU — Considerable interest was aroused in Hawaii by the latest FCC Amateur Proposals. The clubs on Oahu, Maui, and Hawaii have all taken polls on the various issues. Nine Extra Class certificates have so far been issued in the section to EL, ZX, LJ, EM, DK, MG, KS, AO, and SL. Active at the opening gun on 21 Mc. were LJ, RU, MG, and YL. As we go to press with this report news comes that Hawaii will have TV shortly. Those many QST articles on TVI which we have been able to skip over so happily will have to be put to use now! Far Pacific Area: JA2ES/KR6JD is very active traffic-wise and has applied for ORS appointment. KH6AEX now is KG6. JA2KW reports a belated BPL total for March. KG6FAA's monthly totals continued to grow with solid BPL for more than a year now. Traffic: (Apr.) KG6FAA 2375, JA8AB 910, JA2ES 70. (Mar.) JA2KW 3884.

NEVADA — SCM, Carroll Short, Jr., W7BVZ — SEC: JU, ECs: HJ, JLM, JVV, KOA, MBQ, OXN, TJY, VO, and ZT. RM: PST: OPS: JUO, OD: LGS. Nevada State frequencies are 3660, 7225, and 29,360 kc. This is the last report of your present SCM. Beginning next month it will be Ray Warner, JU, who will be writing this report. Here's wishing him lots of luck and hoping he gets monthly reports from all appointees. MRN, JU, and BVZ are on 21 Mc. BVZ got Extra Class ticket — the hard way! MJP is portable on 7 and 3.5 Mc. PSG is on 3.5 Mc. from Nellis. Novice RNZ, in Gardnerville, was trained by TJY. VO has a new receiver, an AR-88, and a 2-kw. emergency generator. NWU is phase-modulating his little Collins rig on 3.9 Mc. KIO resigned as Las Vegas EC; OXX is the new EC. WN6FWX/7 now is WN7PKE. I'll still be watching 7225 kc. in the daytime. Traffic: W7JU 18.

(Continued on page 94)

A ONCE-IN-A-LIFETIME OPPORTUNITY TO



make
your hobby
your job

Although you are probably employed as an engineer in the electronics industry right now, how often have you said, when dreaming up a hot new circuit for your rig, "Boy, I wish I could make ham radio my job!"

Well, now you have a once-in-a-lifetime chance to do just that — if you've got the stuff we need! The type of man we're looking for is not just another engineer. He must be a top-flight man with an electrical engineering degree from an accredited college. He should have a good communication background, but more than that he should have a passion for true *creative* electronic engineering. He should be a man who loves to think up new ideas and work 'em out.

Are *you* that man? If you are, National offers you an exceptionally good salary, generous social benefits and a pretty swell bunch of people to work *with*. Most of all, you'll be working for the outstanding maker of ham equipment — you *can* make your hobby your job!

Write and tell us about yourself — where you went to school, what you've been doing, what you'd like to do — and, of course, include the usual details of age, marital status, present salary, etc. We'll give you a definite decision just as soon as possible.

A stylized, handwritten signature in dark ink, appearing to read 'W.A. Ruddy'.

President, National Company, Inc.

Write to
Personnel Department

NATIONAL COMPANY, INC.

61 Sherman St.
Malden, Mass.



**The Data
that Launched
Thousands of
Careers is
Yours FREE . . .
to show**

How

YOU CAN BE SUCCESSFUL in TV and ELECTRONICS

You can plod along for years, then something happens.

Your earnings rise. You become more confident.

"Luck," "Contacts," some may say.

But in your heart, you will know the answer: "Training."

And it all may have started the moment you filled out a coupon requesting a copy of a free booklet named "Your Future in the New World of Electronics."

From this data you get knowledge of where you stand in Electronics, an industry pleading for trained men.

More than \$7 billion in electronics contracts have been awarded for defense. Top manufacturers sold about \$3 billion worth of electronic merchandise in 1951. By 1960, radio-electronics should do no less than 10 billion dollars per year, excluding military orders.

Within 5 years, says the Chairman of the FCC, there will be 1,500 TV stations and in 10 years, 2,500. There are 14,196,000 TV sets and over 100,000,000 radios in operation. Countless positions must be filled.

To fill these posts, trained men are needed — men who somewhere along the line take time to improve their knowledge, their skills. Men who, today, perhaps, take two minutes to send for a booklet.

"Your Future in the New World of Electronics" shows you how CREI Home Study leads the way to greater earnings through the opportunities described above. An accredited technical school, CREI does not promise you a "snap." You must study to convert your ambition into technical knowledge.

Since its founding in 1927, CREI has provided thousands of professional radio men with technical educations. Leading firms choose CREI courses for group training in electronics at company expense, among them United Air Lines, and RCA-Victor Division. CREI alumni hold top positions in America's leading firms.

CREI courses, prepared by recognized experts, are practical and easily understood. You get the benefit of personal supervision by a CREI Staff Instructor, who knows and teaches you what industry wants.

At your service is the CREI Placement Bureau, which finds positions for students and graduates. Although CREI does not guarantee jobs, requests for personnel far exceed current supply.

Now is the time of decision. Neither luck nor contacts will propel you forward unless you have the skill to back them up. Only technical training can bring you increased earnings in this new Age of Electronics. Fill out the coupon and mail it now. We'll promptly send you your free copy of "Your Future in the New World of Electronics." The rest — your future — is up to you.

MAIL COUPON FOR FREE BOOKLET

CAPITOL RADIO ENGINEERING INSTITUTE

Dept. 167D, 16th & Park Rd., N.W., Washington 10, D.C.

Send booklet "Your Future in the New World of Electronics" and course outline.

CHECK FIELD OF GREATEST INTEREST

- ☐ TV, FM & Advanced AM Servicing
☐ Aeronautical Radio Engineering
☐ Practical Television Engineering
☐ Broadcast Radio Engineering (AM, FM, TV)
☐ Practical Radio Engineering

Name.....

Street.....

City..... Zone..... State.....

If residence school in Wash., D.C. preferred, check here ☐

SANTA CLARA VALLEY — SCM, Roy I. Cousin, W6LZL — SEC: AEV, EC: CLF, IXJ, JWD, QIE, CER, CLJ. The SSCARA had QYT from Stanford. The subject of the talk was Instantaneous Prediction of Radio Transmission Path. The Monterey Bay Radio Club had Professor A. Sheingold, of the Dept. of Electronics and Physics at Navy Line School. The subject of the talk was Single Sideband. The NPEC had a guest speaker from the Hopkins Eng. Co. The subject of the talk was Noise Suppression. The second meeting was held at its new location at the Elm Court Recreation Center, Spruce Avenue, So. San Francisco. PMK is the new club call of the NPEC. Next meetings are MMG and IUW as OO, and CLJ as EC of the Salinas Area. Endorsements of certificates went to AEV, CER, GFJ, and MMG. QNK and TFZ, who did very fine jobs as EC of their areas, have had appointments cancelled. New calls in the area are WN6, NOG, OJO, PBN, PIE. FYK still is looking for the TVI-proof rig. BPT still is going great guns in the traffic efforts. RFF is reworking the 20-meter beam while the band is in poor condition. ZXS is on 80 and 40 meters with new 832 final. GCG and NBD are on new 21-Mc. band. YWD got up a new 144-Mc. antenna at new QTH. MUJ is QRT while building a new house. The San Mateo County Amateur Radio Club held its Fifth Annual Hamfest June 1st at Coyote Point, San Mateo. The SSCARA is planning for its Annual Hamfest August 9th at the Wieland's Brewery, San Jose. RUO is chairman of the Bar-B-Que committee. CFK is in charge of publicity. Traffic: W6BPT 743, HB 31, MMG 29, RFF 6.

EAST BAY — SCM, Ray H. Cornell, W6JZ — Asst. SCMs: Guy Black, 6RLB, and Julio Amaro, 6WGM. SEC: RVC, RM, IPW, PAM, KZF. With your new job, East the task of writing up the section notes falls on RLB. Therefore, I can report a few things about the OM himself. Ray is a fellow who is always spending hours of his spare time doing things for other fellows for which he gets little credit. An example is running code practice three times a week. Ray is a genuine experimenter who can make his gear hum, fix it up and beg. At one time or another he has taken part in every kind of amateur activity — even 'phone! He recommends his S-36 with Panadapter and sniffer probe for stubborn TVI cases. Among those opening up the new 21-Mc. band at zero hour were JZ, KEK, and HEK. WB talked on pi networks to the NBARA and the SARO. The editor of the NBARA's monthly bulletin now is ARK, who does a fine job. JDO reports working a portable KC7. The May meeting of the CCRC was held at the home of DNX. A trophy is to be awarded the club with the best Field Day score, according to rules agreed on at the meeting. See WGM for details. Among those present at the April 19th Pacific Division Director's meeting were BF, EY, WGM, NJO, HRO, and QDE. All the TVI committees were sorry to hear of the resignation of Frank Roach from the FCC staff. Good luck in your new job, Frank. The SARO held its first hidden transmitter hunt of the year. The Richmond Club has reactivated its TVI committee. PLB is switching to 2 meters. RXW now is on the Peninsula. Traffic: W6IPW 192, QXN 152, JOH 124, EJA 13, WOD 11.

SAN FRANCISCO — SCM, R. F. Czeikowitz, W6ATO — Phone JU 7-5561, SEC: 6NL, Phone PL 5-6457. MARIN Area: EC: KNZ, Tamalpais Club EC: ZUB. Visitors at the April meeting of the Tamalpais Club were OEI, HST, and 0BMX, the latter from St. Paul, Minn. NEA was proposed for membership. YME's call was "pucked out of the hat" to be used as the Club's Field Day call. MQQ and FQS were appointed to serve on the Marin Area TVI Committee, jointly with Marin Radio Club members LUM and BCM. Reorganization now being complete, the Marin Club meets the second Friday in a new meeting place, the American Legion Hall, Larkspur, Calif. The Tamalpais Amateur Radio Club meets the third Friday in the home of OZC in Tiburon. All are welcome to both clubs. Santa Rosa Area: EC: LOU. Congratulations on their election to all the new officers of the SCRA. They are EBI, pres.; WDM, vice-pres.; and JTR, secy.; while DTV and DZM are the new directors. Mr. Frank Roach, FCC engineer, and R. F. Czeikowitz, SCM and Vice-Director, were present at the May meeting, to provide the Club TVI Committee, ADM, DZM, and KIW, with procedures and technical information on handling TVI complaints with the FCC. The meeting was held in Sonoma, with members the guests of the Naval Reserve unit there. The SCRA now has 16 stations on 144 Mc. and 6 on 28 Mc. active in civil defense. Many thanks to JTR for the news. The Sonoma County Radio Amateurs meets the first Wednesday in the Taproom of the Grace Bros. Brewery, Second St., west of the Freeway, Santa Rosa. Eureka Area: EC: SLX. New members of the Humboldt Amateur Radio Club are Larry Tipton, Bob Olsen, Henry Pierson, and Dalee Dolson, WN6JTD, who has an ARC-5, and has made more than 70 QSOs. Congrats to Gene Bass on his new Novice call and to KTV on his new Advanced Class license. J. Lane Dam has had a busy time — he has joined the HARC, has taken his exam for Novice license, and has received his "greetings" from the Draft Board. Remember the Simulated Emergency Test in October and prepare to do an even better job than was done last year. Eureka has been assigned TV channels 3

(Continued on page 96)

NOW AVAILABLE

ROTHMAN MODULATION

Broadcast Quality • No Over-Modulation

High Efficiency • Less Equipment



MARMAX 50 WATT MOBILE TRANSMITTER


Model MT-52. Net.\$79.50

With One Set of Plug-In Coils

The heart of the MARMAX MOBILE is the MARMAX MOBILE PLUG-IN MODULATOR MO-52. Also obtainable separately for your present Mobile Transmitter.

MARMAX MOBILE MODULATOR

Model MO-52. Net.\$12.50



1 KW MARMAX MODULATOR

Model KW-52. Net.\$54.00

High Fidelity Modulation for powers from 50 watts to 1 KW with built-in speech amplifier for high impedance microphones.

IMMEDIATELY AVAILABLE

If your favorite dealer cannot supply, write direct to factory.

All Units Complete With Tubes — Wired, Tested and Guaranteed


Marmax Electronics

716 NEW YORK AVENUE

ALAMOGORDO, NEW MEXICO

LICENSE

MANUAL



typical questions and answers
plus — license data and complete study guides for all amateur exams —

Novice

Technician

Conditional

General

Advanced

Extra-Class

50¢ postpaid

(no stamps please)

The American Radio Relay League

West Hartford 7, Conn.

and 13 — so start to clean up the harmonics in those rigs. See Phil Rand's TV Interference booklet for ways and means, as well as the many excellent articles in the past year or two in QST. The FCC is solidly behind the amateurs in defending him from unwarranted attack by TV viewers. But, above all, train yourself to be DIPLOMATIC for your coming investigations on TVI. Diplomacy is three-quarters of the battle. The Humboldt Amateur Radio Club meets the second and fourth Fridays in the YMCA rooms, rear of Municipal Auditorium, entrance on "E" St., Eureka, *San Francisco Area*. EC: BYS, Plans for the Pacific Division Convention, to be held July 4th, 5th, and 6th, are complete and an excellent time is promised to all by the sponsoring Central California Radio Council, and Larry Reed, chairman of the event. Preregistration is \$6.00 to June 21st, and registration AFTER that date is \$7.50. Send all registrations to Harry Witake, secy., 1256 Masonic Ave., San Francisco. The SFRC meets the fourth Friday at the American Legion Hall, 1641 Taraval St., and the High Frequency Amateur Mobile Society meets the second Friday at 1625 Van Ness Ave. Traffic: W6UEV 256, ATO 7. SACRAMENTO VALLEY — Acting SCM, Willie van de Kamp, W6CKV — JRY now holds Advanced Class license. TV reports 2-meter activity on the increase with some DX. Sacramento radio clubs held a joint meeting for Ken Hughes, VRG was visitor in the Chico Area. SYN's XYL now has her own call, OKF. Marysville boasts WN6LGX. JDN has good luck with n.f.m. on 32V-2. The Mt. Shasta Radio Club had rig at the Hobby Show. AF is having noise limiter troubles. KFO got 1st-class radiotelephone license and a wife and now is awaiting discharge. The GERC provided radio communications for the Chico State College Pioneer Day Parade. The treasurer of the Sacramento Valley Radio Club is QKJ, not QKT as recently reported. ILZ has been mobile for a year and got Advanced Class license in October, 1951. Traffic: W6PIV 205, JDN 83, KFO 16.

ROANOKE DIVISION

NORTH CAROLINA — SCM, J. C. Geaslen, W4DLX — This month adds another North Carolina name to the list of Silent Keys, that of R. E. Dawson, Jr., DSY, of Charlotte. Bob was known worldwide for his work on the DX bands. Congrats to Katherine, SGD, on winning the YL-OM Contest. The Asheville Club has reorganized with AFM, pres.; MZS, vice-pres.; VG, treas.; and E. P. Echards, secy. The Club has an active TVI Committee for the education of the TV lookers and servicemen; also classes for Novice and brush-ups for the old-timers. AKC reports that NCN closed down for the summer May 10th and hopes to see all the old members back fresh in September. The Tar Heel Net will continue throughout the summer months as usual. Let me remind the North Carolina gang to hold week-end gum-beatings a few kc. off 3865 kc. because our many mobiles like to get out on these nice week ends. One big home-station carrier can snow under all the mobiles. AKC, BDU, and DLX took part in the C.W. CD Party. REZ, CVQ, NYN, and DLX were active in the 'Phone CD Party. NYN won the last one. IPO, of Sanford, is home from Korea and back on 75 meters. Activity reports were low this month but with all these new proposals I guess you fellows are too worried to write. Let's keep the ARRL informed through our Division Director, CVQ, on how we feel about these recent proposals so that we don't come out on the short end of the stick. Traffic: W4AKC 213, RRH 138, IMH 135, BAW 56, BDU 42, PIC 40, DLX 19, CGL 15.


SOUTH CAROLINA — SCM, T. Hunter Wood, W4ANK — A club has been formed in Spartanburg with the following officers: CPZ, pres.; NTO, vice-pres.; and Ralph Queen, secy.-treas. The club is planning ARRL affiliation. FM has worked 4X4PK for WAC after 30 years hamming. RXO is Class I Official Observer and has a feature article in May CQ on mobile rigs. DMX, DX, EDQ, FM, and MPR were appointed OPS during May. All ARRL members should submit application to the SCM for official station appointment. TWW and TWX have received their General Class tickets. WN4RFI is on 80 meters from Clinton. SUE is on all bands with a BC-610 from Fort Jackson. DCE has been transferred to Guam. SOD has 12 watts on 40 meters from Naval Base, S. C. 8GBD has moved to Charleston. 1AKN was a visitor at the Naval Base Club. Ben Tean, W4DX, 1306 Fair St., Camden, S. C., has accepted appointment as Section Emergency Coordinator for South Carolina and all ECs should report their activities to the SEC without delay. Traffic: W4ANK 480, THR 113, CHD 76, FM 18, EDQ 8.

VIRGINIA — SCM, H. Edgar Lindauer, W4FF — Word has been passed down that the week-end period beginning Oct. 11th has been approved for the Roanoke Division Convention to be held at Richmond. The place is Hotel Jefferson. There will be plenty of timely technical talks and demonstrations. Formal announcements and programs will be mailed later but in the meantime make plans to attend. Despite extremely poor conditions on most of the bands the 3rd Annual Virginia QSO Party brought out plenty of aspirants. C.w. was particularly troublesome on 40 meters with skip reigning throughout.

(Continued on page 98)

ALLIED has it!

THE NEW NATIONAL NC-183D RECEIVER



the de luxe dual-conversion receiver

NATIONAL's all-new top quality performer. Tunes 540 kc to 31 mc, and 47-55 mc. Covers 160, 80, 40, 20, 15, 11-10 and 6 meter Amateur bands. Double-conversion, 3 IF stages and 16 tuned circuits from 4.4-55 mc; single-conversion and 12 tuned IF circuits below 4.4 mc. Six selectivity positions (5 crystal). Selectivity: sharpest position 0.24 kc at 6 db and 7.2 kc at 60 db. Image rejection: 62 db at 10 meters. Has 1 uv. sensitivity on 6 meters for 10 db signal-to-noise ratio. Bandspeed calibrated for 80, 40, 20, 15, 11-10, 6 meters. Top features include: double-diode noise limiter and AVC on both phone and CW; S-meter; edge-lighted dials; accessory socket; auxiliary power socket; phono input; 500 or 8 ohm speaker output; audio output, 8 watts. In gray steel cabinet, 19 $\frac{3}{4}$ x 10 $\frac{1}{2}$ x 15". For 110-120 or 220-240 volts, 50-60 cycles AC. Supplied complete with 15 tubes, voltage regulator and rectifier. Less speaker. Shpg. wt., 65 lbs.

97-666. NC-183D. Only \$369.50

\$55.43 down, \$27.76 mo. for 12 mos.

97-719. NFM-83-50 Narrow Band FM Adaptor. Adapts the NC-183D (or HRO-Sixty below) for NBFM reception. Plugs into accessory socket on receiver chassis. Shpg. wt., 2 lbs. Only \$17.95

97-663. NC-183DTS 10" PM Speaker. Housed in metal case to match NC-183D. 13 x 8 $\frac{1}{2}$ x 11". Shpg. wt., 12 lbs. Only \$16.00

ALLIED HAS IT! THE NEW NATIONAL "HRO-Sixty"

Virtually no images and a remarkable new standard of selectivity—the ultimate in receivers. Coils supplied cover 480 kc to 35 mc continuously; provide superb bandspeed on 80, 40, 20, 11-10 meters. Features include: 2 RF stages; 12 tuned circuits at 465 kc IF; voltage and current regulation, 6-step crystal filter, hi-fi P-P audio output; ANL with threshold control; phono input; "S" meter; universal antenna input. Complete with 15 tubes, voltage and current regulators and rectifier. Gray steel cabinet, 10 $\frac{1}{4}$ x 19 $\frac{3}{4}$ x 16 $\frac{1}{2}$ ". For 115 or 230 volts, 50-60 cycles AC. Shpg. wt., 84 lbs.

97-722. HRO-Sixty. (Price to be announced.)

97-789. 15-meter bandspeed coil for the HRO-Sixty. (Price to be announced.)

97-721. HRO-50TS. 10" speaker in matching cabinet. Shpg. wt., 10 lbs. Only \$16.00

97-717. HRO-50-XCU-2. 100/1000 kc crystal calibrator. Only \$24.50

The ever-famous HRO—
now with dual conversion!



ALLIED STOCKS ALL NATIONAL RECEIVERS AND EQUIPMENT

97-727. NC-125 Communications Receiver... \$149.50

97-728. 6" Speaker for above Receiver... 11.00

97-729. Narrow Band Adaptor for above... 18.95

97-724. Select-O-Ject... 28.75

97-711. SW-54 Four-Band Receiver... \$ 49.95

97-632. HFS Receiver-Converter... 142.00

97-633. AC Power Supply for above... 22.43

97-631. 6-Volt Power Supply for above... 52.40

All NATIONAL Equipment is available on ALLIED'S Easy Terms: Only 15% down, 12 months to pay



free 212-PAGE CATALOG

You'll find everything you want in station supplies in this complete 212-page Catalog. Get your FREE copy today. And get quick service, money-saving values, easy-pay terms, and real help from ALLIED'S Ham staff. Get and use your ALLIED Catalog!

ALLIED RADIO

ALLIED RADIO CORP., Dept. 15-G-2

833 W. Jackson Blvd., Chicago 7, Ill.

☐ Send FREE ALLIED Catalog

☐ Enter order for National Model

Enclosed \$ _____ ☐ Full Payment

☐ Part Payment (Bal. C.O.D.)

Name _____

Address _____

City _____ Zone _____ State _____

- **ELECTRONIC
DESIGN ENGINEERS**
- **TECHNICAL WRITERS**
- **DESIGN DRAFTSMEN**
- **PHYSICISTS**

Westinghouse offers you SECURITY AND OPPORTUNITY

EE's and ME's with over 3 years experience . . . a number of excellent positions are now available in our Electronic & X-ray and Air-Arm Divisions for work on:

- Broadcast Transmitters
- Power Line Carrier Communication Equipment
- Railroad Radio
- Radio Frequency Heating
- Medical and Industrial X-ray
- Commercial Radar
- Balancing Equipment
- Military Radar (ship, ground, airborne)
- Military Transmitters
- Specialized Electronic Equipment
- Fire Control Systems
- Automatic Pilots
- Guided Missiles

Check These Outstanding Benefits: Top pay, ideal working conditions, advancement on merit, graduate study opportunities, employee scholarships, paid re-location expenses, Baltimore location.

Send resume of experience and education to: Manager of Industrial Relations, Westinghouse Electric Corp., 2519 Wilkens Ave., Baltimore 3, Maryland.

If you are using your greatest skill in a defense industry, do not apply

YOU CAN BE SURE...IF IT'S
Westinghouse

SNH reports TVI has been defeated after much prolonged agony. Questionnaires for TCC stations are out. Look them over seriously and fill out for immediate return to Headquarters if you can qualify. RVO skeds Guantanamo Bay, Cuba, Tues. and Fri. and makes a nice link to the newly-acquired arm to our traffic system permitted by recent FCC-State Dept. Decree. LW operated at NSS Annapolis Naval Academy on Armed Forces Day. SHJ again hits BPL for the third consecutive month, with FOR duplicating his last month's BPL on deliveries. Virginia Phone Net climaxed the season operations with its annual picnic and hamfest at the farm of NV near Palmyra. IYI had his first 21-Mc. contact with KV4AA. JAQ and his 75-meter mobile was active in Virginia. Q80 Party hopping county lines for additional contacts. PWX drove 200 miles to Sky Line to surprise the gang with extra contacts on VFN frequency but couldn't squeeze in. PVRC is laying the ground work for a special mass meeting of all Novice licensees in the area with a view of indoctrination into the various phases of ham radio and the fields of interest that can be enjoyed with courses for hurdling the General Class. The men sparking that program are KFC and CC. We regret to announce the passing of RTO. Sam was a sergeant in the Marines and participated in the first landing on Guadalcanal ten years ago. He had been confined to Veterans Hospital, Dayton, Ariz., following an auto accident last February. Traffic: W8HJ 549, FOR 479, FV 129, FF 94, PXA 56, NV 52, JAQ 46, KX 46, SNH 25, CFV 24, NUU 23, IYI 18, OKN 15, RDJ 15, W3TT 4, 12, W4RYO 11, HQN 2, LW 2.

WEST VIRGINIA — SCM, John T. Steele, W8MCR — The Stonewall Jackson ARC exhibited the civil defense film "And a Voice shall be Heard" at its regular club meeting April 19th. Local defense officials and disaster chairman of the Red Cross were among the visitors. Some surprise was expressed at the preparedness of the city on which the film is based but it was well received and interesting. "March of Time" directed the production of the film under the supervision of General Electric Co. The Club meets the first and third Saturdays of each month and the members are active locally on 50 Mc. W8IJM, now W8IJJ, got his WAS in the Hallcrafters Contest. AUJ again made BPL. YPN has a new Viking. The Tri-City Club and KVARA co-sponsored a 10-meter emergency test run Sunday May 4th. Three fixed and six mobile stations were used. Manning the mobiles were L1LGB, CLX, QHG, DAR, ATF, and IJM, while the fixed stations were operated by ETF, HZH, and IAJ. Excellent results were reported. Traffic: W8AUJ 734, BWK 77, YPR 32, FUS 21, GEP 9.

ROCKY MOUNTAIN DIVISION

UTAH — SCM, Floyd L. Hinshaw, W7UTM — Flood Patrol activities preclude sending reports this month. It is known that JVA has been Acting Net Control Station for 10-meter patrol of flooded sections of the Salt Lake City Area, and further news will be reported after the emergency passes. UTM has been practically inactive this month because of work QRM caused by illnesses in his office. Traffic: W7UTM 252.

WYOMING — SCM, A. D. Gaddis, W7HNI — The YO Net affords a practical means for handling traffic in Wyoming. Check in on 3622.5 kc. — we need your help. PKX makes BPL. A good job well done, Wally! OZK is the new EC for Cheyenne. GZG is helping on the net. AEC is planning an egg-throwing contest for the hamfest. Watch out, Margaret! Lloyd Michaels is new president of the Laramie Club. KFY has new 75-ft. vertical. ROK has received his ticket. Congrats, OM. The Casper gang reports plans for the biggest and best hamfest are near completion. It should be the event of the summer with contests and prizes galore, so don't miss it. Traffic: W7PKX 527, K7FAO 89, W7HNI 16, GZG 11.

SOUTHEASTERN DIVISION

ALABAMA — SCM, Dr. Arthur W. Woods, W4GJW — A ATF and AUP claim first occupancy of the 21-Mc. band in Alabama at the stroke of 2:00 a.m. May 1st. BFM meets AENP, AENB, and 3 MARS nets. In addition to the Tennessee Net, DID now is using 810s in the final and feeds antenna with coax. DXB meets AENP reliably. HFP says it's 50-50 traffic and ragchewing at his shack. KNW meets AENP and AENR regularly. MVM, now in Birmingham, meets AENB and RN5, and also MARS Net, besides scoring 4965 in the CD Party. Another regular is PPK, who calls in on AENP, AENB, and AENR. RTI reports that WN4VSE passed her General Class exam two days after receiving her Novice ticket. Traffic: W4HFP 56, BFW 48, KNW 38, MVM 22, DXB 12, RTI 11, DID 8, GJM 8, PPK 8.


EASTERN FLORIDA — SCM, John W. Hollister, Jr., W4FWZ — The passing of DU is recorded here in deepest sorrow. The memorial service for Doc by the K. of Kc. Net is worthy of mention. Recent ARRL appointments: SHG as EC, OVO as EC, AWY as EC, AKF as OO, TRA as ORS and OO, TRP as OBS and OO, TVQ as OO. Here is the Novice net information: TRA and a group of Novices (Continued on page 100)

Look AT ALL THAT'S New at TERMINAL

FIRST with the NEWEST for PEAK PERFORMANCE!

New SONAR 3-BAND RECEIVER Model MR-3

A real communications receiver, tailored to your needs for top mobile performance plus compactness!




Covers 75, 20 and 10 meters. Stages: 12AT7 grounded grid R. F., B. F. O.; 6UB osc.-mixer; 2-6CB6 I. F. stages (6-7kc); 6AL5 2def., N. L.; 6AT6 audio; 6AQ5 audio (4.5 watts); OB2 voltage regulator. Sensitivity: 1 microvolt. A. N. L. and B. F. O. push button operated. Requires 250 volts at 80 Ma. D. C. Supplied with tubes, but less power supply and speaker.

89.95

New SUPERIOR POWERSTAT

Small in size —
BIG in
performance!




Model 10
This compact unit is actually a variable transformer rated at 150 watts capacity! Input voltage of 120 volts 60 cycles smoothly delivers 0-132 volts continuously variable. Only 3" diameter, 2 1/4" deep and mounts like any rheostat.

8.50

TERMINAL has the most complete stock of POWERSTAT in New York! Check with TERMINAL for POWERSTAT answers to your variable AC voltage control problems.

New GONSET All-Band Fixed-Mobile TRANSMITTER




35 to 50 watts multi-band "Commander" Transmitter

Famous GONSET brings you a 35 watts phone, 50 watts C.W. transmitter measuring only 5 3/8" high, 8 1/4" wide, 7 1/4" deep! Small enough for under-dash mounting in your car! Features: 1.7 range, matching to any antenna! Requires 300 volts D. C. at 200-235 Ma. and 6.3 volts at 3.15 amps. Complete with tubes and coils for 10-11, 15, 20, 40, 75 and 80 mtrs.

124.50

New NATIONAL NC-183D RECEIVER



A newly designed receiver — not a warmed-over version of the famous NC-183! New-type miniature tubes in the R. F. and I. F. circuitry for improved sensitivity and selectivity. Dual conversion I. F. System, with a 1720 Kc. first conversion frequency, gives sharp selectivity similar to the HRO-50-T1. Fully adjustable automatic noise limiter, amplified and delayed A. V. C., and instant band change. The finest communications receiver at anywhere near this price.

369.50

SPEAKER, 16.00
NBFM-83-50, 17.00
SOJ-3, 28.75

New MORROW 2 and 3 Band Mobile Converter



Features full-width illuminated dial, built-in automatic noise limiter, 3-gang 20-1 ratio tuning condenser, separate isolated coils for each band and stage, single-point tuning; high image rejection, birdies negligible; antenna trimmer on front panel, low drift precalibrated oscillator, AVC on preselector for no strong signal blocking. I.F. output frequency 1525 Kc. Gray hammer-tone finish. Complete with instructions for easy installation with any auto receiver.

53.85

63.75

New HY-LITE



Well-known 2 and 3 element HY-LITE Beams are now available for 15 meters. Can also be supplied in combination with either a 10 or 20 meter or 2 or 3 element beam.

2E15T
(illustrated)
45.50
3E15T
59.00

New FREQUENCY ASSIGNED FOR MODEL RADIO CONTROL!

(Effective March 24, 1952, the frequency of 27.255 mc. has been assigned for radio control of objects or devices. The tolerance is .04%.)

PETERSEN CRYSTAL, Type Z-9
9085KC with high 3rd Harmonic output at 27.255 mc. This holder is similar to the Ham Crystal and will fit a Locust socket or the proper Crystal socket.

4.90

Terminal Radio Corp.

New York's Dependable Radio Supply House

85 CORTLANDT ST., NEW YORK 7, N.Y.

phone: WORTH 4-3311



**COMPLETE STOCK
IMMEDIATE DELIVERY
AT...**

HUDSON
RADIO & TELEVISION CORP.

PYRAMID

GLASSEAL

HERMETICALLY SEALED

Miniature

PAPER CAPACITORS

With Metal-Glass End Seals

★ **Surpass JAN Specifications
for Paper Capacitors!**

★ **Extreme Dependability at
Wide Temperature Ranges!**

PYRAMID

Send for Catalog!

**metallized
paper capacitors**

- ★ **Minimum Size!**
- ★ **Minimum Weight!**
- ★ **Maximum Quality!**

**Also Complete Stocks of Pyramid Paper
Tubular and Electrolytic Capacitors**

Send for Catalogs!

LARGEST STOCK OF JAN COMPONENTS

Your Inquiries are Invited!

One Call for All!

HUDSON
RADIO & TELEVISION CORP.

2 Great Salesrooms in New York City

48 WEST 48th ST. • 212 FULTON ST.

Phone: Circle 6-4060

Teletype: N. Y. 1-1299

have it going! Net call is FNN. WN4TYI reports these Tech. Class calls: UKL, UCZ, WN4TYI, WN4UNW, WN4VPB, WN4VPC. Clewiston: It's BPL for PJU with a total of 1204. Gratton reports that 504 out of 599 received were overseas messages. Coral Gables: TRA, 13 years old, is one of our youngest ORS. Deland: PJJ has been MO'ing the K. of Kc. Net from around the State such as at LJM and AYX. Ft. Lauderdale: The April 7th Red Cross alert was tops and showed the AREC to good advantage. New Club officials: MLS, FNR, QBY, CON, JVF, LTG, ex-UP, and IM. Jacksonville: HWA, with a couple of CQs on 21 Mc., latched a ZL. JGD got some nice publicity for Florida and ham radio in the local press doing a good turn for VE1KK. Lakeland: NAK and the AREC are having regular drills. Miami: SAT ran up 10,800 points in the April CD Party with 5.4 watts. Orlando: TVQ reports the N dropped from the following, who passed Class B exam: TVQ, TVS, UHE, UHD, UGT, TKD, TFP, and THX. TVQ's dad, AWS, passed Extra Class exam. TVQ built new rig and an electronic key. Winter Garden: SVX says he and TAS, TJU, and SVW are trying to start a rag-chewer's net on 7250 kc. each Sunday at 3 p.m. West Palm Beach: RTX was elected mayor at Haverhill. Rebel Club members in contests: WNAUGD and UGT (now minus the N) were high for the section in the Novice Roundup. CKB was section high on c.w. in the CD Party, and glass-arm BRB was high in the 4th call area for phone in the CD Party. Traffic: W4PU 1204, PZT 241, FPC 226, DRD 188, W4VH 74, W4AL 68, TRA 62, HWA 45, OMN 38, FJC 34, ALP 27, FWZ 27, IQV 27, RWM 18, IM 14, NAK 9, SIZ 9, TYE 9, DES 8, IYT 7, NRT 7, TVQ 7, TKD 5, RT 4.

WESTERN FLORIDA — SCM, Edward J. Collins, W4MS/RE — SEC: PQW, EC: PLE. PAA has a new Extra First-Class ham ticket. VCB and UTB are now General Class and are awaiting a new 32V-3 Collins. Our midist and is a 6-meter man. UCY continues to be the DX man. FHQ keeps things going on 28 Mc. PTK and TTM had their ECO reworked by NJB. The EARS Hamfest was an FB outing. RJR won the left-foot sending contest. VMV is building a big rig. SZH is doing likewise. PQW has been mobile in W5-Land. DXQ is looking at high power. DAO wants HRO. RZY keeps 75 meters hot. AXP is rebuilding. NYZ is going mobile. MS is dreaming of s.a.b. rig and working 6 meters. ISW joins the gang on 20-meter phone. QK is contemplating 20-meter phone. BFD works 10 meters late at night. NN and AGB are doing an FB job on 75 meters. Traffic: W4AXP 3, MS 2.

GEORGIA — SCM, James P. Born, Jr., W4ZD — The Georgia Cracker Radio Club's Hamfest will be held Aug. 3rd at Dixon's Lodge on U. S. Highway 80 at Lizella, Ga. which is 12 miles from Macon. Tickets may be obtained by contacting NS, the Club's secretary, 129 North Candler Street, Decatur, Ga. TVN has a new mobile rig on 28 Mc., also a new 28-Mc. wide-spaced beam. TGO now has his General Class license and a new 28-Mc. mobile transmitter. GVV has a new 32V-3 Collins. MTS is building a vertical antenna for 7 Mc. OSE, our Route Manager, is doing an FB job with the Brass Pounders Net. The Camp Gordon Radio Club made all the members of the Amateur Radio Club of Augusta honorary members of their club. HYW has returned to the air with a Collins 310B-1 exciter and a 300-watt p.p. 4-65A final on all bands. K4WAR has a new 14-Mc. beam. VTA is the new call of the Confederate Signal Corps of Atlanta. EJC is building a 200-watt phone rig for the South Atlanta c.d. control center. POI has returned to Atlanta after a visit to KP4 and KV4-Land. The new call of Kenneshochee Radio Club of Marietta is BTI. PFA has moved from Macon to Atlanta and has a new 1-kw. 3.85-Mc. phone rig. EWN is moving to Baltimore, Md. The Macon Radio Club has a new call, BKM; also a new 400-watt all-band phone and c.w. rig. HZG returned to Atlanta from Miami for a visit with FBH, MTS, and ZD. Traffic: K4WAR 1463, W4OSE 179, EJC 45, POI 35, ZD 29, MTS 20, HYW 6, TVN 6.

WEST INDIES — SCM, William Werner, KP4DJ — SEC: ES, CP, a new OBS, will broadcast ARRL bulletins on 3925 kc. Mon., Tues., Wed., Thurs., 8 p.m. AST. A new 10-meter net is flourishing, with AQ, DJ, DU, IO, LX, OO, PD, PW, NL, HZ, FS, LC, and RA reporting to NCS CY each Friday at 8 p.m. on 28.8 Mc. KP4ID, installed on the main floor of the Red Cross Building in San Juan, uses 400 watts on 3925 kc., is NCS for AREC nets and soon will operate 28.8 Mc., 3925 kc., and 3550 kc. simultaneously using 3-kw. emergency power plant. UW renewed ORS appointment. NO has been appointed Assistant Director MARS. ZK is a member of the Old Old-Timers Club, having been continuously licensed for 40 years. W4ARK now is KP4RK. W4NRW/KP4 now is KP4SK. W4CG/KV4, now KV4BB, has a kw. on 75 meters. DV has 10-meter mobile and is adding 200 watts for 20/75M with 12-volt supply in the station wagon. CP, GN, IO, LX, MQ, PD, and PT joined the AREC. Traffic: KP4DV 7, DJ 6.

CANAL ZONE — SCM, Everett R. Kimmel, KZ5AW — An all-YL AREC net held its first drill in April, covering the entire Isthmus in a simulated daytime emergency in which the OMs were presumed to be away at work. SEC was NCS to get the gala started, but they gave him a bad

(Continued on page 108)

Walter Ashe AGAIN CUTS PRICES ON USED HAM GEAR

Sensational Reductions on Reconditioned, "good-as-new" Receivers and Speakers

All equipment thoroughly checked and guaranteed to be in normal operating condition. While the following is only a partial list of our huge inventory, bargains like these simply can't last. So act now and avoid disappointment. Wire, write, phone or use the handy coupon today! When ordering indicate first, second and third choice. All merchandise subject to prior sale.



National NC-183
Shipping Weight
64 lbs.



Hallicrafters 538-B
Shipping Weight
14 lbs.



Hallicrafters SX-43
Shipping Weight
58 lbs.



Send For Free List of
Additional, Money Saving
Values In Used Test and
Communication Equipment

Walter Ashe
RADIO CO.
1125 PINE ST. • ST. LOUIS 1, MO.



Hallicrafters S-388.....	\$ 34.50
" SX-42 (less speaker).....	189.50
" SX-43 (less speaker).....	119.50
" S-47 (less speaker).....	79.50
" SX-62 (less speaker).....	199.50
" SX-71 (less speaker).....	139.50
" R-42 Speaker.....	19.50
" R-44 Speaker.....	12.50
" R-46 Speaker.....	12.50
National HRO-5TA1 with speaker...	149.50
" HRO-7 with speaker...	175.00
" NC-183 with speaker...	199.50



Hallicrafters SX-62
Shipping Weight
68 lbs.

FREE! New 1952 Catalog

Send For Your Copy Today!

All prices F.O.B. St. Louis • Phone CHestnut 1125

Walter Ashe Radio Company Q-52-7

1125 Pine Street, St. Louis 1, Mo.

☐ Enclosed is \$_____ for
(Show make and model no. of used equipment desired)

☐ Rush Free Copy of Complete List of Used Test and Communication Equipment.

☐ Send new 1952 catalog.

Name _____

Address _____

City _____ Zone _____ State _____

FOR MOBILE It's MALLARD



NEW MALLARD THREE BAND CONVERTER

... provides extra sensitivity and rock-like stability needed for dependable Mobile QSOs. Excellent for fixed station use also.


Features: ★ Accurately calibrated nylon gear-drive dial with glare-free illumination ★ Slug-tuned coils ★ Low drain tubes ★ Easy—plug-in—connections ★ Low drift oscillator using 6AB4 tube ★ 1-f. amplifier with 1500 kc. output ★ Built-in noise limiter ★ Tuned pre-selector, mixer, oscillator. Mallard Three Band converter. **Amateur Net.....\$39.95**

NEW MALLARD MOBILE TRANSMITTER

High efficiency, top quality components, skilled engineering—these characteristics best describe the new Mobile transmitter.

Specifications: ★ 40 watts on 75, 20 and 10 meter bands, using 6146 final mod. by 6L6s PP ★ 2 xtal sockets with selector switch ★ ECO socket ★ Hi-level AM modulation 100%—Built-in speech clipper ★ Plug-in coils for highest efficiency ★ Antenna relay for push-to-talk ★ Low impedance co-ax output. New Mallard Mobile Transmitter, with tubes and coils for one band, less mike and power supply. **Amateur Net.....\$119.95**

Mallard Hi-Q Loading Coils



Hi-Q 20 loading coil for 20 meter band. Plated 1/8" copper wire. Weatherproof plexiglas housing. Provision for exact inductance adjustment. Sturdy, efficient! **Amateur Net.....\$8.95**

Hi-Q 75 loading coil for 75 meter band. Two pie-wound coils for greatest efficiency. Plexiglas housing and Insulux-treated copper wire to resist moisture and fungus and maintain high Q. Easily installed, adjusted to exact inductance. **Amateur Net.....\$7.95**



New! Hi-Q 10 & 160 Meter Loading Coils

Hi-Q10 for 5' whip, same construction as Hi-Q20, adjustable. **Amateur Net.....\$7.95**

Hi-Q160 for 96' whip, three pie-wound coils, same construction as Hi-Q75. **Amateur Net.....\$8.95**

Adaptors available for installing Hi-Q coils on non-standard mounts

Mallard Single Band Converters

Models 10N, 20N, 75N. **Amateur Net.....\$39.95**

Mallard Mobile Equipment by:

HARTLEY MFG. CO.

5810 West Erie Street

Chicago, Ill.

At your distributor's—or write to

HARTLEY SALES CO.

1616 Cord Street

Indianapolis 24, Ind.

time right from the beginning when they came back using the proposed and strange-sounding NATO phonetics which they had all taken the trouble to memorize. In the net were, as they called themselves, Kilo Zulu Fives, Alpha Coco, Bravo Metro, Coco Nectar, Delta Golf, Golf Queen, Kilo Alpha, Lima Metro, Metro Lima, and Nectar Nectar. Net procedure by the YLs was perfect and messages were all in proper ARRL form. WZ was the first man on 21 Mc. RV is Acting PAM and CZARA activities manager while PC is Stateside. FL built a neat vacuum tube-keyer. EE, LL, and LP are latest members of the Monday night AREC net.

SOUTHWESTERN DIVISION


LOS ANGELES—SCM, Samuel A. Greenlee, W6ESR—**1 SEC:** KXSX, PAM: PIB, RM: FYW, GJP, Section Traffic Net: L. A. Section Net (LSN) Mon. through Fri. c.w. 3600 kc. at 2130 (note new time). El Capitan Net (ECN), 3655 kc. at 1930. BPL this month was made by HK, KYV, GYH, NCP, GKM/6, and GJP. The section is going all-out in an endeavor to eliminate origination of the "junk" type of message. In our opinion, our services can be evaluated in a higher bracket than that value placed upon us when we solicit or are requested to handle message that should properly go by a 2-f. posted. In addition, the nets within the section are taking a dim view of traffic that seems to arrive by mule train. BLY reports: MYJ was guest of the Radio 50 Club; ISQ, HAM, and NXJ are new members; LVQ now is Class A; and CEA and FAI were back in W9-Land, digging out snowbound trains (they're diesel specialists). KLY is really in the traffic game. PMS is recovering from a long absence (note time traffic! Break MCAN-4 after 1100 PDST (3905 kc.). Extry! CMN is mobile (phone, yet). CK asks how come off-frequency, etc., operators don't seem to be in the Call-book. One for the revenooers, Pappy? DTY finally did it! He changed jobs to be on the bands more. OHX is graduating from H. S. IZO got a new Viking, FMG (mgr. of LSN) reports WPF has an OT certificate. WPF and IZO now is mobile on all bands. KYV gets his traffic the hard way, on a dead band. KXSX is completing a swing around LAX emergency nets. PIB finally licked Virus X. A new traffic man on ECN-LSN, HJK, age 12 (good, too), says a new club is starting in WLA. HK got himself a bass thaattt! W6N6NJU is coaching a friend for the WN county. Resides a jillion skeds, GYH likes to add to the Long Beach Club had a ham-booth at the L. B. Hobby Show, with GKM as bossman. Noticed DDE lately? The guy is everywhere there is a net. GJP says it's certainly a pleasure to listen to LSN since FMG took over, a hot net if there ever was one. FYW reports W6OXJ is a young'n who operates like an old-timer. LZS has a new mobile. YLRC news, per CEE, president, WSV is the proud mama of a new jr. operator, WNA QCV and OBZ are mother and daughter. They and AVE, KER, MFP, and NLM were among those at the April meeting. KQS is on 15, as is BHG, who worked the world including a VK on opening day. JXF is M/M with 50 watts. NVJ is on 10. GEB reminds us that CUF made a record score in the SS Contest; two of his "students" have their WNA's. GJP is coming up. Thanks also to BUK, CFL, EBK, EPL, LDR, PIB, WOO, and YSK for reports. MU asks "wha-happen" to 107 NCP reports a goodie: He was asked by HQX and HK to help get a medical priority message into Lawton, Okla., had just been monitoring a W5 on MARS, broke him and found his QTH as Lawton. The message consumed a matter of minutes from JA-Land and possibly saved a life! FKH (his son, 11, is W6N6YM) has snappy remote control job. AREC notes per KXSX, SEC: He regrets the resignation of VMW, COZ, and ZGZ. They did a grand job. New ECs: SW (Mt. Baldy); NSX (Long Beach); and VCU, back in harness for Glen-Area. He's mighty proud, suh, of his boys. Traffic: W6HK 3315, KYV 3005, GYH 1720, NCP 900, GKM/6 759, GJP 358, DDE/FAE 281, FMG 252, HLT 106, BLY 100, HOV 99, KQZ 72, KXSX 72, CMN 74, CK 54, GEB 52, OHX 47, IZO 29, COF 20, FW 17, KXSX 16, PIB 11, DTY 2, HJK 2, W6N6NJU 2.

ARIZONA—SCM, Albert H. Steinbrecher, W7LVR—This is your new SCM's first activities report. PLM has new GP antenna on 10 meters. PEF, daughter of PLM, got her Adv. CL; KQY, XYL of MAE, got her 6-m. Adv. CL; MID got his Ex. CL; and NYK got 3rd-class 'phone license. QAP is in Nicksville. JGZ, MLL, and PKU had good scores in the last CD Party. Tucson expects to have the Meade W. Powell Memorial Station, GV, in operation in the new Red Cross Building in October. NYK, Tucson EC, reports a c.d. station is being established, and advises Emergency Managers are available to anyone upon request. The 6-m. net in Tucson is composed of FGG, HUV, LFX, LLO, LVR, NVN, NYK, OFA, OXN, and TXM, is looking for DX around the State. Also on 2 meters are FGG, LVR, NVN, and UPF. Anyone on these bands, please report your activities. LNJ and LSK are on 2 meters. We regret the passing of THJ on March 20th. All present appointments will remain "is." Watch expiration dates and send in for endorsement. Additional appointments for RM, OO, OBS, OES, OPS, and ORS are available to anyone interested. (Continued on page 104)

Micro-Match

M. C. JONES ELECTRONICS RF MEASURING INSTRUMENTS

MORE QSO's PER WATT! Use an M.C. Jones Micro-Match SWR meter and get your antenna to really soak up the soup and squirt it out! Write for literature on other models for FM and TV transmitters... RF Power Meters, Monitors, etc.



MM 2


MODEL MM 2 SERIES

Measure RF power and standing wave ratio on coaxial transmission lines over a wide range of frequencies and power levels. Can be left in line to monitor standing wave ratio and RF power level while transmission line is in use. Coupler unit can be placed in transmission line at any point or mounted directly inside of transmitter. Range 3-162 mc; directivity more than 20 db; power loss less than 3/10 of 1 db. No power source required.

Model No.	Line Impedance	Watts	NET
MM2	52 ohms	20-500	\$41.25
MM3	72 ohms	20-500	41.25
MM4	52 ohms	2-500	44.50
MM5	72 ohms	2-500	44.50

Model MM 1

Measures SWR and RF power on open wire transmission lines from 70 to 300 ohms. Range 3-30 mc; power 10-1000 watts. Housed in single case; other features same as MM 2 series.....\$32.50



MODEL MM 1

MODEL MM 252 AND MM 272 DIRECT READING SWR & WATTMETER

Reads directly on 3 scales: 0-10, 100 and 1000 watts. Can be left in line at power levels up to 500 watts and used to measure momentary power up to 1000 watts. Continuously monitors power or SWR at levels up to 500 watts and absorbs less than 3/10 db power. Equipped with one meter for both power and SWR, a selector switch and a calibration control for SWR meter. Units connected by 3-wire cable. Range 3-162 mc. MODEL 252-52 Ohms Impedance EACH MODEL 272-72 Ohms Impedance...\$68.00

NEW!

JUST ANNOUNCED!

JOHNSON KIT FOR TVI-PROOFING VIKING I TRANSMITTER

At Last! You can eliminate television interference from your Johnson Viking I Transmitter. New kit includes meter and dial shields, filters, all formed shielding, hardware, chokes, capacitors and complete instructions. HARRISON HAS IT!

NET.....\$24.75


JOHNSON 52-OHM LOW PASS FILTER

Rated at 1KW power with low SWR. Better than 60 db attenuation at television frequencies. Low insertion loss. New design permits easy replacement of Teflon discs in case of damage or burn out. HARRISON HAS IT!

NET.....\$16.50

New DOW-KEY COAX RELAY

52-Ohm Line



with External SPDT Switch

A continuous duty relay containing only one moving part - AC types free of hum or chatter. Extruded dual body, precision machined to take standard coax connectors. All contact points pure silver. Handles full KW with reasonable SWR. DC types make positive contact even under severe vibration. Coils draw only 3 watts.

6, 12 or 24 Volts DC	NET \$10.50
6, 12 or 24 Volts AC	NET \$10.50
110 Volts AC	NET \$11.50

NOTE: Optional receiver shorting device protects relay against RF damage. Built in, if specified. \$1.00 extra.

**FREE!...NEW
HAM-A-LOG**

Write for your free copy TODAY! It's filled with the latest Amateur Equipment.

SINCE 1925 -
ELECTRONIC
PARTS AND
EQUIPMENT
DISTRIBUTORS

AMPHENOL

AMPHENOL FOLDED DIPOLE
TWIN-LEAD AMATEUR ANTENNAS

New Models Available Shortly
For 10, 20 & 40 Meter Bands

WRITE FOR PRICES
AND INFORMATION



HARRISON RADIO CORPORATION

225 GREENWICH ST. (10 West Broadway)

NEW YORK 7, N. Y.


Barclay 7-7777

Famous Guns



**Elgin Cutlass-Pistol,
Caliber .54, 1837 Model, made**

by C. B. Allen. Invented by George Elgin of New York, this formidable arm was intended to take the place of the cutlass and pistol commonly used by naval boarding parties. One of several variations of this weapon is the shorter Bowie-Knife Pistol.



**Kentucky (actually Pennsylvania)
Flintlock Pistol, Caliber .36, Revolutionary Period. Made by the same Pennsylvania gunsmiths who crafted the famous "Kentucky" rifles, these full-stocked pistols actually were rifles-in-miniature. Every "Kentucky" pistol is unique; the same gunsmith never made two alike.**

Instant-heating Weller Soldering Gun

For light or heavy work. Dual heat greatly increases tip life. Switch instantly to high or low heat as job requires. Pre-focused spotlights end "blind soldering". Exclusive tip-fastening arrangement assures full, constant heat. Shatter-proof plastic housing. Perfect balance. Low-cost, replaceable tips. Pays for itself in a few months. See at your Distributor or write for Bulletin direct.

Get SOLDERING TIPS, new Weller Handy Guide to faster, easier soldering. 20 pages fully illustrated. Price 10c at your Distributor, or order direct.

BETTER FROM GRIP TO TIP!

Weller SOLDERING GUNS

834 Packer Street, Easton, Pa.

The Finest Soldering Tool for the Finest Craftsmen

EAZON

Z Match Antenna Connector

A mechanical aid to good electrical matching. The type 3WA is dimensioned to allow the coax and center of the antenna to form a natural match when assembled. See the improvement over other methods of assembly. Types 3W and 4W make ideal junctions for stubs or harmonic traps. Made to fit RG/8U or 11/U. Wt. 4 ozs.

Type 3WA (see cut) Antenna Match \$4.60 Net
Type 4W Cross connector 3.60 Net
Type 3W Tee connector 3.00 Net

See your dealer or write to

DALLAS C. AKERS CO.

33 Greenwood Ave. East Orange, N. J.

Send reports and information for this column promptly after the 1st of each month. Traffic: W70XN 38, LVR 4.

SAN DIEGO—SCM, Mrs. Ellen White, W6VYM—Astr. SCMs: Shelley E. Trotter, 6BAM; Richard E. Huddleston, 6DLB; Thomas H. Wells, 6EWU. RM: IZG, ECs: IOK and DEY. The largest monthly traffic yet to be submitted to your SCM was run up by HQX, of Camp Pendleton, for a total of 6645. April traffic: TET, GTC, and IZG received their first BRAT certificates for April traffic. New to SSN and due for appointment as OR is SC of Newport Beach. TZB's new harmonic is competing with ham radio for attention these days. The Orange County Radio Club's class in theory and code is snowed under with applications! HJG has dropped the "N" from his call and is sporting a 10-meter mobile rig. A new YL in the SD YLRL, WN4UDM/6, is waiting for her new W6 call. Convention plans are hopping in the San Diego Area. The Southwestern Division ARRL Convention will be held locally in Balboa Park in October. For further dope, contact convention chairman, XYU. The YLRL 80 c.w. net plans to use 3735 kc. for its permanent net frequency, net meeting 9:00 p.m. PDT Wednesday nights. GIMG is presenting JAZES, Mt. Fuji, Japan, and hopes to be back in San Diego some time during this summer. DEY is planning construction of a 32 ft. by 16 ft. ham shack in the near future. The section award will lose K6CN to W4-Land. It'd like readers of this column to seriously think of applicants for the post of SCM. My term is up in October, so get going and pick applicants for the post. For details on applications, consult QST, Traffic: W6HQX 6645, BAM 765, ELQ 336, IZG 306, GTC 83.

WEST GULF DIVISION

NORTHERN TEXAS—SCM, William A. Green, N5BKH—Asst. SCM, Joe G. Buch, 6CDU. SEC: JQD, RM: QHT, PAM: IWQ, ETARC, under the guidance of IRC and LGV, entertained about 400 people at the Commerce annual picnic. ARK, EC for Fort Worth, had an excellent exhibit at the Alert America Show in that city with much traffic handled. During the visit of the same convoy to Dallas, ham radio unwittingly stole the show with its booth. Working under the direction of LEZ were the Grand Prairie ARC, the Caravan Club, and the Dallas ARC. Thanks to radio WEB for the publicity program. Our SEC met with the Lanessa ARC where e.d. plans were worked out with the police and the Chamber of Commerce. Traffic still is holding at a high level with 27 stations setting a record for this section. Super delivery was given by KPB, who drove 120 miles to deliver a message. NTX now is meeting every night on 3760 kc. at 1900 with all hands welcome. OHV is on 3999 kc. with a pair of 4-125As in single sideband, the first in this section. New equipment department: TYU has a 75-watt rig, TLW has an all-band 150-watt amplifier and modulator, SQW/VRX has a new call, LFN has that Extra Class ticket, UXY made a W6 contact with his first traffic. Traffic: W5QHI 1169, BKH 436, PAK 272, ARK 197, JOG 180, UTW 151, SQW 119, QMF 81, SNX 79, LEZ 56, IWQ 48, TLW 47, KPB 40, RRM 36, PXL 30, CWE 28, PCN 26, ASA 25, SGR 20, RHP 19, GZH 18, UFP 18, SRQ 12, PYQ 8, OHY 7, UXY 5, TYU 2.

OKLAHOMA—SCM, Jesse M. Langford, W5GVV—SEC: AGM, RM: OQD, PAMs: GZK and ATJ. The Tulsa Radio Club held a very successful picnic at Lake Claremore Sunday, May 4th, with a total attendance of 95, ten coming from Kansas for the event. Twenty-one mobiles were at the lake. EHC spent most of the month of April in Texas. LXX now holds an Extra Class license. UEH has new General Class license. UZG is a new resident of Oklahoma City. RIT is working on new shack. The Easter Pageant traffic from the Lawton Area was light compared to other years because of rainy, cold weather but was handled in good shape and all cleared by Sunday evening. OIZ will meet informally from May 31st until Sept. 2nd when the regular schedule will be resumed. OQD will vacation in California. FME is back from Korea and at home in Enid. The Southwest Amateur Radio Club meets the first Monday of each month at the City Hall in Fredrick. Club call is UVX. HDN is the president, with OZE vice-president. Skip has wrecked SW's schedules. BDX now is operating single sideband. FOM has 144-Mc. antenna and soon will be active on that band. SNL and SNM are engaged in a new business. OQB has moved to Cherokee. Traffic: W5MRK 525, FOG 430, FOM 301, WIRJD/5 234, W5GZK 214, QVV 214, OQD 160, JHA 137, MFX 125, VHY 118, RTT 115, MQI 93, KY 62, FKL 60, GVV 55, CRQ 25, LXH 24, ESB 11, HFN 10, SWI 10.

SOUTHERN TEXAS—SCM, Dr. Charles Fermaglich, W5JFF—RN5 meets on 3645 kc. Mon. through Fri. at 2000 CST. SJA is helping PDE get Class B and A tickets. CVQ is active at U. of T. ACL is experimenting. The Novice Emergency net of Texas, sponsored by the Texas State Guard, is doing nicely on 3726 kc. The Odessa Radio Club now is affiliated with ARRL. SJA reports RLY got 1st-class commercial ticket. STG is at U. of T. with FB TVI-proof 10-meter mobile. QPL operates a TV shop in Conroe. WN5TWB gets up at 3 a.m. to work DX. QJD, his XYL, RTT, and son SHB, are one of the most active ham families in East Texas. NHB is active on CERN and HEN and looking for 110-volt 60-cycle emergency plant. ULN now

(Continued on page 106)

"PICON"

There's a short but potent sentence in the Communications Act of 1934, as amended, which reads:

The [Federal Communications] Commission, if public interest, convenience or necessity will be served thereby, subject to the limitations of this Act, shall grant to any applicant therefor a station license provided for by this Act.

Thus the fate of an application for a new broadcast station, for example, may depend entirely upon the applicant's ability to demonstrate that his proposed station will operate in the "public interest, convenience or necessity." The phrase is so often used in Washington that it is sometimes shortened to "picon."

There is no space on the application form for an amateur station license, you may have noticed, requiring your proof of "picon."

Why not?

For a very good reason:

Because amateur radio as an institution, through your American Radio Relay League, has established itself as a service operating in the public interest, convenience and necessity. Proof of your individual right to a station license is furnished for you by ARRL speaking for the amateur service.



Are you doing **your** part to support organized amateur radio activities by membership in the League?

QST and ARRL Membership

\$4 in U.S.A., \$4.25 in Canada • \$5 elsewhere



THE
"ORIGINAL
DASHBOARD
XMTR."

EVERYTHING AT YOUR FINGERTIPS

with

SUBRACO MT-15 X

GO "DASHBOARD" MOBILE-

WITH TUBES

High impedance
input

\$109.50

Low impedance
input

99.55

... with this high quality, compact, efficiently designed, 30 watt AM phone 10-11 meter transmitter, small enough to mount in most glove compartments or under any dash. For complete details write for catalog Q-527.

SUBURBAN RADIO COMPANY

158 CENTRAL AVENUE

ROCHELLE PARK

NEW JERSEY

Unless You are Einstein



... why not let an ARRL Lightning Calculator solve that knotty problem, save hours of operating time, or time you might better be putting in constructing that new rig?

If you're trying to figure out how many turns to wind, you will find the answer by using the Type A Lightning Calculator. No more groping for formulae. Guess-work and doubt are eliminated. Be sure — and be accurate — with one of these dandy time-savers. Know you have a sound piece of equipment, a rig that operates correctly.

ARRL LIGHTNING CALCULATOR

Type A or Type B

\$1.00

POSTPAID ANYWHERE

36 LA SALLE ROAD
THE AMERICAN RADIO RELAY LEAGUE, INC.
WEST HARTFORD 7, CONNECTICUT



Founded in 1909 RADIO TELEPHONY RADIO TELEGRAPHY RADAR & LORAN

Courses ranging in length from 7 to 12 months. Dormitory room and board on campus for \$48.00 a month. The college owns KPAC, 5 kW broadcast station with studios located on campus. New students accepted monthly. If interested in radio training necessary to pass C.C. examinations for first-class telephone and second-class telegraph licenses, write for details.

PORT ARTHUR COLLEGE PORT ARTHUR TEXAS
Approved for G. I. training

has a total of 19 states worked. His XYL is WN5VNI. WN5URW/5 is very active on 80-meter c.w. RIH is clamp-tube modulating a 696 with 100 watts. RSJ and ADZ opened 15 meters at 0159.5 May 1st, each with 1 kw., but heard no one else. BZO is really turning out an FB mobile antenna. EYV is working 1s and 6s on 21 Mc. The Texas State Guard is sponsoring a Novice club in the Woodboro and Refugio Area. TSG is furnishing a ham shack and equipment. Membership includes WN5UD, WN5IYS, WN5VIQ, WN5VPC, WN5VPP, and WN5VPQ. The club is spearheaded by EYV. LS gave a swell program to the HARC on electronic voltage regulators. JYM has a new 400-watt rig on 75, 40, and 80 meters. MIZ is working on new 75 meter mobile rig. LSE now is on 75-meter mobile and is working on 1 kw. rig. DUG is helping Hank Schreier to get back on after many years. LLT is helping others to clear up their TVI. ADZ says the 14-Mc. beam works well on 21 Mc. but in reverse direction. RPW has 300-watt TVI-proof rig on all bands. LS is on 40-meter c.w. with at least 1 kw. NN also is running 1 kw. on 40 and 75 meters. TNR is building new 150-watt final for 10 and 80 meters. WN5VBR gets lots of QSLs. HPB soon will be active on 2 and 80 meters. LGE is active on 2 and 40 meters. FWC is heard from 2 to 160 with an FB signal. QZG has gone mobile. QJS reports 12 finished the first 12-week course of c.d. training. NZX is heard on 144 Mc. OPP and RWB have ham shack together and work lots of 20-meter c.w. DX. SDA is on 75, 20, and 10-meter bands with three-element wide-spaced beam. LLU has burned up VFO so he is rock-bound on 10-20-meter phone. BHO recently addressed the Bayshore Radio Club. UBX is going to 120 watts on 20, 40, and 80 meters. RSA is all set with emergency equipment. STG is at U. of T. on all bands and mobile. RVE is set up on all bands with fixed-emergency and mobile. UQG is active with all bands. DSH is active on 10 meters. NXX reports WN5TYI has mobile on 2726 kc., Texas State Guard frequency. HMO is a newcomer to Alice. PTV still is making with the traffic-handling. Traffic: W5MN 706, W4RZU/5 155, W5RIH 87, FJF 31, NIY 3, NPX 1.

NEW MEXICO — SCM, Robert W. Freyman, W5NXX — The State emergency drill was held Apr. 27th. The Los Alamos group had 12 stations active in Espanola Valley. State nets on 3633 and 3838 kc. and MARS were saturated by messages from field stations. Santa Fe operated on 75, 80, 6, and 2 meters. Albuquerque to Santa Fe was worked 89 on 2 meters. NFU is out of the hospital and back on 2 meters. LFH, MYQ, KCW, and NFU are active in Albuquerque-Santa Fe-Los Alamos-2-meter net. FKP, KWP, and KCW are going strong on 6 meters. RWB is using a kite antenna for effective coverage of the State using low power on 4 Mc. SPM, new Class A, has 26 states toward WAS with 20 watts on 7 Mc. LEF is new OO. JZT is working on new VFO. UVA is mobile on 75 meters. New Novices are WN5VES, in Zuni; WN5VRC, in Las Vegas. GGO has a new jr. operator. New clubs have been organized in Pecos and Tularosa Valleys. Extra Class tickets: CA, CTG, LEF, MUK, and NNE. RLI and UKZ, OM-XXL, are on 80 meters from Socorro. PLK has a new 32V-2 and Morrow 3-band converter. MYM is completing 300-watt phone-c.w. rig. OBZ and UZC now are with CAA in Las Vegas. Traffic: W5IGO 237, NKG 153, NXE 44, ZU 54, JZT 47, PLK 44, RMH 40, NJR 34, LRG 32, RMU 23, SPM 18, NZT 16, MYQ 10, DWB 8, UVA 8, PSV 6, PDO 2.

CANADA MARITIME DIVISION

MARITIME — SCM, A. M. Crowell, VE1DQ — SEC: FQ, RM, OM, EC, EK. Recent visitors to the Halifax gang were DL1XB and W4SAL. The former previously had QSOed OM and was his guest while here en route to Montreal. The latter was the guest of FQ, who still is local "Northern Messenger" for all points north. "When 14 Mc. is open." SI is the newest 3.8-Mc. mobile and uses an ATR-5 in his station wagon. Welcome back to OC, who returns after a long illness. We expect to hear VE3EV, ex-EP and VO6EP, on soon from Yellowknife, N.W.T., with a VES or fixed portable VE4. Active now on 3.8-Mc. mobile in this area are BC, DQ, ET, FQ, GL, JW, and PT. ED now is Official Observer. WL has his OES appointment. EK says things are not too good in BERU tests. DB got his DXCC at last but says PJ5 was disallowed. HI! KM, HC, PT, and LZ handled traffic during the Air Show at H.M.C.S. Shearwater. HC has been quite active on 3.5-Mc. c.w. because of a landlord who has BCL. We hear via the grapevine that OM, our RM, and WL, our OES, officially opened the 21-Mc. band in the VE1 section. Traffic: (Apr.) VE1FQ 131, YV 92, MK 57, AL 48, AAK 27, ZO 23, ABR 13, ABJ 12, XH 11, JH 10, DB 9, FR 6, ZM 6, PS 5, AAL 4, AAN 2, JL 2. (Mar.) VE1FQ 120.

ONTARIO DIVISION

ONTARIO — SCM, G. Eric Farquhar, VE3IA — Now located in Ottawa and looking for 14-Mc. contacts is Bill Stephen, ex-2LC, 3AD, now 3NM. BJR reports the following reporters on the Ontario section net: ATR, BBM, BL, BME, BMG, BOZ, BVR, BXX, DGA, DHV, DU,

(Continued on page 108)



HENRY RADIO offers YOU:

LOW PRICES: You can't beat my wholesale prices.

FAST SERVICE: You get fast service. I have big stocks of Collins, National Hallicrafters, Hammarlund, RME, Johnson, Harvey-Wells, Lysco, Gonset, Morrow, Mallard, Eldico, Master Mobile, Hy-Lite, all other receivers, transmitters, parts at lowest prices.

BIG TRADES: I want trade-ins. I trade big. Tell me what you want—what you have to trade. Get my offer. I pay cash for receivers and transmitters too.

TIME PAYMENTS: Get what you want and pay by the month. I give you better terms because I finance all terms myself. Write for details.

SATISFACTION: Try any communications receiver ten days—if you return it your only cost is shipping charges. I want you to be satisfied. Ask any ham about Henry Radio.

PERSONAL ATTENTION: You get personal attention. Bob Henry, W6ARA, runs the Butler store. Ted Henry, W6UOU, runs the Los Angeles store. Bob Henry can be reached nearly 24 hours a day, 7 days a week. Write, phone, wire or visit either store. Send us your orders and inquiries. Export inquiries solicited too.

Bob Henry
W6ARA

Butler 1, Missouri
Phone: 395

HENRY RADIO STORES

11240 Olympic Blvd.
LOS ANGELES 64
BRADSHAW 2-2917

"LARGEST DISTRIBUTORS OF SHORT WAVE RECEIVERS"

• WANTED • RADIO COMMUNICATIONS

THE United States Government has openings for radio operator-technicians who are interested in careers in radio communications and general electronics involving extensive overseas assignments.

Applicants should have the following technical qualifications: (A) Two years active radio experience in the design, construction, and maintenance of transmitting and receiving equipment and the ability to copy International code at fifteen words per minute, preferably on a typewriter. (B) Knowledge of radio wave propagation and practical design and construction of antennae.

The required personal qualifications are as follows: (A) Age, over 21 and must be able to pass a thorough physical examination. (B) Indicate a willingness to serve overseas extensively and in any location required.

Current starting salaries for non-supervisory radio operator technicians range from \$1410 to \$1205 per annum. Salaries, leave, promotions, employee benefits, transportation and baggage allowances, cost of living differential allowances, etc., are in accordance with current government regulations.

Interested personnel are requested to write a brief application letter to Box 1116, Main Postoffice, Washington, D. C. Considerable duplication of effort will be avoided if the following outline is adhered to:

1. Experience and training.

- a. Number of months radio training and type (college, service schools, technical and/or trade schools).
- b. Number of years radio experience and type (military, merchant marine, commercial, government).
- c. Amount of this experience in telegraphy and amount in construction or maintenance.
- d. Present radiotelegraph code speed.
- e. Present or past radio licenses, including amateur.

2. Marital status.

If your initial application appears promising, you will be sent full application forms upon which detailed information can be entered.

WE'RE READY

ON

15

METERS . . .
ARE YOU?

2 and 3 Element Arrays
ALSO
20-10-2 Meter Beams

Attention
CD
OFFICIALS

Whether you are using Amateur frequencies or a special assigned frequency, HY-LITE assures you the finest in construction and performance. Send us your specifications and freq. for our quotation.
• You're RIGHT with HY-LITE.

SEE YOUR DEALER OR WRITE
DEPT. 7-2 FOR PRICES

HY-LITE Antennae

Makers of Fine Antennas for AMATEUR • FM • TELEVISION

242 EAST 137TH ST., NEW YORK 51, N. Y.

**HY-LITE
BEAMS
HY-LITE
BEAMS
HY-LITE
BEAMS
HY-LITE
BEAMS
HY-LITE
BEAMS
HY-LITE
BEAMS**

EAM, EAU, GI, SG, and WY. Toronto's simulated emergency test of April, under the capable leadership of LL, was well attended and successful. The Ontario 'Phone Net on 3765 kc. continues to be a popular outlet. TRN operates on Eastern Standard Time on 3675 kc. A hearty welcome to DFX, a newcomer in Kincardine. VD reports he is almost surrounded by plumber's delights now. BLY tried out nip-and-tuck while home for the Easter holidays. DFE and MW are heard on AFARS. Though away from home quite a bit, BPE returns for LO-NITES. OJ confines his activities to 50 Mc. CJ, well-known as VP5BP, spoke to large audiences at meetings of the Hamilton Amateur Radio Club and the Norktown Club of Toronto on his second expedition to the Cayman Islands. BQF tried out 21-Mc. folded dipole. Welcome to Hamilton, BJR, ex-4EA. BIK is doing a fine job with code classes. Redecorating and wiring of BBV shack keeps Wes occupied. BGT has returned to AFARS Net. Home from Florida are DND and WY. BXB keeps an eye on new beam. The Oshawa Hamfest went over with a bang. BJV does a nice job editing the Norktown Club bulletin. AJR, with her mobile, enjoys Southern Ontario highways. The Ontario 'Phone Club picnic will be held on July 6th at Queens Park, Stratford. Keep an ear to the mobile transmissions for details. Direct news from you fellows would be appreciated. Page 6 this issue gives the QTH. Traffic: (Apr.) VE3ATR 185, BUR 120, BJV 72, GI 50, EAM 39, IA 38, BMG 35, WY 25, PH 23, EAU 15, BPE 3, DFE 2, OJ 2. (Mar.) VE3BER 33, BUS 22, PH 14, VD 6.

QUEBEC DIVISION

QUEBEC — SCM, Gordon A. Lynn, VE2GL — HW, whose usual hang-out is on 40 meters, has been giving 80-meter c.w. a whirl and renewing old acquaintances on that band. He reports very little traffic and several days with the North Country missed because of poor conditions, and claims the first VE2 QSO on the new 21-Mc. band, working VE2IL at 12:01 A.M. May 1st. VP2GG and G13DZE visited CA. AHY is rebuilding the rig with a pair of 813s for 28 Mc. AHY and DH are AEC in their respective districts. ANC is building a 10-meter rig with an 813, and at present is on all bands c.w. and 144-Mc. phone. EY is building a 10-meter converter so he can participate in c.d. exercises. KG transmits ARRL bulletins each night at 1930 on 28,440 kc. and Saturdays and Sundays at 1300 on 28,550 kc. He has a 10-meter beam on top of a 50-ft. tower with a five-element 144-Mc. beam stacked on the 10-meter beam. Chambly County-Laprairie Section AREC held its first c.d. course in the St. Lambert Fire Station April 29th, with an attendance of 26 out of 35 enrolled members. AIO is quitting h.f. for 420 Mc. and is making good progress on his new receiver. WW has worked 6 countries and NI 10 countries on the new 21-Mc. band. WA claims 101 countries confirmed. YN is ex-VE3AGG and is on 75, 40, and 20 meters with HF-200 in the final at 200 watts, reactance modulated for the 'phone bands. AMB is on 75-meter 'phone with 616 30 watts modulated with a pair of 807s. Traffic: VE2CA 24, GL 14.

VANALTA DIVISION

BRITISH COLUMBIA — SCM, Will Moorhouse, VE7US — B — The VARC held a dance which was well accepted and many prizes were won. AMP is on in Alberni. Tye Club news is expected soon. QC has an excellent traffic total and is quite busy with his net work. He has 150 watts now. AMJ is active but nothing startling; he also is busy giving c.w. practice. AEW is interested in AREC. ACW is on 75 meters from Victoria. AOB is on with 350-plus watts finally. US discarded 833A and went back to 810s at home station. ASA QSYs to 80 meters for skeds on c.w. UT (LJ) QSYs to Estevan. ZT now is in VE4-Land for DOT. Mobiles in use in B.C. are becoming more active for the summer. DD has been reappointed as SEC for another year. Alberni DARC has been reorganized with 25 members and should produce results. AFO-10D mobiles are having QSOs daily across lunch-tables. Y1/M is active on AREC again. A new ham for the lower Fraser Valley is AQH. AQS is back on dry land and running 2 watts. SH finally broke the silence with 15 watts input. Parksville is at last on the air — JI. DH can always be counted on for contact on 3755 kc. US again is mobiling in the interior of B.C. Traffic: VE7QC 96, Y1 17, DH 9, AOB 6, AMJ 3, CX 2.

PRAIRIE DIVISION

SASKATCHEWAN — SCM, Harold B. Horn, VE5HR — SEC: BZ, PAM: JW, RM: TE. Activity has been low this month and so were reports. 50 Mc. is taking an upward swing with quite a number of the boys giving it a try. The Moose Jaw gang, CO, HE, OM, AR, and NC are on every Sunday at 1300, as are EE and JF at Saskatoon. The Yorkton gang also is getting organized on that band. JK reports hearing signals on 50 Mc. but no DX. QL has a four-element rotary wide-spaced beam and converter working and is starting on transmitter next. JF now is OES. LY also is CHJIS on AFARS. UO has new Commander receiver. The Moose Jaw Club now has a station with the call MA. HR got in on LO-NITE but the band was poor

(Continued on page 110)


HARVEY HAS THE MOST COMPLETE STOCK OF MOBILE GEAR

SONAR MOBILE Rcvr. Model MR-3

Complete coverage for 10-11-20-75 meters. 8 tubes, 4.5 watts audio output. Uses: 12AT7 RF stage and B.F.O.

12AT7 oscillator mixer
(2) 6CB6 I.F. stages
6AL5 2nd detector and noise limiter
6AT6 1st audio
6AQ5 audio output
OB2 voltage regulator

1 Microvolt signal produces 0.5 Watt audio output. A.N.I. and B.F.O. are push-button operated.




Requires 250 Volts at 60 to 80 mls.
Size: 4-9/16" x 5-3/16" x 5-11/16".
Complete with tubes... less power supply and speaker. \$89.95

Model SR-9 Receiver. A 9-tube superhet with built-in automatic noise limiter, voltage-regulated oscillator, and slide-rule dial. Sensitivity better than 5 microvolt. Size: 4-9/16" x 5-3/16" x 5-11/16". \$72.45

Model MB-26 Transmitter. 6-watt output... 6 standard tubes. Built-in antenna relay with connectors for power and antenna. Size: 6 1/2" x 7" x 5 7/8". \$72.45
AC Power Supply for SR-9 and MB-26 \$30.00

Note: Receiver and transmitter are available in a choice of 2, 6, 10 meters, and commercial frequencies, AM and FM, as well as 108-132 mc for aircraft.

JOHNSON VIKING Mobile Transmitter Kit



A low cost, efficient and extremely flexible rig, in kit form, ready for quick and easy assembly.

AMPLIFIER INPUT: Up to 60 watts 100% modulated, 30 watts input at 300 volts.

RF SECTION: Three full stages, 807 output amplifier.

AUDIO SECTION: 6BM6 speech amplifier, 6BH6 driver, and push-pull 807 modulator.

FREQUENCY RANGE: 75, 20, and 10 meters with provision for one additional band.

FREQUENCY CONTROL: Crystal... VFO input and power receptacle provided.

Other Features Include: Bandswitching, gang-tuning, crystal selector assembly, RF fixed bias supply, all stages metered.

Net Price... Approximately \$75.00

Available Soon!

Order Now for Early Delivery.

A HARVEY SPECIAL

#7 Stranded Wire

Heavy Duty Rubber Covered - Tinned. Ideal for Hooking Up Mobile Supplies. 50-foot lengths... each \$4.95



ELMAC-A54

Under-dash Mobile Xmitter.

Measures: 7 1/4" x 7 1/2" x 12"

Weights: 14 1/2 lbs.

For Carbon Mike Input... Net \$139.00
For Dynamic or Crystal Mike, Net 149.00
Power Supply, 110 volts AC, Net 39.50

MORROW CONVERTORS



The latest in Mobile Converters... Easy to operate... Sturdy construction for long, trouble-free service.

Model 2BR for 10-75 meters, net \$54.95

Model 2BRLN for 10-75 meters, net \$49.95

Model 3BR for 10-20-75 meters, net \$64.95

Model 3BRLN for 10-20-75 meters, net \$59.95

The LN series converters are identical to the standard 2BR and 3BR converters, less the noise limiters.

POLICE-ARM

Mobile FM Receivers

High quality, emergency band FM receivers for all applications. Brings in police calls, fire alarms, bus dispatchers, rail communications, etc.

Model M-101 (152 mc to 162 mc) 6 volt mobile... \$72.50

Model M-51 (30 mc to 50 mc) 6 volt mobile... \$72.50

Model AR-2 (108 mc to 132 mc) 115 V. AC or DC... \$49.50

FIRST IN THE EAST THE NEW BAY MOBILE ANTENNA

West Coast amateurs report terrific success with this 75 meter mobile antenna. Utilizing a new method of center-loading, it has outperformed others in on-the-air comparison tests.

Overall length is 9' 3", trimmed, maximum diameter 1 1/4", and it is fully weather-protected by a fibreglass seal over its entire chromed brass surface... \$19.95



COMPLETE HANDSET SPECIAL

Has a single-button high-output carbon-mike and sensitive earphone with push-to-talk switch, 3-foot, 4-conductor rubber covered cable.

Complete with mounting.

A Real BUY... \$12.95



SUPERIOR POWERSTATS

Smooth, efficient voltage control, 0-135 volts output from 115 volt AC line. Models also for 230 volt input. Write for free literature. Models for table and panel mounting.



Type 20, 3 amp... \$12.50

116, 7.5 amps, table mtg... 23.00

116U, 7.5 amps, panel mtg... 18.00

1126, 15 amps... 46.00

1156, 45 amps... 118.00

... and the New:

Type 10, 1.25 amps. (150/165 VA) \$8.50

IN STOCK FOR IMMEDIATE DELIVERY

RAYTHEON Transistors

Type CK716... \$18.00

VISIT THE AUDIO-TORIAL. Come in and visit our new sound department... all these items and many more on working display at all times.

Telephone **hrc** LUssenberg 2-1500

HARVEY

RADIO COMPANY, INC.

103 West 43rd St., New York 18, N. Y.

NOTE: In view of the rapidly changing market conditions, all prices shown are subject to change without notice and are Net, F.O.B., New York City.

BUY OF A LIFETIME! TRIED AND PROVEN THE WORLD OVER



LETTELINE MODEL 240 TRANSMITTER WITH MOBILE CONNECTIONS AND A.C. POWER SUPPLY

This outstanding transmitter has been acclaimed a great performer throughout the world. It is excellent for fixed station portable or mobile operation. Even if you have a transmitter of your own you can't afford to miss this wonderful buy, direct from our factory, ready to operate.

The 240 is a 40 watt Phone CW rig for 160 to 10 meters, complete with: (8 x 14 x 8) cabinet, self contained A.C. power supply, MOBILE connections, meter, tubes, crystal and coils for 40 meters. Tubes: 6V6 osc., 807 final, 6SJ7 crystal mike amp., 6N7 phase inverter, 2 6L6's mod., 5U4G rect. Weight 30 lbs. TVI instructions included, 90-day guarantee. Price \$79.95.

\$25 deposit with order — balance C.O.D.
80, 20, 10 meter coils \$2.91 per set. 160 meter coils \$3.60.
Also for CAP, Broadcast, MARS, Marine, State Guard.

LETTELINE RADIO MFG. CO.

62 Berkeley Street

Valley Stream, N. Y.



TURN "PRO" WITH THE "BIG" LEAGUE

... And you'll
beat 1,000!!

YOUR AMATEUR EXPERIENCE MAY
QUALIFY YOU FOR A HIGH-PAYING
ELECTRONICS OR RADIO POSITION
WITH BENDIX RADIO.

These jobs open:

- LAB. TECHNICIANS
- TECHNICAL WRITERS
- DRAFTSMEN

(Mech. & Elect.)

• ENGINEERING POSITIONS

We have openings in excellent positions which carry engineering responsibility. If you have a good background of practical experience, you need not have a degree.

Write, Wire or Phone MR. E. O. COLE Dept. L

Bendix Radio

DIVISION OF BENDIX AVIATION CORPORATION

BALTIMORE-4, MD. Phone: TOWSON 2200

Makers of the World's Finest
Electronic Equipment

and he did not do so well. Congratulations to QZ on the high score in the SS. Ex-80H now is 50H at Swift Current, and is heard on 14 Mc. JG, Swift Current Area EC, sends in an FB report on the Duncan Dam Emergency. EM reports better reception since he moved back to the farm and also less BCI. BZ has a new receiver and frequency meter. UC is busy watching his TV screen and getting some signals. DR and FY rebuilt their mobiles and put out a nice signal on 75 meters. Traffic: VE5TE 29, HR 14, PJ 10, JK 2, BZ 1.

World Above


(Continued from page 63)

problem by connecting shielded series-tuned traps to ground from both sides of the antenna pick-up winding on his 6BQ7 converter for 144 Mc. They consist of slug-tuned windings and 100- μ fd. fixed condensers, two sets separately shielded.

W9MBI, Coleta, Ill., sends in an interesting graph of the signal levels measured in his nightly contacts on 420 Mc. with W9ZHB, with records of barometric pressure, weather conditions and wind velocity for the same period. All the high-signal dates show a barometer reading over 30, and still air or wind of very low velocity. The total signal variation over this 40-mile path is around 20 db. Crystal-controlled transmitters and receivers, and 16-element arrays are used at each end.

Here is news of interest to the v.h.f. fraternity of Southern California, received too late for inclusion in its proper spot in this department. The Two Meters and Down Club of Los Angeles will hold a v.h.f. roundup and picnic on July 27th at Buena Park. There will be mobile competitions on all bands, and many other events for v.h.f. men and their families.

This information is from W6MVK, who also included results of the club's v.h.f. contest for the period ending April 30th. The marathon mileage award was won by W6AJF, with 12,713 miles. The expedition award went to W6IHK/6 for his 190-mile work. The new All-California v.h.f. activity award was won by W6MHF, with 470 contacts. Dave nosed out W6AJF, who had 462.



"The QRN is getting rough,
But lightning can't strike here!"
Let's contemplate Simp's smoking bones
And shed a mournful tear.

Answer to QUIST QUIZ on page 10

Neither one. If the transmitter, receiver and S-meter circuits are all linear, there will be no change of the S meter with modulation. The lamp of an antenna ammeter is a power-actuated device, and the average power level of an a.m. signal increases with modulation. The S meter is a voltage-actuated device, and the average voltage of a properly modulated signal is the same regardless of the modulation percentage (up to 100%). In practice, non-linearities in the transmitter, receiver or S-meter circuit can be responsible for some slight kicks. An S meter that shows kicks on every signal would make the receiver or S-meter circuit suspect, and it can be checked on a good h.c. station (except when they overmodulate during a commercial).

Lafayette

**your open door
to HAM VALUES
... for 31 years**



Scotty Says

Get your order in early for the
Gonset "Commander." Mark
your order to my attention
on this and the Specials for
prompt attention.
DUNCAN SCOTT W2LAL



**ELDICO
TR75TV
TRANSMITTER
KIT
\$59.95**

MD40P Modulator Kit.....\$44.95
Grid Dip Oscillator Kit.....29.50



**EICO KITS
221K VTVM
\$25.95
WIRED
\$49.95**

511K VOM Kit.....\$14.95
536K Multimeter Kit.....12.90
P75K HF Probe Kit.....3.75
P75 Probe Wired.....5.95

AMATEUR SPECIALS



Aerovox .05 mfd.
7500 VDCW oil-
filled condenser **75¢**

.05 mfd 2500 VDC GE oil filled condenser..... **75¢**
.5 mfd 600 VDC oil filled bathtub Aerovox **25¢**
2.0 mfd 600 VDC oil filled Micamold..... **75¢**
.006 mfd 2500 VDC Mico C-D..... **10¢**

Sprague Koolohm Resistor
120 watt 10,000 ohm — **75¢**

Toggle switches SPDT and DPST — **29¢ ea.**


RG59U coaxial cable — \$4.50 per 100 ft.

**GONSET
TRI-BAND
CONVERTER
\$47.60**



10-11, 15, 20 and 75 meters

**THE NEW
GONSET
"COMMANDER"
MULTI-BAND
TRANSMITTER
\$124.50**



Frequency range 1.5 to 54 mc.


New Gonset "Scout" Converters Single
band converters for 10-15-20 or 75
meters.....\$39.95

Gonset Noise Clipper..... 9.25

SPECIAL

110 Volts AC from 6 Volts DC. Terado
Converter Supplies 45 watts 110 VAC
from auto battery.....\$11.20

Lafayette TWO-WAY INTERCOM



Complete 2-way system with tubes (50B5,
35W4, 12AT6), cord, plug and
50 feet of hookup wire. For 110V.
AC or DC operation, P24999.....

17⁹⁵

free



Complete electronic equipment buying guide
for the radio amateur, experimenter and
service engineer. Drop in for Free Copy

Lafayette Radio



Radio Wire Television Inc.

NEW YORK 13, N. Y.
100 SIXTH AVENUE
REctor 2-8600

BOSTON 10, MASS.
110 FEDERAL STREET
Hubbard 2-7850

NEWARK 2, N. J.
24 CENTRAL AVENUE
Market 2-1661

BRONX 58, N. Y.
542 E. FORDHAM RD.
Fordham 7-8811

NOW . . . **AS FOR**
MANY YEARS . . .



**THE
OVERWHELMING
FAVORITE
OF AMATEURS**

ASTATIC

D-104 MICROPHONE

OLDTIMERS or newcomers—it makes no difference in the matter of microphone preference among Hams. Now, as for many years, an overwhelming majority prefer and use the famous Astatic Model D-104. Outstanding performance features are high output level (approx. —45 db) and definitely reduced R.F. feedback tendencies. A model employing ceramic element, with performance comparable to the crystal unit except for slightly lower output, is also available. If you would like complete details on the D-104 or other Astatic Mikes, please write.


THE Astatic CORPORATION
ASTATIC
CONNEAUT, OHIO
IN CANADA: CANADIAN ASTATIC LTD. TORONTO, ONTARIO

EXPORT DEPARTMENT: 401 Broadway, New York 13,
N. Y. CABLE ADDRESS: ASTATIC, New York.

JOHNSON

**VIKING 1
TRANSMITTER KIT**

(amateur net) only **\$209⁵⁰**



features

- 150 Watts Input on All Bands • Band Switching 160 thru 10 Meters • AM Phone or CW • Continuous Tuning Final Tank • Front Panel Controls • Unique Pierce Oscillator • VFO Input Receptacle • 10 Crystal Positions • PI-Network Coupling • Freedom from Parasitics • Two Complete Power Supplies • All Stages Metered • Desk Cabinet 11-3/16" x 15" x 21"

Write for Illustrated Folder TODAY!



E. F. JOHNSON CO.
WASECA, MINNESOTA

144-Mc. Amplifier

(Continued from page 15)

800 watts on c.w. These levels represent a lot more power than we need most of the time on 2, however, so the 4-125As are usually loading along at 200 to 300 watts input, with everything running a comfortable black.

In general, the manufacturer's typical operating conditions may be followed closely with excellent results. There is one slight variation that appears helpful: there is always a tendency for v.h.f. rigs to draw excessive plate current, and we have found it possible to run high values of plate current at relatively low plate voltages effectively with these tubes. They take 600 watts input with a 1500-volt plate supply beautifully, by running the screen voltage somewhat above the typical value of 350. With the heavy plate loading, there is a lower-than-average screen dissipation, and everything runs nicely. Flipping one switch drops the screen voltage to 300 and the final plate voltage to 800. The input with the same loading is then around 200 watts, which still makes an impressive 2-meter signal.

And what about TVI? Well, it varied with different receivers, but there was no r.f. interference that could not be cured readily enough. For test purposes, we have a system whereby a typical "fringe area" signal can be put into the receiver on any channel from 2 through 13, and this rig was operated in conjunction with nine different receivers on each of these channels. There was a very slight pattern on some of the receivers having 21-Mc. i.f. systems, apparently the result of 24-Mc. output from the oscillator stage of the exciter. Receivers having 45-Mc. i.f.s showed a similar pattern from the 48-Mc. stage in the exciter. These patterns had nothing to do with radiation from the final stage, and thus were independent of power or antenna location.


There was image TVI on Channel 2 in one receiver, and the tripler passed some energy on 192 as well as 144 Mc. There was some 192-Mc. pattern from the 48-Mc. exciter stage (4×48 Mc.), and it increased as the three stages in the transmitter were turned on individually, causing fairly bad interference in Channel 9. This same sort of thing develops in Channel 10 as the frequency is raised much above the low end of the band. The cure here is the same as for any harmonic trouble, except that it should be easier in this case, the trouble having been caused in the low-level stages. The transmitter is designed so that shielding can be added, and a low-pass filter, details of which will appear in QST at a later date, can then be inserted in the antenna circuit to get rid of the 192-Mc. radiation.

There was no interference from the 144-Mc. radiation from the transmitter on eight of nine receivers checked on all channels, 2 through 13. We feel safe in saying that, if you have TVI with a 2-meter rig, it is probably the result of trouble in the lower-frequency stages, or it is audio pick-up that is present only with amplitude modulation.

LOOK STEINBERGS LOOK

SUPER SPECIALS

3-BAND RADIO



KARADIO MODEL 80-C, 3-band mobile receiver for under-dash mounting. Covers broadcast band 540-1650 KC; 2.8-7.5 MC; 4.8-17.5 MC; which includes the 75 and 20 meter bands. 6 tubes: 6BA6 R.F., 6BE5 Mixer, 6BA6 I.F., 6AT6 demod.—1st Audio, 6AQ5 output, 6X5GT rectifier.

Vibrator power supply mounted in metal case with 6" PM speaker, for fire-wall mounting. 3-ft. plug-in cable included.

Receiver only 4 1/2" high, 6 1/2" wide, 6" deep. Mounting hardware, complete manual, fused battery lead, included.

Front panel RF gain control, Audio, Band Switch, Tuning.

Here's an excellent mobile receiver at a nice saving. Regular price is \$110. We have just 23 to sell at **\$63.00**. Standard 90-day RTMA warranty.



2/8/8 MFD. 500 V. D.C.

Triple 8 mfd. 500 working volt D.C. oil-filled condenser, common negative, solder terminals, hermetically sealed, 5" x 3 3/4" x 2 1/4". A one-time buy. **\$1.95**

PHOSPHOR BRONZE AERIAL

125 ft. of the finest aerial wire obtainable. 42-strand phosphor-bronze with linen center. Will not stretch, very high tensile strength, diameter approximately same as No. 14 copper, very flexible. Excellent for transmitting or receiving antenna, control cable, guy wire. Regular list \$4.95. **90¢**

POLIALARM — EMERGENCY MONITORS

PR-31 (30-50 Mc, FM) 115V, AC-DC.....**\$44.95**
PR-8 (152-163 Mc, FM) 115V, AC-DC.....**\$44.95**
AR-2 (108-132 Mc, AM) Aircraft band.....**\$49.50**
M-31 (30-50 Mc, FM) 6 volt mobile.....**\$72.50**
M-101 (152-163 Mc, FM) 6 volt mobile.....**\$72.50**

MINIMUM ORDER \$2.00.
 Send 20% deposit with COD orders. Please include sufficient postage or instruct us to ship by Express Collect. Overpayment will be refunded by check.

ELMAC-A54

Under-dash Mobile Xmtr.




VFO or Crystal control. Direct-reading VFO on all bands—75, 20, 11, 10. • Plate modulation • Completely band-switching, fone or CW. • 50 Watts max. input. Power required: 300-500 V.D.C. at 250 ma., 6.3 V AC or DC at 4.5A. • Uses 3-6AG5, 6AR5, 6C4, 12AU7, 2-6L6G, 807, (included). • Only 7 1/2" x 7 1/2" x 12", 14 1/2 lbs.

For carbon mike input.....**\$139.00**
 For Dynamic or crystal mike.....**\$149.00**
 Power Supply, 110 Volt AC.....**\$39.50**
 ELECTRO-VOICE 210 Mobile Carbon Mike.....**\$17.10**
 ELECTRO-VOICE 600D Mobile Dynamic Mike.....**\$23.10**

MORROW 3-BAND CONVERTER

- Single point tuning; high image rejection, birdies negligible
- Automatic Noise Limiter—Built In
- 1-Microvolt Sensitivity—All Bands
- Antenna Trimmer on Front Panel
- Beautiful Grey Hammertone Finish
- Low drift, Pre-calibrated Oscillator
- Full Width Dial—Calibration Accuracy 1%
- AVC On Preset, No Strong Signal Blocking
- I.F. Amp. with 4 Tuned Circuits, Output 1525 Kc.
- Complete with Mounting Hardware, Manual
- Case—Height 4", Width 5 1/2", Length 6 1/2"



\$64.95

HI-Q. 20 coil to base load 96" whip.....**\$8.95**
 HI-Q. 75 coil to base load 96" whip.....**\$7.95**

MONITORADIO 2-meter RECEIVER



Model AR-3. 118-149 Mc, AM, 115V, AC-DC, 6 tubes, crystal diode. Variable sensitivity, Improved squelch, Drift compensated, Black plastic cabinet. 10 1/2" x 6 1/2" x 7". 5" PM speaker. Wt. 5 lbs.....**\$49.50**

Your order will receive my personal attention and will be shipped the same day order is received. We distribute all top-flight amateur lines... let us know what you need.
 73, Jule Burnett, W8WHE

Steinbergs

633 WALNUT STREET • CINCINNATI 2, OHIO

COMPONENT APPLICATION ENGINEERS

Collins Radio Company needs experienced component application engineers. Experience in component application or testing and specifications is required. E.E. degree desirable but equivalent additional experience will be considered. Immediate need is for men familiar with motors, dynamotors, vacuum tubes, transistors, meters relays, transformers, capacitors and resistors.

SALARY COMMENSURATE WITH ABILITY

Write fully — today . . . Address letter to

COLLINS RADIO COMPANY

Cedar Rapids, Iowa

MORE SIGNALS PER DOLLAR
From Money Invested in an Antenna

Self Supporting
STEEL TOWERS
For Rotary Beams, FM, TV



ATTRACTIVE—NO GUY WIRES!

- 4-Post Construction for Greater Strength!
- Galvanized Steel—Will Last A Lifetime!
- SAFE—Ladder to Top Platform
- COMPLETE—Ready to Assemble
- Easy to Erect or Move
- Withstands Heaviest Winds

EASY MONTHLY PAYMENTS
Up to 12 Months to pay

Here Is An Inexpensive
Answer for
COMMUNITY TV ANTENNAS!

Width at
Base Equal
to 1/3 Height

Vesto Towers are available in a wide range of sizes to meet requirements of amateurs and commercial users alike. Note the low prices for these quality lifetime towers: 22'—\$94.75, 28'—\$115.75, 33'—\$135.75, 39'—\$157.75, 44'—\$178.75, 50'—

\$217.75, 61'—\$279.75, 100'—\$1060.00. Towers are shipped to your home knocked down, FOB Kansas City, Mo. 4th class freight. Prices subject to change . . . so order now! Send check or money order . . . or write for free information.

WRITE TODAY
FOR COMPLETE
FREE INFORMATION
AND PHOTOGRAPHS

VESTO CO., Inc.
20th and Clay
North Kansas City, Mo.

The Siamese Paddle

(Continued from page 16)

The paddles are made of pieces of $\frac{1}{8}$ -inch polystyrene or lucite sheet, $2\frac{1}{4}$ inches long and 1 inch wide. A hole to pass a machine screw that fits the knob hole in the key arm is drilled in each paddle, $\frac{1}{2}$ inch from one end. Most key knobs have a standard 8-32 thread. The exact manner of mounting the paddles depends on factors to be discussed presently.

If you can locate a piece of $\frac{1}{2}$ -inch steel or brass, you can add a weighting base with rubber feet like the conventional bug. The base shown is 6 inches long and 3 inches wide. Be sure that the mounting screws on the underside of the bakelite base don't protrude so as to short on the metal base. If the weighting base is omitted, the key can be screwed or cemented to the operating table. Rubber cement sets quickly and yet permits removal without difficulty. Also, it will not mar the finish of an operating table.

Adjustment

The adjustment of the key depends largely on the personal preferences of the operator. I have mine adjusted so that both sets of contacts cannot be closed simultaneously. However, many of those who are using electronic keyers of the self-completing type find possible many short-cuts in the forming of certain characters and increased ease of handling in other ways if it is possible to close both circuits at once when desired. For instance, closing the dot side while dashes are being sent does not interfere with the sending of dashes. Therefore, when both sides are closed, the change-over from dashes to dots can be accomplished merely by opening the dash side. Actually, it is necessary to open the dot side only for spaces.

As shown in the photograph, the paddles are mounted on the inward sides of the key levers, with the heads of the 8-32 screws also on the inside. With this arrangement, it may be necessary to bend the key levers slightly if it is desired to prevent closing both circuits at the same time. Place a thickness or two of paper between the contacts of each key and press the two paddles together between the thumb and forefinger. Then the levers should be bent slightly so that when the paper is pinched securely between both sets of contacts, the heads of the 8-32 screws are in contact.

After the photograph was made, an arrangement making this adjustment more convenient was found. The paddles were placed on the outer side of the key levers and the screws were reversed with the heads on the outside. A locknut was first run onto each screw. Then the screw was passed through the paddle, threaded into the key lever and then fastened with another locknut on the inside. Now the above adjustment can be made simply by adjusting the screws with a screwdriver and locking with the two nuts. I prefer the wider paddle spacing that results with

(Continued on page 116)



COMPARE! COMPARE! COMPARE!

Fellows — NOW is the best time to trade for a new receiver or transmitter. Our stocks are complete — our prices are LOW. I'll give you the best deal on your used equipment. WRL gives you • TAILOR-MADE TERMS • LOWER PRICES • LIBERAL TRADE-INS • COMPLETE STOCKS • PERSONALIZED SERVICE. You'll benefit most by dealing with WRL, "One Of The World's Largest Distributors Of Amateur Radio Transmitting Equipment."

We Finance Our Own Paper—No Red Tape—No Delays
(Special attention given to foreign orders)

Leo I. Meyerson WØGFO

**SEND
TODAY**


FREE!

NEW

1952

WRL

CATALOG



"NO TVI with GLOBE KING 400B XMTR"

Sam Brodsky, W4JZQ, 418 E. Colonial Ave., Elizabeth City, N.C., is an enthusiastic WRL GLOBE KING owner who writes the following unsolicited letter:

"There is no TVI generated from the GLOBE KING 400 B which I purchased from you. I can run the XMTR at a full 420 watts and the transmitting antenna is only 8 ft. away from the TV antenna with no TVI filter on my TV set or on the XMTR; just a brute force filter in the AC line. I get no TVI on my TV set."

Signed, Sam Brodsky, W4JZQ

NEW WRL 400B GLOBE KING XMTR **KIT FORM** **WIRED-TESTED**
\$475.00 **\$495.00**

WRL 165 WATT GLOBE CHAMPION XMTR

(less accessories)

KIT FORM

WIRED

\$329.50 **\$349.50**

WRL 40 WATT TROTTER XMTR

More Watts Per Dollar

KIT FORM

WIRED

\$89.50 **\$99.50**

NEW ELMAC-A54 UNDER DASH XMTR

Mobile



VFO or Crystal control. Direct-reading. VFO on all bands—75, 20, 11, 10. • Plate modulation. • Completely band-switching, fone or CW. • 50 Watts max. input. Power required: 300-500 V.D.C. at 250 ma., 6.3 V AC or DC at 4.5A. • Uses 3-6AG5, 6AR5, 6C4, 12AU7, 2-6L6G, 807, (included). • Only 7 1/2" x 7 1/2" x 12", 14 1/2 lbs.

For carbon mike input **\$139.00**

For dynamic or crystal mike **\$149.00**

Power Supply, 110 Volt AC **\$ 39.50**

NEW WRL LOG BOOK

For mobile or fixed stations. Spiral binding—turns up—lies flat. Full column log listing all FCC required info. Log will accommodate 1,525 stations. Front and back covers show "Q" signals, phonetic alphabet, and amateur international prefixes. **25¢**

GIANT RADIO REFERENCE MAP



Just right for your control room walls. Approximately 28" x 36". Contains time zones, amateur zones, monitoring stations. Mail coupon today and **25¢**

CU ON 10-20 & 75 METERS

WRITE FOR DETAILED SPECIFICATION EQUIPMENT SHEETS

**WRITE
WIRE**

**PHONE
7795**

World Radio
LABORATORIES COUNCIL BLUFFS, IOWA

World Radio Laboratories, Inc.
744 West Broadway
Council Bluffs, Iowa

Q-7

Please send me:

- ☐ New Log Book
☐ New Catalog
☐ Radio Map

- ☐ ELMAC-A54 Info
☐ Globe King Info
☐ Globe Champion Info
☐ Used Equipment List

Name

Address

City

State

URGENTLY NEEDED

TECHNICAL WRITERS for

Collins Radio's Engineering

Publications Department

COLLINS RADIO COMPANY's ever-growing leadership in the fields of communications, navigation and broadcasting is placing an increasing importance upon the completeness and quality of the technical literature required to support its equipment in the field.

If you are qualified to write such material, join us and watch electronics progress with Collins.

Collins' facilities include a complete, self-sufficient publications organization, including writers, editors, artists, draftsmen and a well-equipped offset printing plant.

Duties . . .

Preparing and editing copy for commercial and government operating and maintenance manuals, engineering reports and equipment specifications.

Qualifications . . .


Degree in electrical engineering or degree in journalism and several years of practical radio experience.

• • •

Write us fully about yourself — today. The jobs are open now! Address your letter to MERRILL S. SMITH, Collins Radio Company, Cedar Rapids, Iowa.

DOW CO-AX RELAY

FOR 52 OHM LINE



1. Insertion in 52 ohm co-ax line causes negligible change in s.w.r., up to 100 Mc.
 2. Handles power up to 1000 watts.
 3. When in transmit position it grounds receiver antenna lead. This protects receiver against injury from r.f. and reduces to a minimum the capacity coupling between receiver and relay contacts.
 4. Fits standard connectors for RG-8/U co-ax.
 5. No chatter. Specially built for "Silent operation".
 6. Externally mounted SPDT switch operated by relay can be used for opening B+ of receiver when transmitting, or for other control purposes.
 7. Over-all length 4 1/4". Over-all width 3".
- NET 115 volt AC (for fixed station) \$12.50
 PRICES 1/2 volt DC (for mobile use) 11.50
- See your distributor, but if he has not yet stocked Dow Co-ax Relays, order now direct from factory. Send check, money order, or will ship C.O.D. Prices are Net, FOB shipping point: Warren, Minn., or Winnipeg and Montreal, Canada.

Dealer Inquiries Invited

THE DOW-KEY CO., INC. Warren, Minnesota

THE DOW-KEY CO.
578 Goulding Street
Winnipeg, Canada

THE DOW-KEY CO.
2310 Wilson Avenue
Montreal, Canada

this arrangement, although others may prefer the closer spacing when the paddles are on the inside. It will usually be possible to use the screwdriver adjustment, even with the paddles on the inside, although it may be necessary to file the nuts down to fit the space between the key levers.

If simultaneous closing of both sides of the circuit is desired, adjustment is merely a matter of setting the contact spacing, bearing play and spring tension to suit the operator, using the adjusting screws already provided on the keys for these purposes. If you have a light touch, it may be necessary to change the springs to lighter ones, or to cut a turn or two off the existing springs and stretch to fit the space.

In the electronic-keyer circuit, the "arm" connection will be made to one of the terminals connected to the frames of the keys, while the two "side"-contact connections will be made to the terminals connected to the straps leading to the stationary contacts. Depending upon how these two "side" contacts are connected, the keyer can be operated either right-handed or left-handed. Simply reversing these connections reverses the operation.

Getting the Most Into Your Antenna

(Continued from page 23)

if you try to use a parallel-tuned coupler in circumstances that call for the use of series tuning, you just won't get maximum performance from your antenna. Selection of the right type involves drawing a sketch of the current distribution on your particular system. This is easier if you get in the habit of thinking in terms of quarter wavelengths at the frequencies you plan to use. For example, a quarter wavelength at 3725 kc. (the center of the present Novice assignment in the 3.5-Mc. band) is 62.8 feet. It is safe to round this off to the nearest ¹ whole number, or 63 feet. You know, then, that in whatever system you choose to erect, the distance between the end of the antenna and the first maximum current point is going to be 63 feet. Measure off the flat top and the feed line, and sketch in the current pattern so that you have a drawing that resembles one of those shown in Fig. 1. Indicate the points at which current maxima and minima occur, and when you have reached the end of the line you will have a pretty good idea of what conditions will be encountered there. For example, in sketch C of Fig. 1, if your feed line has to be short, terminating at points AA', you will know that parallel feed is required, because the feed point is at (or near) a current minimum. The same applies if the feeders are a half wavelength longer, ending at DD'. If the feeders can be a half-wave long,

(Continued on page 118)

¹ This computed from the formula

$$l \text{ (feet)} = \frac{468}{f \text{ (Mc.)}}$$

which appears on page 28 of the A.R.R.L. Antenna Book.

LEEDS

Our 29th Year
QUALITY - PRICE
DEPENDABILITY

BICO KITS

ALUMINUM CHASSIS

7x 9x2	\$1.03
7x11x2	1.06
7x13x2	1.20
10x14x3	1.97
7x15x3	1.76
7x17x3	1.91
8x17x3	2.03
10x17x2	1.91
10x17x3	2.20
11x17x3	2.29
12x17x3	2.67


FLEXI-MOUNT ALUMINUM BOXES Gray Hammerhead finish

435	2 1/2 x 2 1/2 x 1 1/2	\$.69
436	2 1/2 x 3 1/2 x 1 1/2	.69
437	2 1/2 x 4 x 1 1/2	.72
438	2 1/2 x 4 x 2 1/4	.95
439	2 1/2 x 5 x 2 1/4	.98
441	3 x 5 1/4 x 2 1/2	1.05
440	4 x 5 x 3	1.08
442	5 x 6 x 4	1.33
443	5 x 7 x 3	1.49
447	5 x 17 x 4	3.75
444	6 x 8 x 3 1/2	2.18
445	6 x 10 x 3 1/2	2.69
446	7 x 12 x 4	3.19

145K	Signal Tracer	\$19.95
221K	V.T.V.M.	25.95
315K	Signal Generator (De luxe)	39.95
320K	Signal Generator	19.95
322K	Signal Generator	23.95
360K	Sweep Generator	34.95
400CK	Conversion Kit (Push-Pull 5" Scope)	8.95
425K	5" P.P. Scope	44.95
511K	Multitester	14.95
526K	1000 ohm per volt Multimeter	13.90
555K	20,000 ohm per volt Multimeter	29.95
625K	Tube tester	34.95
950K	Resistance Capacitance (Bridge & R.C.L. Comp.)	19.95
1040K	Battery eliminator & charger	25.95
1171K	Resistance decade	19.95
P75	RF Probe (Xtal type) for VTVM	5.95
P76	RF Probe (Scope)	5.95
HVP-1	Hi-Voltage probe	6.95

Write for circular on wired instruments.

THE NEW MODERN ANSWER TO VARIABLE A-C VOLTAGE CONTROL OF 50-100-150 WATT LOADS



Type 10 POWERSTAT
MORE EFFICIENT than the wasteful, heat-dissipating resistance type controls. LESS SPACE is required. Not only is it compact but since it does not produce heat there is no ventilation problem. **RUGGEDLY CONSTRUCTED** for long life and dependable service. **EASILY ADAPTED** to any load within its rating. **SMOOTH CONTROL** is assured by glass smooth commutator surface and advanced winding technique. **CONSERVATIVELY RATED** with rated output current available at any brush setting. **SIMPLE MOUNTING** to back-of-panel by means of a single hole. Locked in position by keying arrangement.

INPUT OUTPUT 1 lb., 13 oz.
120 Volts 0 - 120 Volts
60 Cycles 0 - 132 Volts
1 Phase 1.25 Amperes
150/165 VA

\$8.50

UNIVERSAL MODULATION TRANSFORMERS

Tapped Series-Parallel Coils Provide a Wide Range of Modulation Ratios

Type No.	Pri. Impedance	Pri. M.A. Per Side	Sec. Impedance	Max. Sec. M.A.	Watts	Dimensions			Price
						H.	W.	D.	
A-3194	2000-20000	50	2000-20000	50/100	15	3 3/4"	2 3/4"	2 3/4"	\$4.32
A-3195	2000-20000	150	2000-20000	150/300	60	3 3/4"	3 1/2"	4 1/4"	9.41
A-3196	2000-20000	220	2000-20000	220/440	125	4 3/4"	3 1/2"	4 3/4"	13.23

MODULATION TRANSFORMERS

For Specific Applications

Type No.	Output Tubes	Ohms Impedance		Max. M.A.		Watts	Dimensions			Price
		Pri.	Sec.	Pri.	Sec.		H.	W.	D.	
A-3008	PP6AQ5, 6V6, 6F6, Single 6A6, 6N7, 53	10000 c.t.	4000-5000 7500-10000 12000	70	60	10	2 1/2"	2 1/2"	2 1/2"	\$2.12
A-3199	PP2A3, 6A3, 6B4, 6L6, 45, 46, 59	6000 c.t. 3800 c.t. 3000 c.t.	5000-8000 10000	80	100	25	3 1/2"	2 1/2"	2 1/2"	5.80
A-3110	PP6L6, 807, RK41, HY56, HY61, HK24	6600-3800 c.t.	4000-5000 7500-10000 12000	175	150	60	4 3/4"	3 1/2"	3 1/2"	8.53
A-3111	PP-800, 809, TZ-40, T-55, HK-54, RK-31, HY-40, 811, 807, 812	15000-6900 c.t.	3000-4000 5000-6000	250	300	175	4 3/4"	3 1/2"	5 1/2"	12.94

POLYSTYRENE

TUBING 12" LENGTHS

O.D.	I.D.	WALL	PRICE
1/4	1/8	.062	\$.07
5/16	3/16	.062	.10
3/8	1/4	.062	.13
1/2	3/8	.062	.18
5/8	1/2	.062	.23
3/4	5/8	.062	.29
1	3/4	.062	.38
1 1/2	1 1/4	.125	1.13
2	1 3/4	.125	1.50

ROD 12" LENGTHS

O.D.	Price	O.D.	Price
1/8	\$.03	3/4	\$.80
3/16	.06	7/8	1.15
1/4	.10	1	1.55
5/16	.16	1 1/4	2.30
3/8	.21	1 1/2	3.30
1/2	.40	1 3/4	4.50
5/8	.57	2	5.90

SHEET-CLEAR MASKED BOTH SIDES

SIZE 12" x 12"		SIZE 12" x 24"	
1/16"	\$2.50	1/16"	\$4.90
3/32"	2.75	3/32"	5.25
1/8"	3.00	1/8"	5.90
3/16"	3.75	3/16"	7.25
1/4"	4.60	1/4"	8.25

Larger Thicknesses Up to 1"
Prices on Request

If not rated 25% with order, balance C.O.D. All prices F.O.B. our warehouse New York. No order under \$2.00. We ship to any part of the globe.

Both Rod and Tubing also available in 48" lengths to order.

LEEDS RADIO CO.

75 Vesey Street
Cortlandt 7-3440

Dept. QS 6
New York City 7

ANNOUNCING

The **NEW**

1952 U.H.F. RESONATOR

ANTENNAS

FOR
THE 10 and 20 METER BANDS

FEATURING

- **STRONGER CONSTRUCTION**
- **LIGHTER WEIGHT**
- **ADJUSTABLE SPACING**


All these outstanding features WITH
THE SAME HIGH GAIN but at NO
INCREASE IN PRICE

Write for Descriptive Literature

U.H.F. RESONATOR CO.
224 Seventh Street Racine, Wisconsin

ROUND, SQUARE, KEY and "D" OPENINGS QUICKLY MADE

with Greenlee Radio Chassis Punches



Save hours of hard, tedious work
... cut accurate holes in chassis for
sockets, plugs, controls, meters,
panel lights, etc. with GREENLEE
Punches. In 1-1/2 minutes or less
make a smooth hole in metal, bak-
elite or hard rubber up to 1/16" thick.
Easy to operate. Simply turn with
ordinary wrench. Wide range of sizes. Write for details.
Greenlee Tool Co., 1867 Columbia Ave., Rockford, Ill.



points *BB'*, you should expect to use a series-tuned coupler, because the feed point shows a current maximum. If it works out so that the end of the feed line is midway between a current maximum and a current minimum, as shown at points *CC'*, don't give up the ship; you can still lick your problem. It is sometimes possible to lengthen or shorten the feeders to get away from this intermediate point merely by rearranging the route taken by the feed line on the way into the house. If this is impossible, you can add length right inside the operating room by the simple expedient of adding on a few feet of 300-ohm Twin-Lead.² This is not the best way in the world to do it, but in most cases the power loss in the Twin-Lead will be negligible when compared with the benefits obtained by getting better coupling than you would have been able to obtain without it. In low-power stations (150 watts or less), the Twin-Lead is able to stand the strain admirably. If you prefer to be really efficient about it, refer to the methods shown in the *Antenna Book*,³ but the Twin-Lead dodge will work amost as well.

In the case of the single-wire antenna shown in Fig. 1A, the length is of less importance, because the pi-section coupler can cope with almost any conditions. It is good to know, however, whether you are going to have to feed the end of the wire at a point of high or low current. This can be determined, of course, by drawing the curves as in Fig. 1. If the length of the "single-wire" antenna can be made to come out so that it is resonant at the operating frequency, it will be much easier to get power into it than if it is a random length. Resonant or not, it will probably not do quite as good a job as either the Zepp or the center-fed antenna for the reasons explained earlier. It is, however, usable in emergency conditions and in locations where the use of something better is impossible. In most cases, it is advisable to connect the chassis of a pi-section coupler to a good external ground. This is especially true in cases where the antenna must be less than a quarter wave length long. The ground connection can be to either a cold water pipe in the house or a metal rod driven several feet into the ground just outside the house.

In summary, then, the use of a resonant antenna is suggested, because it is the easiest way to eliminate coupling problems. While a single-wire antenna will work, it is not as apt to radiate the power where it will do the most good. It is better to put up either a Zepp, or a center-fed antenna with a balanced feed line, and of these two, the center-fed is by far the most flexible.

A subsequent article, a direct follow-up of this one, will describe the construction and use of antenna couplers suitable for the Novice, and will provide the bridge between the fundamentals discussed here and their practical application.

² How much Twin-Lead to use depends upon the difference in length between the end of your feeders and the next quarter wavelength point. In cutting the required length of Twin-Lead, multiply the number of feet required to make up the deficiency by 0.82, to compensate for the difference in velocity factor between the open-wire line and Twin-Lead.

³ See the *A.R.R.L. Antenna Book*, page 124.



Check THESE RADIO VALUES . . .

RECEIVERS

Collins 75 A2 with speaker	\$440.00
Hammarlund HQ-129-X with speaker	214.00
RME-50 with speaker	213.50
National new model NC-183-D with speaker	385.50
National HF8 with power supply	164.43
National HRO-50T1 with speaker	395.50
National SW-54	49.95
Hallicrafters new model SX-73	975.00



Hallicrafters SX-62 less speaker

\$289.50

Hallicrafters SX-71, less speaker	\$199.50
Hallicrafters S-72 portable, less batteries	109.95
Hallicrafters S-72L marine band portable, less batteries	119.95
Battery pack for Model S-72	4.17
Hallicrafters S-76, less speaker	169.50
Hallicrafters S-77A	99.95
Hallicrafters S-40B	99.95
Hallicrafters S-38C	49.50
Hallicrafters S-80	44.50
Hallicrafters S-81	49.50
Hallicrafters S-82	49.50
Hallicrafters Speakers for models SX-62, SX-71, S-76	19.95
Mallory VP-555-H Vibropack output 300-VDC @ 200 ma	33.63
Mallory VP-557 Vibropack output 400-VDC @ 150 ma	33.63



Single button carbon hand MICROPHONES

with push-to-talk switch, similar to T-17B... MADE IN ENGLAND... each **\$3.95**

BARGAIN SPECIALS

4, 5 & 6 prong ceramic sockets made by Johnson. Each . . . \$.20
GE plate circuit relay, 8000 ohm, DPDT contacts close @ 8 ma.
Each . . . 1.95

TRANSMITTERS

Johnson Viking Transmitter Kit less tubes, mike or crystal	\$209.50
Full Kit of Tubes	39.00
Johnson VFO Kit, less tubes	42.75
Kit of Tubes	2.69
Harvey-Wells TBS-50C Bandmaster Senior	111.50
Harvey-Wells TBS-50D Bandmaster DeLuxe	137.50
Elmac Portable Transmitter Model A-54H, uses carbon mike	139.00
Elmac Portable Transmitter Model A-54H, uses crystal or dynamic mike	149.00
Collins Model 32V3 Transmitter, less microphones and crystal	775.00
Lyaco Model B-129 Transmaster 10 meter, less tubes	29.95
Lyaco Model A-175 Transmaster 75 meter, less tubes	29.95
Lyaco Model A-140 Transmaster CAP meter, less tubes	29.95
Lyaco Model 381 VFO, less tubes	28.95
Lyaco Model 401 Modulator, less tubes	19.95
Eldico 2 meter transmitter kit	49.95
wired and tested	74.55
Eldico GDO kit	29.50
wired and tested	43.00
Millen 9651 Grid dip oscillator	61.50
Morrow Converters, Model 2 BR for 10-75 meters	54.95
Morrow Converters, Model 3 BR for 10-25-75 meters	64.95
Gonset Model 3005 Tri-band Converter	47.60
Gonset Model 3008 2 meter Converter	44.50
Gonset Model 3002 3-30 meter Converter	44.75
Gonset Steering Pot Bracket	3.90
Gonset Noise Clipper	8.25
Eldico 2 meter Receiver Kit, Complete	59.95
Eldico 2 meter Receiver Kit, wired and tested	89.95

VARIABLE CONDENSERS

	Length	Height	Width	Each
MB7938 Capacity 3-26 mfd., .100 spacing	2	1 1/2	3 1/2	\$.75
MAP16 Capacity 10-75 mfd., .100 spacing	3 1/2	2 1/2	2 1/2	1.20
MA56912 Capacity 10 mfd., .020 spacing	3 1/2	1 1/2	1 1/2	.70
MA56906 Capacity 25 mmfd. per sec., .020 spacing, butterfly type	1 1/2	1 1/2	1 1/2	1.35
Acorn tube sockets made by EF Johnson for 954, 955, etc. tubes				.20
2 mfd. 1000 V pyranol cond.				2.95
2 mfd. 2000 V pyranol cond.				5.95
4 mfd. 3000 V pyranol cond.				9.95
Bias trans. 117 volt primary sec. 117 volt tapped at 104, 91, 78, 65, 52, 39, 26, 13 @ 40 ma.				1.95
Clarostat 50 watt rheostat, 250 ohm			lots of 10	1.35
DeJur 50 watt rheostat, 50 ohm			lots of 10	1.20
DeJur 50 watt dual 2000 ohm			lots of 10	.99
			lots of 10	2.30
			lots of 10	1.88

USED EQUIPMENT

Hallicrafters SX-28, with speaker	\$175.00
Hallicrafters SX-42, with speaker and tilt base	195.00
Hallicrafters S-72 Portable — LIKE NEW — less batteries	85.00
Hallicrafters S-20R	45.00
Bud VFO-21 variable frequency oscillator	42.00
Gonset 2 meter Converter — LIKE NEW	39.00
RME-69 Receiver with noise clipper and speaker	75.00
Hallicrafters SX-43 with speaker — LIKE NEW	160.00
Hammarlund SP-46GSX with speaker and power supply	275.00
Harvey-Wells Bandmaster DeLuxe — LIKE NEW	124.00
Harvey-Wells Bandmaster Senior — LIKE NEW	100.00
National NC240D with speaker	175.00

Write Us For Any Other
Items You Are Looking For.
These Items Change Daily.
Liberal Trade-In Allowances.

Foreign Trade Welcome!
All inquiries answered.

FORT ORANGE
Radio Distributing Co., Inc.
904 BROADWAY, ALBANY 4, N. Y., U. S. A.
AMATEUR HEADQUARTERS

Long Distance Phone: ALBANY 5-1594 . . . Cable Address: "UNCLE DAVE"

WANTED Engineers and Scientists

Unusual opportunities for outstanding and experienced men

These top positions involve preliminary and production design in advanced military aircraft and special weapons, including guided missiles.

IMMEDIATE POSITIONS INCLUDE:

- Electronic project engineers
- Electronic instrumentation engineers
- Radar engineers
- Flight test engineers
- Stress engineers
- Aero- and thermodynamicists
- Servo-mechanists
- Power-plant installation designers
- Structural designers
- Electro-mechanical designers
- Electrical installation designers
- Weight-control engineers

Excellent location in Southern California. Generous allowance for travel expenses. Write today for complete information on these essential, long-term positions. Please include résumé of your experience and training. Address inquiry to Director of Engineering,

NORTHROP AIRCRAFT, Inc.
1029 East Broadway
Hawthorne (Los Angeles County), Cal.



TELEVISION • RADIO ELECTRONICS

Training in all branches of television, radio and electronics. FCC exam. preparation. Write for free catalog.

COMMERCIAL RADIO INSTITUTE

(Founded 1920. Apprs. by MD. Board of Education)
Dept. B, 38 West Biddle Street Baltimore 1, Maryland

If You Telegraph You Need A

VIBROPLEX



Semi-Automatic Key
Twice as easy
as hand sending

Order
Yours Today!

No other key takes the strain and effort out of telegraphing like the Vibroplex. It brings to you the ease of semi-automatic action, simplicity of operation and advantage of machine speed. The use of patented jewel movement assures smoother, easier operation and longer life. Don't wait for signs of arm trouble. Start using the Vibroplex today and see how easily and effortlessly you send... no arm-tiring effort... no strain. Everyone will notice the improvement in your keying. Whether you choose the **Super De Luxe Presentation** with 24-K gold-plated base top and super-speed control main-spring that lets you send from dead slow to top speed, and requires no additional weights for slowest sending — or one of the other models — you'll get the finest key your money can buy. **ORDER YOURS TODAY!** Left-hand models, one dollar more. At dealers or direct. **FREE** catalog.

Headquarters for NEW portables, all models and styles of type. Also, **REBUILT** standard and portable typewriters with **ALL CAPITAL** letters and other styles of type. Immediate delivery. **Get our prices before you buy!**

THE VIBROPLEX CO., INC.

833 Broadway New York 3, N. Y.



Driven Arrays

(Continued from page 81)

db. to an S point. The author's thanks are due to the numerous VK stations who have cooperated in these tests.

Good DX reports have been obtained from all directions on 14 Mc., although the steep slope of the ground makes it impossible to get the angle of radiation just right for all directions. On 28 Mc. reports from W, VE, ZE, ZS and VQ have been very satisfactory in spite of adverse conditions during most of the tests, but certain other directions have proved difficult apparently because of an unsuitable angle of radiation. In this respect the performance should be neither better nor worse than that of other types of beam, and no difficulty should arise with a normal flat site and a height of 40 or 50 feet.

Happenings

(Continued from page 88)

77) The vote having been taken, the result of the ballot was announced by the tellers as follows:

Whole number of votes cast	18
Necessary for election	10
For Mr. Bailey	7
For Mr. Dosland	11

Mr. Dosland, having received the majority of the votes cast, was thereupon declared by the tellers to be elected President of the League for a term of two years. The Chair congratulated Mr. Dosland upon his election. (Applause) Mr. Dosland spoke briefly in appreciation. (Applause)

78) On motion of Mr. Groves, a unanimous standing vote of applause was given to Mr. Bailey in appreciation of his service to the Board and the League.

79) Nominations for First Vice President being in order, Mr. Roberts nominated Mr. Groves. Mr. Johnston nominated Mr. Noble. Whereupon, on motion of Mr. Jacobs, unanimously VOTED that the nominations are closed.

80) The vote having been taken, the result of the ballot was announced by the tellers as follows:

Whole number of votes cast	18
Necessary for election	10
For Mr. Groves	11
For Mr. Noble	7

Mr. Groves, having received the majority of the votes cast, was thereupon declared by the tellers to be re-elected First Vice President of the League for a term of two years. (Applause)

81) Nominations for Vice President being in order, Mr. Noble nominated Mr. Handy. Whereupon, on motion of Mr. Reid, unanimously VOTED that the nominations be closed and that the Secretary be instructed to cast one ballot electing Mr. Handy Vice President of the League for a term of two years.

82) Nominations for Secretary being in order, Mr. Dosland nominated Mr. Budlong. Whereupon, on motion of Mr. Brabb, unanimously VOTED that the nominations be closed and the Secretary is instructed to cast one ballot electing Mr. Budlong as Secretary of the League for a term of two years.

83) Nominations for Treasurer being in order, Mr. Griggs nominated Mr. Houghton. Whereupon, on motion of Mr. Roberts, unanimously VOTED that the nominations be closed and that the Secretary is instructed to cast one ballot electing Mr. Houghton as Treasurer of the League for a term of two years.

84) Mr. Griggs reported orally for the Membership and Publications Committee, following which extensive discussion ensued. On motion of Mr. Roberts, unanimously VOTED that the Board wishes to express its satisfaction to the League's management for its effort in the membership campaign enunciated as a result of the 1951 Board meeting

(Continued on page 122)



Ham's Paradise!

CONCORD — A Grand Old Name in ELECTRONICS

A GRAND OLD NAME IN ELECTRONICS COMES TO NEW YORK



For many months past NIAGARA RADIO SUPPLY CORP. has filled these pages with unsurpassed bargains in Amateur Radio Equipment.

Newer and better bargains are contemplated, but under a new name—CONCORD RADIO of New York.

NIAGARA'S vast experience in catering to ham requirements and CONCORD'S tremendous purchasing powers have been combined to give you one of the greatest selections of electronic parts and equipment ever assembled under one roof at lower than ever prices.

Our exciting new store has been crammed full—from floor to ceiling—from basement to roof—of almost anything you will ever want.

Get our Grand Opening Bargain Flyer and your name on our HAM mailing list, free for a QSL card addressed to Mack Santer, W2ZPW, c/o CONCORD's Ham Department.

WATCH THESE SPACES FOR MORE and BETTER
BARGAINS IN ELECTRONIC EQUIPMENT

CONCORD

RADIO

55 VESEY ST. - NEW YORK 7, N.Y.

Dept. Q-7-2

**GUARANTEE
OF SATISFACTION**
All items ordered
must meet
with full approval
or your
money back.

TOWERS by TRYLON

Amateur radio types • Guyed towers for FM-TV antennas • Vertical radiators • Micro-wave towers • Commercial communication towers • Transmission line supports, etc.

Completely fabricated by the most modern methods by 20-year tower specialists, Trylon towers offer top value for any installation—commercial or amateur. Special design and construction features assure maximum dependability.

Made only by
WIND TURBINE COMPANY
WEST CHESTER, PA.

RADIO and TELEVISION

Over 30 years N.E. Radio Training Center. Train for all types FCC operators' licenses. Also Radio and Television servicing. FM-AM broadcasting transmitters at school. Send for Catalog Q.

MASS. RADIO SCHOOL

371 Huntington Avenue Boston 15, Massachusetts
Lic. by Comm. Mass. Dept. Educ.

Q H (QUICK HEADING) BEAM

10 and 20 meter Q H Beams available soon by arrangement with designer. See June QST.

For additional information regarding this remarkable array, write to M. E. Wood, 18 Richardson Avenue, Wakefield, Mass.



**WESTON
LABORATORIES**

Weston 93, Mass.
Wellesley 5-4500

★ CRITICALLY NEEDED

This is a picture of the T5-174 Heterodyne frequency meter. It looks exactly like a BC-221 but covers a higher frequency. We have defense orders we can not fill for lack of this item. If you know anyone who has a T5-174 or have one yourself, please sell it to us or exchange it for new ham gear of your choice. Write, wire or phone.

and that it is expected that this campaign will be continued and intensified in all phases in which success has been indicated.

85) During the course of the above action the Chair announced that with the concurrence of the new President-elect, the following committee appointments are made for the coming year:

For the Finance Committee:

Mr. Noble, Chairman
Mr. Hill
Mr. Hughes

For the Planning Committee:

Mr. Brabb, Chairman
Mr. Groves
Mr. Johnston

86) On motion of Mr. Hill, unanimously VOTED, after discussion, that all divisions of the League which exceeded the national average in membership increase during 1951 are commended.

87) On motion of Mr. Watkins, unanimously VOTED that the Membership and Publications Committee be retained for one year to aid and direct the Headquarters staff in implementing and conducting the membership campaign previously authorized by the Board.

88) On motion of Mr. Roberts, unanimously VOTED that, pursuant to the terms of the Trust Agreement under the Pension Plan, the following persons are appointed to serve as a Pension Committee from this date until June 2, 1953: Arthur L. Budlong, George Grammer, David H. Houghton.

89) Moved, by Mr. Brabb, that, pursuant to Article 7 of the Amended Articles of Association, the Board now appoints three directors to the Executive Committee. But, after discussion, with the permission of his second, Mr. Brabb withdrew the motion.

90) On motion of Mr. Brabb, unanimously VOTED the Board now proceeds to the designation of an additional director to the Executive Committee as required under the terms of Article 7 of the Amended Articles of Association. Whereupon, on motion of Mr. Hill, the Board unanimously VOTED to designate Mr. Noble as a member of the Executive Committee.

91) At this point, at 12:40 P.M., upon request of the Board, the Chair directed that all Headquarters staff personnel retire from the meeting; at 1:10 P.M., at the request of the Board, they rejoined the meeting.

92) On motion of Mr. Reid, the following resolution was ADOPTED:

WHEREAS, the position of General Manager of the League has for a period in excess of five years been a position to which a salary of fifteen thousand dollars (\$15,000) per annum was attached; and Whereas the Board has from year to year heretofore employed Arthur L. Budlong to fill that position on a temporary salary somewhat less than that ascribed to the position;

Now, be it RESOLVED, that effective May 1, 1952 the salary to be paid Mr. Budlong is to be that prescribed for the position of General Manager, viz., fifteen thousand dollars (\$15,000) per annum.

93) At this point, Mr. Hughes invited directors to attend the Pacific Division Convention which is to be held in San Francisco the weekend of July 4, 1952. Mr. Griggs similarly invited members of the Board and the Headquarters staff to attend the Southwestern Division Convention at San Diego the weekend of October 11, 1952.

94) Whereupon, on motion of Mr. Johnston, the Board adjourned *sine die* at 1:17 P.M.

95) (In the course of its deliberations the Board also discussed, without formal action, 1800-2000 kc. privileges and suballocations, the Canadian reciprocal licensing treaty, 21-Mc. TVI, mailing of Director Letters to retiring directors, amateur traffic nets, Canadian suballocations, IARU band planning, engineering standards for amateurs, policy on use of director administrative funds, coordination of TVI committee efforts, ARRL membership and amateur license figures, and the new Novice promotional booklet. Time in session, as a Board: 9 hours, 41 minutes. As a Committee of the Whole: 3 hours, 3 minutes. Total time in session, 12 hours, 44 minutes. Total expenditures authorized, \$18,050.)

A. L. BUDLONG
Secretary

*Build
YOUR
OWN*

TEST EQUIPMENT

Heathkit



Heathkit
AUDIO GEN. KIT \$34.50



Heathkit
TUBE CHECKER KIT \$29.50



Heathkit
PUSH-PULL... 5" OSCILLOSCOPE KIT \$43.50



Heathkit
TELEVISION GENERATOR KIT \$39.50



Heathkit
SIGNAL TRACER KIT \$19.50



Heathkit
CONDENSER CHECKER KIT \$19.50



Heathkit
IMPEDANCE BRIDGE KIT \$69.50



Heathkit
R.F. SIGNAL GEN. KIT \$19.50



Heathkit
ELECTRONIC SWITCH KIT \$19.50



Heathkit
BATTERY ELIMINATOR KIT \$24.50



Heathkit
VACUUM TUBE VOLTMETER KIT \$24.50



Heathkit
HANDITESTER KIT \$13.50

HEATH COMPANY
BENTON HARBOR 9,
MICHIGAN

EXPORT AGENT
ROCKE INTERNATIONAL CORP.
13 E. 40th St.
NEW YORK CITY (16)

*W*hat's New?

See ELDICO SEPTEMBER **QST**

BE A RADIO ENGINEER

You can enter this uncrowded, interesting field. Defense expansion, new developments in electronics demand trained technicians. Study all phases radio & electronics theory and practice: TV; FM; broadcasting; servicing; aviation, marine, police radio. 18-month course equal in radio content to 4 yrs. college. H.S. or equivalent required. Begin Jan., March, June, Sept. Campus life. Write for Catalog.

VALPARAISO TECHNICAL INSTITUTE
Dept. TN Valparaiso, Ind.

LEARN CODE!

SPEED UP Your
RECEIVING
with G-C

Automatic Sender

Type S
\$24.00 Postpaid in
U. S. A.


Housed in Aluminum Case. Black Instrument Finished. Small—Compact—Quiet induction type motor. 110 Volts—60 Cycle A.C.

Adjustable speed control, maintains constant speed at any setting. Complete with ten rolls of double perforated tape. A wide variety of other practice tapes available at 50c per roll.

GARDINER & COMPANY

STRATFORD

NEW JERSEY



ATTENTION MOBILE HAMS

Complete mobile package — nothing else to buy. Outstanding mobile signals use Motorola equipment — backed by years of communication equipment experience — World's largest producer of 2-way mobile equipment.

A mobile transmitter with a double feature FM or AM at flip of the switch, the MOTOROLA FMT-30-DMS (27-30 MC.)... **\$130.00**

P-7253 spring base rear — mount antenna **\$23.13**

New Gon-set Tri-Band Spread Converter... **\$47.60**

MOTOROLA P-69-13 or 18-ARS receiver with special noise limiter for use with any converter having 1440-3000 KC. **\$60.00**

3-30 famous Gon-set converter complete to connect to the P-69-13 or 18-ARS receiver. **\$44.75**

P-327-E Fire wall loud speaker **\$7.50**

The above comes complete with all necessary accessories and mounting hardware. Order direct or through the Motorola National Service Organization member in your area.

NOTE: This Receiver and Transmitter is equipment which has been returned from the field, modified and rebuilt for Amateur Service.

For further information write to:

MOTOROLA INC.

Amateur Sales Dept. QST — July

1327 W. Washington Blvd. Chicago 7, Illinois
Attention: Harry Harrison, W9LLX, Tel. Taylor 9-2200 Ext. 161

YL News and Views

(Continued from page 39)

operators. Both YLs obtained their tickets through classes held at the hospital. . . . W3RXV and W5RZJ recently received their MARS calls and W8HDB regularly operates the MARS station at Wright-Patterson Air Force Base in Dayton. . . . WN4UDQ, Dorothy, is a new Novice in Tennessee, and K25KA, Catherine, is a new Canal Zone YL. . . . Anita, ex-WSTAY and now W4JCR, is living on the highest mountain around Asheville, N. C. She's hoping the elevation will help her contact many of her old YL friends. . . . OM G3FPEK aments that of approximately 7000 amateurs in England, only about 20 are members of the fair sex. . . . W1FTJ, member of the Concord Brass-pounders and custodian of the Worked New Hampshire



Four Canadian YLs who help keep YL activity thriving in VE-land are VE3DEX, Violet (lower left), who concentrates on 80 c.w. and builds most of her own gear; VE3BGG, Marie (lower right), who also likes 80; VE3DTW, Ethel (upper left), who, with the OM, operates 10 and 2 from the Port Willer Lighthouse on Lake Ontario; and VE3DGT, Margaret (upper right), who is at home on all bands from 80 through 10 meters.

Certificates, reports that Dottie, W3JSH (Coraopolis, Pa.), was the only YL to work all N. H. counties in the WNH QSO Party. . . . The L. A. YLRC gave a shower for W6WSV, the Club's Publicity Chairman, three weeks before Carol's new son arrived. . . . W6s BLI FEA GEV GQZ HHD MWU PJF QVK ZKD ZYD and W4KZT attended the Fresno Radio Club's annual hamfest in May. . . . Since receiving her license in 1938, W8SKZ has spent most of her operating time on forty. . . . Judy Volpe, age nine, daughter of W1LEL, passed the Novice Class examination and is awaiting her call. . . . W8GJP, who planned entertainment for XYLS at the "Ham-Vention" sponsored by the Dayton Amateur Radio Assn., reports that the following YLs enjoyed ham doings at the affair: W3UUG, W8s FYT GJP HDB HUX HWX JLP RVP and W9s ILH JUJ and QLH. . . . While touring Europe this spring, W6UXF enjoyed the hospitality of G3ACC, Meg, and G2YL, Nell. . . . We are sorry to record the passing of W6SLT, Edna McGeorge of Los Gatos, California. Edna was an active YL until the onset of serious illness two years ago.

Miscellany

The YLRL Photograph Album and Club Scrapbook are available for display at YL meetings and gatherings. If either or both books are desired, please write to YLRL Publicity Chairman, W1QON.

Wonder how many YLs have passed the Extra Class exam? We'd like to hear from those who have made the grade. Any "grandmother-class" girls among us?

In response to many requests for the information, we'd like to ask how many teen-age or younger YLs there are the world over. YLs sixteen or under, do drop us a card, so we'll know who you are and approximately how many of you there are.

RIDER · Tek-File
The EASY way to
service tv
receivers!
NOW packs 1-60

JOHN F. RIDER

Publisher, Inc.

480 Canal Street, New York 13, N. Y.

WOW! See **ELDICO**
SEPTEMBER QST




**RADIO • TELEVISION •
ELECTRONICS**

in all Technical Phases
New Classes (Day & Evening) Start
1st of Dec., Mar., June, Sept.

FREE PLACEMENT SERVICE FOR GRADUATES
For Free Catalog write Dept. ST-52

RCA INSTITUTES, INC.

A Service of Radio Corporation of America
350 WEST 4th ST., NEW YORK 14, N. Y.



MAKE THIS YOUR HOME FOR IMPORTANT WORK UNDER IDEAL CONDITIONS

- TV RECEIVER DESIGN ENGINEERS
- ELECTRONICS ENGINEERS
- FIELD ENGINEERS
- TEST & INSPECTION ENGINEERS
- LAB. TECHNICIANS

NEEDED TO WORK ON: Radar, G.C.A., Mobile Radio, Auto Radio, Airborne Communication & Navigation Equipment, Television, Antennas, Microwave Equipment, Servo Mechanisms, Guided Missiles and Test Equipment Design.

YOU BENEFIT AT BENDIX RADIO:

from high wages, a modern, air-conditioned plant, paid vacations and holidays, group insurance and a good chance for advancement.


Housing immediately available in the beautiful suburban and country areas that surround the Bendix Radio plant.

Write, Wire or phone
MR. E. O. COLE, DEPT. K

Bendix Radio

DIVISION OF BENDIX AVIATION CORPORATION
BALTIMORE-4, MD. Phone: TOWSON 2200

VHF COMMUNICATIONS 6-Meter Coils



- ✓ general amateur communications equipment
- ✓ for Civilian defense radio nets.
- ✓ intercity, county and local and mobile emergency radio networks.

These popular members of a famous family do big jobs in small places with low losses!

Rated from 25 to 150 watts, they are available in various types including variable center link, fixed center and end-linked models and straight, without link. Write for B & W catalog.

B & W products are featured by leading distributors

B&W

BARKER & WILLIAMSON, Inc.

237 FAIRFIELD AVE., UPPER DARBY, PA.

TESTERS

BUILD YOUR FUTURE AT

SPERRY

ELECTRO-MECHANICAL • To test complex apparatus involving electrical servos, synchros, computing mechanisms and gyros. Familiar with schematics, trouble shooting, adept in the use of oscilloscope, VTVM and Volt-Ohm-Milliameter; 2 years engineering school or equivalent required; also 2 years service or industrial experience on gun-fire control computing mechanisms.

ELECTRONIC • Minimum 2 years experience in industry or government service in test, maintenance, and trouble shooting of radar systems; 2 years engineering school, 2 years amateur operating experience or equivalent required.

• COST OF LIVING ADJUSTMENT

• FULL EMPLOYEE BENEFITS

• TOP RATES

Send Resume or Apply in Person to
Employment Office

SPERRY GYROSCOPE CO.

Division of the Sperry Corporation

GREAT NECK, LONG ISLAND, N.Y.

Another ELDICO

FIRST!

See SEPTEMBER QST ...

AN/APR-4 COMPONENTS WANTED

In any condition. Also top prices for: ARC-1, ARC-3, APR-1, APR-5A, etc.; TS-34 and other "TS-" and standard Lab Test equipment, especially for the MICROWAVE REGION; ART-13, BC-348, BC-321, LAE, LAF, LAG, and other quality Surplus equipment; also quantity Spares, tubes, plugs and cable.

ENGINEERING ASSOCIATES

434 Patterson Road

Dayton 9, Ohio

EASY TO LEARN CODE

It is easy and pleasant to learn or increase speed the modern way — with an **Instructograph Code Teacher**. Excellent for the beginner or advanced student. A quick, practical and dependable method. Available tapes from beginner's alphabet to typical messages on all subjects. Speed range 5 to 40 WPM. Always ready, no QRM, beats having someone send to you.

ENDORSED BY THOUSANDS!

The **Instructograph Code Teacher** literally takes the place of an operator-instructor and enables anyone to learn and master code without further assistance. Thousands of successful operators have "acquired the code" with the **Instructograph System**. Write today for full particulars and convenient rental plans.



INSTRUCTOGRAPH COMPANY

4709 SHERIDAN ROAD, CHICAGO 40, ILLINOIS

Mast Loading and Guying

(Continued from page 44)

a few days in advance by several alternate layers of roofing compound and impregnated burlap or cloth commonly used for roof patching.

Resonances

Any flexible structure is subject to "resonances," which must be classified under "undetermined" factors. The values given in Tables I and II are based on ample factors of safety, and no resonances should be encountered.


Resonances can be damaging, but frequently they can be overcome by various changes that will change the natural frequency — after the source is located — including:

1. Moving guy points on the mast.
2. Damping the vibrations by wrapping the mast with heavy tape at two or three points along its length, or by plugging the ends with wood dowels 1½ to 3 feet long.
3. Cushioning the base of the mast with an 8-by-24-by-2-inch creosoted wood block (cypress or redwood preferred), laid over 6 inches of cinders or sand, and grounding the base of the mast electrically with a wire and ground rod.

160-Meter Rig

(Continued from page 60)

increased slowly while checking the stability. For normal operation at maximum legal input, the screen voltage is raised to 350 and the plate



A view of the VFO section with the cover removed. The inverted 6AG7 socket is just to the left of the tuning condenser. RFC₁ is to the front of the 6AG7 socket, the shielded wire connected to the choke is the keying lead. The grid coil is mounted on a half-inch cone insulator. The padder condenser is mounted on a "U"-shaped bracket to the right of the tuning condenser.

voltage to 1200 or 1250. The coupling to the antenna or load can then be adjusted to bring the power input up to 200 watts.

As mentioned previously, the rig works quite

(Continued on page 128)

PREVIEW ANNOUNCEMENT

The NEW GONSET 2-METER TRANSMITTER-RECEIVER

*A*nother GONSET first, answering the need for a complete two meter fixed-portable unit, the new GONSET 2-METER TRANSMITTER-RECEIVER provides an ideal unit for home, mobile and portable use.

- ★ Crystal control 12 watt transmitter
- ★ T.V.I. Proof
- ★ Super-het receiver
- ★ Small size — $8\frac{1}{2}$ x $10\frac{1}{4}$ x 6 deep
- ★ Universal power supply, 110 VAC — 6 VDC.
- ★ Uses either crystal or carbon mike
- ★ Needs only microphone and antenna to go on the air



GONSET CO.

801 S. Main Street
BURBANK, CALIF.

SAVE \$62.50 ON THESE 'SCOPES!

YOU PAY ONLY \$35

- REGULARLY \$97.50
- HARVEY LABS 188-TS
- 2" VISUAL ALIGNMENT

Primary use: examination and alignment of tuned circuits. Fine modulation percentage indicator for "ham" work, also FM gear. Sweep circuit easily added to make a complete oscilloscope. Controls: vert. and horiz. centering; vert. and horiz. gain; focus; intensity; attenuator switch; uses phone jacks for input. About 1 volt for full deflection — vert. and horiz. deflection sensitivity. Flat within 3 db 20-20,000 cps. Consumes 33 watts. Complete with 902A 2" CRT, 2 — 6SJ7, 6X5GT, 5Y3GT, 115V AC power supply, instructions, schematic. In gray crackle metal case, $10\frac{1}{2}$ x $7\frac{1}{2}$ x $11\frac{1}{2}$ ". Shipping wt. 22 lbs. Mail your order today!



ONLY 15
AVAILABLE

RADIO SHACK

CORPORATION

167 Washington St., Boston 8, Mass.

BE SAFE WITH

Q-max

A-27

LOW-LOSS LACQUER & CEMENT

• Q-Max provides a clear, practically loss-free covering, penetrates deeply to seal out moisture, imparts rigidity and promotes electrical stability. Does not appreciably alter the "Q" of R-F coils.

• Q-Max is easy to apply, dries quickly, adheres to practically all materials, has a wide temperature range and acts as a mild flux on tinned surfaces.

In 1, 5 and 55 gallon containers.

Communication Products Company, Inc.

MARLBORO, NEW JERSEY
(MONMOUTH COUNTY)
Telephone: Freehold 8-1880



Evans RADIO

Service to hams

• "YOUR FRIENDLY SUPPLIER"

by hams. Nationally accepted brands of parts, tubes and equipment. Trade-ins and time payments. Write WIBFT.

10 HILLS AVENUE

• CONCORD, N. H.

IT'S NEVER BEEN
DONE BEFORE. . .
See **ELDICO**
SEPTEMBER **QST**



RECEIVING SENDING
CODESPEED *without strain*

CHAMPIONS ENDORSE CANDLER WAY

Get skill, accuracy, speed with the highly endorsed Candler System. Learn to send and receive by telegraph or radio code. Government service and commerce need thousands of better trained operators. Air commerce, mail, freight, etc., demand expert, reliable operators. Good pay. Get the Candler System, the maker of champions. It teaches you the "knack" of sound sense, alertness, speedy sending and receiving without strain. Adventure — good pay. Learn at home or wherever you are. Rush name today for free book.

FREE!

CANDLER SYSTEM CO.

Dept. 4-H, Box 928, Denver 1, Colorado, U.S.A. and at
52b, Abington Road, Kensington High St., London W.8, England

nicely doubling frequency in the output stage to 80 meters. In this case, it may be of some advantage to raise the screen voltage to 400.

This transmitter has been in almost constant use since it was built and I have been highly pleased with the results and the reports.

ARRL Articles — By-Laws

(Continued from page 59)

responsible for the general supervision of the affiliated societies and their welfare, and for the relations existing with them; he shall keep the records and conduct the correspondence with them.

7. These Rules and Regulations shall have the force and effect of By-Laws of the League. They may be amended as necessary from time to time by the Executive Committee. Amendments or revisions shall become effective as of the date of their publication in "QST".

RULES AND REGULATIONS OF THE COMMUNICATIONS DEPARTMENT

(Rules and Regulations of the Communications Department are now in preparation.)

How's DX?

(Continued from page 67)

in TKX! AC3PT, the Maharaj Kumar of Sikkim, fills a 40-meter zepp with 60 watts from a 6L6-807 rig. He receives with an AR88. Located in The Palace, Gangtok, the Maharaj writes an enthusiastic letter to WIBDI anent conditions and the like. He looks forward to working W/VEs as conditions improve. W2TXB's experiences on the QSL front go like this: "Last year . . . I sent out 211 QSLs to which 72 did not reply, 33 per cent. I sent 106 direct by air mail or regular mail and 31 failed to reply. Of 105 sent via QSL bureaus, 41 did not reply. I would like to take off my hat to the VP8s — worked 4 of these and each one in a different country; all came through with cards." VP5BN of Jamaica takes time out every six weeks to clean up all QSL debts. He ships 'em out via bureaus and all incoming cards are answered. Those interested in direct replies or replies via air mail must accommodate with IRCs. F7AS (W6KEN) accompanied F7BB to Monaco as 3A2AQ. The station was on the air for four days in late April with a 50-watter, an HRO and a V beam oriented U.S.A.-ward. There was A3 operation on 20 and 40, c.w. on 20, 40 and 80. While conditions for W/VEs were extremely odiferous, a long list of contacts accumulated. Jim remarked on the excellent welcome and hospitality put forth by 3A2 officialdom. Andorra is next on F7BB's agenda. MI3ZX reports the bands poor in general and hears that AP7IR (IIIR) will operate from a spot very close to Tibet. Also, that VQ3PBD will operate as VQ1PBD immediately if not sooner. The MI3US gang is curious about one BK2HY "in Antarctica" and 6A4AA. [The latter sounds like a refugee from a tube socket. Boss. — Jeeves]. GM3CSM was to meet W6s AM and MA at the Prestwick airport on the first leg of the Wallaces' European tour. One-hundred-twenty-five EA QSOs (with at least three for each of the nine EA call areas!) will qualify you for the *España Diploma* offered by URE. Write the society for complete details. Twelve Ws have earned the "Worked Cuba" award sponsored by ARALV. Seven QSL cards confirming contact with each of the seven geographical CM/CO call areas (CM1 through CM8, excluding CM4) will do the trick. "4X4=16" is the title of an award presented by IARC of Israel. QSLs verifying sixteen QSOs with 4X4s on four amateur bands

(Continued on page 130)



**When You Plan Your Civil Defense
Nets, You'll Get
Longer Range
with Premax**

ANTENNAS

Whether it's RACES, the Amateur Net in CD, a mobile job on 75 or 20, or a CAP or Marine fix, you'll find Premax Low-Cost Antennas will give you more range and stronger signals. Convenient, easy to install — just what you need.



**Get the New Antenna
Bulletins Today**

PREMAX PRODUCTS

DIVISION CHISHOLM-RYDER CO., INC.

5202 HIGHLAND AVE., NIAGARA FALLS, N. Y.

ATTENTION, VIKING 1 OWNERS

Available thru your JOHNSON distributor, the VIKING 1, TVI SUPPRESSION KIT. Included are all the necessary custom made shields, chokes, capacitors and hardware. Simple installation is assured by careful design.

The shield encompassing the transmitter chassis fits inside the standard Viking 1 cabinet without affecting its appearance or operation. Perforated etched aluminum shield panels are formed and punched, ready for assembly. The lid of the shield is removable for ready access to tubes and crystals. Completing the shielding are: an aluminum chassis bottom plate, meter shield and shield for the dial aperture. Assembly is by means of thread cutting screws furnished.

The individual filters consisting of low inductance chokes and ceramic disc capacitors are located as follows: meter leads keying lead, VFO power socket, PA high voltage lead, PA screen and buffer plate supply. Similar filters are provided for the AC line, filaments and for a lead to actuate an antenna relay. Antenna relay terminals are included for those desirous of adding this accessory.

Equipped with the TVI SUPPRESSION KIT, installed in accordance with instructions furnished, a JOHNSON LOW PASS FILTER and an effective ground, it is possible to operate the VIKING 1 transmitter in virtually any location without television interference.

230-20 • Low Pass Filter Amateur Net \$16.50
230-21 • Viking 1, TVI Suppression Kit Amateur Net \$24.75




E. F. JOHNSON COMPANY

**WASECA,
MINNESOTA**



NATIONAL

- Proven
- Dependable
- Quality



VERSATILE SHAFT COUPLINGS

National makes a complete line of insulated and non-insulated, flexible and rigid shaft couplings designed for a wide variety of practical applications. They are free of backlash, mechanically strong and fit all popular shaft diameters. Write for drawings and specifications.

National



NATIONAL COMPANY, Inc.
MALDEN, MASSACHUSETTS

are required. Write IARC for the pitch in detail.
 KX6AO (ex-KH6VB-KM6AO) is looking for Novices on 11 meters. Chuck has a BC-610, a 3-element rotary on 10 meters and a Sterba on 20. He finds the latter band consistently good in the late Kwajalein evenings.
 Some choice squibs from W5KUC's West Gulf DX Bulletin: KP4ZK is ex-2FB of 1912. . . . ZL1HY may put the ZM7 prefix to work on Union Island. . . . W3GRF paid a personal visit to G2ML. . . . The West Gulf DX Club held a bang-up meeting in Shreveport where an election of officers installed W5KUC president, W5CEW veep, W5UCQ secretary and W5FXN treasurer. Chosen for the club policy committee were W5s ASG ECK ENE KC and MIS, to work with W5s KUC and CEW. . . . "Juice" notes: It's Rio de Oro for EA8AW around September. Lately available are FL8MY, 4W1MY, VR4AF, VR7AB (Nauru), FO7AW and KC6QL (Truk). Good luck!

W1RWS pulled the QSL-of-the-Month from his office mailbag. It's an IYAK card confirming a 14-Mc. 'phone QSO with W4OSU.

Correspondence

(Continued from page 69)

NOVICES SPEAK UP

1338 Washtenaw
Ann Arbor, Mich.

Editor, QST:

I deplore the trend in radio magazines in general that treat the Novice as a rank newcomer to radio theory. Most Novices I am sure are well up on their theory — they just can't send or copy the code fast enough!!!

— Jerome S. Miller

Kellogg Star Route
Oakland, Ore.

Editor, QST:

I do not know if this matter has been called to the attention of all radio amateurs or not, but the fact that there are so many high-power transmitters operating in the Novice band of 3700-3750 kc. limits my hobby to the more quiet hours. I am sure that I speak for many Novices running low power that would like to operate when that band is at its best. We all can take QRM in our stride — but I am sure there is a solution to this problem.

— John R. Barrett, WN7PXS

PUBLIC SERVICE

c/o U. S. Veterans Hosp.
San Fernando, Calif.

Editor, QST:

With some time on my hands at present I have been trying to settle in my own mind my place in the scramble by various agencies for hams to operate civil defense and/or disaster relief stations.


I hear and read about CAP, MARS, AREC, and here in California the Defense and Security Corps (National Guard Reserve), all trying to recruit hams. Each has a set of assigned frequencies, call letters, procedures and network of stations. In addition, competition seems to exist as to who arrives first or is best organized.

What confuses me is this: Where do I stand? Is the ham to join a quasi-service organization in order to most fully utilize his potentialities or should he affiliate with all and juggle call letters, etc., as he meets with the many varied services.

— Arnold D. Senterfitt, W6ESV

[EDITOR'S NOTE: Coordination and cooperation with non-amateur agencies and organizations, especially the military, civil defense and the Red Cross, are of paramount importance. We believe this can best be accomplished not necessarily by individual-amateur participation in one to the exclusion of others, but through the medium of the amateur service's own emergency organization, the Amateur Radio Emergency Corps (AREC), which works with and for all agencies to the degree public need and service require.]

FOR MOBILE COMMUNICATIONS



POLIC-ALARM MONITORADIO

Users of FM 2-Way Radio Communications equipment throughout the entire nation, find Polic-Alarm and Monitoradio a welcome innovation to low-cost mobile communications radio.

6 MODELS FOR ALL SYSTEMS

6 VOLT MOBILE

M-51 Tuneable 30-50 MC (Illustrated)

M-101 Tuneable 152-163 MC

115 VOLT AC-DC

PR-31 Tuneable 30-50 MC

PR-8 Tuneable 152-163 MC

AIRCRAFT 115 VOLT AC-DC

AR-2 AM Tuneable 108-136 MC

AR-3 AM Tuneable 118-149 MC

(includes the 2-meter Amateur Band)

For complete information see your
Jobber or write us today!

RADIO APPARATUS CORPORATION

55 N. NEW JERSEY STREET • INDIANAPOLIS 4, INDIANA • PHONE: ATLANTIC 1624

QST BINDERS



HANDSOME

•
PRACTICAL

•
USEFUL

Keep your back issues of QST in a neat orderly way. No more fishing through a disordered stack of loose, dog-eared copies, digging for a back issue, and finding it the last one under the pile...

- Holds 12 issues of QST
- Opens and lies flat to any page
- Protects and preserves your copies
- QST's always available for reference

PRICE \$2.50 postpaid

Available only in United States and Possessions

The AMERICAN RADIO RELAY LEAGUE, Inc.
WEST HARTFORD 7, CONN.

HAM-ADS

(1) Advertising shall pertain to radio and shall be of nature of interest to radio amateurs or experimenters in their pursuit of the art.

(2) No display or character will be accepted, nor can any special typographical arrangement, such as all or part capital letters be used which would tend to make one advertisement stand out from the others.

(3) The Ham-Ad rate is 30¢ per word, except as noted in paragraph (6) below.

(4) Remittance in full must accompany copy. No cash or contract discount or agency commission will be allowed.

(5) Closing date for Ham-Ads is the 25th of the month preceding publication date.

(6) A special rate of 7¢ per word will apply to advertising which, in our judgment, is obviously non-commercial in nature and is placed and signed by a member of the American Radio Relay League. Thus, advertising of bona fide surplus equipment owned, used and for sale by an individual or apparatus offered for exchange or advertising inquiring for special equipment, if by a member of the American Radio Relay League take the 7¢ rate. An attempt to deal in apparatus in quantity for profit, even if by an individual, is commercial and all advertising by him takes the 30¢ rate. Provisions of paragraphs (1), (2) and (5), apply to all advertising in this column regardless of which rate may apply.

(7) Because error is more easily avoided, it is requested signature and address be printed plainly.

(8) No advertiser may use more than 100 words in any one issue nor more than one ad in one issue.

Having made no investigation of the advertisers in the classified columns, the publishers of QST are unable to vouch for their integrity or for the grade or character of the products or services advertised.

QUARTZ—Direct importers from Brazil of best quality pure quartz suitable for making piezo-electric crystals. Diamond Drill Carbon Co., 719 World Bldg., New York City.

MOTOROLA used communication equipment bought and sold, W5BCO, Ralph Hicks, 204 E. Fairview, Tulsa, Okla.

SUBSCRIPTIONS, Radio publications a specialty. Latest Call Books, \$2.50. Earl Mead, Huntley, Montana. W7LCM.

QSL's-SWL's Meade W0KXL, 1507 Central Avenue, Kansas City, Kans.

ANNOUNCING Chicago Hamsters Radio Club Eighteenth Annual picnic at Frankfort Grove, Ill., Aug. 10th, 1952. Donations \$1.50.

3-Element 2-meter beams, Riverside Tool Co., Box 87, Riverside, Ill.

WANTED: Your surplus radio receivers, transmitters, ARC-1, ARC-3, ART-15. We buy anything. What have you? Tom Allen, 159 Carlton Ave., Brooklyn 5, N. Y.

QSL's Taylor, (W5VME) Little Rock, Miss.

QSL's, SWL's, America's Finest! "On Vacation," C. Fritz, 1213 Briargate, Joliet, Ill.

WANTED: Your attendance at the Mid-American and Dakota Division ARRL Convention, September 5, 6 and 7, 1952. Nicollet Hotel, Minneapolis, Minn.

QSL's: Fluorescent QSL's radiant and glowing with quality control. QSL's Kromekote three colors and up. Rainbow maps, DX QSL's. Samples rushed, 10¢. Elmer Fred, Box 86, Lynn, Pa.

QSL and SWL cards. Samples, WISQF, Minner, Candia, N. H.

PHONE, patch schematics, practical discussion, \$1.00. Nichols WIMK.

WANTED: Top prices paid Navy gelays 1F, 1G, 1CT, 5F, 5G, 5CT and BC-348; BC-221, AN ART-15, AN/ARC-1, AN/ARC-3, RTA-1B. Leticron Research, 719 Arch St., Philadelphia.

TRANSFORMERS 1000 Va. 4400-2200-1100-1100-2200-4400. G-E \$15. 2MF condensers, 4000 VDC, continuously. \$9. G-E, both guaranteed. Dawson, 5740 Woodrow, Detroit, Mich.

QSL's, Brownie, W3CJL, 433 Chestnut, Emmaus, Penna.

10 and 20 meter beams, \$23.25 up. Aluminum tubing, etc. Willard Radcliff, Fortoria, Ohio.

QSL's: \$2.00 will bring you 100 two-color cards, 24 hour service. Wahl, W3GFF, 1805 Kenilworth Ave., Washington 19, D. C.

SPECIAL: Used S.W. Diathermies. Cost over \$500 now: 500-900 watts input. Tubes, meter, transformers, condensers, etc. worth more than we are asking. Portables, \$25. Consoles, \$35. F.O.B. Chicago. Medical Arts Supply Co., 500 S. Wolcott Ave., Chicago 12, Ill.

FOR SALE: Gonset Tri-band w/mount, \$15; BC-348K, 110V, w/spkr and S-meter, \$65; Montaradio 10-50 Mc, \$45; All in good condx. W1UHQ, 108 Westminster St., Hyde Park 6, Mass. Talamian.

SELL NC57B receivers, guaranteed to be in perfect condition. Best offer above \$70 positively takes it. All offers answered. A.C. Victor, 1008 No. Spring St., Beaver Dam, Wis.

INSTRUC TOGRAPH for sale. Almost new 117 VAC model, audio oscillator, ten tapes, instructions. Only need key and earphones. \$27 F.O.B. Will give free a used code course, best obtainable W6JOM, 715 Mira Mar, Long Beach, Calif.

SELL: Crystals, 7250 Kc. 3735 Kc. 3570 Kc. in holders, \$1. each. 2-250TH, 1-450TH, \$15 each; 100TH, \$5; 2-811, 2-812, 3-1H75, \$2 each; 2 API, 2-2C40, \$5 each; tubes all new, 2-2" round G-E 0-1 milliameters, \$2.50 ea., 3" round G-E C-100 milliammeter, \$1.75. Snopceae tube \$4. J. E. McMillan, 10221 Doty Inglewood 2, Calif.

QSL cards? Modernistic? Cartoons? State-map? Rainbow-map? QSL samples, 25¢. Sakkera, W8DED, Holland, Michigan.

WANTED: Early DeForest and Marconi Wireless apparatus. Also early tubes and early magazines, call books, text books and other literature. Franklin F. Wingard, Rock Island, Ill.

WANTED: Navy Selcons, types 1F, 1G, 1CT, 5F, 5G, 6G, 7G, etc. Autoseals, AV-1, AV-5, AV-101D, AV-201, etc. Tubes, Test equipment, Signal Corps equipment. Send lists. Top prices. Electro, 110 Pearl St., Boston, Mass.

WANTED: Communication receiver, transmitter, V.F.O., tube tester, etc. Please furnish full description, etc. New York City or vicinity preferred. W2NXP, George A. Laine, 222 East 7th St., Brooklyn 18, N. Y.

2500 W.V., 5000 V. test oil mica condensers, 3/4" thick. Special, \$1.95 each; 2 for \$3.50. Eight position circuit transfer push-button switches. Silver plated contacts. Excellent for band-switching and meter switching use. Includes 8 bakelite buttons. No escutcheon plate. Special, \$1.29 each; 2 for \$2.00. Money-back guarantee. All shipments cash with order, shipped prepaid. Limited quantities. Planet Television Corporation, 685 Broadway, Brooklyn 6, N. Y.

10-20 element 2-meter aluminum Brownie beams. Made to order. Write H. W. Snyder, W3LMC, 4330 Glenmore Ave., Baltimore 6, Md.

FOR SALE: Stancor 60P-50 watt fone and cw transmitter, 160M thru 10M. Oscillator coils and all tubes furnished. Best offer over \$50.00. W8ZCV, P. O. Box 147, Trotwood, Ohio.

1 75A1 Collins receiver, new, \$275.00; **1 RME-70 receiver**, \$75.00; **1 Viking transmitter**, wired, tubes, used ten hours, \$275.00; **1 BC-221s original book and crystal set**, \$25.00; **1 BC-221 chassis** without cabinet, \$35.00; **1 459A new transmitter**, \$20.00; **1 696 transmitter**, \$20.00; **6 BC-45 05ers**, \$15.00 each; **20 374N Command receivers**, all bands, \$1.00 each; **20 T117 receivers** with tubes, \$1.00 each; **1 600 cycle 1000 Hz oscillator**, \$1.00 each; **1 600 cycle 1000 Hz oscillator**, complete with tubes, \$3.00 each; **1 with power pack**, ready to go, \$5.00; **1 DW 1 direction-finder** with 10 ft. extension loop, \$25.00; **1 ARS scope** with order, \$15.00 each; **1 Collins HVC VFO** built-in 40-mtr. amplifier, \$100.00. All inquiries will be answered. Reply to "Radio", P.O. Box 550, Little Rock, Ark.

NATIONAL NC-57B, 1 year old. Asking \$70.00. W2MMPB, 210 Jewett Ave., Buffalo 14, N. Y.

WANTED: TA-12C Bendix transmitter. State condition and price. W6GX, 2133 Stacia Way, Sacramento 18, Calif.

RADIO & Television News, Engineering Edition, 1945-1951 inclusive, \$25.00. QST: 1946-1951, \$15.00; good condition. In binder. Bob Abernethy, W2PQV, 120 Frederick Ave., Babylon, L. I., N. Y.

FOR SALE: Collins 110B3, built-in phase modulator and external modulator using 815, \$225.00. F.O.B. Gablin, Nevada, E. Williamson, W7NWU.

SELL or trade: Converted Mark II \$35.00. Michael Schilder, W2LKC, 44 Malone Ave., Long Beach, N. Y.

GRID Dip 6-150 Mc., \$10.00; **10-meter mobile trans.**, \$10.00; **10-meter converter**, \$10.00. W6RET, \$50 So. "G", Oxnard, Calif.

SELL: QST 1937-1950. Missing only 9 issues. W2RCV, Box 208, MIT Dorms, Cambridge 39, Mass.

WANTED: Cash or trade, fixed frequency receivers 28-42 Mc. W9YIV, Troy, Ill.

FOR SALE: Stancor 60N, 100 watts, de-TV'd with low pass filter, 52 countries on \$10, \$100; NRI Comm. course; SCR522 (2 receivers) partially converted; Micramold XTR-1 partially assembled; S-38, needs work, \$15.00; AVR20a, A. Nelson, W2HPD, 39 East 7th St., New York, N. Y.

WANTED to buy: Compact high power phone transmitter, band-switching 75-20. Only interested in quality job. Send details and price in first letter. W3LIG, National Bank Bldg., Corry, Penna.

TAYLOR T814, used little; Johnson Split-Stator 150 mfd. 7000V insulation; swap for three 2" meters 50-100-500 Ma. or Vibronex. C. A. Andreen, W8EKQ, 829 East 88th St., Cleveland 8, Ohio.

FOR SALE: Unused 3000 watt 110V.A.C. Kato generator. Factory remanufactured, \$250, plus shipping charges. Dr. C. H. Scheffey, Mayo Clinic, Rochester, Minn.

BARGAINS! New and reconditioned Collins, Hallicrafters, National, Hammarlund, Johnson, Harvey-Wells, Gonset, Elmac, Morrow, RME, Lyco, Millen, Meissner, others. Reconditioned S-38, \$29.00; S-53, \$49.00; S-40A, \$69.00; S-40B, \$79.00; S-43, \$119.00; SX-42, \$199.00; SX-62, \$199.00; SV-54, \$15.00; NC-57, \$69.00; NC-173, \$139.00; NC-183, \$199.00; HRO-50, \$249.00; HO129P, \$139.00; Meissner EX, \$59.00; Bandmaster transmitters, DB22A, HF-10-20, VHF-12-24, RME45, HRO-7, HRO-50T, SP400K, Lyco 600, Collins 75A1, Collins 32V, others. Shipped on trail. Time payments. List free. Henry Radio, Butler, Missouri.

DON'T Fail! Check yourself with a time-tested "Surecheck Test", similar to the F.C.C. tests. Novice, \$1.50. General, \$1.75. Advanced, \$2.00. Amateur Radio Supply, 1013 Seventh Ave., Worthington, Minnesota.

WANTED: Any QST's before 1921, Wireless Age, Electrical Experimenter, Radioconductor, Proceedings of IRE 1913 to 1920, Collins "Wireless Telegraphy," any Marconi, DeForest, Electro Importing, Mesco, Union Wireless apparatus. Amateur apparatus manufactured before 1914. Please describe all items fully and give price. Louis Kizilo, W1AAT, 100 Bay View Ave., Salem, Mass.

BARGAINS: Extra special Motorola P-69.13 mobile receivers, \$29.50; Globe King, \$315.00; HT-9 \$199.00; HRO-50 \$275.00; Lyco 600 \$109.00; HRO-7 \$199.00; Collins 75A1, \$275.00; HRO-ST, \$175.00; SX-71, \$159.00; HRO Senior, \$119.50; RME 2-11, \$99.50; RME 2-11, \$99.00; Meissner EX, \$59.00; S-40A or SX-16, \$69.50; VHF-152, \$59.00; HF-10-20, \$59.00; SX-24, \$69.00; Globe Trotter \$79.50; Meissner Signal Calibrators, \$24.95; MB611 mobile transmitters, \$29.00; 90800 exciter, \$29.50; RCA Channeler, \$69.50; SX-10 \$14.95; Gonset 10-11 converter, \$24.95, and many others. Large stock trade-in; free trial. Terms financed by Leo, W6CFO. Write for catalog and best deal to World Radio Laboratories, 740-44 West Broadway, Council Bluffs, Iowa.

INSTRUCTOGRAPH, ten tapes less key and phones, \$25.00. Jack Schlosser, 3214 17th Avenue, Sheffield, Ala.

QSL! Samples 106. Tooker, Drawer T, Lakehurst, New Jersey.

JOHNSON Viking mobile transmitters will be available either in kit form, or complete just as soon as the factory makes delivery. Write for quotation on a completed unit. We supply the Viking VFO complete at \$54.95, and the Viking transmitter complete at \$275.00. Terms, trades; write Carl, WJBF, Evans Road, Concord, N. H.

SELL: Lyco 10m mobile 12 watts with mike, \$12.00. 25 watt mobile 2E26, \$18.00. CW xmitter 610-811, no power supply, \$11.00. W4SJ, Box 1269, Nashville, Tenn.

NEW crystals for all commercial services at economical prices; also regrounding or replacement crystals for broadcast, Link, Motorola, G-E and other commercial types; no amateur. Over 16 years of satisfaction and fast service! Eldson Electronic Company, Phone 3-3901, Temple, Texas.

IMMEDIATE delivery: power supplies for Bandmaster transmitters. \$39.50. F.O.B. Alco Electronics, 102 Marston, Lawrence, Mass.

STATION call plates. Cast aluminum. Black and silver finish. Four styles: top or bottom of auto license, panel mounting, and desk display. Specify which desired. Size approximately 2 1/2" x 10 1/2". Letters. \$2.95 each. W. L. Waddell, W4UQJ, 3783 Ellijah Drive, Brookhaven, Georgia.

WANTED: Millen 90810 VHF transmitter and other VHF gear; 522 ARC 1-4-5, etc. Describe and price in first letter. Cyril F. Hoffman, Uvalde, Texas.

SELL: BC-610E transmitter, BC-614E speech amplifier, 70A junction box, complete with 10, 20, 40 and 80 meter coils, 70A transformer, HO-120X and speaker. Best cash offer. W4EAS, 4544 Ramona, Jacksonville, Fla.

WOULD like help from local operator on code and theory. R. Caro, 20 Orchard St., Welleley 81, Mass.

FOR Sale: Hallcrafters SX-28A, like new, \$200.00. Two complete Abbott TR-4 2-meter receiver-transmitter with power supplies and microphones, only \$60 for both. Peck, W20IF, 205 Perrine Ave., Auburn, N. Y.

SELL: 400 watt fone xmitter in excellent cond. Includes Class B modulator, VFO, five power supplies, furniture cabinet, \$300. Navy officer wishes to sell because of continual movement. Freight prepaid from San Francisco. E. S. Pratt, 315 Jefferson Terrace, East Point, Georgia.

HALLCRAFTERS S-72 portable rcvr. used only slightly, new condx. \$75. Save \$35.00! Letting 240 wdt coils for 4 bands and 2 stals. \$70.00. No trades. All letters will be answered. Blum, 2661 Dibble Ave., Columbus 4, Ohio.

SELLING complete National Schools Radio Television Electronics course. First \$50.00. Fox, Box 4143, College Station, Texas.

NOW need following copies Radio Amateur Call Book: 1949 Winter, Fall; 1918 Summer; 1915 Winter, Spring, Summer; 1914 Winter, Fall; 1912 Winter, Summer, Fall; 1910 Spring, Summer; 1929 Spring; 1928 all four copies 1927, Spring, Summer; 1926 Winter, Spring, Summer; 1925 any copy; 1924 Winter, Summer, Fall; 1923 Summer, Fall; 1922 Spring, Summer, Fall. Also U.S. Govt. Printing Office Edition "Commercial Stations", 1922, '25, '26. "Amateur Stations", 1925, '26. Also looking for Year Book of Wireless Telegraphy & Telephony, Marconigram Magazine, Blue Book List of Calls, QST 1915-20, ARRL List Member Stations, Bob Willits, W1PN, Box 26, Hyannis, Mass.

ATTENTION Novices! NC-57 in A-1 condition. Have to sell. First \$75 takes this fine rcvr. Would prefer a local deal. Spencer Miller III, W1VNN, 259 Longmeadow St., Longmeadow, Mass.

NOVICE transmitter for sale. Hallcrafters HT-17, brand new, complete with all coils, 80-10, \$50. Also large list of tubes, parts, etc. New York City. Phone Selidwick 3-3690, W2ENP.

WILL Trade: New Clough Bregmole Model 245A capacity and resistance bridge, with other features. New Solar Model CF V.T.V.M. capacity and resistance bridge, with quick condenser check. Both sell for \$250. Will trade for 16" V.T. in good condx. George Kasik, W9NSA, Box 69, Fox River, Grove, Ill.

KILOWATT transmitter, 10 and 75 meters. In good condition. Sale: \$450 cash or reasonable trade. Full description and details on request. W4JHZ, 8230 Division Ave., Birmingham, Alabama.

WANTED: FB7 coils for 10, 20, 80 and 160-meter bands, also SW1 coils, 60 series, for 10 and 80 meters. Schneider, W6JXW, 456 West Fir Ave., Oxnard, Calif.

FOR Sale: Hallcrafters S-39 portable, less batteries. In gud condx. \$40. Want: NC-57. Two coils for HRO 5. Any frequency, prefer high. Whattam, W2CZE, 29 Mount View, Newton, N. J.

TELETYPE midjet printers, tape transmitters, write for prices and information. We want: PE-237, BC-1306, GN-58, GN-45, TC5, ART-13, ATC, DY-11, DY-12, DY-17, RA-14, RA-62, BC-348, BC-312, BC-342, teletype, APS, Radar, BC-610-E, Test Equipment, technical manuals, tubes, Arrow Appliance, 25 Harrison Court, Lynn, Mass.

FOR Sale: Complete mobile station TB550C, Lyco 381, Gonset 3-30, Master bumper antenna, 20M, 75M coils, relay with auxiliary contacts, auto relay with built-in noise limiter, PE103, \$225, W4OCN, M. E. Dunn, RFD #1, Shickshinny, Penna.

SELL: Harvey-Wells Bandmaster deluxe model TBS 50D, with AC power supply APS50, \$130.00; RME VHF152A, 2-6-10 meter converter, \$60.00; Stancor C1405 500 ml swinging choke, \$10.00; Stancor P4086, 5V, T-14 amp filament transformer, \$7.00; Aerovox 3011 2 mfd 3000V condenser, 2 at \$9.00 each. Send check for money order for one-third. Balance plus express charges C.O.D. C. N. Crapo, W9VD, 2111 E. Newton Ave., Milwaukee 11, Wis.

SELL: Electronic "Mon-Key" and a "Speed-X" automatic key. R. Harrison, W8FVU, 310 Washington, Baraboo, Ohio.

SELL: BC-221 for \$75.00; 2-100TH's for \$10.00; 2-VT127A's for \$55.00. F.O.B. No C.O.D.s. W4IPS, P.O. Box 236, Vienna, Va.

QSL and SWL cards. Samples. W7PVZ, Jacobs Johnson's Point, Olympia, Wash.

SELLING estate of late Joe Crabbill, W1PCC. Selling ham gear including NC-240D and VHF 152A, \$200.00 for both. Also 250-watt xmitter, BC-654A, PE 103A, etc. List on request to W1QKE, 109 Glenwood Street, Lowell, Mass.

QSL Cards, \$1.95 and up. Atlantic Press, Clifton, N. J.

SELL: Bendix TA-12 100-watt transmitter and power supply. Bandwidthing, VFO on 80-40-20; \$100.00. Hallcrafters S-38, \$30. W6PBE, Box 3096, Carmel, Calif.

SELL: Teletype equipment, panoramic adaptor, BC-221 freq. meter, 250TH, 1M freq. meter with modulation. Want: PE-237, GN-58, BC-1306, APS-3 cables. Technical manuals. T. Clark Howard, W1AFN, 46 Mt. Vernon St., Boston 8, Mass.

10 and 20 Meter beams, \$32.25 up. Aluminum tubing, etc. Willard Radcliff, 1720 No. Countyline St., Fostoria, Ohio.

QSL'S, SWL'S. Samples 106. Refunded. Harma, W2JME, 225 Maple Ave., North Plainfield, N. J.

CRYSTALS: Low drift, high activity, tailor-made, 3500 to 8500 kilocycles, FT-243's. Desired frequency within 2 Kc. \$1.00 each, .01% crystals, \$2.00 each. Hundley Crystal Co., 2951 No. 36th St., Kansas City 4, Kansas.

QSL'S-SWL'S. Super-gloss, 10 colors, four card-stocks, seven styles. Samples, 106. Almar Printing Service, Farragut, Iowa.

SELENIUM rectifier and transformer kit 28VDC/12 Amp., \$11.95; Snooperscope, infrared, see-in-dark tube, data, \$4.98; 1N34 diodes prepaid USA, 7 for \$4.65; sell your surplus tubes and equipment. Free Tablogram. "TAB", 109 Liberty St., New York City, N. Y.

WANTED: BC-221 in good condition, 304TL's. W2HWC, Box 199, Rt. 43, Nixon, N. J.

HARRISON'S QSLs. Samples for \$5. 8001 Piney Branch Road, Silver Spring, Md.

QST back issues, 1933 thru 1940. List. Herbert Johnson, P. O. Box 151, Rifton, N. Y.

NEW VHF152A, \$69.95, used DB22A, \$49.95, SX-25 with speaker, \$100.00; Welco 50-watt all-band phone xmitter, \$95.25, with VFO, \$110.00, perfect; Collins 32V1, \$465.00. W0KKU, 5615 Annonaga Ave., Arvada, Colo.

USED tubes: 833's, \$5.00; 84's, 50c; 902's, \$1.25; 872, \$1.00; 845's, \$2.00; 805's, \$2.00. Curtis, W5AQC, Longview, Texas.

WANTED: Late model Globe King transmitter. Best offer takes large, used, unconverted prop-chip motor. H. F. Cushing, W1EUS, 16 Preston Drive, Manchester, Conn.

TRADE: For guns or outdoor motor. Complete station, 30w, 10 m phone/c.w. with VFO, heavy duty power supply, in steel cabinet 12 x 18, with 300 ohm dipole, relay, mike, key, spare tubes. Rcvr AC BC-224H, with bf noise limiter, crystal converter for 10 m, speaker, phones, Also MP21 base & 30 ft. steel vertical, etc. Write W5SPS, Box 1320, Bryan AFB, Bryan, Texas.

SELL new Meissner 250-watt modulator and speech amplifier with tubes and power supply on one chassis, factory-wired. Photo. Want reasonable cash offer. R. Long, 184 L. Street, South Boston, Mass.

FOR Sale: Collins 75A-2, completely new, guaranteed perfect, first \$150.00 takes it. F.O.B. W1CPI.

VIBROPLEX Champion 1 year old, \$7.00. W8SNM, 26-160th Ave., St. Petersburg 6, Fla.

DELUXE 813 TVI-proof AM/CW transmitter. (See 1952 Handbook, p. 185). 5314 ultramodern, 350 watts, VFO and modulation monitor. Presto to take in 15' Parmat cabinet rack. Spare tubes and coaxial antenna relay included. Best offer around \$400.00 or complete with new 75A2 rcvr \$750. W2TLG, 68 Vernon Ave., Rockville Center, N. Y.

SOS! Who will lend me schematic for Patterson PR-15 receiver? Will photostat and return promptly. John P. Ramsey, W1N1JG, 81 Spring Garden Street, Hamden, Conn.

CLEANING house: Eimac 304TL, new, \$5.00; Gammatron VT127A, new, \$2.50; used, \$1.50; (2) 614's, slightly used, \$2.50 each; Johnson 100DD70 condenser, slightly used, \$7.00; 100D90, \$6.00; Mod. xform Thorndarson 84M70 pp 807's to 5, 7.5, 10 and 75-watt, new condx. \$6.50; Sangamo G-2 mica Cond. .0039 8000 volts, new, \$6.00; Triplet 3 round 0-200 microammeter, new condition, \$6.00; PE 101C, new, \$7.50. W9JTF, Box 9, Brisclynn, Minnesota.

QSL'S, SWL'S. High quality. Reasonable prices. Samples. Write to Bob Teachout, W1FSV, 40 Elm Street, Rutland, Vermont.

WANTED: QST's, from 1929 to 1940. H. Zimmer, Zimmer Co., 1213 Fulton Road, Canton 3, Ohio.

WANTED: Collins 310 Series exciter or 32V2. State condition and lowest price. Paul Z. Haus, W2VH, 25 Upland Drive, Chappaqua, New York.

SELL: (No trades!) 4-250A, used less than 10 hours, with stocket, \$20.00, fil. trns., same \$5.00; 304 TL new, \$5.00; pair VT-127A, \$10.00 (new); pair 8012A, new, \$2.00; dynamometer 5 101B-10 6-12V DC-SRV, new, \$10.00. beam as my ad "QST" April must go, best offer. All F.O.B. Cheshire, Conn. W1AH, Main St., Cheshire, Conn.

COLLINS 32V2 wanted. W9JKC, P.O. Box 266, 695 Vernon Avenue, Glenview, Illinois.

TRADE: Have BC-459 converted, BC-654 Air King wire recorder; Motorola 34 mc fm police transmitter with Carter genemotor; receiver and speaker, separate Carter 600 v. genemotor. Want: 10-20-75 Mobile transmitter and converter, Graham H. Hicks, W510P, Box 364, Natchez, Mississippi.

FOR Sale: NC-183 with speaker, new, in original cartons. Price: \$175.00. C. W. Ehlers, 319 Union Street, Jersey City 4, N. J.

COLLINS 30K-1 transmitter for sale. Filtered and re-tuned, 4-250A final, 500 watts phone, Stainless steel, Box 789, Anderson, Indiana.


SELL HT-18, perfect. Best offer over \$78. W8FRW, Ryan, 520 Loveman Avenue, Worthington, Ohio.

FOR Sale: NC-183, in excellent condition, W1BB.

Designed for



Application



90651

The No. 90651 GRID DIP METER

The No. 90651 MILLER GRIP DIP METER is compact and completely self contained. The AC power supply is of the "transformer" type. The drum dial has seven calibrated uniform length scales from 1.5 MC to 300 MC plus an arbitrary scale for use with the 4 additional inductors available to extend the range to 220 kc. Internal terminal strip permits battery operation for antenna measurement.

**JAMES MILLEN
MFG. CO., INC.**

MAIN OFFICE AND FACTORY
**MALDEN
MASSACHUSETTS**




Index of Advertisers

Akers Co., Dallas, Tex.	104
Allied Radio Corporation	97
A.R.R.L. License Manual	96
QST	105
Calculators	106
Binders	131
Ashe Radio Company, Walter	101
Astac Corporation, The	112
Barker & Williamson, Inc.	125, 136
Belden Manufacturing Co.	87
Bendix Radio Division	110, 125
Brush Development Company	88
Candler System Company	128
Capitol Radio Eng. Institute	94
Chicago Transformer Company	79
Collins Radio Company	2, 114, 116
Commercial Radio Institute	120
Concord Radio	121
Communication Products Company	128
Dow-Key Company, Inc.	116
Eitel-McCullough, Inc.	85
Eidico of New York, Inc.	123, 124, 126, 128
Electro-Voice, Inc.	81
Engineering Associates	126
Evans Radio	128
Fort Orange Radio Distrib. Company	119
Gardiner & Company	123
Gates Radio Company	89
General Electric Company	127
Gonset Company, The	118
Greenlee Tool Co., The	118
Hallcrafters Co., The	4, 5
Hammarlund Manufacturing Co.	91
Harrison Radio Corp.	103
Hartley Manufacturing Company	102
Harvey Radio Company	109
Harvey-Wells Electronics	86
Heath Company, The	123
Henry Radio Stores	107
Hudson Radio & Television Corp.	100
Hy-Lite Antennae, Inc.	108
Instructograph Company	126
Johnson Company, E. F.	112, 129
Knights Company, The James	135
Leeds Radio Company	117
Letting Radio Manufacturing Company	110
Mallory & Company, P. R.	83
Marmax Electronics	95
Mass. Radio & Teleg. School	122
Merit Transformer Corporation	92
Millen Mfg. Co., Inc., The James	134
Motorola, Inc.	124
National Co., Inc.	Cov. III, 77, 93, 130
Northrop Aircraft	120
Petersen Radio Company	7
Port Arthur College	106
Precision Apparatus Company	82
Premax Products Co.	129
Radio Apparatus Corporation	131
Radio Corporation of America	Cov. IV
Radio Shack Corporation, The	111
Radio Wire Television	111
Raytheon Manufacturing Company	90
RCA Institutes, Inc.	124
Rider Publisher, Inc., John F.	124
Sperry Gyroscope Co.	126
Steinberg's, Inc.	113
Suburban Radio Company	105
Terminal Radio Corporation	99
Triplet Elec. Instrument Co.	84
U.H.F. Resonator Company	118
United Transformer Company	Cov. II
Valparaiso Technical Institute	123
Vesto Company, Inc.	114
Vibroplex Co., The	120
Weller Electric Corporation	104
Westinghouse Electric Corporation	98
Weston Laboratories	122
Wind Turbine Company	122
Wood, M. E.	122
World Radio Laboratories, Inc.	115



PRODUCTS

keeping communications ON THE BEAM




**JK STABILIZED
H-17 CRYSTAL**

CRYSTALS FOR THE CRITICAL

The small, compact H-17 is designated as a military type crystal for its use in mobile units common to the military. Frequency range: 200 kc to 100 mc. Hermetically sealed holders; wire-mounted, silver-plated crystals.

*the JK
FD-12*



FREQUENCY AND MONITOR MODULATION

Monitors any four frequencies anywhere between 25 mc and 175 mc, checking both frequency deviation and amount of modulation. Keeps the "beam" on allocation; guarantees more solid coverage, too!

"High Gear" Response to High Power Maintenance!

Dawn or dusk, it doesn't matter. These heroes of the high wires arrive to stop power trouble before it starts. Their "nose for disaster" is in the service truck, in the mobile radio unit which often relies on JK crystals and monitors to keep their assigned radio frequency on the beam!

THE JAMES KNIGHTS COMPANY

SANDWICH 6, ILLINOIS



Hams! Engineers! Servicemen!

IT'S HERE!

B&W

MODEL 600

Dip Meter

Supplied complete
with 5 color-coded
plug-in coils

VERSATILE AND COMPACT

Few instruments will prove so handy in so many ways as this versatile B&W Model 600 Dip Meter. Ideal for lab, production, service, or ham shack use, it provides a quick, accurate means for measuring resonant circuit frequencies, spurious emissions and many other tuned circuit characteristics. Shaped for easy use in today's compact electronic assemblies, highly sensitive and accurately calibrated, it incorporates many features previously found only in higher-priced instruments. You'll find dozens of uses for it as...

... **A Grid Dip Oscillator** for determining resonant frequencies of tank circuits, antennas, feed line systems, and parasitic circuits; aligning filters and traps; peaking coils, neutralizing and tuning xmitters before power is applied.

... **An Absorption Wave Meter** for accurately identifying the frequency of radiated power from various xmitter stages; locating spurious emissions causing troublesome TVI and BCI, and many similar uses.

... **An Auxiliary Signal Generator** providing a signal for tracing purposes and for preliminary alignment of receivers, converters, and I-F stages.

... **An R-F Signal Monitor** for audible observation of hum, audio quality, and other audible characteristics of radiated power.

... **For Capacity, Inductance, and "Q"** measurements in conjunction with other components of known value.

A Quality Instrument Priced Within Reach of All




- ✓ Covers 1.75 to 260 mc. in 5 bands
- ✓ Adjustable sensitivity control
- ✓ Handy wedge-shape for easy access in hard-to-get-at places
- ✓ Size 3" x 3" x 7". Weighs only 2 lbs.

- ✓ Monitoring jack and B+ OFF switch
- ✓ Rust-proofed chassis, aluminum case
- ✓ Built-in power supply for 110 volts A.C.


Sold by B&W distributors throughout U.S.A. and Canada. Data bulletin sent on request.

PRICE
\$48 net

BARKER & WILLIAMSON, Inc. 237 Fairfield Avenue, Upper Darby, Pa.



THE NEW
HRO *Sixty*
 IS HERE!




**Without using crystal filter*



Dual Conversion! 12 Tuned I. F. Circuits!

Here now — the HRO Sixty — latest and greatest of a great series! Now, in addition to all the wonderful features of the HRO-50T1, you get *dual conversion* on all frequencies above 7 mcs. *plus* 12 permeability-tuned circuits in the 3 456-kcs. I. F. stages! Other new features include current-regulated heaters in the high-frequency oscillator and the 6BE6 mixer. High-frequency oscillator and S-meter amplifier are voltage regulated.

Be sure to see and hear the ultimate — **the HRO Sixty!**



Why RCA-developed **beam power** tubes are best for your transmitter

SIMPLY STATED, beam power tubes combine good output efficiency with low drive requirements.

But, let's get down to cases...

...because you get high output with low driving power, you need fewer intermediate stages. Fewer stages mean a compact, efficient transmitter.

...since high driving power is *not* a requirement, there is less chance of TVI.

...for economy—most beam-power-tube circuits can use simple, inexpensive, low-voltage power supplies.

...beam power tubes are superior for quick-change, multi-band transmitters because they seldom require neutralization in well-designed circuits.

...the fact that plate voltage can be changed without affecting other circuit adjustments makes it simple to reduce power for local QSO's.

...beam power tubes operate efficiently as frequency multipliers, drivers, finals, and modulators.

There you have the reasons why beam power tubes lead all other types in modern transmitter design.

And remember—there's an RCA beam power tube for every input up to 500 watts (per tube)...and every frequency from 1.8 to 148 Mc.



TUBES FOR THE PROFESSIONAL

...PRICED FOR THE AMATEUR

The dependability of commercially proved RCA Tubes costs you no more. Buy genuine RCA Tubes and you buy the best. See your local RCA Tube Distributor.



RADIO CORPORATION of AMERICA
ELECTRON TUBES
HARRISON, N.J.